

NETVANTA 1335 SERIES

P/N 1700515E2/E12, 1700525E2/E12

NETVANTA 1335 POE SERIES

Power over Ethernet (PoE) technology provides the ability to detect attached powered devices (PDs) and deliver 48 VDC to the PD via existing CAT5 cabling. The NetVanta 1335 PoE units are fully compliant with the power delivery options called out in the IEEE 802.3af Power over Ethernet specification. By default, the PoE interfaces discover and provide power to IEEE compliant PDs.

To disable power detection and supply, use the **power inline never** command in the CLI. To disable power detection and supply from the graphical user interface (GUI), select the **Ports** page. Then select a single port from the list (e.g., **switchport 0/1**). This will bring up the port detail page for **switchport 0/1**. On this page, there is a check box to enable power detection.

NETVANTA 1335 WIFI SERIES

The NetVanta 1335 Wireless Fidelity (WiFi) Series provides a single access point for connection with IEEE 802.11a/b/g wireless networks. A dual radio design with two dual-band external antennas is used to support concurrent 802.11a and 802.11b/g connections.

GETTING STARTED

Two configuration methods are available for your NetVanta 1335 Series units:

- Web-based GUI
- AOS command line interface (CLI)

The GUI lets you configure the main unit settings and provides online guidance and explanations for each setting. However, using the AOS CLI may be necessary for more advanced configurations.

ACCESS THE GUI

You can access the GUI from any Web browser on your network by following these steps:

1. Connect the switch to your PC using any of the 24 Ethernet ports on the front of the unit.
2. Set your PC to a fixed IP address of 10.10.10.2. If you cannot change the PC's IP address, you will need to change the unit's IP address using the CLI. (Refer to the next two sections for instructions.)
3. Enter the unit's IP address in your browser address line. The default IP address is 10.10.10.1.
4. You will then be prompted for the user name and password (the default settings are **admin** and **password**).
5. The initial GUI screen appears.

ACCESS THE CLI

Access the AOS CLI via the **CONSOLE** port or a Telnet session. To establish a connection to the NetVanta unit's **CONSOLE** port, you need the following items:

- VT100 terminal or PC (with VT100 terminal emulation software)
 - Straight-through serial cable with a DB-9 (male) connector on one end and the appropriate interface for your terminal or PC communication port on the other end
1. Connect the DB-9 (male) connector of your serial cable to the **CONSOLE** port on the rear panel of the unit.
 2. Connect the other end of the serial cable to the terminal or PC.
 3. Insert the connector of the provided power cord into the power interface on the rear panel of the unit, and plug the cord into a standard electrical outlet.
 4. Once the unit is powered up, open a VT100 terminal session using the following settings: 9600 baud, 8 data bits, no parity bits, and 1 stop bit. Press **<Enter>** to activate the AOS CLI.
 5. Enter **enable** at the **>** prompt. Enter the enable password when prompted. The default password is **password**.



*The configuration parameters used in the examples outlined in this document are for instructional purposes only. Please replace all underlined entries (**example**) with your specific parameters to configure your application.*

CONFIGURE THE UNIT'S IP ADDRESS

The following steps create an IP address and subnet mask for the virtual interface **vlan 1**. If you are not sure what IP address to assign, please contact your network administrator.

1. At the **#** prompt, enter **config terminal**.
2. At the **(config)#** prompt, enter **interface vlan 1** to access the configuration parameters for the virtual LAN (VLAN) interface.
3. Enter **ip address 10.26.12.12 255.255.255.0** to assign an IP address to the VLAN interface using a 24-bit subnet mask.
4. Enter **no shutdown** to activate the virtual interface to pass data.
5. Enter **exit** to return to the Global Configuration mode.

ENABLE TELNET ACCESS

The following steps create a password of **adtran** for Telnet access. By default, Telnet access is enabled with a password of **password**.

1. Verify that the prompt of your unit displays **(config)#**.
2. Enter **line telnet 0 4** to change the configuration parameters for the Telnet sessions.
3. Enter **login** to initiate Telnet access.
4. Enter **password adtran** to change the login password for the Telnet sessions.
5. Enter **exit** to return to the Global Configuration mode.
6. Verify that the prompt of your unit displays **(config)#**.
7. Enter **do write memory** to save the current configuration.



Important: For additional details on product features, specifications, installation, and safety, refer to the appropriate hardware installation guide on the **AOS Documentation** CD shipped with the base unit and available online at www.adtran.com.

INSTALLING THE ANTENNAS (WiFi SERIES ONLY)

The NetVanta 1335 WiFi Series ships with two dual-band RP-SMA detachable antennas. These must be installed before operating the unit.

1. Place either of the two antennas directly onto the antenna port labeled **ANT 1** on the rear panel.
2. Twist the antenna onto the threads until it is secure.
3. Repeat step 2 with the second antenna, attaching it to the **ANT 2** port.

ETHERNET PINOUTS

Pin	Name	Description
1	TX1	Transmit Positive
2	TX2	Transmit Negative
3	RX1	Receive Positive
4, 5	—	Unused
6	RX2	Receive Negative
7, 8	—	Unused

CONSOLE PINOUTS

Pin	Name	Description
1	DCD	Data Carrier Detect (output)
2	RD	Receive Data (output)
3	TD	Transmit Data (input)
4	DTR	Data Terminal Ready (input)
5	SG	Signal Ground
6	DSR	Data Set Ready (output)
7	—	Unused
8	CTS	Clear to Send (output)
9	—	Unused



CONFIGURE YOUR APPLICATION

More detailed documentation for configuring your ADTRAN unit is provided on the *AOS Documentation* CD included in your shipment. For more detail on hardware setup, refer to the appropriate NIM quick start guides and the hardware installation guide. For more detail on configuring your system, refer to the *AOS Command Reference Guide*, configuration guides, and technical support notes.