

License Management, Emergency Unlock Reset Key Required

Virtual Multimedia Resource Function

Operating Instructions

Copyright

© Ericsson AB 2017–2019. All rights reserved. No part of this document may be reproduced in any form without the written permission of the copyright owner.

Disclaimer

The contents of this document are subject to revision without notice due to continued progress in methodology, design and manufacturing. Ericsson shall have no liability for any error or damage of any kind resulting from the use of this document.

Trademark List

All trademarks mentioned herein are the property of their respective owners. These are shown in the document *Trademark Information*.

Contents

1	Overview	1
1.1	License Management, Emergency Unlock Reset Key Required Alarm Description	1
2	Procedure	3
2.1	Prerequisites	3
2.2	Cease the License Management, Emergency Unlock Reset Key Required Alarm	3





1 Overview

This instruction concerns alarm handling.

1.1 License Management, Emergency Unlock Reset Key Required Alarm Description

The License Management, Emergency Unlock Reset Key Required alarm is raised when the `EmergencyUnlock.activationsLeft` counter is decremented.

The possible alarm causes and fault locations are explained in [Table 1](#).

Table 1 Alarm Causes

Alarm Cause	Description	Fault Reason	Fault Location	Impact
1	License Management, Emergency Unlock Reset Key Required	Emergency Unlock mode has been activated.	License server	WARNING: Emergency Unlock mode can be initiated for one additional seven-day period. MAJOR: Emergency Unlock mode cannot be reactivated.

The alarm attributes are listed and explained in [Table 2](#).

Table 2 Alarm Attributes

Attribute Name	Attribute Value
Major Type	193
Minor Type	393216
Managed Object Class	Lm
Managed Object Instance	ManagedElement=<node_name>, SystemFunctions=1, Lm=1
Specific Problem	License Management, Emergency Unlock Reset Key Required



Attribute Name	Attribute Value
Event Type	qualityOfServiceAlarm (3)
Probable Cause	m3100AlarmIndicationSignal (1)
Additional Text	Emergency Unlock Reset Key required
Perceived Severity	One of the following: —Major (4) – Counter activationsLeft is set to 0 and Emergency Unlock mode cannot be reactivated until the counter is reset. —Warning (6) – Counter activationsLeft is set to 1 and Emergency Unlock mode can be activated only once more.



2 Procedure

The following procedure describes how to cease a License Management, Emergency Unlock Reset Key Required alarm.

2.1 Prerequisites

This section provides information on the documents, tools, and conditions that apply to the procedures in this document.

2.1.1 Documents

Before starting this procedure, ensure that the following document is available:

- Data Collection Guideline for vMRF

2.1.2 Conditions

Before starting this procedure, ensure that the following conditions are met:

- A License Management, Emergency Unlock Reset Key Required alarm is raised.
- No ongoing maintenance activities are affecting the node.
- The reason for entering Emergency Unlock mode is known
- The user ceasing the alarm has proper authority to handle configuration management of the network elements.
- An Ericsson Command-Line Interface (ECLI) session in Exec mode is in progress.

2.2 Cease the License Management, Emergency Unlock Reset Key Required Alarm

Steps

1. Contact your Ericsson supplier to order an Emergency Unlock Reset Key and have it provisioned in NeLS. For more information on provisioning licenses in NeLS, refer to the documentation that comes with your version of the product software.



Result: After the emergencyResetKey has been successfully provisioned, EmergencyUnlock.activationsLeft is automatically reset.

Note: LM must have NeLS access to reset
EmergencyUnlock.activationsLeft.

2. Use ssh to connect to the COM CLI Management System server port on the blade where the active COM CLI is running:

```
ssh <username>@<blade_IP_address> -p 22 -t -s cli
```

Note: The default COM CLI Management System server port is 22.

3. Check the value of EmergencyUnlock.activationsLeft:

```
show  
ManagedElement=1, SystemFunctions=1, Lm=1, EmergencyUnlock=1,  
activationsLeft
```

The system returns activationsLeft=2 if the counter has been reset.

4. Check the alarm status.

If the alarm is still active, consult the next level of maintenance support.
Further actions are outside the scope of this instruction.