

Extreme Switch Firmware Upgrade

Cloud Execution Environment

OPERATING INSTRUCTIONS

Copyright

© Ericsson AB 2016. All rights reserved. No part of this document may be reproduced in any form without the written permission of the copyright owner.

Disclaimer

The contents of this document are subject to revision without notice due to continued progress in methodology, design and manufacturing. Ericsson shall have no liability for any error or damage of any kind resulting from the use of this document.

Trademark List

All trademarks mentioned herein are the property of their respective owners. These are shown in the document Trademark Information.



Contents

1	Introduction	1
1.1	Concepts	1
1.2	Prerequisites	1
2	Procedure	4
2.1	Identify Switch and Switch Status	4
2.2	Log on to the Selected Switch	4
2.3	Set Switch to Maintenance Mode	5
2.4	Select Download Partition	5
2.5	Install EXOS Core Image	6
2.6	Install Modular Software Package	6
2.7	Use the Newly Installed Partition	7
2.8	Reboot and Activate the New Packages	7
2.9	Check the Status of the Upgraded Switch	7
2.10	Recover Traffic Switch from vCIC	8
2.11	Log Out of the Switch	9
	Reference List	10





1 Introduction

This Operational Instruction describes how to upgrade the firmware for the Extreme switch.

Switches are upgraded in pairs, and this document describes procedures for one pair of switches. In case of 2 pairs of switches, repeat the procedures for the second pair.

The upgrade involves the following steps:

- Identifying the switch role
- Identifying the switch status
- Checking that the switch is functional
- Performing the upgrade
- Rebooting and activating the switch

1.1 Concepts

Before starting the procedure, ensure that the terminology is understood:

Switch	Status
Selected Switch	The switch selected for upgrade
Upgraded Switch	The switch after its upgrade
Other Switch	The switch within the pair that is not yet selected for upgrade

1.2 Prerequisites

This section provides information on the documents, tools, and conditions that apply to the procedure.

1.2.1 Documents

Before starting the upgrade procedure, ensure that the following documents are available, are read and understood:

- The address variables used in the document *IP and VLAN Plan*, Reference [1] are used throughout this document, and are summarized in the table below.



	Network/VLAN	IPv4 Address Variable
	fuel_ctrl_sp (admin)	<Fuel (static)>
	fuel_ctrl_sp (admin)	<CIC (dynamic, "static pool")>
Traffic	cee_ctrl_sp	<Traffic_switch_A (static)>
Traffic	cee_ctrl_sp	<Traffic_switch_B (static)>
Storage	cee_ctrl_sp	<Storage_switch_A (static)>
Storage	cee_ctrl_sp	<Storage_switch_B (static)>
Control	cee_ctrl_sp	<Control_switch_A (static)>
Control	cee_ctrl_sp	<Control_switch_B (static)>

- *Security User Guide*
- *System Hardening Guideline*
- *Extreme X460 Configuration* for X460 switches.

Note: The procedure depends on the role of the switch.

If there are two X460 switches, they are **Control** switches.

If there are only two X670V switches, then both are **Mixed** switches, with both traffic and storage switch functions.

If there are four X670V switches, or four X770 switches, then there are two Traffic switches combined with two Storage switches.

Traffic switches and **Mixed** switches are operated using *Neutron*, but **Storage** switches are not. In the procedure, the steps for *Neutron* are skipped in case of pure **Storage** switches. The affected steps start with the following text: *Not applicable for Storage switches*.

Variables used in the commands are listed below:

Variable	Value
<user-name>	Example: admin



Variable	Value
<switch-name>	<CEE Region Name>_TRAFFIC_SWA_X770
	<CEE Region Name>_TRAFFIC_SWB_X770
	<CEE Region Name>_TRAFFIC_SWA_X670V
	<CEE Region Name>_TRAFFIC_SWB_X670V
	<CEE Region Name>_STORAGE_SWA_X770
	<CEE Region Name>_STORAGE_SWB_X770
	<CEE Region Name>_STORAGE_SWA_X670V
	<CEE Region Name>_STORAGE_SWB_X670V
	<CEE Region Name>_CONTROL_SWA_X460
	<CEE Region Name>_CONTROL_SWB_X460
<switch-ip>	<Traffic_switch_A (static)>
	<Traffic_switch_B (static)>
	<Storage_switch_A (static)>
	<Storage_switch_B (static)>
	<Control_switch_A (static)>
	<Control_switch_B (static)>
	Example: 192.168.2.2

1.2.2

Conditions

Before starting the upgrade procedure, ensure that the following conditions are met:

- The new version of the Extreme switch image has been uploaded or copied to either the Fuel Master node, a terminal server, or maintenance laptop.
- The pair(s) of Extreme switches to be upgraded are fully functional and alarm-free.
- Check in the Release Notes of the new firmware if the new firmware supports the switch model.



2 Procedure

This section describes the firmware upgrade procedure for one pair of switches.

In case of 2 or more pairs of switches, repeat the procedures for the second pair.

2.1 Identify Switch and Switch Status

If there are two X460 switches, then they are Control switches, go to Section 2.2 on page 4.

If the switch is a **Storage** switch, go to Section 2.2 on page 4.

To identify switch status, do:

1. Check that the switch status is `ACTIVE`. Do this step for both switches.

```
root@node-6: neutron device-show <switch-name>
```

Field	Value
admin_state_up	True
device_type	TOR_SWITCH
firmware_version	15.4.1
id	3757da15-7942-4db9-98d5-c05ecfefc5b8
management_ip_address	192.168.6.1
model	SummitXX70V
name	DC154_SWA_XX70V
password	NetworkAdmin
status	ACTIVE
user_name	network_admin
vendor	extreme
vr_total	63

Example 1 Switch Details

For more information, see the *Data Collection Guideline*.

2.2 Log on to the Selected Switch

1. Log on to the switch by either of the following ways:

- Log on to the switch from a terminal server, Fuel Master, or a maintenance laptop via SSH. Use the following command with a valid username and the management IP address of the switch from VLAN cee_ctrl_sp:

```
ssh <user_name>@<switch-ip>
```

- Log on to the switch by using a serial connection.



2. Check for warnings, errors, and critical statements in the switch log.

```
<switch-name>.1 # show log severity [critical | error |
warning ] chronological
```

Note: If the switch log shows errors or critical statements, contact the next level of maintenance support.

3. Log out of the selected switch.

```
<switch-name>.2 # logout
```

4. If the switch is a Storage switch, go to Section 2.4 on page 5.
5. If the switch is a Control switch, go to document *Extreme X460 Configuration*, section *Configuration of Switch*.

2.3 Set Switch to Maintenance Mode

Perform the following steps for the selected switch:

1. Inform *Neutron* by switching the device status to *maintenance*. Use the following command:

```
neutron device-update <switch-name> --status=MAINTENANCE
```

```
neutron device-update <CEE Region Name>_TRAFFIC_SWB_X670V --status=MAINTENANCE
```

Example 2 Switch Device Status to Maintenance

2. Verify that the device status has changed to *maintenance*. Contact the next level of maintenance support if the device status does not change.
3. Go to Section 2.4 on page 5.

2.4 Select Download Partition

1. Use the “management_ip_address” on VLAN *cee_ctrl_sp* to log on to the selected switch.

```
ssh network_admin@<management IP address of the
selected switch>
```

To select which partition to use when downloading an image, do the following:

1. Use the `show switch` command to determine the selected and booted images.
2. Check if they are in the primary or secondary partition.
3. Select the partition. When installing the new firmware image, make sure to select the other partition, not the partition from where the current image is booted from.



Note: The selected image partition indicates which image is to be used at the next reboot. The booted image partition indicates the image used at the last reboot.

2.5 Install EXOS Core Image

To install the image, do the following steps:

1. Download and validate the new image to the switch using scp/scp2:

```
scp2 {vr vr_name} user [hostname | ipaddress]:remote_
file local_file
```

```
scp2 vr "VR-Default" root@<Fuel (static)>:/var/lib/tftpboot⇒
/summitX-15.6.1.4.xos⇒
summitX-15.6.1.4.xos
```

Example 3 Validate Image Using SCP/SCP2

2. Install the image by issuing the following command:

```
install image local_file {partition}
```

```
install image summitX-15.6.1.4.xos secondary
```

Example 4 Install Image Command

Note: Here, the secondary partition is selected, because the current image is booted from the primary partition.

2.6 Install Modular Software Package

To add the SSH module to the switch, do the following steps:

1. Download the new image to the switch using scp/scp2:

```
scp2 {vr vr_name} user [hostname | ipaddress]:remote_
file local_file
```

```
scp2 vr "VR-Default" root@<Fuel (static)>:/var
/lib/tftpboot⇒
/summitX-15.6.1.4-ssh.xmod⇒
summitX-15.6.1.4-ssh.xmod
```

Example 5 Download Image Using SCP/SCP2

2. Install the software module by issuing the following command:

```
install image local_file {partition}
```

Note: The version of the SSH module must be the same as the version for the EXOS core image.



```
install image summitX-15.6.1.4-ssh.xmod secondary
```

Example 6 Install Image Command

Note: Here, the secondary partition is selected, because the current image is booted from the primary partition.

2.7 Use the Newly Installed Partition

Select the newly installed partition to use after the reboot by issuing the following command:

```
use image {partition} <partition>
```

```
use image partition secondary
```

Example 7 Use Image Command

2.8 Reboot and Activate the New Packages

To reboot and activate the new packages, do the following steps:

1. Reboot the system by issuing the following command:

```
reboot
```

2. The following options are available:

y Save and reboot

n Reboot without save

cr Cancel command

3. From the options available, choose **n**.

2.9 Check the Status of the Upgraded Switch

To check the status of the upgraded switch, do the following:

1. Log on to the upgraded Extreme switch, and issue the following command:

```
show switch
```

Note: For an output example, see Example 8.



```

Current State:      OPERATIONAL
Image Selected:     secondary
Image Booted:       secondary
Primary ver:        15.6.1.4
Secondary ver:      15.4.1.3
Config Selected:    ericsson_default.cfg
Config Booted:      ericsson_default_backup.cfg

```

Example 8 Switch Status

2. Check that the switch state is `OPERATIONAL`, and the new EXOS image is installed. Ensure that the upgrade procedure was successful.
3. Log out of the upgraded switch.

```
<switch-name>.1 # logout
```

4. If the selected switch is Traffic or Mixed and accessible through Neutron, continue with Section 2.10 on page 8.
5. If the selected switch is a Control or Storage switch, continue with the other switch. Go to Section 2.2 on page 4.
6. If both Control or Storage switches are upgraded, go to Section 2.11 on page 8.

2.10 Recover Traffic Switch from vCIC

Perform the following steps on the upgraded traffic switch:

1. Recover the switch from the vCIC by using the following command:

```
neutron device-recover <switch-name>
```

```
neutron device-recover <CEE Region Name>_TRAFFIC_SWB_X770
```

Example 9 Recover Switch from vCIC

Note: The recovery process includes a new reboot.

2. Confirm that the upgraded switch operates properly when booted from the vCIC. Use the following command:

```
neutron device-show <switch-name>
```

```
neutron device-show <CEE Region Name>_TRAFFIC_SWA_X670V
```

Example 10 Neutron Device Show

Note: The status of the switch must be `ACTIVE`. It can take about five minutes to have the status displayed.

3. If both traffic switches are upgraded, go to Section 2.11 on page 8.
4. Otherwise, continue with the other switch. Go to Section 2.2 on page 4.



2.11 Log Out of the Switch

1. Log out of the switch.

```
# logout
```

2. Procedure complete.



Reference List

- [1] *IP and VLAN Plan*, 2/102 62-CRA 119 1862/5 Uen