

**REPLACING PAGE ADDENDUM**

***Filing Instructions:***

1. REMOVE FROM THE SECTION THE PAGES NUMBERED THE SAME AS THOSE ATTACHED TO THIS PINK SHEET.
2. INSERT THE ATTACHED PAGES INTO THE SECTION IN THEIR PLACE.
3. PLACE THIS PINK SHEET AHEAD OF PAGE 1 OF THE SECTION.

**OUTGOING SENDER CONNECTOR  
AND OUTGOING SENDER LINK CIRCUITS  
TESTS USING OFFICE TEST FRAME CIRCUIT SD-27633-01 (J23260)  
NO. 5 CROSS BAR OFFICES**

**1. GENERAL**

**1.001** This addendum supplements Section 218-461-501, Issue 2. The attached pages must be inserted in the section in accordance with the filing instructions above.

**1.002** This addendum is issued to revise Test C. This addendum does not affect the Equipment Test Lists.

**4. METHOD**

The following change applies to Part 4 of this section.

- (a) Test C, Step 1 verification revised.

**Attachments:**

**Page 3 dated December 1972, reissued  
Page 4 dated December 1972, revised**

| STEP | ACTION   | VERIFICATION |
|------|--|--------------|
| 13   | Set RSG switch to OSB- to select sender group. |              |
| 14   | Set RSS switch to select sender to be tested.  |              |

#### 4. METHOD

| STEP | ACTION | VERIFICATION |
|------|--------|--------------|
|------|--------|--------------|

##### A. Trunk Access to Senders

|    |  |   |
|----|--|---|
| 15 | Operate ST key.  | At TIC—<br>TB-, FS-, TS-, FAK or FBK lamps lighted corresponding to location of trunk on trunk link frame.<br>CN-, S- lamps lighted corresponding to location of sender in OSC.<br>OS-, OSG-, SSA or SSB lamps lighted corresponding to sender and sender group selected. |
|    |  | <b>Note:</b> TM1 relay will operate causing TF lamp to light and call will not complete.  |
| 16 | Momentarily operate RLS key.   | All lamps extinguished.   |
| 17 | At OTF—<br>Restore ST key.   |   |
| 18 | Repeat Steps 13 through 17, selecting a different sender on each call until all senders are tested to this particular trunk. |   |
| 19 | At jack, lamp, and key circuit—<br>Remove make-busy plug from MB- jack of trunk selected.                                    |   |
| 20 | Repeat Steps 11 through 19, selecting each trunk of trunk group.   |   |
| 21 | At OTF—<br>Restore all keys and switches not required in next test.  |   |

##### B. Sender Selection by Marker

|    |                 |   |
|----|-----------------|---|
| 15 | Operate ST key. | At TIC—<br>TB-, FS-, TS-, FAK or FBK lamps lighted corresponding to location of trunk on trunk link frame.<br>CN-, S- lamps lighted corresponding to location of sender in OSC. |
|----|-----------------|---|

**SECTION 218-461-501**

| <b>STEP</b>                                  | <b>ACTION</b>  | <b>VERIFICATION</b>  |
|--|--|--|
|  |  | DR- lamp lighted corresponding to marker used in test.<br>OS-, OSG-, SSA or SSB lamps lighted corresponding to sender and sender group selected. |
|  |  | <b>Note:</b> TM1 relay will operate causing TF lamp to light and call will not complete.   |
| 16   | Momentarily operate RLS key.   | All lamps extinguished.  |
| 17   | At OTF—<br>Restore ST key.   |  |
| 18   | Repeat Steps 13 through 17, selecting a different sender on each call until all senders are tested to a particular marker. |  |
| 19   | Repeat Steps 15 through 18, selecting a different marker until all markers are tested.                                     |  |
| 20   | At jack, lamp, and key circuit—<br>Remove make-busy plug from MB- jack of trunk selected.                                  |  |
| 21   | At OTF—<br>Restore all keys and switches not required in next test.  |  |
| <b>C. False Continuity—MA Relay</b>          |  |  |
| 1  | At jack, lamp, and key circuit—<br>Insert make-busy plugs into each SCMB- jack for each marker of OSC under test.          | At outgoing sender connector frame—<br>Check for no ground on contacts of relay in connector as follows:<br>♦12M♦ of MA1<br>♦01M♦ of MA2.        |
| 2  | At jack, lamp, and key circuit—<br>Remove make-busy plugs from SCMB- jacks.  |  |
| <b>D. Line Link Pulsing Circuit Features</b> |  |  |
| 1  | At OTF—<br>Restore all keys and switches.  |  |
| 2  | At TIC—<br>Momentarily operate RLS key.  | All lamps extinguished.  |
| 3  | Have an incoming trunk made busy at originating office.  |  |