

DIMENSION[®] PBX
DCTS FEATURE TEST
NO LINE PREFERENCE

CONTENTS

- 1. GENERAL
- 2. TEST SET UP

- 3. NO LINE PREFERENCE TEST
- 4. RESTORATION

1. GENERAL

- 1.1 This test section provides testing information for No Line Preference.
- 1.2 With No Line Preference the station user will not be automatically connected to any line upon going off-hook. There will be no I-USE indication in the idle state and users are required to depress a line button every time a call is originated.

2. TEST SET-UP

- 2.1 Connect Electronic Telephone Set to circuit selected with No Line Preference. This set will be referred to as Set-N during the test procedure.

3. NO LINE PREFERENCE TEST

- 3.1 At Set-N verify that all I-USE lamps are off.
- 3.2 At Set-N go off-hook.
- 3.21 No I-USE lamp lighted. Dial tone not received.

- 3.3 At Set-N depress any assigned line button.
- 3.31 I-USE lamp for selected line lighted.
- 3.311 Status lamp associated with selected line steadily lighted. Dial tone received.
- 3.4 At Set-N go on-hook.
- 3.41 Status and I-USE lamps go off.

4. RESTORATION

- 4.1 Determine requirements of next test and disconnect telephone sets not required.

Manager, Denver PBX PECC

PRIVATE

THE INFORMATION CONTAINED HEREIN SHOULD NOT BE DISCLOSED TO UNAUTHORIZED PERSONS. IT IS MEANT SOLELY FOR USE BY AUTHORIZED BELL SYSTEM EMPLOYEES. Printed in U.S.A.