

REGISTRATION INTERFACE

SERIES SINGLE LINE

TIP AND RING ARRANGEMENTS

RJ16X, RJ31X, RJ32X, RJ33X, RJ34X, RJ35X, RJ36X, RJ37X, AND RJ38X

1. GENERAL

1.001 This addendum supplements Section 463-400-130, Issue 3. Place this pink sheet ahead of Page 1 of the section.

1.002 This addendum is issued to correct the lead designated as R1 in Table D.

2. CHANGES TO SECTION

2.001 On Page 14, Table D is obsolete. A new Table D is shown in this addendum.

NOTICE

Not for use or disclosure outside the
Bell System except under written agreement

TABLE D
COM KEY TELEPHONE SETS (NOTE)

TELEPHONE SET CODES	TELEPHONE SET TERMINATIONS						D6AA CORD			
	T1*				R1*		T	R †	A	A1
	(BL)-LINE SW		(O)-STRAP		(Y)-RECALL ‡					
	FROM	CONNECT TO D6AA	FROM	CONNECT TO D6AA	FROM	CONNECT TO D6AA	(G)	(R)	(Y)	(BK)
832A,B,C,			22	(W)	4	(BL)	22	4	15	10
832BM,CM,DM,EM †	22	(W)			4	(BL)	22	4	15	10
2832A,B,C,			22	(W)	4	(BL)	22	4	15	10
2832BM,CM,DM,EM †	22	(W)			4	(BL)	22	4	15	10
833B,C			22	(W)	4	(BL)	22	4	15	10
833BM,CM,DM,EM †	22	(W)			4	(BL)	22	4	15	10
2833B,C			22	(W)	4	(BL)	22	4	15	10
2833BM,CM,DM,EM †	22	(W)			4	(BL)	22	4	15	10

Note: RJ35X should not be connected in COM KEY telephone sets equipped with privacy because of possible circuit incompatibility.

* Remove designated leads from terminals in "T1" and "R1" columns—connect to (W) and (BL) leads from D6AA cord using spare terminals or D-161488 connectors. Connect other cord leads to terminals shown in "D6AA cord" column.

† When using these sets with speakerphone or headset adjunct, it may be necessary to strap out the line switch contact in the tip of the line (BL leads).

‡ In older sets not equipped with a RECALL button, remove the (G) line switch lead from terminal 6 and connect to (BL) D6AA cord lead. Connect (R) cord lead to terminal 6.