


## REFERENCE

608-, 618-, 634-, 635-, 636-, 637-, 638-, 639-,  
682-, AND 683-TYPE TELEPHONE SETS

## IDENTIFICATION



### 1. GENERAL

- 1.01** This section contains information on 600-series CALL DIRECTOR® telephone sets.
- 1.02** The reasons for reissuing this section are listed below. Revision arrows are used to emphasize the more significant changes.
- Add the 620A, 620C, 621A, and 621C faceplate assemblies
  - Show the 20R1, 20T1, 21R1, and 21T1 faceplate assemblies MD.
- 1.03** All four letter coded sets are furnished from the factory in only the numerical code (1), and all other numerical coded sets are rated MD. Sets can be equipped with different modular key arrangements by ordering the appropriate 635-, 658-type key, or 76A lamp socket. Refer to the appropriate table in this section for recommended layout arrangements of field-installed keys.
- 1.04** The 634DAMS1, 635DAMS1, 636CAMS1, 637DAMS1, 638CAMS1, 639DAMS1, 682AAMS1, and 683AAMS1 sets are furnished equipped with a new line switch which breaks both the tip and ring side of the line instead of the ring side only.
- 1.05** Early models designated with a single letter code (A, B, C, or D) are equipped with 598-, 599-, 656-, or 657-type keys using a KS-type connector. Later models designated by a double letter (AA, CA, or DA) and triple letter (AAM, CAM, or DAM) are equipped with 635-type keys using 508- or 509-type plugs. The 598- and 599-type keys are electrically and mechanically interchangeable with the 656- and 657-type. None of these keys, however, are compati-

ble with the 635-type keys and cannot be intermixed. Current production 635-type keys have been modified for easy lamp replacement. Remove lamp cap and insert 553C tool through hole in top of button. In early production keys, it was necessary to remove faceplate, key collar, and button to change lamps.

**1.06** All triple and four letter coded sets (modular) are furnished from the factory equipped with a G15A handset, H4DU handset cord, and 616E jack assembly. Early model (nonmodular) single and double letter code sets were furnished equipped with a G3-type handset and cord.

**1.07** All single, double, and triple letter coded sets are rated MD and will be replaced by modular four letter coded sets, respectively, except for the 608C and 618B sets which will be replaced by the 682AAMS1 and 683AAMS1 sets, respectively.

### 2. IDENTIFICATION

- 2.01** The faceplate assemblies listed in Tables C through G consist of a faceplate and three mats; one each in Silver (-78), Gold (-79), and the coordinated color. The coordinated color suffix is found in Table B.
- 2.02** Table A lists the major features of these CALL DIRECTOR telephone sets, refer to Table B for ordering information.
- 2.03** The 667B (MD) transmitter may be modified with the D-180196 Kit of Parts to reduce pickup due to mechanical vibrations.
- 2.04** Ringer volume control is in two steps. A third step to silence the ringer is blocked by a stop screw which can be removed.
- 2.05** The 811218585 blocking rings or 812365948 button stops are no longer shipped loose with

### NOTICE

Not for use or disclosure outside the  
Bell System except under written agreement

**SECTION 502-601-101**

each set. These items must be ordered separately if required.

**2.06** Current production telephone sets are equipped with a satin-silver (-87) mounting cord.

**2.07** Current production telephone sets are factory-equipped with a KS-20419L1 (10 volt ac only) buzzer. Provisions are made for mounting one KS-8109L2 buzzer when an additional buzzer is desired.

**3. TABLE INDEX**

**3.01** The following is a table index:

- Table A — Major Features
- Table B — Ordering Guide
- Table C — Faceplates and Mats For 608- and 618-Type Telephone Sets
- Table D — Faceplates and Mats For 634- and 635-Type Telephone Sets
- Table E — Faceplates and Mats For 636- and

**637-Type Telephone Sets**

- Table F — Faceplates and Mats For 638- and 639-Type Telephone Sets
- Table G — Faceplates and Mats For 682- and 683-Type Telephone Sets
- Table H — Bezel and Housing Assembly
- Table I — Replaceable Components
- Table J — Key Arrangements—18-Button Single Letter (MD) Code Sets
- Table K — Key Arrangements—18-Button Double Letter (MD), Triple Letter (MD), and Four Letter Code Sets
- Table L — Key Arrangements—30-button Single Letter (MD) Code Sets
- Table M — Key Arrangements—30-Button Double Letter (MD), Triple Letter (MD), and Four Letter Code Sets
- Table N — Key Identification

**TABLE A**  
**MAJOR FEATURES**

FEATURE \ SET CODE										
	608	618	634	635	636	637	638	639	682	683
18-Button		•	•		•		•		•	
30-Button	•			•		•		•		•
2-/4-Wire Operation	•	•							•	•
Handset/Headset Operation	•	•			•	•	•	•	•	•
Concentrator			•	•			•	•		
Speakerphone	•	•	•	•					•	•
1A KTS					•	•				
1A1, 1A2, 6A, and 6B KTS	•	•	•	•	•	•	•	•	•	•

**TABLE B**  
**ORDERING GUIDE**

TELEPHONE SET		FACEPLATE	
COLOR	COLOR SUFFIX	COORDINATED COLOR	COLOR SUFFIX
Black	(-03)	Charcoal	(-70)
Green	(-51)	Light Green	(-71)
Yellow	(-56)	Light Yellow	(-72)
White	(-58)	Light Gray	(-73)
Light Beige	(-60)	Muted Beige	(-75)
Aqua Blue	(-62)	Muted Blue	(-76)
Any Color Tel Set *		Silver †	(-78)
		Gold †	(-79)

\* Silver or gold for sets using clear faceplates with mats only.

† The 620A-, 620C-, 621A-, and 621C- faceplate assemblies are not available in this color.

TABLE C

## FACEPLATES AND MATS FOR 608- AND 618-TYPE TELEPHONE SETS

TEL SET	SET CODE	FACEPLATE ASSEMBLY	FACEPLATE ONLY	MATS (NOTES 1 AND 2)
608B, C	3, 12, 17, 20	21G1	812066157 (P-20F615)	818861700 (P-88F170) 818861718 (P-88F171) 818861726 (P-88F172) 818861734 (P-88F173) 818861759 (P-88F175) 818861767 (P-88F176) 818861783 (P-88F178) 818861791 (P-88F179)
		21M1	812066199 (P-20F619)	818668709 (P-86F870) 818668717 (P-86F871) 818668725 (P-86F872) 818668733 (P-86F873) 818668758 (P-86F875) 818668766 (P-86F876) 818668782 (P-86F878) 818668790 (P-86F879)
618A, B	2, 7, 11, 13	20E1-	812066041 (P-20F604)	818860702 (P-88F070) 818860710 (P-88F071) 818860728 (P-88F072) 818860736 (P-88F073) 818860751 (P-88F075) 818860769 (P-88F076) 818860785 (P-88F078) 818860793 (P-88F079)
		20G1-	812066066 (P-20F606)	818669707 (P-86F970) 818669715 (P-86F971) 818669723 (P-86F972) 818669731 (P-86F973) 818669756 (P-86F975) 818669764 (P-86F976) 818669780 (P-86F978) 818669798 (P-86F979)

**Note 1.** Seventh and eighth digits of comcode number designate color code as shown in Table B

**Note 2.** Last two digits of P-number designate color code as shown in Table B

◆TABLE D◆

## FACEPLATES AND MATS FOR 634- AND 635-TYPE TELEPHONE SETS

TEL SET	SET CODE	FACEPLATE ASSEMBLY	FACEPLATE ONLY	MATS (NOTES 1 AND 2)
634A, B, C, D	1, 2, 6, 7, 9, 10	20A1-	812066009 (P-20F600)	818060709 (P-80F070) 818060717 (P-80F071) 818060725 (P-80F072) 818060733 (P-80F073) 818060758 (P-80F075) 818060766 (P-80F076) 818060782 (P-80F078) 818060790 (P-80F079)
	4	20B1-	812066017 (P-20F601)	
	11, 13	20C1-	812066025 (P-20F602)	818661704 (P-86F170) 818661712 (P-86F171) 818661720 (P-86F172) 818661738 (P-86F173) 818661753 (P-86F175) 818661761 (P-86F176) 818661787 (P-86F178) 818661795 (P-86F179)
	12	20D1-	812066033 (P-20F603)	
634DA, 634DAM, 634DAMS1	1, 2, 4, 6, 7	620A- 20R1-*	802697003* (P-269700)*	828230706 (P-82L070)* 828230714 (P-82L071)* 828230722 (P-82L072)* 828230730 (P-82L073)* 828230755 (P-82L075)* 828230763 (P-82L076)* 828230789 (P-82L078)* 828230797 (P-82L079)*
	11, 12, 13	20S1-	802697011 (P-269701)	828231704 (P-82L170) 828231712 (P-82L171) 828231720 (P-82L172) 828231738 (P-82L173) 828231753 (P-82L175) 828231761 (P-82L176) 828231787 (P-82L178) 828231797 (P-82L179)
632A, C, D	1, 2, 3, 10, 11, 12	21A1-	812066090 (P-20F609)	818664708 (P-86F470) 818664716 (P-86F471) 818664724 (P-86F472) 818664732 (P-86F473) 818664757 (P-86F475) 818664765 (P-86F476) 818664781 (P-86F478) 818664799 (P-86F479)
	4	21B1-	812066108 (P-20F610)	
	16, 17	21C1-	812066116 (P-20F611)	818665705 (P-86F570) 818665713 (P-86F571) 818665721 (P-86F572) 818665739 (P-86F573) 818665754 (P-86F575) 818665762 (P-86F576) 818665788 (P-86F578) 818665796 (P-86F579)
	18	21D1-	812066124 (P-20F612)	

See notes and footnotes at end of table.

♦TABLE D♦ (Contd)

## FACEPLATES AND MATS FOR 634- AND 635-TYPE TELEPHONE SETS

TEL SET	SET CODE	FACEPLATE ASSEMBLY	FACEPLATE ONLY	MATS (NOTES 1 AND 2)
635DA, 635DAM, 635DAMS1	1, 2, 3, 4, 10, 11, 12	621A- 21R1-*	802697029 * (P-269702)*	828234708 (P-82L470)* 828234716 (P-82L471)* 828234724 (P-82L472)* 828234732 (P-82L473)* 828234757 (P-82L475)* 828234765 (P-82L476)* 828234781 (P-82L478)* 828234799 (P-82L479)*
	16, 17, 18	21S1	802697037 (P-269703)	828235705 (P-82L570) 828235713 (P-82L571) 828235721 (P-82L572) 828235739 (P-82L573) 828235754 (P-82L575) 828235762 (P-82L576) 828235788 (P-82L578) 828235796 (P-82L579)

**Note 1.** Seventh and eight digits of comcode number designate color code as shown in Table B

**Note 2.** Last two digits of P-number designate color code as shown in Table B.

\* Manufacture discontinued.

♦TABLE E♦

## FACEPLATES AND MATS FOR 636- AND 637-TYPE TELEPHONE SETS

TEL SET	SET CODE	FACEPLATE ASSEMBLY	FACEPLATE ONLY	MATS (NOTES 1 AND 2)
636A, B, C	1, 2, 6, 7, 9, 10	20E1-	812066041 (P-20F604)	818860702 (P-88F070) 818860710 (P-88F071) 818860728 (P-88F072)
	4	20F1-	812066058 (P-20F605)	818860736 (P-88F073) 818860751 (P-88F075) 818860769 (P-88F076)
	14, 15	20H1-	812066074 (P-20F607)	818860785 (P-88F078) 818860793 (P-88F079)
636CA, 636CAM, 636CAMS1	1, 2, 4, 6, 7, 14, 15	620C- 20T1-*	802697086 * (P-269708) *	828238709 (P-82L870)* 828238717 (P-82L871)* 828238725 (P-82L872)* 828238733 (P-82L873)* 828238758 (P-82L875)* 828238766 (P-82L876)* 828238782 (P-82L878)* 828238790 (P-82L879)*
637A, C, D	1, 2, 3, 10, 11, 12, 13, 14, 15	21G1-	812066157 (P-20F615)	818861700 (P-88F170) 818861718 (P-88F171)
	4	21H1-	812066165 (P-20F616)	818861726 (P-88F172) 818861734 (P-88F173)
	5	21J1-	818066173 (P-20F617)	818861759 (P-88F175) 818861767 (P-88F176)
	9, 19	21K1-	812066181 (P-20F618)	818861783 (P-88F178) 818861791 (P-88F179)
637DA, 637DAM, 637DAMS1	1, 2, 3, 4, 5, 9, 10, 11, 12, 19	621C- 21T1-*	802697102 * (P-269710) *	828332700 (P-83L270)* 828332718 (P-83L271)* 828332726 (P-83L272)* 828332734 (P-83L273)* 828332759 (P-83L275)* 828332767 (P-83L276)* 828332783 (P-83L278)* 828332791 (P-83L279)*

**Note 1.** Seventh and eight digits of comcode number designate color code as shown in Table B.

**Note 2.** Last two digits of P-number designate color code as shown in Table B.

\* Manufacture discontinued.

♦TABLE F♦

## FACEPLATES AND MATS FOR 638- AND 639-TYPE TELEPHONE SETS

TEL SET	SET CODE	FACEPLATE ASSEMBLY	FACEPLATE ONLY	MATS (NOTES 1 AND 2)
638A, B, C	1, 2, 6, 7, 9, 10	20E1-	812066041 (P-20F604)	818860702 (P-88F070) 818860710 (P-88F071) 818860728 (P-88F072) 818860736 (P-88F073) 818860751 (P-88F075)
	4	20F1-	812066058 (P-20F605)	818860769 (P-88F076) 818860785 (P-88F078) 818860793 (P-88F079)
638CA, 638CAM, 638CAMS1	1, 2, 4, 6, 7	620C- 20T1-†	802697086† (P-269708)†	828238709 (P-82L870)† 828238717 (P-82L871)† 828238725 (P-82L872)† 828238733 (P-82L873)† 828238758 (P-82L875)† 828238766 (P-82L876)† 828238782 (P-82L878)† 828238790 (P-82L879)†
639A, C, D*	1, 2, 3, 10, 11, 12, 15	21G1-	812066157 (P-20F615)	818861700 (P-88F170) 818861718 (P-88F171)
	4	21H1-	812066165 (P-20F616)	818861726 (P-88F172) 818861734 (P-88F173)
	5	21J1-	812066173 (P-20F617)	818861759 (P-88F175) 818861767 (P-88F176)
	9	21K1-	812066181 (P-20F618)	818861783 (P-88F178) 818861791 (P-88F179)
639DA, 639DAM, 639DAMS1	1, 2, 3, 4, 10, 11, 12	621C- 21T1-†	802697102† (P-269710)†	828332700 (P-83L270)† 828332718 (P-83L271)† 828332726 (P-83L272)† 828332734 (P-83L273)† 828332759 (P-83L275)† 828332767 (P-83L276)† 828332783 (P-83L278)† 828332791 (P-83L279)†

**Note 1.** Seventh and eight digits of comcode number designate color code as shown in Table B.

**Note 2.** Last two digits of P-number designate color code as shown in Table B.

\* 639C, D sets not available in 5, 9, 15 code.

† Manufacture discontinued.

TABLE G

## FACEPLATES AND MATS FOR 682- AND 683-TYPE TELEPHONE SETS

TEL SET	SET CODE	FACEPLATE ASSEMBLY	FACEPLATE ONLY	MATS (NOTES 1 AND 2)
682AA, 682AAM, 682AAMS1	1, 2, 6, 7	620C- 20T1-*	802697086 * (P-269708)*	828238709 (P-82L870)* 828238717 (P-82L871)* 828238725 (P-82L872)* 828238733 (P-82L873)* 828238758 (P-82L875)* 828238766 (P-82L876)* 828238782 (P-82L878)* 828238790 (P-82L879)*
	11, 13	20U1-	802697094 (P-269709)	828239707 (P-82L970) 828239715 (P-82L971) 828239723 (P-82L972) 828239731 (P-82L973) 828239756 (P-82L975) 828239764 (P-82L976) 828239780 (P-82L978) 828239798 (P-82L979)
683AA, 683AAM, 683AAMS1	1, 2, 3, 4, 5, 9, 10, 11, 12, 19	621C- 21T1-*	802697102 * (P-269710)*	828332700 (P-83L270)* 828332718 (P-83L271)* 828332726 (P-83L272)* 828332734 (P-83L273)* 828332759 (P-83L275)* 828332767 (P-83L276)* 828332783 (P-83L278)* 828332791 (P-83L279)*
	17	21U1-	802697110 (P-269711)	828333708 (P-83L370) 828333716 (P-83L371) 828333724 (P-83L372) 828333732 (P-83L373) 828333757 (P-83L375) 828333765 (P-83L376) 828333781 (P-83L378) 828333799 (P-83L379)

**Note 1.** Seventh and eight digits of comcode number designate color code as shown in Table B.

**Note 2.** Last two digits of P-number designate color code as shown in Table B.

\* Manufacture discontinued

♦TABLE H♦

## BEZEL AND HOUSING ASSEMBLY

TEL SET (NOTE 1)	BEZEL ASSY (NOTES 2 AND 3)	HOUSING ASSY (NOTES 4 AND 5)
608B	811159953 (P-11E995)	828119032 (P-81J903) 828119511 (P-81J951) 828119560 (P-81J956) 828119586 (P-81J958) 828119602 (P-81J960) 828119628 (P-81J962)
608C	812652121 (P-26E212)	818433039 (P-84C303) 818433518 (P-84C351) 818433567 (P-84C356) 818433583 (P-84C358) 818433609 (P-84C360) 818433625 (P-84C362)
618A	811159946 (P-11E994)	828118034 (P-81J803) 828118513 (P-81J851) 828118562 (P-81J856) 828118588 (P-81J858) 828118604 (P-81J860) 828118620 (P-81J862)
618B	814455085 (P-44E508)	818432031 (P-84C203) 818432510 (P-84C251) 818432569 (P-84C256) 818432585 (P-84C258) 818432601 (P-84C260) 818432627 (P-84C262)
634A, B, C, D		818430035 (P-84C003) 818430514 (P-84C051) 818430563 (P-84C056) 818430589 (P-84C058) 818430605 (P-84C060) 818430621 (P-84C062)
634DA		840473037 840473516 840473565 840473581 840473607 840473623
634DAM, 634DAMS1	814455085 (P-44E508)	840712012 (Black) 840712020 (Green) 840712038 (Yellow) 840712046 (White) 840712053 (Beige) 840712061 (Aqua Blue)
635A, C, D	812652121 (P-26E212) or 840155642	818431033 (P-84C103) 818431512 (P-84C151) 818431561 (P-84C156) 818431587 (P-84C158) 818431603 (P-84C160) 818431629 (P-84C162)

See notes at end of table.

TABLE H (Contd)

## BEZEL AND HOUSING ASSEMBLY

TEL SET (NOTE 1)	BEZEL ASSY (NOTES 2 AND 3)	HOUSING ASSY (NOTES 4 AND 5)
635DA	840155642	840474035 840474514 840474563 840474589 840474605 840474621
635DAM, 635DAMS1		840712269 (Black) 840712277 (Green) 840712285 (Yellow) 840712293 (White) 840712301 (Beige) 840712319 (Aqua Blue)
636A, B, C	814455085 (P-44E508)	828118034 (P-81J803) 828118513 (P-81J851) 828118562 (P-81J856) 828118588 (P-81J858) 828118604 (P-81J860) 828118620 (P-81J862)
636CA		828534032 (P-85L403) 828534511 (P-85L451) 828534560 (P-85L456) 828534586 (P-85L458) 828534602 (P-85L460) 828534628 (P-85L462)
636CAM, 636CAMS1		840712517 (Black) 840712525 (Green) 840712533 (Yellow) 840712541 (White) 840712558 (Beige) 840712566 (Aqua Blue)
637A, C, D	812652121 (P-26E212) or 840155642	828119032 (P-81J903) 828119511 (P-81J951) 828119560 (P-81J956) 828119586 (P-81J958) 828119602 (P-81J960) 828119628 (P-81J962)
637DA	840155642	828535039 (P-85L503) 828535518 (P-85L551) 828535567 (P-85L556) 828535583 (P-85L558) 828535609 (P-85L560) 828535625 (P-85L562)
637DAM, 637DAMS1	840155642	840712764 (Black) 840712772 (Green) 840112780 (Yellow) 840712798 (White) 840712806 (Beige) 840712814 (Aqua Blue)

See notes at end of table.

♦TABLE H♦ (Contd)

## BEZEL AND HOUSING ASSEMBLY

TEL SET (NOTE 1)	BEZEL ASSY (NOTES 2 AND 3)	HOUSING ASSY (NOTES 4 AND 5)
638A, B, C	814455085 (P-44E508)	828118034 (P-81J803) 828118513 (P-81J851) 828118562 (P-81J856) 828118588 (P-81J858) 828118604 (P-81J860) 828118620 (P-81J862)
638CA	814455085 (P-44E508)	828534032 (P-85L403) 828534511 (P-85L451) 828534560 (P-85L456) 828534586 (P-85L458) 828534602 (P-85L460) 828534628 (P-85L462)
638CAM, 638CAMS1		840712517 (Black) 840712525 (Green) 840712533 (Yellow) 840712541 (White) 840712558 (Beige) 840712566 (Aqua Blue)
639A, C, D	812652121 (P-26E212 or 840155642	828119032 (P-81J903) 828119511 (P-81J951) 828119560 (P-81J956) 828119586 (P-81J958) 828119602 (P-81J960) 828119628 (P-81J962)
639DA	840155642	828535039 (P-85L503) 828535518 (P-85L551) 828535567 (P-85L556) 828535583 (P-85L558) 828535609 (P-85L560) 828535625 (P-85L562)
639DAM, 639DAMS1		840712764 (Black) 840712772 (Green) 840712780 (Yellow) 840712798 (White) 840712806 (Beige) 840712814 (Aqua Blue)
682AA	814455085 (P-44E508)	828534032 (P-85L403) 828534511 (P-85L451) 828534560 (P-85L456) 828534586 (P-85L458) 828534602 (P-85L460) 828534628 (P-85L462)
682AAM, 682AAMS1		840712517 (Black) 840712525 (Green) 840712533 (Yellow) 840712541 (White) 840712558 (Beige) 840712566 (Aqua Blue)

See notes at end of table.

♦TABLE H♦ (Contd)

## BEZEL AND HOUSING ASSEMBLY

TEL SET (NOTE 1)	BEZEL ASSY (NOTES 2 AND 3)	HOUSING ASSY (NOTES 4 AND 5)
683AA	840155642	828535039 (P-85L503) 828535518 (P-85L551) 828535567 (P-85L556) 828535583 (P-85L558) 828535609 (P-85L560) 828535625 (P-85L562)
683AAM, 683AAMS1		840712764 (Black) 840712772 (Green) 840712780 (Yellow) 840712798 (White) 840712806 (Beige) 840712814 (Aqua Blue)

**Note 1.** Sets with the 620A, 620C, 621A, and 621C faceplate assembly do not require a bezel assembly.

**Note 2.** Components of 814455085 (P-44E508) bezel assembly:

- 814455051 (P-44E505) Upper Bezel
- 814455069 (P-44E506) Lower Bezel
- 814455077 (P-44E507) Bezel Retainer
- 997126610 (RM-712661) Bezel Clip
- 840993778 Bezel Spring

**Note 3.** Components of 840155642 bezel assembly:

- 834080939 (P-404093) Upper Bezel
- 834080947 (P-404094) Lower Bezel
- 814455077 (P-44E507) Bezel Retainer
- 997126610 (RM-712661) Bezel Clip
- 840993778 Bezel Spring

**Note 4.** Seventh and eighth digits of comcode number designate color code as shown in Table B unless otherwise specified.

**Note 5.** Last two digits of P-number designate color as shown in Table B.

**TABLE I**  
**REPLACEABLE COMPONENTS**

TEL SET	MTG CORD	DIAL (NOTE 1)	RINGER	HANDSET (NOTES 2 AND 3)
608B, C	D200F-87	8R-58, 8RA-58, 8C-58, or 8CA-58	N1A or T1A	G3-Type or G15A
618A, B	D120C-87			
634A, B, C, D	D50L-87			
634DA, DAM, DAMS1	D50BD-87			
635A, C, D	D80B-87			
635DA, DAM, DAMS1	D80E-87			
636A, B, C	D120C-87			
636CA, CAM, CAMS1	D120M-87			
637A, C, D	D200F-87			
637DA, DAM, DAMS1	D200AA-87			
638A, B, C	D50L-87			
638CA, CAM, CAMS1	D50BD-87			
639A, C, D	D80B-87			
639DA, DAM, DAMS1	D80E-87			
682AA, AAM, AAMS1	D120M-87	8C-58 or 8CA-58		
683AA, AAM, AAMS1	D200AA-87			

**Note 1.** Sets to be used with speakerphone must be equipped with an 8C or 8CA dial.

**Note 2.** Color suffix from Table B must be added.

**Note 3.** Single and double letter coded sets are equipped with G3-type handset and cord. Tripple and four letter coded sets are equipped with G15A handset, H4DU handset cord, and 616E jack assembly.

**TABLE J**  
**KEY ARRANGEMENTS— 18 BUTTON SINGLE LETTER (MD) CODE SETS**  
**(SEE NOTE)**

TEL SET		1ST MODULE	2ND MODULE	3RD MODULE
618A, B 634A, B, C, D 636A, B, C 638A, B, C*	1	599A 657A	598A 656A	105B
	2			598A 656A
	4			617A
	6	105B		
	7	598A 656A		
	9	105B		
	10	598A 656A	617A	598A 656A
	11	599A 657A		667B (MD) Trmtr
	12		598A 656A	
	13	59A		
	14			599A 657A
	15		599B 657B	

**Note:** For button arrangement on keys, refer to Table N.

\* Refer to Tables C, D, E, and F for set codes.

TABLE K

**KEY ARRANGEMENTS—18-BUTTON DOUBLE LETTER (MD), TRIPLE LETTER (MD),  
AND FOUR LETTER CODED SETS (NOTES 1 AND 2)**

TEL SET		1ST MODULE	2ND MODULE	3RD MODULE	
634DA, DAM, DAMS1 636CA, CAM, CAMS1 638CA, CAM, CAMS1 682AA, A.AM, AAMS1 *	1	635A5C	635G5C	111B	
	2			635G5C	
	4			658A	
	6	635AD5C		111B	
	7			635G5C	
	11	635A5C		658A	679A (MD) Trmtr
	12				
	13	635AD5C	635G5C	76A	
	14	635A5C			
	15	635AD5C			

**Note 1.** Refer to Table B for available set colors.

**Note 2.** For button arrangement on keys, refer to Table N.

\* Refer to Tables D, E, F, and G for all set codes.

TABLE L

## KEY ARRANGEMENTS—30 BUTTON SINGLE LETTER (MD) CODE SETS (SEE NOTE)

TEL SET		1ST MODULE	2ND MODULE	3RD MODULE	4TH MODULE	5TH MODULE
608B, C 635A, C, D 637A, C, D 639A, C, D*	1	599A 657A	598A 656A	598A 656A	105B	105B
	2				598A 656A	598A 656A
	3					
	4					617A
	5				617A	59A
	9	105B			105B	
	10	599B 657B				
	11				598A 656A	598A 656A
	12	598A 656A			105B	105B
	13				598A 656A	598A 656A
	14					598A 656A
	15	599A 657A			105B	667B (MD) Trmtr
	16				598A 656A	
	17				617A	
	18				598A 656A	59A
	19	599B 657B			667B (MD) Trmtr	
	20				598A 656A	

**Note:** For button arrangement on keys, refer to Table N.

\* Refer to Tables C, D, E, and F for all set codes.

TABLE M

KEY ARRANGEMENTS—30-BUTTON DOUBLE LETTER (MD), TRIPLE LETTER (MD),  
AND FOUR LETTER CODED SETS (NOTES 1 AND 2)

TEL SET		1ST MODULE	2ND MODULE	3RD MODULE	4TH MODULE	5TH MODULE	
635DA,DAM,DAMS1 637DA,DAM,DAMS1 639DA,DAM,DAMS1 683AA,AAM,AAMS1*	1	635A5C	635G5C	635G5C	111B	111B	
	2				635G5C	635G5C	
	3					658A	
	4					76A	
	5				635AD5C	111B	111B
	9	635G5C				635G5C	635G5C
	10					111B	679A (MD) Trmtr
	11					635G5C	
	12	635G5C					
	16	635A5C			111B	679A (MD) Trmtr	
	17				635G5C		
	18				658A		
	19	635G5C			76A		

**Note 1.** Refer to Table B for available set colors.

**Note 2.** For button arrangement on keys, refer to Table N.

\* Refer to Tables D, E, F, and G for all set codes.

**TABLE N**  
**KEY IDENTIFICATION**

SINGLE LETTER CODE SETS A, B, C, D	598A (MD) OR 656A	599A (MD) OR 657A	599B (MD) OR 657B		617A	59A	667B (MD)	105B
DOUBLE, TRIPLE, AND FOUR LETTER CODE SETS AA, AAM, AAMS1, CA, CAM, CAMS1, DA, DAM, AND DAMS1	635G5C	635A5C		635AD5C	658A	76A	679A (MD)	111B
Button Arrangement	P P P P P P	P P P P P H	C P P P P H	P P P P C H	S S S S S S S S S S S S	L L L L L L L L L L L L	OFF ON T V	B B B B B B

P — Pickup  
H — Hold  
C — Cutoff  
S — Signaling  
L — Lamp  
B — Blank

OFF  
ON Speakephone  
T Transmitter  
V