

KS-16923, LIST 1 TELEPHONE ANSWERING SET INSTALLATION AND CONNECTIONS

1. GENERAL

1.01 This section is reissued to add information on installation of KS-16923, List 11 recording tape (See 4.08).

1.02 It is intended that CD- and SD-95295-01 be used with this section.

2. POWER

2.01 The KS-16923, List 1 telephone answering set, Fig. 1, is designed to operate on 110/125-volt, 60-cycle ac power supply.




Fig. 1 — KS-16923, List 1, Telephone Answering Set, Cover Raised

SECTION 514-150-200

2.02 In no case should the answering set be connected to *direct current*. This would result in serious damage to answering set.

2.03 If direct current is the only available power supply, a KS-15662, List 1 inverter must be used. Installation of this inverter is covered in the section entitled KS-15662 DC-AC Inverter for Use with Telephone Answering Sets.

2.04 A 1-ampere (AGC 1) fuse is provided in answering set for protection (Fig. 2).

2.05 Customer must provide and maintain a standard ac outlet within reach of the 6-foot power cord. Outlet must not be controlled by a switch.

3. LOCATION

3.01 Locate telephone answering set in accordance with customer's wishes after considering the following:

(a) Avoid placing set where it will be exposed to weather or extreme heat.

(b) Locate answering set on table, shelf, or desk that is strong enough to support 65 pounds, its approximate weight.

4. INSTALLATION



Do not connect telephone answering set to power supply until after all other installation work has been completed.

Telephone Answering Set

4.01 Exercise precaution to avoid marring desk, tables, etc.

4.02 Remove cover of answering set to make connections. Remove screws and lift rear panel out (see Fig. 1 and 3).




Fig. 2 — KS-16923, List 1 Telephone Answering Set, Left Side




Fig. 3 — KS-16923, List 1 Telephone Answering Set, Rear Panel Removed

- 4.03** Use a suitable mounting cord between the 42A connecting block and terminal block of telephone answering set.
- 4.04** Insert mounting cord through slot provided in telephone answering set to left of power cord entrance. Anchor cord with suitable fastener using screw hole in front of fuse holder (Fig. 3).
- 4.05** Make connections for type of service required as covered in Fig. 8.
- 4.06** Install KS-16923, List 10 announcement cartridge.
- (1) Place announcement cartridge in its hub.
 - (2) Pull tape from center of cartridge. Pull only enough tape to thread properly.
 - (3) Make sure the tape rides in the groove of guides and that actuator assembly lever rides on top and center of tape.
 - (4) Actuator assembly lever shall drop into slot in tape to stop announce motor when the tape is indexed.
 - (5) Follow path of tape as shown in Fig. 4.




Fig. 4—KS-16923, List 10 Announcement Cartridge

4.07 Check KS-16923, List 11 recording tape.

Recording tape and reels are attached and threaded at factory. They should be inspected before operation of set. Follow path of tape as shown in Fig. 5.

4.08 Installation procedures for KS-16923 List

11 recording tape differ on earlier model sets. Installation procedures for all sets are covered in the plant series section entitled, KS-16923 List 1 Telephone Answer Set, Mechanical Adjustments and Maintenance.

Caution: 5¾-inch reels must be used with earlier model sets with serial numbers 1101 and lower. Do not use 5-inch reels on these sets unless the list 5 recorder has been modified. Recorders which have been modified may be identified by a red marking "RB"

in ⅛-inch characters located to the left of the KS-16923, List 1 name plate at rear of set. Do not use any other reels or tape on these machines. Refer to section covering KS-16923, List 1 telephone answering set, identification and assembly of parts, for description of 5-inch and 5¾-inch reels.

4.09 With AUTO ANSWER OFF key in OFF position, insert power cord plug in power outlet and secure plug as described in the section covering power supply, station systems, installation and maintenance.

4.10 The telephone answering set should now be ready for operation.

4.11 For operation procedure see the section covering KS-16923, List 1 telephone answering set, operation.




Fig. 5 — KS-16923, List 11 Recording Tape

4.12 Foot switch KS-16923, List 6:

- (1) Insert plug of foot switch (Fig. 6) into foot switch jack on telephone answering set (Fig. 1).

4.13 Backspace unit KS-16923, List 8:

- (1) Insert plug of backspace unit (Fig. 7) into foot switch jack of telephone answering set (Fig. 1).
- (2) Insert plug of foot switch into jack of backspace unit (Fig. 7).

- 4.14** The amount of backspace is readily controlled by means of a potentiometer knob (Fig. 1) up to approximately a dozen words.

- 4.15** Instruct customer regarding correct operation. Caution customer against placing objects on telephone answering set.

5. OPTIONS

THINK *Be sure power is off when installing or removing strap from terminals 1 and 2.*

- 5.01** *Talk-down tone:* To disable the 1400-cycle low-level talk-down tone that is transmitted on calling party's line when voice level drops below -45 volume units or disappears entirely, remove strap from terminals 1 and 2 of telephone answering set terminal block.






Fig. 6 – Foot Switch



Front View



Rear View

Fig. 7 – Backspace Unit

5.02 Dictate-button lock: To lock dictate button so that previously recorded announcement cannot be erased:

- (1) Loosen locking screw (Fig. 3).

- (2) Slide locking detail under spring assembly and tighten locking screw (Fig. 3).


5.03 Do not use options listed above without proper authorization.

6. CONNECTIONS (Fig. 8)

TABLE A

E2	E1	E	G	T	R	A	AI	1	2
○	○	○	○	○	○	○	○	○	○

KS-16923, LIST 1 TELEPHONE ANSWERING SET TERMINAL BLOCK



Note 1: Set may be connected on either side of KTU.

* See Table A for mounting cord connections.

† For terminal numbers, see section covering 1A key telephone system, maintenance.




Fig. 8 - KS-16923, List 1 Telephone Answering Set Connections

SECTION 514-150-200




Fig. 8 - KS-16923, List 1 Telephone Answering Set Connections (Cont)

TABLE A

MOUNTING CORD CONNECTIONS

Cord Conductor Color	At Connecting Block on Tel Ans Set	Side of Line Wire to Which Cord Conductor Is Terminated		
		Individual, PBX, or Bridged Service	2-Party Selective or Message Rate Service*	
			Ring Party	Tip Party
Red	R	Ring	Ring	Tip
Green	T	Tip	Tip	Ring
Yellow	G	Tip	Ground	Ground

* Remove strap between T and G on telephone answering set connecting block and place local ground on G.