



Quick Start for Hardware Installation:

Avaya G700 Media Gateway

and

Avaya S8300 Media Server

555-233-150
Issue 5.1
January 2005

Copyright 2005, Avaya Inc.
All Rights Reserved

Notice

Every effort was made to ensure that the information in this document was complete and accurate at the time of printing. However, information is subject to change.

Warranty

Avaya Inc. provides a limited warranty on this product. Refer to your sales agreement to establish the terms of the limited warranty. In addition, Avaya's standard warranty language as well as information regarding support for this product, while under warranty, is available through the following Web site: <http://www.avaya.com/support>.

Preventing Toll Fraud

"Toll fraud" is the unauthorized use of your telecommunications system by an unauthorized party (for example, a person who is not a corporate employee, agent, subcontractor, or is not working on your company's behalf). Be aware that there may be a risk of toll fraud associated with your system and that, if toll fraud occurs, it can result in substantial additional charges for your telecommunications services.

Avaya Fraud Intervention

If you suspect that you are being victimized by toll fraud and you need technical assistance or support, in the United States and Canada, call the Technical Service Center's Toll Fraud Intervention Hotline at 1-800-643-2353.

Disclaimer

Avaya is not responsible for any modifications, additions or deletions to the original published version of this documentation unless such modifications, additions or deletions were performed by Avaya. Customer and/or End User agree to indemnify and hold harmless Avaya, Avaya's agents, servants and employees against all claims, lawsuits, demands and judgments arising out of, or in connection with, subsequent modifications, additions or deletions to this documentation to the extent made by the Customer or End User.

How to Get Help

For additional support telephone numbers, go to the Avaya support Web site: <http://www.avaya.com/support>. If you are:

- Within the United States, click the *Escalation Contacts* link. Then click the appropriate link for the type of support you need.
- Outside the United States, click the *Escalation Contacts* link. Then click the *International Services* link that includes telephone numbers for the international Centers of Excellence.

Providing Telecommunications Security

Telecommunications security (of voice, data, and/or video communications) is the prevention of any type of intrusion to (that is, either unauthorized or malicious access to or use of) your company's telecommunications equipment by some party.

Your company's "telecommunications equipment" includes both this Avaya product and any other voice/data/video equipment that could be accessed via this Avaya product (that is, "networked equipment").

An "outside party" is anyone who is not a corporate employee, agent, subcontractor, or is not working on your company's behalf. Whereas, a "malicious party" is anyone (including someone who may be otherwise authorized) who accesses your telecommunications equipment with either malicious or mischievous intent.

Such intrusions may be either to/through synchronous (time-multiplexed and/or circuit-based), or asynchronous (character-, message-, or packet-based) equipment, or interfaces for reasons of:

- Utilization (of capabilities special to the accessed equipment)
- Theft (such as, of intellectual property, financial assets, or toll facility access)
- Eavesdropping (privacy invasions to humans)
- Mischief (troubling, but apparently innocuous, tampering)
- Harm (such as harmful tampering, data loss or alteration, regardless of motive or intent)

Be aware that there may be a risk of unauthorized intrusions associated with your system and/or its networked equipment. Also realize that, if such an intrusion should occur, it could result in a variety of losses to your company (including but not limited to, human/data privacy, intellectual property, material assets, financial resources, labor costs, and/or legal costs).

5 HWSRQMELOW IRU<RXU&RP SDQ V 7H0FRP P XQFDMRQV 6 HFXUW

The final responsibility for securing both this system and its networked equipment rests with you - Avaya's customer system administrator, your telecommunications peers, and your managers. Base the fulfillment of your responsibility on acquired knowledge and resources from a variety of sources including but not limited to:

- Installation documents
- System administration documents
- Security documents
- Hardware-/software-based security tools
- Shared information between you and your peers
- Telecommunications security experts

To prevent intrusions to your telecommunications equipment, you and your peers should carefully program and configure:

- Your Avaya-provided telecommunications systems and their interfaces
- Your Avaya-provided software applications, as well as their underlying hardware/software platforms and interfaces
- Any other equipment networked to your Avaya products

TCP/IP Facilities

Customers may experience differences in product performance, reliability and security depending upon network configurations/design and topologies, even when the product performs as warranted.

Standards Compliance

Avaya Inc. is not responsible for any radio or television interference caused by unauthorized modifications of this equipment or the substitution or attachment of connecting cables and equipment other than those specified by Avaya Inc. The correction of interference caused by such unauthorized modifications, substitution or attachment will be the responsibility of the user. Pursuant to Part 15 of the Federal Communications Commission (FCC) Rules, the user is cautioned that changes or modifications not expressly approved by Avaya Inc. could void the user's authority to operate this equipment.

Product Safety Standards

This product complies with and conforms to the following international Product Safety standards as applicable:

Safety of Information Technology Equipment, IEC 60950, 3rd Edition, or IEC 60950-1, 1st Edition, including all relevant national deviations as listed in Compliance with IEC for Electrical Equipment (IECEE) CB-96A.

Safety of Information Technology Equipment, CAN/CSA-C22.2 No. 60950-00 / UL 60950, 3rd Edition, or CAN/CSA-C22.2 No. 60950-1-03 / UL 60950-1.

Safety Requirements for Information Technology Equipment, AS/NZS 60950:2000.

One or more of the following Mexican national standards, as applicable: NOM 001 SCFI 1993, NOM SCFI 016 1993, NOM 019 SCFI 1998.

The equipment described in this document may contain Class 1 LASER Device(s). These devices comply with the following standards:

- EN 60825-1, Edition 1.1, 1998-01
- 21 CFR 1040.10 and CFR 1040.11.

The LASER devices used in Avaya equipment typically operate within the following parameters:

Typical Center Wavelength	Maximum Output Power
830 nm - 860 nm	-1.5 dBm
1270 nm - 1360 nm	-3.0 dBm
1540 nm - 1570 nm	5.0 dBm

Luokan 1 Laserlaite

Klass 1 Laser Apparat

Use of controls or adjustments or performance of procedures other than those specified herein may result in hazardous radiation exposures. Contact your Avaya representative for more laser product information.

Electromagnetic Compatibility (EMC) Standards

This product complies with and conforms to the following international EMC standards and all relevant national deviations:

Limits and Methods of Measurement of Radio Interference of Information Technology Equipment, CISPR 22:1997, EN55022:1998, and AS/NZS 3548.

Information Technology Equipment - Immunity Characteristics - Limits and Methods of Measurement, CISPR 24:1997 and EN55024:1998, including:

- Electrostatic Discharge (ESD) IEC 61000-4-2
- Radiated Immunity IEC 61000-4-3
- Electrical Fast Transient IEC 61000-4-4
- Lightning Effects IEC 61000-4-5
- Conducted Immunity IEC 61000-4-6
- Mains Frequency Magnetic Field IEC 61000-4-8
- Voltage Dips and Variations IEC 61000-4-11

Power Line Emissions, IEC 61000-3-2: Electromagnetic compatibility (EMC) - Part 3-2: Limits - Limits for harmonic current emissions.

Power Line Emissions, IEC 61000-3-3: Electromagnetic compatibility (EMC) - Part 3-3: Limits - Limitation of voltage changes, voltage fluctuations and flicker in public low-voltage supply systems.

Federal Communications Commission Statement

Part 15:

Note: This equipment has been tested and found to comply with the limits for a Class A digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications. Operation of this equipment in a residential area is likely to cause harmful interference in which case the user will be required to correct the interference at his own expense.

Part 68: Answer-Supervision Signaling

Allowing this equipment to be operated in a manner that does not provide proper answer-supervision signaling is in violation of Part 68 rules. This equipment returns answer-supervision signals to the public switched network when:

- answered by the called station,
- answered by the attendant, or
- routed to a recorded announcement that can be administered by the customer premises equipment (CPE) user.

This equipment returns answer-supervision signals on all direct inward dialed (DID) calls forwarded back to the public switched telephone network. Permissible exceptions are:

- A call is unanswered.
- A busy tone is received.
- A reorder tone is received.

Avaya attests that this registered equipment is capable of providing users access to interstate providers of operator services through the use of access codes. Modification of this equipment by call aggregators to block access dialing codes is a violation of the Telephone Operator Consumers Act of 1990.

REN Number

For MCC1, SCC1, CMC1, G600, and G650 Media Gateways:

This equipment complies with Part 68 of the FCC rules. On either the rear or inside the front cover of this equipment is a label that contains, among other information, the FCC registration number, and ringer equivalence number (REN) for this equipment. If requested, this information must be provided to the telephone company.

For G350 and G700 Media Gateways:

This equipment complies with Part 68 of the FCC rules and the requirements adopted by the ACTA. On the rear of this equipment is a label that contains, among other information, a product identifier in the format US:AAAEQ##TXXXX. The digits represented by ## are the ringer equivalence number (REN) without a decimal point (for example, 03 is a REN of 0.3). If requested, this number must be provided to the telephone company.

For all media gateways:

The REN is used to determine the quantity of devices that may be connected to the telephone line. Excessive RENs on the telephone line may result in devices not ringing in response to an incoming call. In most, but not all areas, the sum of RENs should not exceed 5.0. To be certain of the number of devices that may be connected to a line, as determined by the total RENs, contact the local telephone company.

REN is not required for some types of analog or digital facilities.

Means of Connection

Connection of this equipment to the telephone network is shown in the following tables.

For MCC1, SCC1, CMC1, G600, and G650 Media Gateways:

0 DQXIDFWUHV 3RUW ,GHQMLHU	), & RGH	62 & 5 (1 \$ 6 & RGH	1 HZ RUN - DFNW
Off premises station	OL13C	9.0F	RJ2GX, RJ21X, RJ11C
DID trunk	02RV2-T	0.0B	RJ2GX, RJ21X
CO trunk	02GS2	0.3A	RJ21X
	02LS2	0.3A	RJ21X
Tie trunk	TL31M	9.0F	RJ2GX
Basic Rate Interface	02IS5	6.0F, 6.0Y	RJ49C
1.544 digital interface	04DU9-BN	6.0F	RJ48C, RJ48M
	04DU9-IKN	6.0F	RJ48C, RJ48M
	04DU9-ISN	6.0F	RJ48C, RJ48M
120A4 channel service unit	04DU9-DN	6.0Y	RJ48C

For G350 and G700 Media Gateways:

0 DQXIDFWUHV 3RUW ,GHQMLHU	), & RGH	62 & 5 (1 \$ 6 & RGH	1 HZ RUN - DFNW
Ground Start CO trunk	02GS2	1.0A	RJ11C
DID trunk	02RV2-T	AS.0	RJ11C
Loop Start CO trunk	02LS2	0.5A	RJ11C
1.544 digital interface	04DU9-BN	6.0Y	RJ48C
	04DU9-DN	6.0Y	RJ48C
	04DU9-IKN	6.0Y	RJ48C
	04DU9-ISN	6.0Y	RJ48C
Basic Rate Interface	02IS5	6.0F	RJ49C

For all media gateways:

If the terminal equipment (for example, the media server or media gateway) causes harm to the telephone network, the telephone company will notify you in advance that temporary discontinuance of service may be required. But if advance notice is not practical, the telephone company will notify the customer as soon as possible. Also, you will be advised of your right to file a complaint with the FCC if you believe it is necessary.

The telephone company may make changes in its facilities, equipment, operations or procedures that could affect the operation of the equipment. If this happens, the telephone company will provide advance notice in order for you to make necessary modifications to maintain uninterrupted service.

If trouble is experienced with this equipment, for repair or warranty information, please contact the Technical Service Center at 1-800-242- 2121 or contact your local Avaya representative. If the equipment is causing harm to the telephone network, the telephone company may request that you disconnect the equipment until the problem is resolved.

A plug and jack used to connect this equipment to the premises wiring and telephone network must comply with the applicable FCC Part 68 rules and requirements adopted by the ACTA. A compliant telephone cord and modular plug is provided with this product. It is designed to be connected to a compatible modular jack that is also compliant. It is recommended that repairs be performed by Avaya certified technicians. The equipment cannot be used on public coin phone service provided by the telephone company. Connection to party line service is subject to state tariffs. Contact the state public utility commission, public service commission or corporation commission for information. This equipment, if it uses a telephone receiver, is hearing aid compatible.

Canadian Department of Communications (DOC) Interference Information

This Class A digital apparatus complies with Canadian ICES-003. Cet appareil numérique de la classe A est conforme à la norme NMB-003 du Canada. This equipment meets the applicable Industry Canada Terminal Equipment Technical Specifications. This is confirmed by the registration number. The abbreviation, IC, before the registration number signifies that registration was performed based on a Declaration of Conformity indicating that Industry Canada technical specifications were met. It does not imply that Industry Canada approved the equipment.

Installation and Repairs

Before installing this equipment, users should ensure that it is permissible to be connected to the facilities of the local telecommunications company. The equipment must also be installed using an acceptable method of connection. The customer should be aware that compliance with the above conditions may not prevent degradation of service in some situations. Repairs to certified equipment should be coordinated by a representative designated by the supplier. Any repairs or alterations made by the user to this equipment, or equipment malfunctions, may give the telecommunications company cause to request the user to disconnect the equipment.

Declarations of Conformity

United States FCC Part 68 Supplier's Declaration of Conformity (SDoC) Avaya Inc. in the United States of America hereby certifies that the equipment described in this document and bearing a TIA TSB-168 label identification number complies with the FCC's Rules and Regulations 47 CFR Part 68, and the Administrative Council on Terminal Attachments (ACTA) adopted technical criteria. Avaya further asserts that Avaya handset-equipped terminal equipment described in this document complies with Paragraph 68.316 of the FCC Rules and Regulations defining Hearing Aid Compatibility and is deemed compatible with hearing aids. Copies of SDoCs signed by the Responsible Party in the U. S. can be obtained by contacting your local sales representative and are available on the following Web site: <http://www.avaya.com/support>. All Avaya media servers and media gateways are compliant with FCC Part 68, but many have been registered with the FCC before the SDoC process was available. A list of all Avaya registered products may be found at: <http://www.part68.org> by conducting a search using "Avaya" as manufacturer.

European Union Declarations of Conformity



Avaya Inc. declares that the equipment specified in this document bearing the "CE" (*Conformité Européenne*) mark conforms to the European Union Radio and Telecommunications Terminal Equipment Directive (1999/5/EC), including the Electromagnetic Compatibility Directive (89/336/EEC) and Low Voltage Directive (73/23/EEC). Copies of these Declarations of Conformity (DoCs) can be obtained by contacting your local sales representative and are available on the following Web site: <http://www.avaya.com/support>.

Japan

This is a Class A product based on the standard of the Voluntary Control Council for Interference by Information Technology Equipment (VCCI). If this equipment is used in a domestic environment, radio disturbance may occur, in which case, the user may be required to take corrective actions.

この装置は、情報処理装置等電波障害自主規制協議会（VCCI）の基準に基づくクラスA情報技術装置です。この装置を家庭環境で使用すると電波妨害を引き起こすことがあります。この場合には使用者が適切な対策を講ずるよう要求されることがあります。

To order copies of this and other documents:

Call: Avaya Publications Center
Voice 1.800.457.1235 or 1.207.866.6701
FAX 1.800.457.1764 or 1.207.626.7269
Write: Globalware Solutions
200 Ward Hill Avenue
Haverhill, MA 01835 USA
Attention: Avaya Account Management

E-mail: totalware@gwsml.com

For the most current versions of documentation, go to the Avaya support Web site: <http://www.avaya.com/support>.

Contents

Chapter 1: Before You Go to the Installation Site	7
Other documents	7
License file, software, and firmware	7
Laptop requirements	8
Chapter 2: Conduct Equipment Inventory	9
Chapter 3: Mount Media Gateway	15
Chapter 4: Install Octaplane Stacking Module.	17
Chapter 5: Connect Media Gateways	19
Chapter 6: Install S8300 Media Server	21
Chapter 7: Install Media and Expansion Modules	23
Chapter 8: Install USB Modem and CD-ROM Drive	25
Chapter 9: Install UPS and Apply Power.	27
Chapter 10: &RQQHFVWKH/ DSVRS * Z LMKRXWDQ 6	
&KDSWU &RQQHFVWKH/ DSVRS * Z LMK 6	

Contents

Chapter 1: Before You Go to the Installation Site

The following activities must be completed before going to an installation site.

Other documents

Obtain access to the following documentation:

- The G700/S8300 Installation guide: *Installation and Upgrades for Avaya G700 Media Gateway and Avaya S8300 Media Server*, 555-234-100.
- The documentation library on CD, installed on your laptop, or accessible from the Avaya Support web site: *Documentation for Avaya Communication Manager, Media Gateways and Servers*, 555-300-151.

License file, software, and firmware

The following tasks must be completed before you can install an Avaya S8300 Media Server and Avaya G700 Media Gateway.

To do before you install the S8300 and G700

1. Meet with the customer to complete the ***Electronic Preinstallation Worksheet***. The Electronic Preinstallation Worksheet contains specific information about the customer's network configuration and telephony requirements. This information is required to use the Avaya Installation Wizard to configure the Avaya IP solution.

Note:

To use the Avaya Installation Wizard, Release 2.0 or later of the Communication Manager must be installed on the media server. If a pre-2.0 release of the Communication Manager is installed on the media server, the software must be upgraded before the Avaya Installation Wizard can be used.

Note:

The current release of the Avaya Installation Wizard supports only an English-language operating system.

2. If you are using the Avaya Installation Wizard to generate *basic translations* on an S8300 primary controller in a G700, get the customer's Name and Number list file and the Custom Templates. Copy these files to your laptop. The Electronic Preinstallation Worksheet contains instructions for the Name/Number and Custom Templates files.

Before You Go to the Installation Site

3. Complete the following steps to retrieve the required license files and password files from Remote Feature Activation (RFA):
 - For an S8300 configured as a primary controller, one license file.
 - If you are using the Avaya Installation Wizard to generate *basic translations* on an S8300 primary controller, you need to retrieve two license files:
 - Generate one license file with FEAT_DADMIN turned on by selecting FEAT_DADMIN on the RFA Features screen.
 - Generate a second license file with FEAT_DADMIN turned off by clearing the FEAT_DADMIN selection on the RFA Features screen. The Modify System Record function is used to create the second license file. This step is not required for installations completed by Avaya authorized dealer technicians.
- Note:**

Each license file must be labeled carefully because the files will be used at different points in the installation process.
- Retrieve the password (authentication) file.
4. Obtain the most recent versions of software and firmware on CD-ROM.
5. If necessary for your installation, obtain a USB CD-ROM drive for use at the site. This drive is not necessary if you have TFTP server installed on your laptop.
6. The technician will be advised if ProVision will be used in addition to the Avaya Installation Wizard. ProVision can be used to upload all of the *Communication Manager* translations. Information on the Avaya Installation Wizard options for ProVision is in the Electronic Preinstallation Worksheet.

Laptop requirements


The laptop PC that you use to access the S8300 and/or G700 and to launch the Avaya Installation Wizard must meet the following requirements:

- A minimum display resolution of 800 by 600
- 10/100 ethernet card installed
- Windows 95 or later
- Internet Explorer 5.0 or later

Once you have verified that all the above activities are completed, you can begin product hardware installation following the instructions in this guide.

Chapter 2: Conduct Equipment Inventory


The following list of equipment contains items that may not be needed for your configuration — those items are specified as "optional" and may not be included in your inventory.



Avaya G700 Media Gateway Chassis



Optional Avaya S8300B Media Server



Optional Avaya MM710 T1/E1 Media Module



Optional Avaya MM711 Analog Media Module

Note:

The Analog and the DCP media modules look similar. Check their labels to verify the module type.



Optional Avaya MM712 DCP Media Module

Note:

The DCP and the Analog media modules look similar. Check their labels to verify the module type.



Optional Avaya MM760 VoIP Media Module



Optional Avaya MM714 4FXS x 4FXO Analog Media Module

Conduct Equipment Inventory




Optional Avaya MM717 24-port DCP Media Module.

Note:


Endpoints connected to this media module must be in-building only.




Optional Avaya MM720 8-port BRI Media Module



Optional Avaya MM722 2-port BRI Media Module




Optional Expansion Module.



Optional C360 Converged Stackable Switch:
C363T/C363-PWR




C364T/C364-PWR



Optional X330STK Octaplane Stacking Module.



Optional USB modem.
Material ID: 700235526




Optional Teac USB CD-ROM Drive.
Material ID: 700289580.



Optional Uninterruptible Power Supply (UPS) for AC-Powered Gateways Only.

Note:

A stand-alone version of the UPS is shown.




Screw Packet and Rack Mount Brackets

For each bracket:

- three flat-head machine screws attach the bracket to the G700
- two round-head lock-washer machine screws attach the bracket to the rack

Note:

There are four sizes of lock-washer screws in the packet for attaching the brackets to the rack. Use the appropriate size screws to match the specific hole size of the rack.



Optional X330SC Short Cable.

Note:


The X3300SC Short Cable is sometimes shipped attached to the X3300STK Octaplane Stacking Module.

Conduct Equipment Inventory


Optional X3300RC Redundancy Cable.




Optional X3300 LC Long Cable.




Optional USB Cable and Adapter for use with the USB modem.




Crossover Ethernet Cable (CAT5)



Serial or "Console" Cable and Adapter




Ground wire.



Optional AC Power Cord




Optional DC Power Cord.



Feet used for table mounting.




Chapter 3: Mount Media Gateway



1. Wear an anti-static ground wrist strap and attach to an approved ground.
2. For rack mount, install the mounting brackets on the left and right sides of the gateway chassis using the flathead screws from the bracket packet.

Note:

The brackets can also be installed in the middle of the chassis.



3. Lift the media gateway chassis and mount in a rack using two lock-washer screws for each bracket.


! CAUTION:

The weight of the media gateway is unevenly distributed and may require two persons to mount in the rack.

Mount Media Gateway



4. For desktop mount. Install feet using plastic push rivets.




5. Connect the ground wire to the ground conductor on the back of the media gateway.

6. Attach the other end of the ground wire to an approved ground.


Chapter 4: Install Octaplane Stacking Module

Note:

Complete these steps only if you are connecting more than one G700 Media Gateway in a stack configuration.



1. Remove the blank faceplate from the Octaplane slot on the back of the media gateway.




2. Align the X330STK Octaplane Stacking Module with the interior guides and insert until firmly seated



WARNING:

To prevent damage to equipment, handle the module by the faceplate or edge.




3. Tighten the captive screws.

Chapter 5: Connect Media Gateways

Note:

Complete these steps only if you are connecting more than one G700 Media Gateway in a stack configuration.



1. Using the gray X330SC short cables, connect the media gateways from the bottom up:


- Connect the light gray connector to the port labeled “Cable to upper unit.”
- Connect the dark gray connector to the port labeled “Cable to lower unit.”
- Repeat both steps until all units in the stack are connected (maximum of 10 units).



Single-stack redundancy

2. For single-stack redundancy, connect the bottom unit and the top unit using the black X330RC redundancy cable:

- Connect the light gray connector to the port labeled “Cable to upper unit: on the top unit of the stack.
- Connect the dark gray connector to the port labeled “Cable to lower unit” on the bottom unit of the stack.



Multiple-stack redundancy

3. For multiple stack redundancy, connect the stacks using the black X330RC redundancy cable and the gray X330LC long cable:

- Connect the light gray connector of the black X330RC redundancy cable to the port labeled “Cable to upper unit” on the top unit of the stack 2.
- Connect the dark gray connector of the black X330RC redundancy cable to the port labeled “Cable to lower unit” on the top unit of the stack1.
- Connect the light gray connector of the gray X330LC long cable to the port labeled “Cable to upper unit” on the top unit of the stack 1.
- Connect the dark gray connector of the gray X330LC long cable to the port labeled “Cable to lower unit” on the bottom unit of the stack 2.


Chapter 6: Install S8300 Media Server

Note:

Complete these steps if you are installing an S8300 Media Server (configured as the primary controller or as a Local Survivable Processor).



1. From the front of the G700 Media Gateway, remove the blank faceplate from slot V1.




2. Remove the LED module (located above slot V1) and place in an anti-static bag.



3. Align the S8300 Media Server with the lower interior guides and insert about 2" into slot V1.

Install S8300 Media Server




4. Align the LED module with the upper interior guides and insert until the faceplate is flush with the S8300 Media Server.
5. Continue inserting both modules together until firmly seated.



WARNING:

Failure to seat both modules together could result in equipment damage.



6. Tighten the captive screws on the S8300.


Chapter 7: Install Media and Expansion Modules

Note:

In each gateway, a single expansion module can be installed in the lower left slot only. If the S8300 is installed (in slot V1), up to 3 media modules can be installed in slots V2–V4. If no S8300 is installed, a fourth media module can be installed in Slot V1.



1. To install a media module, first remove the upper right blank faceplate.




2. Align the media module with the interior guides and insert into slot until firmly seated.
3. Tighten the captive screws.
4. Repeat steps 1 through 3 for each media module to be installed.



5. To install the expansion module, first remove the lower left blank faceplate.
6. Align the expansion module with the interior guides and insert into slot until firmly seated.
7. Tighten the captive screws.

Chapter 8: Install USB Modem and CD-ROM Drive



USB Modem

1. Connect the USB cable to either of the two USB port on the faceplate of the S8300.
2. Following the instructions packaged with the modem, connect the other end of the USB cable to the modem.
3. Connect the analog telephone line to the RJ-11 jack on the modem.



Teac USB CD-ROM Drive

The USB CD-ROM drive is used primarily as a software source location when remastering a S8300 hard drive.

1. Connect the USB cable into either of the two USB ports on the faceplate of the S8300.
2. Connect the other end of the USB cable to the CD-ROM drive.

Note:

If you have installed a TFTP server on your laptop, you can use the your laptop's CD-ROM drive instead of the external USB CD-ROM drive when remastering the S8300 hard drive.

Install USB Modem and CD-ROM Drive

Chapter 9: Install UPS and Apply Power




UPS (AC only)

1. The UPS is an option for AC-powered gateways only. From the back of the G700 Media Gateway, connect the Uninterruptible Power Supply (UPS) using the manufacturer's instructions.

Note:

A stand-alone version of the UPS is shown.




AC power

1. Apply power to each media gateway by connecting the AC power cord.

Note:

There is no on/off switch.
The units will power up
when connected.



DC power

1. Apply power to each media gateway by connecting the DC power cord.

Note:

There is no on/off switch.
The units will power up
when connected.

Install UPS and Apply Power


Chapter 10: &RQQHFWKH / DSVRS

6


*

Z LMRXWDQ

This section assumes the G700 does not contain an S8300 Media Server. Use the Gateway Installation Wizard from the laptop to enter the initial gateway configuration parameters.




1. Connect the RJ45 end of a serial cable to the Console port on the lower right of the front of the G700.
2. Connect the other end of the cable to the Serial port on the laptop.



3. Power on the laptop.
4. Start a Hyperterm (or similar application) session.
5. Start the Gateway Installation Wizard (GIW).



6. Follow the GIW instructions to Enter the configuration parameters.



7R FRQHFWMH FXMRP HUV / \$1

1. Connect a straight Ethernet cable to one of the Ethernet ports (labeled Ext 1 and Ext 2) on the front of the G700.
2. Connect the other end of the cable to a LAN connector.

Chapter 11: &RQQHFWMH / DSVRS * Z LNK 6


This section assumes the G700 has an S8300 Media Server installed.



1. Connect a crossover Ethernet cable to the Services port on the faceplate of the S8300 Media Server.
2. Connect the other end of the cable to the Ethernet port on the laptop.




3. Power on the laptop.
4. Verify the Services network settings:
 - a. IP Address: 192.11.13.5
 - b. Subnet Mask: 255.255.255.252
 - c. Domain Name Service (DNS): disabled.
5. Open MS Internet Explorer and disable the Proxy Server.
6. In the browser address field, initiate access to the S8300 by typing in lower case:
`http://192.11.13.6`




7. Click **Continue** to access the Logon page.

8. Click **OK** or **Yes**, as appropriate, for any security pages that may appear prior to the Logon page.




9. Log in to the S8300 Media server with the **craft** login and password for initial installation.



10. Use the Avaya Installation Wizard. Click on **Launch Avaya Installation Wizard** and continue.

Note:

If you are *not* using the Avaya Installation Wizard, refer to *Installation and Upgrades for Avaya G700 Media Gateway and Avaya S8300*, 555-234-100, for additional instructions.



7R FRQQHFWLRK WKH FXWWRP HUV / \$ 1

1. Connect a straight Ethernet cable to one of the Ethernet ports (labeled Ext 1 and Ext 2) on the front of the G700.
2. Connect the other end of the cable to a LAN connector.



7R FRQQHFWLRK 6%0 RGHP

To configure the G700 and S8300 remotely, connect the USB modem.

1. Connect the USB cable to either of the two USB port on the faceplate of the S8300.
2. Following the instructions packaged with the modem, connect the other end of the USB cable to the modem.
3. Connect the analog telephone line to the RJ-11 jack on the modem.
4. Go to the Maintenance Web Interface and select Modem in the Security Category.
5. Select the box labeled "Enable modem for unlimited incoming calls" and click **Submit**.

