



Job Aid:

Avaya Installation Wizard

for Avaya S8300, S8500, and S8700 Media Servers and
Avaya G350 and G700 Media Gateways

555-245-754, Issue 2
June 2004

Please disregard any references to the S8710 Media Server in this document. The S8700 Media Server is the currently available product. If you need additional information, please contact your Avaya representative or Avaya authorized business partner.

Note: For a demo of the Avaya Installation Wizard, please visit <http://support.avaya.com/avayaiw> and click the [Avaya™ Installation Wizard Demos](#) link.

Introduction

The Avaya Installation Wizard (IW) is a browser-based wizard that is available on the S8300, S8500, S8700, and S8710 Media Servers running Avaya Communication Manager 2.1 or higher software. The IW guides you through the steps required to install and configure a media server with associated gateways.

NOTE: The media server Home Page contains a link to access the IW for installations. You can get the latest version of the IW RPM file and all wizard template files by downloading them from the <http://support.avaya.com/avayaiw> web site. Also visit this web site to get additional information about how the use of the wizard template files can make your job easier.

Configurations Supported by the Avaya Installation Wizard

You can use the Avaya Installation Wizard (IW) to do the following:

- Install an S8500, S8700, or S8710 Media Server
- Install an S8300/G700 stack with S8300 configured as a primary controller or Local Survivable Processor (LSP)
- Install an S8300/G350 with S8300 configured as a primary controller or Local Survivable Processor (LSP)
- Install and configure IA770 INTUITY AUDIX software on an S8300 Media Server
- Install patches to Communication Manager software

- Upgrade Communication Manager software on an S8300, S8500, S8700, or S8710 primary controller

Note: For an upgrade, the system you are upgrading must already be running Communication Manager software, release 2.0 or higher.

- Upgrade firmware on a G350 or G700 Media Gateway and their media modules
- Configure alarming strategy
- Set Product ID and install unicode files
- Configure modems
- Configure SNMP
- For the S8300 with a G700 or G350 only, configure telephony and trunking parameters and trunk diagnostics

Configurations Not Supported by the Avaya Installation Wizard

You **cannot** use the IW to do the following:

- Install a G700 that is not in a stack containing an S8300 Media Server.
- Install a G350 that does not contain an S8300 Media Server.
- Install an LSP or media gateway remotely from an S8700 primary controller. That is, to install or upgrade software on a media server, the IW must be running on that media server. To install or upgrade firmware on a media gateway, IW must be running on the S8300 that resides in the media gateway; or, for a G700 stack, IW must be running on an S8300 that resides in a G700 in the stack.
- Install a P330 Expansion Module in a G700
- Install a W310 Converged Mobility Gateway

Electronic Worksheets and Templates

To allow the IW to automatically configure and install the system, obtain the following files from the project manager and load them onto your laptop:

- Electronic Pre-Installation Worksheet
- Name and Number List (S8300 with a G700 or G350 only)
- Custom Template (S8300 with a G700 or G350 only)

Information on how to use these files is contained within the files themselves.

Electronic Pre-Installation Worksheet

The Electronic Pre-Installation Worksheet (EPW) is filled in by the customer and either the project manager, the software specialist, or another support person who configures Voice over IP systems. The data from this worksheet is automatically pulled into IW to configure the servers and gateways.

Name and Number List (S8300 with G700 or G350 only)

The Name and Number List, like the EPW, is an Excel spreadsheet that contains user administration data. The IW pulls this data to automatically administer users on the new system. This administration includes users' names, extensions, telephone types, classes of service, languages, locations, and voice mail capability.

Custom Template (S8300 with G700 or G350 only)

The Custom Template is a third Excel spreadsheet that allows automatic administration of key custom MultiVantage translations. These are:

- Classes of Service
- Feature Access Codes
- Trunk Access Codes
- Telephone button assignments
- TTI codes
- Voice mail hunt group number and coverage path

Tasks to Complete Before Going Onsite

Before going on site to perform an installation, you must perform some or all of the tasks in the following checklist:

Task	Who does it?	Description
Create RFA Password (Authentication) File	Project Manager or Technician	The Project Manager, software specialist, or another support person who configures Voice over IP systems normally creates the file from the RFA Web site and sends it to the installer.
Create RFA License File	Project Manager or Installer	The Project Manager normally creates the file from the RFA Web site and sends it to the installer. If the server being installed is an S8300 configured as an LSP, the FEAT_LSP feature must be enabled when creating the license file.
If the IW will configure basic translations for an S8300 primary controller, create two RFA license files -- one with DADMIN enabled and one with DADMIN disabled Note: <i>Required for</i>	Project Manager or Installer	If the IW will configure basic translations on an S8300 primary controller, the Project Manager creates two files from the RFA Web site and sends them to the installer. Create one license file with the FEAT_DADMIN feature enabled. Create a second license file with the FEAT_DADMIN feature disabled. The license file with DADMIN enabled is installed during the installation of the S8300. The license file with DADMIN disabled is installed after the completion the

Task	Who does it?	Description
Avaya Direct Installation of an S8300 primary controller with a G700 or G350 only		S8300 installation and basic translations, replacing the DADMIN-enabled license file. The DADMIN-disabled file prevents access via the DADMIN login. Important: Do not create or install the DADMIN-disabled second license file for an LSP or for an Avaya Business Partner installation.
For S8300: Get USB CD-ROM drive or install TFTP server software to your laptop. Get CD-ROM with the server .tar files and the gateway firmware files.	Installer through Tier 3	For a new installation of the S8300, the S8300 hard drive contains the Linux operating system software and the Remastering Program only. The Remastering Program copies the .tar files from the CD-ROM, either from the USB CD-ROM drive or the your laptop's CD-ROM drive, to the S8300 hard drive. The CD-ROM also contains the most recent versions of the G350 and G700 firmware.
For S8500 and S8700: Get CD-ROM with the server .tar files	Installer through Tier 3	For a new installation or an upgrade of the S8500 or S8700, the hard drive must be reformatted. This is done using the internal CD-ROM drive and the CD-ROM containing the server .tar files and the Linux operating system software. The CD-ROM also contains the most recent version of firmware for the IPSI board.
If you have not already done so, get the most recent Installation Wizard RPM file.	Installer	Download the most recent IW rpm file from the Avaya support Web site to your laptop. If the wizard installed on the media server is not as recent, the wizard provides the option to update itself with the rpm file you downloaded. Note: Do not use Wizard versions prior to si-S8x00-2.1-x.
Get the most recent Unicode Message files (Optional)	Installer	Download the most recent Unicode message files for the languages the customer wants.
Get the most recent firmware files and Communication Manager update software.	Installer	Download the most recent firmware and software files. These may be more recent than those on the software CD-ROM.
Complete the Wizard Electronic Preinstallation Worksheet (EPW)	Project Manager with Customer	The Project Manager, software specialist, or another support person who configures Voice over IP systems normally completes the EPW with the customer and sends it to the installer.
For S8300 only: If doing basic translations, complete	Project Manager with	The Project Manager, software specialist, or another support person who configures Voice over IP systems normally completes the Customer Template with the

Task	Who does it?	Description
the Custom Template (spreadsheet) (Optional, based on customer's desire for custom settings)	Customer	customer and sends it to the installer. The Custom Template is used by the wizard to override wizard translation defaults.
For S8300 only: If doing basic translations, complete the Name and Number List (spreadsheet)	Project Manager with Customer	The Project Manager, software specialist, or another support person who configures Voice over IP systems normally completes the Name and Number List with the customer and sends it to the installer. The Name and Number List is used by the wizard to administer stations.
Load all items required for the installation on the technician's laptop.	Installer	Items that must be loaded are Authentication and License file(s). Items that might need to be loaded are: .tar file, .tar.gz file, individual firmware files, EPW, Name and Number List, Custom Template, and Wizard RPM file.

Installing Hardware

Once you have verified that all activities are completed, you can begin product hardware installation following instructions in one of the server installation and upgrades manuals. Choose the appropriate documentation from the following list.

For S8300 with G700:

Quick Start: Avaya G700 Media Gateway Hardware Installation.

Installation and Upgrades for the Avaya G700 Media Gateway and Avaya S8300 Media Server

For S8300 with G350:

Quick Start: Avaya G350 Media Gateway Hardware Installation.

Installation of the Avaya G350 Media Gateway

Upgrade and Service Guide for the Avaya G350 Media Gateway

For S8500:

Getting Started with the Avaya S8500 Media Server

Installation of the Avaya S8500 Media Server.

For S8700:

Getting Started with the Avaya S8700 Media Server with Avaya Media Gateways

Installing the Avaya S8700 Media Server with Avaya Media Gateways

When instructed in the manual, launch the Avaya Installation Wizard.

Setting up the Avaya Installation Wizard Onsite

More details on how to set up your laptop connection to the media server can be found in the documents listed above.

1. Make sure your laptop is correctly configured as shown below.
Note: If you are not using Netswitcher, write down the previous settings so you can re-configure your laptop after the installation.
 - a) IP Address: **192.11.13.5**
 - b) NetMask: **255.255.255.252**
 - c) Disable DNS
 - d) Clear the primary WIN and secondary WIN IP Addresses
2. Open the Microsoft Internet Explorer and disable the Proxy Server. Alternatively, you may continue to use the Proxy Server, but you must enter **192.11.13.6** in the Exceptions box.
3. Connect the laptop to the server's Ethernet Services port with a crossover cable.
4. Launch Microsoft Internet Explorer on the laptop.
5. Do one of the following:
 - Type the following address into the browser in lower case to access the media server Home Page: <http://192.11.13.6>.
6. Enter the appropriate login and password.
If you have not previously installed a password file, use the **craft** login and default password. Otherwise use one of the services logins or the **dadmin** login.
7. Select the **Launch Installation Wizard** link from the home page to launch the wizard.
8. If the currently installed version of the wizard is less than the version you downloaded, select **Install new version of the wizard from my laptop**. Otherwise, go to step 9.
9. If you are installing a new version of the wizard, click the **Browse** button, select the latest wizard RPM file that you previously downloaded from <http://support.avaya.com/avayaiw>, and click the **Continue** button.
10. Proceed as guided through the wizard screens, entering information when prompted to do so.

Note: The current release of the Avaya Installation Wizard supports only an English-language operating system.

Overview of Wizard Tasks

Installation Tasks

The following checklist shows the tasks you perform with the IW during an installation. If a task is optional, you can leave the page for that task blank and move to the next page of the IW.

1. View server type, serial number and Communication Manager software version
2. Import of Electronic Pre-installation Worksheet (EPW). Using the EPW provides default values from the EPW for following steps.
3. Select wizard usage (primary controller, LSP, or upgrade)
4. Review Checklist
5. (For S8300 Only) Initialize NVRAM option (restore factory default settings on all media gateways) [optional]
6. Set date, time and time zone [optional]
7. Enter Product ID [optional]
8. Upgrade Communication Manager software [optional]
9. Install update software [optional]
10. Install Unicode phone message files [optional]
11. (For S8700 and S8710 only) Specify whether you are copying configuration data from the duplicated server or entering it the first time
12. (For S8500, S8700, and S8710 only) Define server names, the default active server, and Ethernet port assignments
13. (For S8500, S8700, and S8710 only) Define Control Network A
14. (For S8700 and S8710 only) Define Control Network B
15. Enter IP address information for the Media Server
16. (For S8300/G700 Only) Enter IP address information for the P330 Stack Processor
17. (For LSP Only) Enter primary controller IP addresses
18. Configure optional services (UPS, DNS, NTP, INADS) (for S8700 and S8710, also configure Ethernet switches and static network routes) [optional]
19. (For S8300) Select translations source (the wizard or skip to add translations after the installation via ProVision, the SAT, or another tool) [optional]
20. Install security files
21. (For S8300 with G700 only) Configure each G700: <ul style="list-style-type: none"> ➤ Enter MGP IP information (Address, Subnet mask, VLAN, IP routing info) ➤ Enter MGC list information ➤ Enter VoIP engine and VoIP media module IP addresses ➤ Media gateway is added to translations

<p>22. (For S8300 with G350 Only) Configure the G350:</p> <ul style="list-style-type: none">• Enter PMI IP information (Address, Subnet mask, VLAN, IP routing info)• Enter MGC list information• Enter SNMP community string
<p>23. (For S8300 Only) Upgrade the firmware for all media gateway components [optional]</p>
<p>24. (For S8300 with G350 Only) Configure G350 Media Gateway modem. This is a different modem than that configured for alarming for the primary controller in Step 24.</p>
<p>25. (For S8300 as Primary Controller Only) If translations source is the wizard, generate basic translations: [optional]</p> <ul style="list-style-type: none">➤ Enter country➤ Import a custom template file that overrides the wizard defaults [optional]➤ Enter call routing parameters➤ Enter dial plan extension ranges➤ Import the name and extension list to administer stations [optional]➤ Configure the IA770 [optional]➤ Configure, check and run diagnostics for IP trunks [optional]
<p>26. Configure, check and run diagnostics on T1/E1, BRI and analog CO trunks [optional]</p>
<p>27. (For S8300 as Primary Controller Only) Display FAC and security code for doing TTI merge of sets [optional]</p>
<p>28. Configure modem [optional]</p>
<p>29. Configure OSS Alarming [optional]</p>
<p>30. Configure SNMP [optional]</p>
<p>31. (S8500 only) Configure the Remote Supervisor Adapter (RSA)</p>
<p>32. (S8300 Only) Install authentication file</p>
<p>33. (If S8300 with G700/G350 and Translations Source is the Wizard and Avaya Installer) Install 2nd license file that disables “dadmin”.</p>
<p>34. Save installation log file</p>

Upgrade Tasks

The following checklist shows the tasks you perform with the IW during an upgrade. If a task is optional, you can leave the associated page of the IW blank and move to the next page. Note that you do not use the EPW or other templates.

NOTE: For an upgrade of an S8300 **from pre-R2.0 Communication Manager software**, you must replace the S8300 Media Server with an S8300B Media Server. In addition, you must format the new S8300B hard drive. Use the CD-ROM containing the .tar file and either the USB CD-ROM drive on the server or your laptop's CD-ROM drive. To use the CD-ROM drive on your laptop, your laptop must also have TFTP server software.

For an upgrade of an S8300 **from R2.0 Communication Manager software**, the customer may or may not already have the S8300B Media Server. Check the hardware version to see if server replacement is necessary. If you replace the server, you must also reformat the hard drive as described above. more information, see *Installation and Upgrades for the Avaya G700 Media Gateway and Avaya S8300 Media Server*.

1. View server type, serial number and Communication Manager version
2. Import of Electronic Pre-installation Worksheet (EPW) [skip]
3. Select wizard usage (Upgrade)
4. Review Checklist [skip]
5. Review IP addresses
6. Set date, time and time zone [optional]
7. Upgrade Communication Manager software [optional]
8. Install update software
9. Install license and authentication files [optional]
10. (For S8300 Only) Upgrade the firmware for all components on each media gateway [optional]

Notes

All trademarks identified by the ® or ™ are registered trademarks or trademarks, respectively, of Avaya Inc. All other trademarks are the property of their respective owners.

Copyright © 2004 Avaya Inc. All rights reserved.