

MULTIFREQUENCY PULSING
RECEIVER FRAME
EQUIPMENT DESIGN REQUIREMENTS
NO. 1 AND TANDEM CROSSBAR SYSTEMS

1. GENERAL

1.001 This addendum supplements Sections 816-030-150 and 817-044-150, Issue 1.

1.002 This addendum is issued:

(a) To revise 1.04 and Table B.

The following changes apply to Part 1 of the section:

(a) 1.04—revised.

(b) Table B—revised.

Change: 1.04

To Read:

1.04 The 2-out-of-6 (2/6) MF signaling code, used by the MF pulsing receiver circuit, consists of six voice frequencies which are pulsed two frequencies at a time for each signal, yielding 15 combinations per signal. Of these, ten are for digits 1 to 0 and five for control information.

Change: Table B

To Read:

TABLE B

FREQUENCIES OF PULSED SIGNAL	2/6 ADDITIVE CODE	NUMERICAL DIGIT
700 + 900	0 + 1 =	1
700 + 1100	0 + 2 =	2
900 + 1100	1 + 2 =	3
700 + 1300	0 + 4 =	4
900 + 1300	1 + 4 =	5
1100 + 1300	2 + 4 =	6
700 + 1500	0 + 7 =	7
900 + 1500	1 + 7 =	8
1100 + 1500	2 + 7 =	9
1300 + 1500	4 + 7 =	0
700 + 1700	0 + 10 =	Code 11
900 + 1700	1 + 10 =	Code 12
1100 + 1700	2 + 10 =	KP
1300 + 1700	4 + 10 =	KP2
1500 + 1700	7 + 10 =	ST

Bell Telephone Laboratories, Incorporated

Dept 5243