

**BELL SYSTEM PRACTICES**  
**Station Installation and Maintenance**

**ADDENDUM C32.509**  
**Issue 1, August, 1954**  
**AT&T Co Standard**

## **TELEPHONE SETS**

### **354, 356, AND 357 TYPES**

### **DESCRIPTION AND INSTALLATION**

#### **1. GENERAL**

1.01 This addendum supplements Section C32.509, Issue 3.

It is issued to include a reference to the 6D dial and unmodified 59A dial adapters, to specify B2AL and B1AL ringers with M3 and M7 mountings, respectively, and to omit reference to 634BD subscriber sets for use as transmitter battery filters.

#### **3. APPARATUS**

Revise information under COMBINATION OF APPARATUS to read:

<u>Telephone Set Code (Note 1)</u>	<u>Telephone Set Mounting</u>	<u>Apparatus Blank</u>	<u>Dial (Note 2)</u>	<u>Handset</u>
354A-3	M3-3	94A-3	—	FIG-3
354C-3	M3-3	—	6A	FIG-3
356A-3	M5-3	94A-3	—	FIG-3
356C-3	M5-3	—	6A	FIG-3
357A-3	M7-3	94A-3	—	FIG-3
357C-3	M7-3	—	6A	FIG-3

#### **Notes:**

1. All codes listed above are for black (-3) apparatus. See Section C30.011, Colored Station Sets, for listing of ivory (-4) apparatus.

2. A 4- or 5-type dial may be used in place of the 6-type. The 5JB or 6D dial is used on ivory sets.

(a) The 59A dial adapter is required with the dial on all sets listed above. The modified 59A dial adapter, covered in Section C34.301, Dial Mountings and Dial Adapters—Description and Use, is designed for use with either the 4-, 5-, or 6-type dials. The unmodified 59A dial adapter, which has a full circular shape, must have the upper segment cut out so that it has the same outline as the modified adapter before it may be used with a 6-type dial.

(b) A 61E filter may be used with 4-, 5-, or 6-type dials. A 61G may be used with 4- and 5-types only. Order filter separately if required.

3.01 Revise to read: The telephone set mountings that form a part of the foregoing telephone sets include the following coded apparatus:

<u>Mounting</u>	<u>Ringer</u>	<u>Con- denser</u>	<u>Induction Coil</u>	<u>Retard Coil</u>	<u>Vacuum Tube</u>
M3-3	B2AL	195A	101B	—	—
M5-3	B3A	195C	101A	—	*426A
M7-3	B1AL	387A	104A	226A	—

\* Some sets may still be equipped with the 333A vacuum tube.

#### 4. INSTALLATION

4.05 Revise to read: Where the transmitter battery for more than one L.B.T., C.B.S. telephone set is obtained from a common source of supply, such as a battery feeder from the central office, an F2B handset should be substituted for the F1G or F1A in 357-type telephone sets. Also, change internal connections as covered in Section C63.435, Telephone Sets 357-Type—Connections. In addition, a battery supply filter is required as covered in Section C63.289, Balancing Network and Battery Supply—Filter Connections.