



NORTEL

Nortel Communication Server 1000

Nortel Converged Office Fundamentals — Microsoft Office Communications Server 2007

Release: 5.5

Document Revision: 02.15

www.nortel.com

NN43001-121

Nortel Communication Server 1000
Release: 5.5
Publication: NN43001-121
Document release date: 9 September 2009

Copyright © 2007-2009 Nortel Networks. All Rights Reserved.

While the information in this document is believed to be accurate and reliable, except as otherwise expressly agreed to in writing NORTEL PROVIDES THIS DOCUMENT "AS IS" WITHOUT WARRANTY OR CONDITION OF ANY KIND, EITHER EXPRESS OR IMPLIED. The information and/or products described in this document are subject to change without notice.

Nortel, Nortel Networks, the Nortel logo, and the Globemark are trademarks of Nortel Networks.

All other trademarks are the property of their respective owners.

Contents

New in this release	9
Office Communications Server 2007 features	9
Other changes	9
Revision History	9
How to get help	13
Getting help from the Nortel web site	13
Getting help over the telephone from a Nortel Solutions Center	13
Getting help from a specialist by using an Express Routing Code	13
Getting help through a Nortel distributor or reseller	14
Introduction	15
Converged Office component overview	17
Converged Office	17
Enterprise Voice	19
OCS 2007 Voice components	20
Media Gateways	22
Mediation Server	22
Remote Call Control with SIP CTI (TR/87)	23
Telephony Gateway and Services	25
Telephony Services (TLSV)	26
Direct SIP	28
Access Edge Server	31
OCS 2007 snap-in	32
Multimedia Convergence Manager	32
CDR data collection	33
SIP CTI (TR/87) Protocol	33
Hardware Load Balancer	36
Office Communicator 2007	37
Documentation References	37
Planning and engineering	41
Planning process	41
Network configuration	42
Multiple customer network	46

Multiple location network	48
Load Balancer planning	48
Load Balancer requirements	50
Redundancy with Load Balancers	51
Nortel Application Switch	52
Capacity planning	52
OC 2007 client requirements	53
Load Balancer capacity requirements	53
SIP CTI (TR/87) services requirements	53
Mediation server requirements	55
Signaling Server requirements	55
Call Server requirements	55
OCS Proxy and MCM capacity requirements	55
General requirements	56
Server topology	57
Operating System Requirements	58
Hardware Requirements	58
Virtual Server 2005	60
Storage	60
Trunks	61
Basic Client Configuration	64
Port use	64
Security	64
Dial Plan considerations	66
Number formats supported by Office Communicator	68
E.164 international format numbers for SIP Gateway and SIP CTI	71
Telephony Gateway and Services planning	71
Systems, platforms, and applications	71
Remote Call Control with SIP CTI	79
LCS 2005 and OCS 2007 coexistence	88
Client considerations	89
Converged Office functionality	89
MCM 2.0 or 3.0 to MCM 3.5	90
Load balancer considerations	90
Migration planning from LCS 2005 to OCS 2007	91
Determine your deployment options	93
Migration process	93
Description of Migration Phases	96
Unified Messaging	97
OCS 2007 users using CallPilot	97
OCS 2007 users using UM 2007—integrated	99
OCS 2007 users using UM 2007—non-integrated	103
Signaling with integrated Voice Mail	105
Signaling with non-integrated Voice Mail	105

Installation **107**

- OCS 2007 installation preparation and deployment 109
- CS 1000 and Signaling Server installation 111
- OCS 2007 component installation 111
- OCS Proxy server installation 113
- Load Balancer installation 114
- MCM installation 115

Configuration **117**

- Active Directory configuration 118
- Office Communications Server configuration 125
 - Load Balancer configuration 126
 - Voice Properties configuration 126
 - OCS configuration procedures 128
 - Configuration of Static Routes 128
 - Host Authorization and Routing configuration 128
 - Mediation Server configuration 140
- MCM 3.5 configuration 142
 - MCM architecture 142
 - MCM Direct configuration 144
 - MCM management console 144
- MCM redundancy with Load Balancer 158
- Telephony Gateway and Services configuration 159
 - Call Server configuration 159
 - Configuring the Codec 159
 - Loss Plan configuration 160
 - Dialing Plan configuration to route to MCM 161
 - Configuring Telephony Services 162
 - Caller ID table configuration 165
 - Home LOC and Home NPA configuration 167
 - DNS Server configuration 167
 - SIP Trunk configuration 168
 - Route list data block 171
 - Domain naming 171
 - URI Mapping 173
 - SIP Gateway CLID Parameters configuration 175
 - SPS configuration 176
 - NRS configuration 177
 - CDR configuration 178
 - E.164 International Format Numbers from Office Communicator - Computer Calls (SIP Gateway) 178
 - Phone number normalization 179
- Direct-SIP configuration 179

Remote Call Control configuration	182
Remote Call Control and PBX integration	182
RCC and PBX integration on OC client	183
CS 1000 configuration	184
Signaling Server configuration	188
SIP CTI Services configuration settings	192
SIP CTI CLID configuration parameters	196
Configuring the SIP URI Map	201
Configuring CDR	201
Dialing E.164 International Format Numbers from Office Communicator - Phone Calls (SIP CTI)	201
Transport Layer Security (TLS) configuration between OCS Proxy/MCM and CS1000	203
Interactions and requirements	203
Example TLS configuration	204
Configuring TLS for Converged Office	204
Configuring OCS certificate	216
Enterprise CA	216
Standalone CA	220
Transport Layer Security (TLS) configuration between OCS Proxy/MCM and Mediation Server	221
OCS Proxy server configuration	222
Normalizing phone numbers	222
SIP Routing and Redundancy configuration	228
OCS 2007 users using UM 2007 in integrated mode	229
Option 1 adding user Alias as Exchange UM	229
Option 2 adding CS 1000 DN as Exchange UM	233

Maintenance **239**

Introduction	239
Communication Server 1000	239
MCM 3.5	239
Remote Call Control	240
Operational Measurements for SIP CTI	242

Troubleshooting **245**

Checking Telephony Gateway (SIP Gateway) configuration	245
Checking Remote Call Control (SIP CTI) configuration	245
Lack of memory on Signaling Server	246
SIP CTI services does not come up	247
SIP Dialog not established	247
Solution 1: Check configuration parameters in AD	248
Solution 2: Confirm FQDN and the IP address are correct	248
SIP CTI service is down	248
MCM not synchronizing new users in AD Cache mode	250

Solution 1: Check the Global Catalog content manually	250
Solution 2: Access permissions for the AD object properties	251
Solution 3: Enable propagation of the AD to the Global Catalog	252
OC client not registered	252
Pop-up not displayed	253
Two pop-ups are displayed	253
Delay for a SIP Gateway call	254
Call Forward is cancelled by Office Communicator	254
Office Communicator disconnecting from the network	254
Capturing traces and logs	255
Communication Server 1000 traces	255
AML traces on the Call Server (SIP CTI only)	255
SIP CTI traces on the Signaling Server	256
SIP Gateway traces on the Signaling Server	257
MCM logs	258
Activating MCM logging	259
OCS logs	261
Case checklists	264

Call Flow and protocol details **267**

Contents	267
Overview	267
Message sequence	268
Call flow	269
Telephony Gateway and Services call flow	269
Supported features	276

Configuration Examples **279**

Contents	279
Introduction	279
Standard Edition	279
Setting up the lab	280
Collecting required data	280
Configuring the Call Server	282
Signaling Server checklist	292
Active Directory user configuration	299
Checking the MCM installation and configuration	302
Enterprise Edition	305
Overview of general lab set-up	305
OCS Management Console	308
Security/Certificates	312
Host Authorization	313
Routing	314
Configuring DNS	316
Active Directory configuration	318

Installing and configuring MCM	319
Signaling Server checklist	322
Configuring NRS	323
Normalizing Phone Numbers	325

Abbreviations**327**

New in this release

The following sections detail what's new in *Nortel Converged Office Fundamentals — Microsoft Office Communications Server 2007* (NN43001-121) for Nortel Communication Server 1000 Release 5.5.

Office Communications Server 2007 features

Signaling traffic between Communication Server 1000 and Office Communications Server 2007 is supported by Multimedia Convergence Manager (MCM) 3.5. Media traffic is supported through the Mediation Server.

The following list shows new Office Communicator 2007 client features for Voice over IP (VoIP) mode:

- Conference Call
- Announced (Consulted) Call Transfer
- Call Forward
- Call Redirect (Deflect)
- Dual Forking
- DoNotDisturb (DND)
- Federated calls

Other changes

Revision History

September 2009

Standard 02.15. This document is up-issued to update the section Direct SIP.

July 2009

Standard 02.14. This document is up-issued to update the UDP Location Code in the table [Table 17 "Feature Interactions of RCC" \(page 86\)](#).

June 2009

Standard 02.13. This document is up-issued to include an MCM command line parameters table in the Configuration section.

April 2009

Standard 02.12. This document is up-issued to exclude the information of Appendix UM Dialing Plan Configurations in Different Deployment Scenarios.

March 2009

Standard 02.11. This document is up-issued to include information on Considering MADN (Multiple Appearance DN).

March 2009

Standard 02.10. This document is up-issued to include information on Flexible Feature Codes with regard to support by RCC.

January 2009

Standard 02.09. This document is up-issued to reflect changes made in sections Configuration and Installation

December 2008

Standard 02.08. This document is up-issued to update Outgoing CLID Name Parameters section in MCM Configuration chapter.

December 2008

Standard 02.07. This document is up-issued to add the chapter UM Dialing Plan Configurations in Different Deployment Scenarios in the Appendix section.

November 2008

Standard 02.06. This document is up-issued to add technical content under section OC Client Presence with Mobile Extension.

October 2008

Standard 02.05. This document is up-issued to update the figure MCM configuration form and add technical content under heading OCS Application parameters.

October 2008

Standard 02.04. This document is up-issued to update the Network Topology field in MCM Configuration form.

October 2008

Standard 02.03. This document is up-issued for Nortel Communication Server 1000 Release 5.5 to support changes in technical content for OCS Proxy server installation.

September 2008

Standard 02.02. This document is up-issued for Nortel Communication Server 1000 Release 5.5. The information is related to technical content in Network Topology fields.

May 2008

Standard 02.01. This document is up-issued for Nortel Communication Server 1000 Release 5.5. The information related to OCS Mediation Server is removed.

How to get help

This chapter explains how to get help for Nortel products and services.

Getting help from the Nortel web site

The best way to get technical support for Nortel products is from the Nortel Technical Support web site:

www.nortel.com/support

This site provides quick access to software, documentation, bulletins, and tools to address issues with Nortel products. From this site, you can:

- download software, documentation, and product bulletins
- search the Technical Support Web site and the Nortel Knowledge Base for answers to technical issues
- sign up for automatic notification of new software and documentation for Nortel equipment
- open and manage technical support cases

Getting help over the telephone from a Nortel Solutions Center

If you do not find the information you require on the Nortel Technical Support web site, and you have a Nortel support contract, you can also get help over the telephone from a Nortel Solutions Center.

In North America, call 1-800-4NORTEL (1-800-466-7835).

Outside North America, go to the following web site to obtain the telephone number for your region:

www.nortel.com/callus

Getting help from a specialist by using an Express Routing Code

To access some Nortel Technical Solutions Centers, you can use an Express Routing Code (ERC) to quickly route your call to a specialist in your Nortel product or service. To locate the ERC for your product or service, go to:

www.nortel.com/erc

Getting help through a Nortel distributor or reseller

If you purchased a service contract for your Nortel product from a distributor or authorized reseller, contact the technical support staff for that distributor or reseller.

Introduction

This document describes the elements and processes necessary to integrate Nortel Communication Server 1000 (CS 1000) with the Office Communications Server 2007 (OCS 2007) in the Nortel Converged Office.

Prerequisites

- Ensure CS 1000 Release 5.5 is installed.
- Microsoft supports the coexistence of LCS 2005 SP1 Standard Edition or Enterprise Edition with OCS 2007 Standard Edition or Enterprise pools. For more information, see [“LCS 2005 and OCS 2007 coexistence” \(page 88\)](#).

Introduction navigation

- [“Converged Office component overview” \(page 17\)](#)
- [“Planning and engineering” \(page 41\)](#)
- [“Configuration” \(page 117\)](#)
- [“Office Communications Server configuration” \(page 125\)](#)
- [“Maintenance” \(page 239\)](#)
- [“Troubleshooting” \(page 245\)](#)
- [“Call Flow and protocol details” \(page 267\)](#)
- [“Configuration Examples” \(page 279\)](#)
- [“Abbreviations” \(page 327\)](#)

Converged Office component overview

This chapter provides a brief technical description of all the components associated with Nortel Converged Office.

Component overview navigation

- [“Converged Office ” \(page 17\)](#)
- [“Enterprise Voice ” \(page 19\)](#)
- [“OCS 2007 Voice components” \(page 20\)](#)
- [“Media Gateways” \(page 22\)](#)
- [“Mediation Server” \(page 22\)](#)
- [“Remote Call Control with SIP CTI \(TR/87\)” \(page 23\)](#)
- [“Telephony Gateway and Services” \(page 25\)](#)
- [“Telephony Services \(TLSV\)” \(page 26\)](#)
- [“Access Edge Server” \(page 31\)](#)
- [“OCS 2007 snap-in” \(page 32\)](#)
- [“Multimedia Convergence Manager” \(page 32\)](#)
- [“CDR data collection” \(page 33\)](#)
- [“SIP CTI \(TR/87\) Protocol” \(page 33\)](#)
- [“Hardware Load Balancer” \(page 36\)](#)
- [“Office Communicator 2007” \(page 37\)](#)
- [“Documentation References” \(page 37\)](#)

Converged Office

Many Nortel CS 1000 customers base their multimedia strategy on deploying Office Communications Server (OCS) 2007 and the Office Communicator (OC) 2007 soft clients.

The Nortel Converged Office feature combines the business-grade telephony of the CS 1000 with the OCS 2007 Enterprise Voice solution to offer a powerful converged office solution set that improves worker productivity. Telepresence and Multimodal (business set Voice over Internet Protocol (VoIP), Instant Messaging (IM), and e-mail) communications bundles, with applications such as Click-to-call and Access mobility, allow workers to stay connected when not at their desks.

Nortel Converged Office comprises the following components:

- Remote Call Control (RCC) with Session Initiation Protocol Computer Telephony Integration (SIP CTI) (TR/87) provides full Microsoft Office telephony integration to control business-grade telephony phones from within Microsoft Office applications, as well as support for a standards-based CTI interface defined by the TR/87 protocol.
- Telephony Gateway and Services provides a basic SIP Telephony Gateway to connect between Private and Public Telephony networks and OC 2007 clients.

Nortel offers unique value with the two components that provide its telephony services to OC 2007 clients and connectivity between the Office Communications Server 2007 and the Nortel telephony network.

Nortel Converged Office provides the following benefits:

- federated IM with industry name instant messaging
- Microsoft application integration
- click-to-call commands and missed call log
- easy-to-use single soft client for IM, telepresence, and VoIP telephony presence integration with Microsoft desktop and applications
- a powerful suite of Nortel applications which include:
 - Nortel Unified Messaging
 - Contact Center
 - Interactive Voice Response (IVR)
 - conferencing
 - click-to-call

Leveraging the CS 1000 and Microsoft desktop software allows end users to access business-grade telephony services on the Nortel CS 1000 from the Microsoft Office Communicator desktop client. End users can:

- originate and receive telephone calls over existing CS 1000 phones from an Office Communicator (OC) 2007 desktop client.


- originate and receive Public Switched Telephone Network (PSTN) calls from the Office Communicator (OC) 2007 soft client when away from the office.
- take advantage of existing business telephony features on the CS 1000.

Enterprise Voice

This section describes the Office Communications Server (OCS) 2007 Enterprise Voice solution. The Nortel Converged Office feature integrates the OCS 2007 with the CS 1000. For a description of the integrated network from the CS 1000 perspective, see [“Network configuration” \(page 42\)](#). Enterprise Voice is Microsoft’s software-powered VoIP solution, a SIP-based implementation of IP telephony for the enterprise that does not rely on proprietary hardware investments. Enterprise Voice is a full-featured VoIP solution that includes connectivity to the PSTN gateways and interoperation with the CS 1000. Enterprise Voice, IM, group IM, enhanced presence, and audio-video conferencing together constitute the Microsoft Unified Communications solution.

The following figure shows the OCS 2007 Enterprise Voice components extracted from the overall OCS 2007 architecture. COMO refers to Communicator Mobile.

Figure 1
Enterprise Voice components - OCS 2007



When a user calls from an Enterprise Voice client by dialing or clicking on a contact name or number in OC 2007 or Outlook:

- the OCS Front End server normalizes the number to the E.164 format, and invokes routing rules based on the location profile and user policy, and directs the call to the appropriate Mediation Server
- the Mediation Server performs all necessary media transcoding and routes the call to the IP-PSTN gateway.
- the IP-PSTN gateway, based on topology, applies local or PBX dialing rules and passes the call to the PSTN or PBX

Enterprise Voice uses Real-Time Transport Protocol (RTP) for media. Like SIP, RTP is an Internet Engineering Task Force (IETF) standard. It defines a packet format to carry audio and video over IP networks.

Enterprise Voice uses SIP for signaling and RTP for media. In the OCS, SIP is used for IM, conferencing, presence subscriptions, video, and voice enabling Enterprise Voice clients to provide a common user experience across the communication modes.

Enterprise Voice is the Microsoft SIP-based implementation of IP telephony for the Enterprise.

SIP sessions can include the sharing of real-time media. However, SIP itself does not handle the actual media data, such as audio, video, and application sharing. This separation means that SIP and various media protocols can evolve independently.

OCS 2007 Voice components

The core routing components for Enterprise Voice reside on the following:

- Standard Edition Server (in the role of Front End Server or Director)
- Enterprise Edition Front End Server

Other core routing server components include


- Translation Service—translates a dialed number into E.164 format based on the normalization rules defined by the administrator.
- Inbound Router—handles incoming calls according to user-specified preferences.
- Outbound Router—routes calls to CS 1000 or PSTN destinations after it applies authorization rules to callers and determines the optimal media gateway to route each call.

OCS 2007 Front End or Director components essential for voice support, but are not voice components include

- User Services—performs Reverse Number Look-up on the target phone number for incoming phone calls.
- User Replicator—extracts user phone numbers from the Active Directory for use by User Services and the Address Book Service.
- Address Book Service—normalizes enterprise user phone numbers to E.164 format to provision user Contacts in Office Communicator.

The following figure shows the components essential for voice support.

Figure 2
Core routing server components



Media Gateways

Media gateways are third-party hardware components that provide a common interface between the Enterprise Voice infrastructure and the PSTN. Media gateways translate signaling and media between the PSTN and Enterprise Voice infrastructure.

Media gateways translate the following protocols between the circuit-switched PSTN network and the packet-switched Enterprise Voice infrastructure:


- Signaling protocol—SS7 and other protocols on the PSTN translate to SIP for Enterprise Voice
- Transport protocol—T-Carrier or E-Carrier on the PSTN convert to RTP or Secure Real-Time Transport Protocol (SRTP) for Enterprise Voice

From the Nortel perspective, the CS 1000 functions as a media gateway for the clients of the OCS 2007 server.

Mediation Server

The Mediation Server provides signaling and media translation between the Enterprise Voice infrastructure and a CS 1000 gateway.

Figure 3
CS 1000 and OCS 2007 logical network elements



The Mediation Server provides the following functions:

- translates SIP over Transport Control Protocol (TCP) (on the CS 1000 gateway side) to SIP over mutual Transport Layer Security (TLS) on the Office Communications Server side
- encrypts and decrypts SRTP on the Office Communications Server side
- translates media streams (G.711) on the CS 1000 gateway side and RT Audio on the Office Communication Server side
- connects clients outside the network to internal Interactive Connectivity Establishment (ICE) components, to enable media traversal of NAT and firewalls
- acts as an intermediary for call flows that a gateway does not support (such as calls from remote workers on an Enterprise Voice client)

The Mediation Server uses the following types of signaling:

- For an inbound call from the CS 1000, the ms-call-source:non-ms-rtc SIP header is inserted by the Mediation Server.
- For an inbound call from the CS 1000, the Mediation Server Back 2 Back User Agent (B2BUA) generates a Session Description Protocol (SDP) offer based on its capabilities in the OCS 2007.
- For an inbound call from the CS 1000, the Mediation Server adds a phone-context attribute to a number that is not in E.164 format.
- For an outbound call from an OC 2007 client, the Mediation Server Back 2 Back (B2B) terminates the dialog and originates a new dialog with the CS 1000. The From header is replaced with a phone number derived from the p-asserted-identity header.
- OC 2007 single step transfer. The Mediation Server terminates the REFER message and returns the response code 202. The Mediation server sends an INVITE message. The Mediation Server does not forward the REFER message to the CS 1000.

Remote Call Control with SIP CTI (TR/87)

The CS 1000 and OCS 2007 integration feature allows clients of the two systems (Microsoft OCS 2007 and Nortel CS 1000) to communicate with each other. You can associate an OC Client, which connects to the OCS, with a CS 1000 line. You can perform operations on the CS 1000 line through the OC Client using Remote Call Control (RCC) often referred to as Phone-Mode. This feature allows for consistent access to RCC, service control and configuration and telepresence functions across different endpoints supported by the CS 1000.

The Nortel Converged Office Solution is implemented through an open interface to ensure that any CS 1000 feature supported through OC 2007 is also accessible to applications from other vendors and application developers who support these interfaces.


The SIP CTI (TR/87) protocol is on the CS 1000 Signaling Server. OC 2007 uses the TR/87 specification to implement phone integration throughout the suite of Microsoft Office applications. You cannot use Office Communicator to invoke a feature that is not supported by the phone.

Example of RCC with SIP CTI (TR/87)

Figure 4 "Remote Call Control" (page 24) shows an example of a CS 1000 call to a mobile client. The following steps correspond to the numbers in the figure:

1. A user selects Call to Chris' mobile phone number from the CS 1000 telephone.
2. The Office Communications Server 2007 sends a call request to the CS 1000.
3. The CS 1000 sets up a call from the user's phone to Chris' mobile phone number.
4. Chris answers his mobile phone and a media path is established between the two phones.

Figure 4
Remote Call Control



The full set of business-grade telephony features available with CS 1000 telephones is integrated with the OC 2007 client and can also be operated from a CS 1000IP Phone, even when the client is unavailable. This integration ensures that telephony service reliability is preserved during interruptions in soft client operation.

With the convergence of the CS 1000 with the OCS 2007, the OC 2007 client compliments the voice communications between two users by allowing other media types, such as IM, file, and application sharing to an existing voice call without the need to establish an independent session between the users.

Telephony Gateway and Services

With the Telephony Gateway and Services component, users can choose how to make and receive calls. For outgoing calls, users can make a call from their Office Communicator soft client instead of their CS 1000 phone. You can handle incoming calls in one of two ways: through the computer with OC 2007 or through a phone. This feature provides users with computer-to-phone and phone-to-computer connectivity, leveraging the Nortel provided dial plan, telephony infrastructure, and telephony features to make and receive calls using Office Communicator (OC) 2007 Client as a soft client.


With this solution, you can configure Telephony Services (TLSV) on the CS 1000 for each user with this functionality. The CS 1000 configured with the TLSV provides number plan translations, Call Detail Recording (CDR) for outgoing calls, and enables telephony features, such as Call forward No Answer to Voice Mail, Attendant Recall, and participation as a client in a Group Call for incoming calls.

With the Telephony Gateway and Services component, you can configure the OC 2007 as a Multiple Appearance Directory Number (MADN) member for users with TLSV on the CS 1000. With TLSV, calls to a user's phone number can be presented to both the desktop phone and to the OC 2007 client simultaneously. The user can then choose to answer on the most convenient device.

The ability to connect between computers and phones is not natively provided by Office Communications Server 2007; however, the Telephony Gateway and Services component enables this functionality using the SIP Gateway and Multimedia Convergence Manager (MCM) application. MCM directs calls from an Office Communicator user to the CS 1000 connected to their twinned telephone. Telephony Gateway and Services allows you to originate and receive SIP calls (for example, VoIP and Computer calls) from Office Communicator.

In [Figure 5 "Dual forking example" \(page 26\)](#), OCS Front End (FE) forks the call to the CS 1000. The twin phone rings once and does not send another invite. The same scenario applies to calls originating from the CS 1000, the OCS does not get informed to perform another fork. A new setting is introduced on OCS 2007 server that enables or disables dual forking for each user. Remote Call Control (SIP CTI) is available when dual forking is enabled.

Figure 5
Dual forking example



Telephony Services (TLSV)

Many of the features provided by CS 1000 to traditional telephones are extended to Office Communicator clients configured with Telephony Services (TLSV). For example, calls that remain unanswered can be forwarded using the Call Forward No Answer feature.

To use the Office Communicator soft client for voice calls using the Telephony Gateway and Services, a TLSV must be configured with the same DN as the user in a MADN arrangement. This offers incoming voice calls to the user's DN on their Office Communicator, as well as any phones that they have been configured with the same DN.

For incoming calls to be extended to the "twinned" Office Communicator client, a UEXT Terminal Number (TN) must be defined for that DN. The TLSV subtype has been introduced so a distinction is made between UEXT associated with the OCS 2007 client and UEXT associated with other types of clients. During call processing, the subtype is checked to determine whether an incoming call should be extended to the UEXT target DN or not. For more information on configuring TLSV, see ["Configuring Telephony Services" \(page 162\)](#).

For outgoing calls from the Office Communicator, the user must have at least one TN configured on the CS 1000 Call Server. The MCM locates the Call Server associated with a user by their numbering plan entry in the NRS. This generates calls from Office Communicator clients on Telephony Gateway and Services to always tandem through the user's active Call Server. Note that with Geographic Redundancy features, a user's active Call Server may change during failure scenarios.

The Network Class of Service (NCOS) setting for outgoing calls from Office Communicator clients is determined by the configuration of the MARP TN when in a MADN group, or by the configuration of the UEXT when it is the only TN for the user.

With TLSV and Remote Call Control configured, users receive one pop-up window for the incoming call to the phone or computer. Users can choose the most convenient way to answer an incoming call.


Telephony Services (TLSV) service

While at the office, a user may decide to use a desktop phone to answer calls. However, the user can still accept calls through the OC 2007 while they travel to locations that have network connectivity (for example, at hotels).

The following steps correspond to the numbers in the figure:

1. The CS 1000 system receives a PSTN call to the user's phone number.
2. The CS 1000 rings the user's phone and uses the TLSV subtype to provide simultaneous ringing to both the user's phone and the Office Communicator voice client.
3. The user can answer the call through the CS 1000 phone or the Office Communicator voice client.

Figure 6
Example call scenario



Users can be reached anywhere on the network and significant cost savings are incurred by using IP telephony through Virtual Private Network (VPN) access to their private network.

As part of the telephony services, many incoming call features are available even when using the OC 2007 as a telephony device or more specifically in Computer mode. Features such as Call Forward No Answer, Unified Messaging, Call Detail Recording, and Attendant Recall are maintained within the CS 1000 system for calls presented to the OC 2007.

Telephony Gateway and Services can access all of the telephony network resources using the OC 2007 client. Calls can originate from the OC 2007 client to the PSTN, phones, or services within the telephony network. Users can access all of their telephony network resources as long as they have the soft client and a high-quality connection to their private network. Telephony Gateway and Services is enabled by the interworking of the CS 1000 SIP Gateway with the OCS 2007 SIP gateway software.


Direct SIP

The following section provides information for configuration and deployment of Communication Server 1000 Direct SIP Gateway for Microsoft Office Communications Server 2007.

This section describes the three options for provisioning a CS1000 as Direct SIP Gateway for Microsoft OCS 2007. The options are:

- Direct SIP (Basic Media Gateway): Standalone
- Direct SIP (Basic Media Gateway): Networked
- Direct SIP (Basic Media Gateway and Converged Users) - Hybrid

Direct SIP (Basic Media Gateway): Standalone




Characteristics:

- OCS users are not associated with a DN on the CS 1000.
- This provides PSTN Gateway services to OCS.
- Nortel CS 1000 Dialing Plan configuration for OCS must be the E.164 format only, as required by the Microsoft Mediation server.
- PEP MPLR28305 need to installed in the GW.

Direct SIP (Basic Media Gateway): Networked

The following diagram shows the standard configuration for using the CS 1000 as a Direct SIP Gateway with OCS 2007 networked with other CS 1000 systems.



Characteristics:


- OCS users are not associated with a DN on the CS 1000.
- CS 1000 users may be configured on the Direct SIP Gateway system but not as converged office users.
- Nortel CS 1000 dialing plan configuration for OCS must be the E.164 format only, as required by the Microsoft Mediation server.
- PEP MPLR28305 need to be installed in both GWs.

ATTENTION

The Mediation server is configured as a Static Endpoint on the Network Routing Service (NRS).

Direct SIP (Basic Media Gateway and Converged Users) - Hybrid

The following diagram defines the standard configuration for using the CS 1000 as an OCS 2007 SIP Gateway for standalone OCS users and Converged Office users in a CS 1000 network. This is a Nortel supported and preferred configuration. The OCS 2007 standalone users and converged office users are co-resident.



Characteristics:

- Converged OCS users are associated with a TLSV UEXT on the CS 1000.
- PEP MPLR28305 installed on SIP GW B only (Direct SIP GW).
- The NRS in this deployment is used as a redirect or proxy server.

It is necessary to have two SIP Gateways and 2 Mediation Servers. One SIP gateway connects to the MCM which in turn connects to a Mediation server for enabling converged users. The second SIP gateway connects to the second Mediation server for enabling non-converged users.

ATTENTION

Users can enable features such as conference on top of this set-up without the need of configuring a DN on the CS 1000. For non direct-SIP users, a virtual TN(UEXT) must be configured in the CS 1000 with a HOT P key in order to extend the call to OCS, and to establish a session thereafter.

Access Edge Server

Access Edge Servers allow internal and external users to communicate across corporate firewalls. Access Edge Servers enable IM and presence, as well as Web conferencing and audio/video (A/V) collaboration between internal and external users.

Access Edge Servers include the following server roles deployed on one or more computers in the perimeter network:

- The Access Edge Server handles the SIP traffic necessary to establish and validate connections between internal and external users.
- The Web Conferencing Edge Server enables external users to participate in internal conference meetings. The Web Conferencing Edge Server handles the exchange of meeting content between internal and external users.
- The Audio/Video (A/V) Edge Server enables A/V conferencing between internal and external users to allow for the sharing of audio and video with external users.

Microsoft recommends that you use the OCS 2007 Director, although it is not required.

ATTENTION

Office Communicator video is supported only for Remote Call Control between two Office Communicator clients. Office Communicator video is not supported if one of the clients goes through the SIP Gateway.

OCS 2007 snap-in

The Office Communications Server 2007 snap-in for MMC is redesigned. The Status pane of the Office Communications Server 2007 snap-in provides configuration settings at-a-glance for your forest, domains, pools, servers, and users. The Status pane also features a new Database tab, which can be used to query a pool's back-end databases. Each query is displayed as an expandable item in a list.

Microsoft Management Console (MMC) is automatically installed on each server in the domain that is running Office Communications Server 2007 or any computer on which Office Communications Server 2007 administrative tools are installed. It is not used to administer Edge Servers or Proxy Servers.

ATTENTION

Enhanced presence must be enabled prior to Converged Office telephony integration. You can enable enhanced presence from the Office Communications Server Users Wizard in the Configure Users Settings window.

Multimedia Convergence Manager

MCM 3.5 is a software component that ensures interoperability between the Nortel CS 1000 and the Microsoft Office Communicator Server (OCS) 2007. MCM 3.5 is compatible with CS 1000 Release 5.0 with PEP and CS 1000 Release 5.5. MCM 3.5 can be used in a mixed environment. For example, it can be configured with SIP TLS to SPS and communicate with

5.0 and 5.5 nodes. The MCM ensures CS 1000 and OCS interoperability of protocols, users, and phone numbers are managed within the Microsoft Active Directory. It also allows the system to block calls where the client is not in the Active Directory (AD). The MCM performs a number of functions that include:

- translation between telephony phone numbers and user IDs within the Active Directory
- authentication of user phone numbers for RCC
- Numbering Plan normalization
- protocol interworking
- redundant connections to the CS 1000 network components (SIP Redirect Service (SRS), Sip Proxy Server (SPS), and redundant Signaling Servers)

CDR data collection

OCS 2007 supports CDR capability. OCS 2007 CDRs collect different kinds of data that include user logon and logoff, IM and audio call details, Conferencing start and join. You must install the Archiving and CDR Server to support these features. The outgoing calls from the OC 2007 to CS 1000 telephone are captured by this server, as well as OC to OC calls. Thus a call accountant can retrieve CDRs from both the CS 1000 and Archiving server to obtain a consolidated report. In RCC mode, CDRs are captured only on the CS 1000 side. For more information, see *Microsoft Office Communications Server 2007 Archiving and CDR Server Deployment Guide* Download Microsoft technical documentation from the Download Center at www.microsoft.com.

SIP CTI (TR/87) Protocol

The SIP CTI (TR/87) FE application introduced with this package is not limited to Microsoft applications. Through support of the ECMA TR/87 standard, Nortel partners can use this interface to develop SIP CTI capabilities for use with any specification-compliant application.

If Preferred Calling Device is configured as Phone, a user receives one pop-up notification with an incoming call, as depicted in [Figure 7 "Call Appearance pop-up window" \(page 34\)](#). The OC user can click Redirect to choose the client as the answering device.

Certain portions of the protocol are not supported at this time. Additional information about the SIP CTI (TR/87) protocol is available to Nortel partners upon request.

Figure 7 "Call Appearance pop-up window" (page 34) shows an example of an incoming call pop-up window.

Figure 7
Call Appearance pop-up window




Figure 8 "SIP diagram" (page 35) depicts the SIP protocol information.

Figure 8
SIP diagram





Figure 9 "IP diagram" (page 36) depicts the IP protocol information.

Figure 9
IP diagram



ATTENTION

Customers must not use their Office Communicator client to call Emergency numbers (for example, 911). To ensure that emergency service organizations can accurately trace the source of the call, always use a desktop phone to place an emergency call.

Hardware Load Balancer

Hardware IP Load Balancers (for example, Nortel Application Switches) are required for multiple Office Communications Server 2007 Enterprise Edition deployment. The Load Balancer presents a single virtual IP (VIP) address to clients to prevent direct access to individual OCS 2007 Enterprise Edition servers. The Load Balancer uses an algorithm (for example, round-robin, or fewest connections) to route new client requests to the Office Communications Servers.

Hardware Load Balancers deliver load distribution to avoid a single point of failure. Other benefits include increased performance and added redundancy. The CS 1000 uses Load Balancers for the signaling path of VoIP calls and Remote Call Control.

A Load Balancer is not required if you deploy:

- a Standard Edition server
- a single Enterprise Edition Front End server

A load balancer is required if you deploy:

- multiple OCS 2007 Enterprise Edition Front End servers
- an Array of Edge Servers
- an Array of Directors in OCS 2007
- an Array of OCS Proxy/MCM servers (for redundancy)

Microsoft recommends deploying a hardware load balancer for arrays of Office Communications Server 2007, Edge Servers, and Directors but it is not a requirement. Office Communications Server 2007 does not support the use of Windows Server 2003 Network Load Balancer in production or lab deployments. The CS 1000 is only concerned with the load balancers for the signaling path for VoIP and Remote Call Control (RCC).

Office Communicator 2007

For detailed information about using Office Communicator 2007 and its components, see *Converged Office User Guide — Microsoft Office Communications Server 2007* (NN43001-123).

Documentation References

A list of Nortel and Microsoft documentation is available for reference from the following Web sites.

- You can download Nortel documentation from the Nortel technical documentation Web site at www.nortel.com.
- Download Microsoft technical documentation from the Download Center at www.microsoft.com.

The following Nortel technical documents are relevant to Nortel Converged Office.

Table 1
Nortel technical documentation

Technical document	Content	Primary audience
<i>Converged Office User Guide — Microsoft Office Communications Server 2007</i> (NN43001-123)	Contains information about using the OC client.	General users
<i>Communication Server 1000E Planning and Engineering</i> (NN43041-220)	Contains instructions about calculating the anticipated call traffic for the CS 1000.	Administrators
<i>Features and Services</i> (NN43001-106)	Contains information about the Multiple Customer environment, Multiple Appearance DN , Call Forward On feature, and defining and configuring a UEXT TN.	Administrators
<i>CallPilot Network Planning Guide</i> (NN44200-201)	Contains information about configuring CallPilot for Telephony Gateway (Computer mode) calls.	Administrators
<i>Communication Server 1000M and Meridian 1 Small System Installation and Commissioning</i> (NN43011-310)	Contains information about CS 1000 Installation and Commissioning	Administrators
<i>Communication Server 1000M and Meridian 1 Large System Installation and Commissioning</i> (NN43021-310)	Contains information about CS 1000 Installation and Commissioning	Administrators
<i>Communication Server 1000E Installation and Commissioning</i> (NN43041-310)	Contains information about CS 1000 Installation and Commissioning	Administrators
<i>Signaling Server Installation and Commissioning</i> (NN43001-312)	Contains information about CS 1000 Installation and Commissioning	Administrators
<i>IP Peer Networking Installation and Commissioning</i> (NN43001-313)	Contains information about creating the required components on a Call Server, dialing plans, configuring codecs, configuring HLOC and HNPA, configuring SIP trunks, configuring NRS, and alternate routing logic (for Geographic Redundancy).	Administrators

Technical document	Content	Primary audience
<i>Transmission Parameters</i> (NN43001-282)	Contains information about configuring the loss plan and DTI Data Bock.	Administrators
<i>Element Manager System Administration</i> (NN43001-632)	Contains information about how to access Operational Measurements through Element Manager.	Administrators
<i>NRS Installation and Commissioning</i> (NN43001-564)	Contains procedural information.	Administrators
<i>Communication Server 1000 with Microsoft Exchange Server 2007 Unified Messaging Fundamentals</i> NN43001-122	Contains information about how to setup Unified Messaging on Microsoft Exchange.	Administrators

Table 2
Microsoft OCS 2007 and OC 2007 documentation

Guide	Contents	Primary audience
<i>Microsoft Office Communications Server 2007 Documentation Roadmap</i>	Guide to the contents and uses of the documentation.	Administrators
<i>Office Communications Server 2007 Technical Overview</i>	Contains a high-level survey and summary of the features, architecture, and protocols of Office Communications Server 2007.	Administrators
<i>Microsoft Office Communications Server 2007 Planning Guide</i>	Contains step-by-step information about planning your deployment.	Senior Administrators responsible for planning deployment
<i>Microsoft Office Communications Server 2007 Enterprise Voice Planning and Deployment Guide</i>	Contains information on how to plan, deploy, and manage the new Enterprise Voice capabilities in Office Communications Server 2007.	Administrators and Telephony Engineers responsible for planning an IP telephony infrastructure and deploying Enterprise Voice
<i>Microsoft Office Communicator 2007 Getting Started Guide</i>	Contains information on how to get started with Office Communicator 2007.	End-users and Administrators
<i>Office Communicator 2007 Quick Reference Cards</i>	Contains a summary of information for Office Communicator 2007.	End-users and Administrators
<i>Migrating to Microsoft Office Communications Server 2007</i>	Contains information on migrating from LCS 2005 to OCS 2007.	Administrators

Planning and engineering

This chapter contains information about topics you must consider before you implement Converged Office.

Planning and engineering navigation

- [“Planning process” \(page 41\)](#)
- [“Network configuration” \(page 42\)](#)
 - [“Small network” \(page 43\)](#)
 - [“Medium network” \(page 44\)](#)
 - [“Large network” \(page 45\)](#)
 - [“Multiple customer network” \(page 46\)](#)
 - [Figure 14 “Multiple location network” \(page 48\)](#)
- [“Load Balancer planning” \(page 48\)](#)
- [“Capacity planning” \(page 52\)](#)
- [“General requirements” \(page 56\)](#)
- [“Telephony Gateway and Services planning” \(page 71\)](#)
- [“Remote Call Control with SIP CTI” \(page 79\)](#)
- [“LCS 2005 and OCS 2007 coexistence” \(page 88\)](#)
- [“Migration planning from LCS 2005 to OCS 2007” \(page 91\)](#)

Planning process

Before you install and configure Nortel Converged Office, you must consider the network size and its impact on the type of software and hardware required.

Nortel recommends that you implement the Telephony Gateway and Services component to provide basic connectivity (which you can more readily debug), followed by the Remote Call Control (RCC) for more complex feature operation. Configure both Telephony Gateway and Services and RCC only in situations where both components are required.

Consider the following during the planning process.

- Consider the size of your network. See [“Network configuration” \(page 42\)](#) for detailed information about determining your network architecture.
- Determine the type of users (internal and external users) and anticipated call traffic. For more information about type of users, see [Table 5 “Maximum supported users for each topology” \(page 57\)](#). For information about calculating the anticipated call traffic for the Communication Server 1000, see *Communication Server 1000E Planning and Engineering* (NN43041-220).
- Determine that the software and hardware components required for the CS 1000 are installed and have the latest software versions. For more information, see [“CS 1000 and Signaling Server installation” \(page 111\)](#).
- Determine that the software and hardware components required for Office Communications Server (OCS) 2007 have the latest software versions. For more information, see [“OCS 2007 component installation” \(page 111\)](#).
- Determine the system requirements for the OC 2007 client. For more information, see [“OC 2007 client requirements” \(page 53\)](#).
- Determine capacity requirements for all components. For more information, see [“Capacity planning” \(page 52\)](#).
- Prepare your infrastructure.
- Plan for external user setup. For more information, see [“Access Edge Server” \(page 31\)](#).
- Plan your implementation strategy.

For more information on deploying OCS 2007, see the *Microsoft Office Communications Server 2007 Planning Guide*. Download Microsoft documentation from the Download Center at www.microsoft.com.

Network configuration

The main consideration when you plan and engineer the Converged Office desktop is the size of the network. Networks are divided into three main categories: small, medium, and large. Each type requires specific configuration.

The following sections describe typical network topologies to assist in determining capacity and robustness requirements.

Note: The descriptions and graphical representations of the three network types are for illustration only, and are not actual configurations. The number of CS 1000 systems and Office Communications Server 2007 servers is based on the engineering guidelines found in this document and those provided by Microsoft.

Small network

If you have a small network that requires ease of management, you can choose a basic configuration. Microsoft recommends the following configuration for small organizations that do not require high availability for OCS 2007.


A small network can include the following components:

- a CS 1000 system with Media Gateway and Signaling Server
- support for IM and conferencing for internal users and can include external users
- up to 5000 users

You will need:

- An Office Communications Server 2007 Standard Edition server
- a single Edge Server deployed in the perimeter network for external user access
- An OCS Proxy server that runs MCM 3.5
- a Mediation server

Figure 10
Small network configuration



Medium network

A medium network can include the following components:


- one or multiple CS 1000 systems with Media Gateway and Signaling Server
- a Primary NRS with an Alternate Network Routing Service (NRS) that co-reside on one of the Signaling Servers
- up to 5000 users
- high availability with system redundancy for OCS 2007

You will need:

- an Office Communications Server 2007 Enterprise Edition
- an OCS Proxy server that runs MCM 3.5
- a Mediation Server

If you install only one OCS 2007 Enterprise Edition server, a Load Balancer is not required. SPS (Linux-based NRS) does not support co-residency.

Figure 11
Medium network configuration



Large network

A large network can include the following components:

- multiple CS 1000 systems with Media Gateway and Signaling Server
- configured collaborative NRS
- redundant Primary and Alternate NRS
- more than 5000 users
- high availability with system redundancy for OCS 2007

You will need:

- an OCS 2007 Enterprise Edition server with Load Balancers to Front End the pool of Enterprise Edition servers
- a redundant OCS Proxy servers that run MCM 3.5 (the recommended deployment requires that MCM reside on a separate OCS Proxy server)

- Mediation servers
- Load Balancers


The redundant, primary, and alternate NRS can be either the VxWorks NRS or the Linux-based NRS (SPS/SRS). For the OCS 2007 Enterprise Edition server, a SQL back end database server is a requirement.

ATTENTION

If you set up more than one server that runs the Enterprise Edition of Microsoft Office Communications Server 2007, you must use a Load Balancer in accordance with the Unified Communications Engineering Rules and Guidelines.

The Load Balancer ensures that the Fully Qualified Domain Name (FQDN) of the pool is not equal to the FQDN of any Front End server in the pool.

Figure 12
Large network configuration




Multiple customer network

You can configure the CS 1000 with a number of customers that have their own set of telephones, trunks, features, restrictions, and numbering plans. In the Converged Office environment, each customer is treated as a separate machine. Each customer shares one OCS deployment, but has their own Node Number, MCM, Signalling Server, and SIP domain in the forest. For more information about the Multiple Customer environment, see *Features and Services* (NN43001-106).

Figure 13 "Multiple customer network" (page 47) provides an example of a multiple customer network. The figure shows two customers: Customer 1 (Ottawa) and Customer 2 (Belleville), each with their own set of associated phones and Signalling Servers. This type of configuration is required for any deployment that uses the Telephony Gateway and Services functionality, or in scenarios where both Telephony Gateway and Services and Remote Call Control functionality is deployed.

Figure 13
Multiple customer network



The Signaling Server for Customer 1 is in the domainOne.com domain. For each customer, you must configure a separate Office Communications Server domain. The Office Communications Server domain used by Customer 1 is in the same domain as the Signaling Server domainOne.com. Each OCS domain requires a separate Active Directory.

The only equipment that Customer 1 and Customer 2 share is the CS 1000 and the NRS. The NRS can only be shared by the two customers if it is configured with both domainOne.com and domainTwo.com.


The Signaling Server, OCS Proxy server (which runs MCM), OCS 2007 Front End server, and Active Directory are separate. The number of Signalling Server(s), OCS 2007 Proxies, and OCS 2007 Front End servers

required for each customer are the same as if each customer were part of a single system. However, the total number of users allowed for the CS 1000 is the total number of users for all customers.

Multiple location network

The following diagram shows the path of an inbound and outbound call in a multiple location network configuration in a single forest deployment. The MCM routes inbound calls from the Signaling Server to the appropriate Mediation Server within the Mediation Server pool. When the current Mediation Server does not answer, MCM jumps to the next Mediation Server.

Figure 14
Multiple location network



For regional or multiple location deployments, it is required to install SPS/SRS. Two Primary/Secondary SPS/SRS may co-exist within one configuration to improve the system's robustness. In the previous versions of the program, the MCM performs polling by sending SIP OPTION request to determine which SPS/SRS is active. The active SPS/SRS becomes the last one to send an OK response. The SIP Proxy Server (SPS) sits between MCM and the TR87 FE application that reside on CS 1000. This SIP proxy allows communication between the CS 1000 and OCS when different transport protocols (TLS and TCP) are used.

Load Balancer planning

This section provide information on the Load Balancer requirements.

Load balancer navigation

- [“Load Balancer prerequisites” \(page 49\)](#)
- [“Load Balancer requirements” \(page 50\)](#)
- [“Redundancy with Load Balancers” \(page 51\)](#)
- [“High-scale and high availability configuration” \(page 51\)](#)
- [“Nortel Application Switch” \(page 52\)](#)

Load Balancer prerequisites

- Before you configure a Load Balancer to connect to the Office Communications Server Enterprise pool, ensure you configure the following:
 - The Load Balancer must meet the Microsoft criteria for a Load Balancer. See [“Load Balancer requirements” \(page 50\)](#)
 - Configure a static IP address for servers within your pool.
 - For each server within the pool a certificate, include for both user and server authentication issued by a certification authority in the pool's local domain.
 - Configure a VIP address and a DNS record for the load balancer.
 - Test users created and SIP-enabled in the pool.
 - Install root certificate from CA in the domain (or trusted CA) on client computers.
 - Log on to all servers in the pool using TLS to ensure server and client certificates work.
 - Configure Port 135 on Load Balancers to enable server-side block and allow functionality for users and move user scenarios to pools through DCOM. For example, perform remote DCOM-based database operations. Nortel recommends the minimum configuration.

Table 3
Load balancer minimum configuration

Service	Protocol	Port (range)	Description
TLS pool	TCP	5061	The client listens over the same connection that is open to the server. By default, the server listens on port 5061 (TCP). The server sends packets to the client only over the client TLS session.
DCOM	TCP	135	Installation and management.

- Optionally, configure the TCP pool on port 5060 for clients to connect to the Load balancer through TCP.

Load Balancer requirements

A Load Balancer for the Office Communications Server (OCS) Enterprise pool must meet the following requirements:

- The Load Balancer must expose a VIP Address through Address Resolution Protocol (ARP).
- The VIP must have a single DNS entry, called the pool FQDN.
- The VIP must be a static IP address.
- The Load Balancer must allow multiple open ports on the same VIP. Specifically, it must expose the ports 5060, 5061, 135, 80, 443, and 444.
- The Load Balancer must provide TCP-level affinity. This means that the Load Balancer must ensure that it can establish TCP connections with one Office Communications Server in the pool and all traffic on that connection is destined for that same Office Communications Server.
- The Load Balancer must provide a configurable TCP idle-timeout interval with a maximum value greater than or equal to the minimum of the REGISTER refresh or SIP Keep-Alive interval.
- The Load Balancer must support a rich set of metrics (round robin, least connections, and weighted). Nortel recommends a weighted least connections-based load balancing mechanism for the Load Balancer. This means that the load balancer ranks all Office Communications Servers based on the weight assigned to them and the number of outstanding connections. The Load Balancer use the rank to pick the Office Communications Server to use for the next connection request.
- The Load Balancer must detect Office Communications Server availability by establishing TCP connections to ports 5060, 5061, or both (often called a heartbeat or monitor). The polling interval must be a configurable value with a minimum value of at least five seconds. The load balancer must not select an Office Communications Server that shuts down until it can establish a successful TCP connection (heartbeat) again.
- Every Office Communications Server must have exactly one network adapter. Multihoming an Office Communications Server is not supported. If a 10/100 network adapter does not meet the required bandwidth constraints, a gigabit network adapter must be used.
- The network adapter must have at least one static IP address. This IP address will be used for the incoming load-balanced traffic.

- The computer must have a registered FQDN. The IP address registered for this FQDN must be publicly accessible from within the enterprise.
- The Load Balancer must include less than one gigabit capacity for up to 50 000 concurrent client connections. One gigabit of capacity is required to support more than 50 000 concurrent client connections.

For more information about Load Balancer requirements, see *Microsoft Office Communications Server 2007 Document: Planning Guide*. Download Microsoft technical documentation from the Download Center at www.microsoft.com.

Redundancy with Load Balancers

You can add redundancy to your network by placing Load Balancers, such as a Nortel Application Switch, for the OCS 2007 Front End servers, and for the OCS 2007 Proxy servers (MCM pool).


The Load Balancer of the MCM pool balances SIP invites from the Mediation Server to the OCS Proxy server (for VoIP mode). The Mediation Server sends all SIP invites to the Virtual IP of this Load Balancer. The Load Balancer then sends the SIP Invite to the least busy Office Communications Server 2007 OCS Proxy. Redundancy is also ensured for calls to an Office Communicator user from the CS 1000 by having a Load Balancer for multiple OCS Proxy servers (MCM pool).

The Load Balancer of the OCS 2007 Front End servers balances SIP invites from the Mediation Server (for VoIP mode) to the least busy Front End server. This is the same load balancer that is used when the Office Communicator addresses the pool for registration. The incoming load balancer balances the incoming traffic to the Front End servers. See [Figure 15 "Incoming Load Balancer" \(page 52\)](#) for an example.

High-scale and high availability configuration

The pool of Front End servers processes inbound and outbound traffic. In this example, the Load Balancer routes incoming SIP messages to the less busy server based on a configured algorithm. The Load Balancer VIP address is used by clients as a single point of connection to the pool. This address is listed in DNS and has an FQDN. Internal OCS clients require the DNS server to establish a connection with the Enterprise Edition Pool.

Figure 15
Incoming Load Balancer



Nortel Application Switch

Nortel recommends that you use the Nortel Application Switch (NAS) for Load Balancing.

Capacity planning

This section provides the capacity requirements for the various components.

Capacity planning navigation

- [“OC 2007 client requirements” \(page 53\)](#)
- [“Load Balancer capacity requirements” \(page 53\)](#)
- [“SIP CTI \(TR/87\) services requirements” \(page 53\)](#)

- “Mediation server requirements” (page 55)
- “Signaling Server requirements” (page 55)
- “Call Server requirements” (page 55)
- “OCS Proxy and MCM capacity requirements” (page 55)

OC 2007 client requirements

The PC that runs the OC 2007 must be registered to the domain in which the OCS 2007 server runs. The OC 2007 client can be installed on a PC that runs most versions of Microsoft Windows with the hardware device driver API DirectX 9 or later. For more information on the OC client requirements, see [Table 11 "Office Communicator client requirements" \(page 60\)](#).

For more information about deploying the OC client, see *Microsoft Office Communicator 2007 Deployment Guide*. Download Microsoft technical documentation from the Download Center at www.microsoft.com.

Load Balancer capacity requirements

Capacity planning for OCS 2007 is measured in terms of the number of clients. However, this becomes difficult to measure because of the enhanced capabilities and services for a pool and the variety of components that can be enabled in OCS 2007. Components can reside on separate servers, which adds to the complexity of capacity planning. A single client user can have multiple connection instances that depend on the features enabled. Each feature has different bandwidth requirements that can differ from one enterprise to another.

For more information on capacity guidelines, see [Table 5 "Maximum supported users for each topology" \(page 57\)](#).

For more information about capacity planning, see the *Microsoft Office Communications Server 2007 Planning Guide*. Download Microsoft technical documentation from the Download Center at www.microsoft.com.

SIP CTI (TR/87) services requirements

When you plan for capacity with Session Initiation Protocol Computer Telephony Integration (SIP CTI) services, observe the following restriction: For a single CS 1000 that supports multiple nodes, (each with SIP CTI services enabled), you can establish multiple SIP CTI (TR/87) sessions for a DN through the same node—but not through different nodes.

To illustrate this, consider the following high-level example:


Client A sends a TR/87 SIP INVITE to Node 1 to monitor DN 1000. The TR/87 association is established. Client B then sends a TR/87 SIP INVITE to Node 1 (the same node) to monitor DN 1000. Both sessions are established successfully. As a result of this sequence, two TR/87 sessions exist for DN 1000 through Node 1.

However, if Client B attempts to send a TR/87 SIP INVITE to Node 2 (which has an AML link to the same call server as Node 1), the attempt to establish the TR/87 session fails because the DN is already in use by Client A's session through Node 1.

To solve this issue when you plan for capacity, SIP routing must ensure that all TR/87 sessions for a DN always terminate on the same node when there are multiple nodes for a single CS 1000 call server, as depicted in [Figure 16 "SIP CTI \(TR/87\) example" \(page 54\)](#).

This issue can arise in cases where a single user has multiple clients logged on simultaneously (for example, a client at home, a client in the office, and a mobile client; each with TR/87 capability).

Figure 16
SIP CTI (TR/87) example



Mediation server requirements

The CS 1000 can process up to 13 000 simultaneous calls. Therefore, you may require several Mediation servers for one CS 1000. To correctly deploy OCS 2007 to interwork with the CS 1000, you must correctly engineer the network to handle the anticipated call traffic. Calculate the anticipated call traffic for the CS 1000 using the instructions in *Communication Server 1000E Planning and Engineering* (NN43041-220). For more information on hardware requirements, see [Table 7 "Mediation Server hardware requirements" \(page 58\)](#).

Signaling Server requirements

The maximum number of SIP CTI (TR/87) users on a single Signaling Server is 5000. One Signaling server can support up to 1800 SIP trunks; therefore, you require up to two Mediation servers for a single Signaling Server. To increase the system capacity, associate a pool of Mediation Servers with each Call Server. MCM routes inbound calls from the Signaling Server to the appropriate Mediation Server within the Mediation Server pool.

For example, MCM works as a software load balancer in addition to a router. MCM uses a round-robin algorithm for load balancing. When the current Mediation Server does not answer, MCM jumps to the next Mediation Server. You can use load balancing for direct mode and with SPS or SRS.

For Release 5.0, 1 GB of memory is required for a standard Signaling Server. All signaling servers must run the latest software version. For information on geographic redundancy, see ["Geographic redundancy" \(page 85\)](#).

Call Server requirements

The CS 1000 must run Release 5.5.

For different CPUs, the number of supported users are:

- CP PII: 7000 users
- CP PIV: 13 000 users
- CP PM: 13 000 users

OCS Proxy and MCM capacity requirements

The MCM is required to reside on a separate OCS Proxy server and the capacity of the OCS Proxy server with MCM depends on the hardware platform and the usage. For example, VoIP calls only, SIP CTI calls only or a combination of both. Because capacity characterization cannot be conducted on all server platforms, Nortel recommends using standardized

sets of relevant benchmarks available from the Standard Performance Evaluation Corporation (SPEC). SPEC is a non-profit corporation formed to establish, maintain, and endorse benchmarks that can be applied to the newest generation of high-performance computers. A compressive list of benchmarks is available at www.spec.org.

The server used for capacity characterization had a SPECint_rate2000 value of 18.6. See [Table 4 "Maximum call rate" \(page 56\)](#) for the maximum call rate of this server for the three different configurations.

Table 4
Maximum call rate

Usage	Maximum call rate
VoIP calls	15 000
SIP CTI (TR/87) calls	10 000
Combined	12 500*
* Depends on the ratio of either call scenarios assumed 50% of each. For example: Worst case—all SIP CTI calls, Best case—all VoIP calls.	

The number of users the OCS Proxy server with MCM can handle depends on the usage and the number of calls per hour per user. For example, assuming 5 cph/user for VoIP calls would give 3000 users (15 000 cph/5 cph/user = 3000 users).

The following are the formulas (based on SPECint_rate2000) to calculate the maximum call rate for different platforms:

- VoIP calls only. Number of calls per hour supported = $(15\,000 \times \text{SPECint of HW}) / 29.8$.
- SIP CTI (TR/87) RCC calls only. Number of calls per hour supported = $(10000 \times \text{SPECint of HW}) / 29.8$.
- Both VoIP and SIP CTI (TR/87) RCC calls combined. Number of calls per hour supported = $[(15\,000 \times \text{SPECint of HW}) \times (\text{VoIP\_call\%}) + (10\,000 \times \text{SPECint of HW}) \times (\text{SIPCTI\_call\%})] / 29.8$.

ATTENTION

VoIP_call% or SIPCTI_call% must be less then 100%.

ATTENTION

An OCS Proxy is not an Access Proxy. For more information on OCS proxy hardware requirements, see [Table 8 "OCS Proxy server hardware requirements" \(page 59\)](#).

General requirements

This section provides general guidelines and requirements to follow when you deploy the Office Communications Server 2007.

General requirements navigation

- [“Server topology” \(page 57\)](#)
- [“Operating System Requirements” \(page 58\)](#)
- [“Hardware Requirements” \(page 58\)](#)
- [“Virtual Server 2005” \(page 60\)](#)
- [“Storage” \(page 60\)](#)
- [“Trunks” \(page 61\)](#)
- [“SIP access port ” \(page 61\)](#)
- [“Basic Client Configuration” \(page 64\)](#)
- [“Port use” \(page 64\)](#)
- [“Security ” \(page 64\)](#)
- [“OC client authentication” \(page 64\)](#)
- [“Authorization of TR/87 \(Remote Call Control\) service requests” \(page 64\)](#)
- [“Signaling and media encryption” \(page 65\)](#)
- [“Dial Plan considerations” \(page 66\)](#)
- [“Computer \(SIP\) Calls” \(page 67\)](#)
- [“Phone \(RCC or TR/87\) Calls” \(page 67\)](#)
- [“Number formats supported by Office Communicator” \(page 68\)](#)
- [“E.164 international format numbers for SIP Gateway and SIP CTI” \(page 71\)](#)

Server topology

Use the following table to determine the maximum supported users for your topology.

Table 5
Maximum supported users for each topology

Topology	Servers required	Maximum clients
Standard Edition Server	1 Standard Edition server, (Optional) Archiving Server collocated	5000
Enterprise pool: Consolidated Configuration	4 Enterprise Edition Front End servers running all server roles, 1 back end SQL server (Optional), 1 Archiving server	4 servers X 5000 users per server = 25 000 maximum clients

Topology	Servers required	Maximum clients
Enterprise pool: Expanded configuration with Mid-Range Performance SQL back end	4 Front End servers, 2 Web Conferencing servers, 2 A/V Conferencing servers, 2 IIS servers, 1 back end SQL server (Optional), 1 Archiving server	10 000 users per access edge server and 50 000 maximum clients
Enterprise pool: Expanded configuration With High Performance SQL back end	8 Front End servers, 4 Web Conferencing servers, 4 A/V Conferencing servers, 2 IIS servers, 1 back end SQL server (Optional), 2 Archiving servers	125 000

Operating System Requirements

The operating system platform requirements for all Office Communications Server 2007 server roles are:

- Minimum: Microsoft Windows Server 2003 SP1.
- Recommended: Windows Server 2003 R2 with SP2.

Hardware Requirements

Use the following table to determine hardware requirements for the OCS 2007 Standard and Enterprise Edition server.

Table 6
Office Communications Server 2007 Standard and Enterprise Edition hardware requirements

Hardware	Requirements
CPU	Dual processor, dual core 2.6 GHz +
Disk	2 x 18 GB For collocated Standard Edition Server, add: 2 x 36 GB, 15K RPM, RAID 0, for database log files 2 x 36 GB, 15K RPM, RAID 0, for database data
Cache	1 MB L2 per core
Memory	2 GB (4 GB for Standard Edition server or Consolidated Enterprise Edition server)
Network	Gbit NIC

Table 7
Mediation Server hardware requirements

Hardware
Single processor, dual core, 2 GHz, Memory: 2GB RAM 2 x 1 Gbit NIC
Single processor, dual core, 3 GHz Memory: 2GB RAM 2 x 1 Gbit NIC

Hardware	
Dual processor, dual core, 3 GHz Memory: 2GB RAM 2 x 1 Gbit NIC	
Dual processor, quad core, 2.66 GHz, Memory: 2GB RAM 2 x 1 Gbit NIC	

Table 8
OCS Proxy server hardware requirements

CPU	Dual processor, dual core 2.6 GHz +
Disk	2 x 18 GB
Cache	1 MB L2 per core
Memory	2 GB
Network	Gbit NIC

Table 9
Back end database for a small to medium Enterprise pool

CPU	Dual processor, dual-core 2.6 GHz +
Disk	Drive 1 (2 x 18 GB) for OS and Page File Drive 2 (36 GB, 15K RPM) for database log file Drive 3 (36 GB, 15K RPM) for database log file Drive 4 (8 x 36 GB, 15K RPM, RAID 0+1) for database files
Cache	2 MB L2 per core
Memory	8 GB
Network	Gbit NIC

Table 10
Back end database for a large Enterprise pool

CPU	Quad processor, dual-core 2.6 GHz +
Disk	Drive 1 (2 x 18 GB) for OS and Page File Drive 2 (4 x 36 GB, 15K RPM, RAID 0+1) for database log file Drive 3 (4 x 36 GB, 15K RPM, RAID 0+1) for database log file Drive 4 (8 x 36 GB, 15K RPM, RAID 0+1) for database files
Cache	2 MB L2 per core
Memory	16 GB
Network	Gbit NIC

Table 11
Office Communicator client requirements

Operating System	• Windows Vista 32-bit (RTM) operating system • Microsoft Windows XP Professional with Service Pack 2 • Windows 2000 Professional with Service Pack 4 (requires Microsoft Windows Media technologies player, version 9, and Microsoft Windows Installer, version 3.0 or later) Hardware device driver must be API DirectX 9 or higher.
Computer/Processor	• Data and Voice: 500-megahertz (MHz) or higher processor. Intel Pentium-compatible • For video: 1 GHz or higher
Memory	512 megabytes (MB) of RAM
Install Space	1.5 MB

Virtual Server 2005

Microsoft Virtual Server 2005 is not supported as part of the Nortel Converged Office feature. The Nortel software component Multimedia Convergence Manager (MCM) must not be installed on Office Communications Server that runs Microsoft Virtual Server 2005. For additional information about Virtual Server 2005, see the Virtual Server Web site at www.microsoft.com/windowsserversystem/virtualserver/default.mspx.

Storage

Store internal hard disks used for operating system and executable software, data, and transaction files separately. The following lists shows storage options:

- Direct access storage device (DASD)
- Storage Area Network (SAN)
- Redundant Array of Independent Disks (RAID)

Onboard storage:

- 2 SCSI Channels (split backplane)
- Five 18-GB hard disks, 15 000 rpm SCSI disk drives

Optional SAN:

- One Fibre Channel Host Bus Adapter (HBA)
- SAN unit

Trunks

To handle the traffic between the CS 1000 and the Office Communications Server 2007, you must configure sufficient SIP trunks and UEXTs. The number of additional SIP trunks needed is determined by:

Determine the number of SIP trunks required by multiplying the number of OC 2007 clients that use the SIP Gateway feature by the percentage of users you expect on the phone at any time.

For example, 100 Office Communicator SIP Gateway users x 10% on the phone at a time = 10 additional SIP trunks.

The percentage of users on the phone is decided by standard practice and the environment involved (For example, Call Center or Normal Office).

TLSV has replaced Personal Call Assistant (PCA). TLSV is used to extend the call over a SIP trunk to the OCS client from the CS 1000 system.

SIP access port

Table 12 "Inputs" (page 61) defines the inputs used to calculate SIP access ports and TLSV requirements.

Table 12
Inputs

Input	Description
TN_MO_Users	Total number of Office Communicator users that use the SIP Access Ports for voice services.
UEXT_MO_Users	Number of Office Communicator users that use Universal Extension (UEXT) with Telephony Services (TLSV) subtype. The UEXTs required here are additional to the number of UEXTs provided in the Enterprise Configurator (EC) tool Software screen.
P_UEXT_SIP	Percentage of UEXT calls that use the soft client to answer a call.

Calculations Use the following formulas to calculate traffic requirements (MO indicates Microsoft Office Communicator):

- Traffic for UEXTs = (UEXT_MO_Users) x (CCS per user) x (1 - P_UEXT_SIP) x 10%
- Traffic for SIP ports = (TN_MO_Users - UEXT_MO_Users) x (CCS per user) + (UEXT_MO_Users x P_UEXT_SIP) x (CCS per user)
- Total SIP Traffic = (Traffic for UEXTs) + (Traffic for SIP ports)
- Number of MO SIP ports = Poisson (Total SIP Traffic) at P.01 Grade of Service

Table 13 "Traffic figures" (page 62) shows traffic in CCS and number of ports calculated based on the Poisson formula at P.01 Grade of Service.

Table 13
Traffic figures

Traffic (CCS)	Traffic (Erlang)	Number of ports
5	0.14	2
10	0.28	3
15	0.42	3
20	0.56	4
25	0.69	4
30	0.83	4
35	0.97	5
40	1.11	5
45	1.25	5
50	1.39	6
55	1.53	6
60	1.67	6
65	1.81	6
70	1.94	7
75	2.08	7
80	2.22	7
85	2.36	7
90	2.5	8
95	2.64	8
100	2.78	8
125	3.47	9
150	4.17	10
175	4.86	12
200	5.56	13
225	6.25	14
250	6.94	15
275	7.64	16
300	8.33	17
325	9.03	18
350	9.72	19
375	10.42	19

Table 13
Traffic figures (cont'd.)

Traffic (CCS)	Traffic (Erlang)	Number of ports
400	11.11	20
425	11.81	21
450	12.5	22
475	13.19	23
500	13.89	24
550	15.28	26
600	16.67	28
650	18.06	29
700	19.44	31
750	20.83	33
800	22.22	35
850	23.61	36
900	25	38
950	26.39	40
1000	27.78	42
1500	41.67	58
2000	55.56	74
2500	69.44	90
3000	83.33	106
3500	97.22	121
4000	111.11	137
4500	125	152
5000	138.89	168
6000	166.67	198
7000	194.44	228
8000	222.22	258
9000	250	288
10 000	277.78	318
20 000	555.56	611
30 000	833.33	908
40 000	1111.11	1205
50 000	1388.89	1502

Table 13
Traffic figures (cont'd.)

Traffic (CCS)	Traffic (Erlang)	Number of ports
60 000	1666.67	1799
70 000	1944.44	2096

Basic Client Configuration

The TLSV subtype has been introduced. Basic Client Configuration (BCC) can program the new TLSV subtype for UEXT TNs. The TLSV subtype is the required value for all UEXTs associated with OCS 2007.

LD 11 supports the administration of telephones. BCC uses REQ commands, such as NEW, CHG, and OUT. In LD 20, BCC uses the PRT command to retrieve phones from the Call Server.

Port use

The CS 1000 uses the following ports related to TCP and TLS.

- 5060: TCP
- 5061: TLS

The dynamic port range used by Office Communicator for SIP/RTP is 1024 - 65535.

The port range can be controlled (restricted) to a smaller range using the group policy settings as described on the Microsoft Web site: support.microsoft.com/default.aspx?scid=KB;EN-US;903056

Port ranges must not overlap.

Security

When you consider a Converged Office deployment, ensure you understand the following security concepts and integrate them into your deployment planning.

OC client authentication

Authentication of Office Communicator clients is provided by the Office Communications Server. For more information about authentication, see *Microsoft Office Communications Server 2007 Planning Guide*. Download Microsoft documentation from the Download Center at www.microsoft.com.

Authorization of TR/87 (Remote Call Control) service requests

Authorization of TR/87 (Remote Call Control) service requests within a Converged Office deployment is handled by the Nortel MCM. The main requirement for authorization of service requests arises from Office Communicator users who can manually override the Phone Integration


settings in Active Directory provisioned by an administrator. To ensure that each Office Communications Server user is restricted to the Active Directory configuration provisioned by an administrator for Remote Call Control, MCM provides an option to enable or disable authorization of TR/87 service requests. For details about the authorization process and MCM configuration requirements, see [“Configuring MCM for Remote Call Control” \(page 157\)](#).

Signaling and media encryption

IP connectivity between the Office Communications Server and the CS 1000 is provided by TCP and TLS. Similarly, Office Communications Server server-to-server traffic can also be TCP or TLS.

To provide signaling security between the Office Communications Server and the CS 1000 (see [Figure 17 “Signaling security” \(page 65\)](#)), Nortel Contivity VPN routers can be used to tunnel SIP signaling between the Office Communications Server and the CS 1000. A single VPN router that supports the Office Communications Server can service multiple individual VPN routers from multiple CS 1000 deployments.


Figure 17
Signaling security



- Secure Management Zone (SMZ) provides management access to local and remote devices over a secure connection. SMZ documents the LAN and WAN configurations required for secure management.
- Virtual Private Network (VPN) enables secure communications through Secure Internet Protocol (IPSec) encryption.
- Transport Layer Security (TLS) ensures that third-parties cannot eavesdrop or tamper with messages when a server and client communicate.

Secure end-to-end policy is not supported with this application.

Figure 18
Signaling security with TLS



Dial Plan considerations

Nortel Converged Office is comprised of the following two components:

- SIP CTI Services provides CS 1000 native TR/87 support to enable the Remote Call Control functionality available with Office Communicator.
- Telephony Gateway and Services allows you to originate and receive SIP calls (for example, VoIP and Computer calls) from Office Communicator.

Whether you choose one or both components for deployment, an Office Communicator is essential. This allows the existing dial plan (that users have become accustomed to with their existing telephony interfaces) to extend seamlessly to the Office Communicator client for either call type. This includes all existing CS 1000 dial plan features such as Coordinated Dial Plan (CDP) and Uniform Dial Plan (UDP), and Group Dial Plan.

The following lists summarize the features that contribute to the dial plan configuration for the Converged Office feature from the perspective of calls originated and received from Office Communicator.

Computer (SIP) Calls


- Number format entered in Active Directory or Office Communicator
- Office Communications Server Address Book Service Normalization rules
- Network Redirect Service (NRS)
- CS 1000SIP Gateway configuration
- CS 1000Call Server configuration relating to the SIP Gateway
- OCS Location Profile, Policy, Phone Usage, and Route configuration.
- OC client configuration in the Active Directory

Phone (RCC or TR/87) Calls

- The format of the number itself entered in Active Directory or entered in Office Communicator
- Office Communications Server Address Book Service Normalization rules
- CS 1000SIP CTI Services Configuration
- CS 1000Call Server Configuration relating to PBX telephones
- OC Client configuration in the Active Directory

The number format and normalization support provided by Office Communications Server is used to format numbers for both Remote Call Control and computer calls. However, the interface from which they originate and receive calls from the CS 1000 is the TR/87 Front End and SIP Gateway respectively (as illustrated in [Figure 19 "Signaling and media paths" \(page 68\)](#)).

Figure 19
Signaling and media paths



Number formats supported by Office Communicator

Dialstrings and E.164 International number format are the two types of numbers used by Office Communicator. Both number formats apply to computer and phone calls with Office Communicator.

Dialstrings

By default, digits dialed from Office Communicator that are not fully qualified are sent as dialstrings. The sequence of digits entered in Office Communicator are sent directly to the Call Server to be dialed. This allows a user to dial all numbers that you would typically expect to dial from a phone local to the CS 1000. Normalization rules should be defined in the Location Profile to convert the dialstrings to the E.164 International format for all types of PSTN calls. For example, NXX, NPA and International.

E.164 International Format Numbers


The recommended format of numbers stored in Microsoft applications is the E.164 International number format. This is a variable length number that consists of a plus sign (+) followed by a 1 to 3 digit country code and a national number 15-n digits long—where n is the length of the country code.

All E.164 numbers presented to the CS 1000, computer, or phone are expected in the following format:

+<country code><national number>


For example, in North America, the Office Communicator Phone Number configuration input dialog box would have an entry similar to [Figure 20 "North American format" \(page 69\)](#).

Figure 20
North American format



Outside North America, the Office Communicator Phone Number configuration input dialog box would have an entry similar to [Figure 21 "Outside North America format" \(page 69\)](#).

Figure 21
Outside North America format



The Normalization feature, provided by the Office Communications Server Address Book Service, can be used to ensure that formats used within a local deployment that do not conform to the convention can be converted without changes to the original numbers.

For example, in the Netherlands, numbers in Active Directory can be entered in the following format: +31(0)123456789

A normalization rule can be used to strip the digit in brackets to conform to the expected format for E.164 numbers when using the Converged Office feature: +31123456789

For more information about Normalization rules, see [“Creating Normalization rules” \(page 224\)](#).

Handling numbers called from Office Communicator in E.164 format requires that the Call Server be configured to ensure that the number requested is within the defined dial plans:

Within North America

Various types of numbers can be recognized, including international, national, local (for example, NPA, NXX, and Free Calling Area Screening), or private, that use one or two access codes and number translators (AC1 and AC2). The E.164 number that enters the Call Server for Converged Office calls must be recognizable by the Call Server so that the call can be routed appropriately. The number is interpreted based upon the access code used within the called number as it enters the Call Server (AC1 or AC2).

If calls that enter the Call Server are identified as international and outside of North America (for example, the country code is not 1), the translator must contain entries that recognize the international numbers and route the call to the appropriate route list. These entries are generally within the existing AC1/AC2 translator, as they are used to route international calls that are dialed directly from telephones.

If calls that enter the Call Server are national or local, the translation used must recognize numbers with the national dialing prefix (for example, Converged Office calls) and numbers without the national prefix (for example, local calls dialed by users). To enable this recognition without duplication of number plan entries, a Home NPA (HNPA) entry can be added to the AC1 translator to recognize calls within the local NPA that include the North American national dialing prefix (for example, 1613 within NPA 613). After matching the HNPA entry within AC1, the translation software automatically uses the AC2 translator to recognize the rest of the digits received.

Outside North America

Various types of numbers are recognized, including international, national, local, or private that use one of two access codes and number translators (For example, AC1 and AC2) and SPN entries. The E.164 number that enters the Call Server for Converged Office calls must be recognizable so that the call can be routed appropriately. The number is interpreted based upon the access code used within the called number as it enters the Call Server (AC1 or AC2).

If calls that enter the Call Server are international and outside of the country of the caller, the translator must contain entries that recognize the international numbers and route the call to the appropriate route list. These entries are generally within the existing AC1/AC2 translator, as they are used to route international calls that are dialed directly from telephones.

E.164 international format numbers for SIP Gateway and SIP CTI

For information about E.164 international format numbers for SIP Gateway (Computer) calls, see [“E.164 International Format Numbers from Office Communicator - Computer Calls \(SIP Gateway\)” \(page 178\)](#).

For information about E.164 international format numbers for SIP CTI (Phone) calls, see [“Dialing E.164 International Format Numbers from Office Communicator - Phone Calls \(SIP CTI\)” \(page 201\)](#).

Telephony Gateway and Services planning

This section describes the planning and engineering issues associated with the Telephony Gateway and Services component.

[Table 14 “Systems, platforms, and applications” \(page 71\)](#) identifies the systems, platforms, and applications supported by the Telephony Gateway and Services component.

Telephony Gateway and Services navigation

- [“Systems, platforms, and applications” \(page 71\)](#)
- [“Capacity” \(page 72\)](#)
- [“Redundancy” \(page 72\)](#)
- [“SIP routing” \(page 72\)](#)
- [“Feature Interactions” \(page 73\)](#)

Systems, platforms, and applications

Table 14
Systems, platforms, and applications

System, platform, or application	Supported
M1/CS 1000 Systems	
CS 1000M Cabinet	Yes
CS 1000M Chassis	Yes
CS 1000M Small	Yes
CS 1000M HG	Yes
CS 1000M SG (CP3/4)	Yes

Table 14
Systems, platforms, and applications (cont'd.)

System, platform, or application	Supported
M1/CS 1000 Systems	
CS 1000M SG (CP PIV)	Yes
CS 1000M MG (CP3/4)	Yes
CS 1000M MG (CP PIV)	Yes
CS 1000E	Yes
MG 1000B	Yes

Capacity

For more information relating to the Telephony Gateway and Services and Remote Call Control components, see [“Capacity planning” \(page 52\)](#).

Redundancy

Office Communications Server 2007 redundancy model is supported, with limitations, using Load Balancers.

NRS redundancy NRS redundancy is similar to Converged Office redundancy; a heartbeat mechanism between MCM 3.5 and NRS servers is implemented. When a heartbeat failure from the primary NRS server is detected, all messages are redirected to the secondary NRS server.

SIP routing

MCM directs calls from an Office Communicator user to the CS 1000 connected to their twinned telephone. A user can have a telephone number in Active Directory associated with their account as depicted in [Figure 22 “SIP routing” \(page 73\)](#), the number is 231-3052. Calls made from a user to any endpoint (Public or Private) are directed to their CS 1000. The CS 1000 tandem the call to the other CS 1000 (if necessary).

SIP routing ensures the following:

- Outgoing Office Communicator calls made by a twinned client can be tracked by Call Detail Recordings (CDR).
- Calls from an Office Communicator to incompatible systems can be made.

In [Figure 22 “SIP routing” \(page 73\)](#) the user david@ocsserver.com calls 6-441-5431 (AC1-LOC-DN). The From header in the INVITE has David's Line URI in the format of E.164;ext=2313051. The MCM gets the extension number 2313051 and uses the NRS to find the CS

LG-Nortel IP Phone 8540 OCS desk phone An Enterprise Voice only client (no PBX integration enabled) that is configured for an OC 2007 client or 8540 OCS desk phone, will be able to make PSTN calls using the CS 1000 as the gateway. You are required to configure a TN and twinned UEXT on the CS 1000 even if there is no actual phone present for this client. This is because the MCM will perform homing on each OC client that makes an outgoing call before allowing it to proceed with the call.

Mixed network with SPS and SRS servers On a mixed network where both SPS and SRS servers are present, MCM must be configured in SRS mode for collaboration server routing to work properly.

RCC only mode Nortel recommends you do not define users with RCC only mode since certain restrictions apply to this functionality. .

Bandwidth usage direct OC-to-OC audio call The bandwidth usage of a Mediation Server direct OC-to-OC audio call is not calculated on the CS 1000. This portion of the required bandwidth should be calculated with Microsoft consultation and added to the Nortel bandwidth recommendations for Converged Office users. Failure to do so might impact the quality of the Converged Office calls in case bandwidth usage exceeds the planned limits.

Microsoft CFAC Microsoft does not support Call Forward All Calls (CFAC) to voice mail on the OC client when users have Call Forward No Answer (CFNA) configured to voice mail and not Office Communicator. In order to have this functionality for an Enterprise Voice user with PBX integration, voice mail should be configured on the user's phone. If the user is in VoIP only mode (no phone) then the only option is for the administrator to configure the TLSV with Call Forward No Answer (CFNA). In this case, the calls will ring 4 times before being redirected to voice mail.

Office Communicator-initiated Call Transfer in Computer and PBX Integration Enabled If the Office Communicator transfers a call, the SIP stack of the CS 1000 must handle the request to transfer the call. As such, the number a user is transferred to is not subject to the Class of Service associated with either user (the transferred party or the party performing the transfer). The Class of Service and Call Restriction that control the transfer is that of the SIP trunk itself.

Multiple customer operation Multiple customer operation is not supported within a single Signaling Server; a separate Signaling Server is required for each customer. Each customer configured on the Call Server requires a separate node number and domain. For more information about how to configure a multiple customer environment, see [“Multiple customer network” \(page 46\)](#).

Deployment You can find all of the information required to support Office Communications Server 2007 and Microsoft Office Communicator deployment on the Microsoft Web site. Download Microsoft technical documentation from the Download Center at www.microsoft.com.

MCM 3.5 uses LDAP queries to the Active Directory server for some OC user's attributes. You must engineer the Active Directory server properly to provide the expected performance for the LDAP queries (less than 25 milliseconds). Office Communications Server and Active Directory APIs are used for queries and mapping.

Office Communications Server 2007 availability The Office Communications Server 2007 delivers an availability of up to 99.99% as described on the Microsoft Web site at www.microsoft.com. This is a Microsoft limitation.

Office Communications Server 2007 redundancy The Office Communications Server 2007 redundancy model is supported, with limitations, using Load Balancers.

Office Communicator Web Access Converged Office requires the client support SIP Gateway functionality. The Web version of Office Communicator, called Office Communicator Web Access, does not support SIP Gateway. Therefore, Office Communicator Web Access does not work with Converged Office.

Office Communicator Mobile Converged Office requires the client to support Telephony Gateway. The Mobile version of Office Communicator, called Office Communicator Mobile (COMO), has limited support for Telephony Gateway. Telephony Gateway is only supported when the device runs Windows Mobile 5.0. VoIP calls work for incoming calls, but outgoing VoIP calls can only be placed to other Office Communicator users (computer to computer calls). Outgoing VoIP calls to telephone numbers for Microsoft Office Communicator Mobile are not supported.

OC Client Presence with Mobile Extension Mobile Extension (Mobile X) users who have Converged Office Licenses automatically have cell phone presence indication extended to Office Communication Server (OCS) in the case of SCR but not MCR. If OCS users require presence indication of users with a Mobile Extensions not associated with OCS, additional licenses (AST and TR87) must be configured. One AST and TR87 are required for each Mobile Extension user that does not have OCS.

The scenarios in which you can use OC Client Presence with Mobile X are as follows:

- The OC Client works in Computer mode, like a SIP software phone. It does not converge on either the UEXT for a Mobile X or a desktop phone associated with a Mobile X. The OC Client's status does not affect the status of the Mobile X.
- A desktop phone is configured along with a UEXT for a Mobile X. Nortel recommends that an OC Client must converge on the desktop phone. The OC Client will not lose related call control features, such as Call Making, Call Transferring and Call Forwarding, which are supported on the OC Client. The converged OC Client works in Phone mode. Its displayed status must reflect the status of the converged desktop phone, instead of the UEXT for a Mobile X.
- No desktop phone is configured along with a UEXT for a Mobile X, then an OC Client can converge on the UEXT. The OC client will not support call control features. When a mobile phone is idle and its UEXT is in idle status, the converged OC Client displays **Online**. When a mobile phone is in conversation and its UEXT is busy, the converged OC Client displays **In a call**.

The points of interoperability of the OC Client and Mobile X are as follows:

- There is no MADN/MCR interworking with OCS with desk set/multiline.
- There is no handoff from the OCS Client to a desk phone though the handoff key (no busy detection).
- There is no presence when talking on a Mobile phone for watchers on the OCS Client when OCS Client is logged out.
- There is no support for ACD with Mobile X in combination with Desk set for ACD usage.
- There is no RCC control of MOBX if it is the only set off CS 1000 presence.

Microsoft Virtual Server 2005 Microsoft Virtual Server 2005 is not supported as part of Nortel Converged Office.

DTMF CS 1000 supports in-band DTMF digits and out-of-band DTMF digits for SIP calls through RFC2833. RFC2833 is an out-of-band mechanism for DTMF signaling. DTMF digit handling using RFC2833 enables Nortel CS 1000 products to work with other SIP products that support out-of-band DTMF signaling.

With RFC2833, a key press on a telephone translates to a signaling packet (or packets) that flow with the VoIP stream to the far end. These signaling packets are RFC packets which contain the DTMF key that was pressed. The same principle applies to TDM devices that are involved in a VoIP call. The Voice Gateway (VGW) TN that converts the TDM stream to VoIP also detects a tone on the TDM side and translates it to RFC2833 packets on the VoIP side. The VGW TN can receive an RFC2833 packet on the VoIP side and generates a tone on the TDM side.

Configure the correct Loss Values for in-band DTMF. For more information about configuring the CS 1000 to support in-band DTMF tones, see [“Call Server configuration” \(page 159\)](#).

2050 Soft phones Due to RFC2833 not being supported, 2050 soft phones are not recommended to be deployed in a network with OCS 2007 components.

ITG-Pentium cards ITG-Pentium cards are not supported (regardless of load) due to RFC2833 not being supported.

Multimedia Communicator Server MeetMe Conference support In Release 5.5, there are no limitations for Office Communicator calls to the Multimedia Communicator Server (MCS) MeetMe bridge provided that all tandem nodes run Release 5.5 software.

Codecs G.711 A/MU law is supported for the Mediation Server. The G.711 codec must use a 20-ms payload at this time, due to the Microsoft Office limitation. The Mediation Server does not support G.723 and G.729.

Video support Office Communicator video is supported for Remote Call Control between two Office Communicator clients and VoIP calls directly between two OC clients without going through the Mediation Server. Office Communicator video is not supported if one of the clients goes through the Mediation Server.

Video Call Transfer Office Communicator calls made in Computer mode that have established video can transfer to another Office Communicator user in Computer mode—although the new call is audio only. The transferred Office Communicator user experiences the call becoming audio only. After the transferred call is answered by the new endpoint, video can be established. As with all Call Transfers in Computer mode, it is a Blind Call Transfer, where the call is immediately transferred to the new party.

Local Tones Office Communicator supports the generation of local tones (for example, Ringback), but the tones that the Office Communicator generates are unique tones that are not specific to any country. Ringback

is generated only for a configured number of cycles; after which the other end continues to ring, but there is no audible ringback.

Quality of Service Office Communicator 2007 supports Quality of Service (QoS) 802.1 p and 801.2.

Voice mail Voice mail is not supported for direct Office Communicator calls. Voice mail is supported only with TLSV, SimRing, and CD1 Call Forward No Answer and MCS 5100 Advanced Screening calls.

Long distance/overseas control Long distance or overseas calls from Office Communicator are allowed based on the Network Class of Service (NCOS) for the MARP TN of the number and extension associated with the Office Communicator user. For example, if user david@ocsuser.com has a number and extension of 3052, david@ocsuser.com can call the same long distance and overseas numbers that the number and extension 3052 can on the CS 1000. For more information, see [“Call Server configuration” \(page 159\)](#).

MCS 5100 MCS 5100 interoperability and federation with Office Communications Server requires that a CS 1000 reside between the two servers, and is limited to voice.

SIP Trunks TCP or TLS-based SIP trunks are supported. SIP trunks and gateways must be enabled with enough trunks to handle the traffic between the CS 1000 and Office Communications Server. For more information, see [“Trunks” \(page 61\)](#).

Phone mode Office Communicator supports phone mode where it controls the desktop telephone to originate or answer calls and the VoIP mode where voice calls can originate or be answered from the client.

Hold and Transfer Office Communicator supports Hold and Transfer in stand-alone or VoIP mode.

ipDialog Ethernet Phone Office Communicator clients can work with the ipDialog Ethernet Phone only if it is tandemed through a CS 1000.

Country or region tone configuration Country or region tone configuration is not supported by Office Communications Server or Office Communicator.

Conference Incorrect participants are displayed on the conference conversation window in the following scenario. For example, User A makes a call by SIP alias in Office Communicator–Computer mode to User B in Office Communicator–VoIP mode. User B answers the call and conferences in User C in Office Communicator–VoIP mode. User C is

invited to the conference by phone number. User C joins the conference. This results in four participants being displayed in the conversation window instead of three. This is a Microsoft limitation and can be reproduced when the CS 1000 system, Mediation Server outbound routing, and static Front End routes are disabled.

Active Directory configuration A record in the Active Directory must be created for all CS 1000 phones whether there is an Office Communicator client associated with it or not. If a CS 1000 phone is not in the Active Directory, an OC client user will notice the following:

- Cannot add the telephone number to the Office Communicator Contact List.
- Will receive two toasts when calls are made from these telephones.

UEXT (TLSV) Busy status feature UEXT Busy status feature is not applicable for TLSV subtype. TLSV acts in the same way as PCA based on SCR or MCR treatment.

The busy status of Office Communicator (OC) cannot be tracked because calls made to or from Office Communicator (OC) that are not routed through the CS 1000 Call Server are not known to the CS 1000 Call Server.


DTMF detection In order to handle DTMF detection properly with OCS 2007, all network components must support RFC 2833 which means all Branch or Main offices need to be running a Release. 5.0 software as a minimum. Otherwise there will be problems interacting with Interactive Voice Response (IVR) systems, collect calls, using meet-me conference bridges, and so on.

Remote Call Control with SIP CTI

The Remote Call Control component works in all configurations that include a Signaling Server and is supported for IP, digital, and analog telephone types.

Office Communicator client uses the ECMA TR/87 specification. [Figure 23 "Simple network diagram" \(page 80\)](#) shows a sample customer network that deploys Active Directory, the OCS 2007 Front End, OCS proxy server with MCM, and CS 1000.

Figure 23
Simple network diagram



The TR/87 FE is the application that resides on the CS 1000 Signaling Server to support the telephony control requests and responses received from the Office Communicator 2007 client within an Office Communications Server 2007 deployment.

CS 1000 is supported in both the Office Communications Server 2007 Standard Edition and Enterprise Edition network configurations. For more information about restrictions, see ["Capacity planning" \(page 52\)](#).

[Table 15 "Supported systems, platforms, and applications" \(page 80\)](#) identifies the systems, platforms, or applications that are interoperable or supported by the Remote Call Control component. Interoperable means that this feature will not negatively impact any existing functionality (regardless of whether this feature actually interacts with the system, platform, or application).

Table 15
Supported systems, platforms, and applications

Systems, platforms, and applications	Interoperable	Supported
M1/CS 1000 systems		
Option 11C Cabinet	Y	N
Option 11C Chassis	Y	N
Option 61C (CP-P11 and -P1V)	Y	N
Option 81C (CP-P11 and -P1V)	Y	N
CS 1000M SG (CP-P11 and -P1V)	Y	Y

Table 15
Supported systems, platforms, and applications (cont'd.)

Systems, platforms, and applications	Interoperable	Supported
CS 1000M SG (CP PIV)	Y	Y
CS 1000M MG (CP-P11 and -PIV)	Y	Y
CS 1000E SA/HA (CP-P11, -PIV, and -PM)	Y	Y
MG 1000T (SSC)	Y	N
MG 1000B (MGC and CP-PM)	Y	Y*
MG 1000E (MGC)	Y	Y*
* Digital and analog telephones in Branch Offices are supported when access to the proxy/redirect server and OCS 2007 is available.		
Other systems, call servers and gateways		
CS 2000	Y	N
CS 2100	Y	N
MCS 5100/CD	N	N
SRG 1.0	Y	Partial*
SRG 50	Y	Partial*
BCM 50 version 2.0	Y	Partial**
BCM 50 version 3.0	Y	Partial*
BCM 200/400	Y	Partial**
Norstar VoIP Gateway (NT9B10AA)	Y	N
NetRIO Service Management Center (SMC)	Y	N
* Telephones in normal mode (network connection to the main office up) are supported. No RFC 2833 support. Tandem calls out of a BCM/SRG from OCS with DTMF do not work. ** Telephones in normal mode are supported. No RFC2833 support. Tandem calls out a BCM/SRG from OCS with DTMF would not work.		
Nortel applications		
IP Phone 2001	Y	Y
IP Phone 2002 Phase I	Y	Y
IP Phone 2002 Phase II	Y	Y
IP Phone 2004 Phase 0/I	Y	Y
IP Phone 2006	Y	Y
IP Audio Conference Phone 2033	Y	Y
IP Softphone 2050	Y	N

Table 15
Supported systems, platforms, and applications (cont'd.)

Systems, platforms, and applications	Interoperable	Supported
Mobile Voice Client 2050	Y	N
WLAN Handset 2210	Y	Y
WLAN Handset 2211	Y	Y
WLAN Handset 2212	Y	Y
IP Phone 1110	Y	Y
IP Phone 2007	Y	Y
IP Phone 1120E	Y	Y
IP Phone 1140E	Y	Y
IP Phone 1150E	Y	Y
TDM Phones M3900 series	Y	Y
M3000	Y	Y
M2317	Y	Y
M2006	Y	Y
M2008	Y	Y
M2316	Y	Y
M2016S	Y	Y
PC Console Interface Unit	Y	Y
CDR	Y	N
Telephony Manager (TM)	Y	Y
Element Manager (EM)	Y	Y
Element Subscriber Manager (ESM)	Y	N
Call Pilot	Y	N
Call Pilot Mini	Y	N
Meridian Mail	Y	N
Meridian Mail Card Option	Y	N
Meridian/Succession Companion DECT (DMC8 version)	Y	N
VoIP-802.11 Wireless IP Gateway	Y	N
Remote Gateway 9150	Y	N
Meridian Home Office MHO-II – MD'ed	Y	N
Remote Office 9115/ IP Adaptor	Y	N
Carrier Remote	Y	N
Fiber I and Fiber II	Y	N

Table 15
Supported systems, platforms, and applications (cont'd.)

Systems, platforms, and applications	Interoperable	Supported
Symposium Desktop TAPI Service Provider for MCA	Y	N
Meridian Link Services [MLS]	Y	N
Symposium TAPI Service Provider	Y	N
Symposium Agent	Y	N
Symposium Agent Greeting	Y	N
Symposium Express Call Center (SECC)	Y	N
Symposium Call Center Server [SCCS]	Y	N
Symposium Web Centre Portal (SWCP)	Y	N
Periphonics Open IVR (VPS/is)	Y	N
Periphonics Integrated Package for Meridian Link (IPML) – VPS	Y	N
Periphonics Multimedia Processing Server (MPS) 100	Y	N
Periphonics Multimedia Processing Server (MPS) 500	Y	N
Integrated Call Assistant	Y	N
Integrated Conference Bridge	Y	N
Integrated Recorded Announcer	Y	N
Integrated Call Director	Y	N
Hospitality Integrated Voice Services (HIVS)	Y	N
Enterprise Data Networking	Y	N
UM2000	Y	N
Multimedia Application Server MAS	N	N
Nortel Multimedia Conference	Y	N
Third party applications		
Application gateway 1000	Y	N
Microsoft Office Communication Server	Y	N
MS Exchange Server	Y	N
MS Virtual Server 2005	Y	N
Audio Code Mediant 2000 SIP-PRI Gateway	Y	N
Competitors		

Table 15
Supported systems, platforms, and applications (cont'd.)

Systems, platforms, and applications	Interoperable	Supported
Cisco H.323 GW	Y	N
Avaya H.323 GW	Y	N
Cisco SIP GW	Y	N
Avaya SIP GW	Y	N
Verizon SIP Trunk	Y	N
AT&T SIP trunk	Y	N
Broadsoft	Y	N
ACME SBC	Y	N
3100 Mobile Communication Gateway	Y	N

Redundancy

Remote Call Control (RCC) services are supported (with limitations) in the following scenarios:

- Single node redundancy
- Campus redundancy
- Geographic redundancy

Single node Redundancy

The same master and follower mechanism used for Virtual Trunk (VTRK) and TPS applications is used to support redundancy within a node for RCC. After the master of the node fails, one of the followers takes over the node IP and continues to deliver service. VoIP mode session state is preserved when a new master is elected.

Redundancy across multiple nodes is possible using the Least Cost Routing feature of NRS. When considering a multinode redundant configuration, see the restrictions on establishing TR/87 sessions from multiple nodes that have AML links to a single Call Server. For more information, see [“Capacity planning” \(page 52\)](#) .

Campus redundancy

Campus Redundancy increases the distance between the two CPU cores of CS 1000E.

The CS 1000E is the only large system that supports this feature.

Geographic redundancy

Geographic Redundancy can be supported with the limitations that currently exist for SIP gateway SIP traffic. The main impacts are.

- During transition periods, situations can arise where IP phones are registered to a Call Server that is different from the call server that provides support for the TR/87 FE. In this situation, TR/87 support is undefined. TR/87 clients can register successfully; however, the status of the IP Phone is impacted by any actions performed on the telephone or the TR/87 client, as the FE and IP Phone interface different Call Servers. NRS is required to support redundancy.
- After an event occurs that causes the IP Phones to register to a server other than the Front End server (and then to return to the Front End server), the Office Communicator 2007 client does not automatically follow the IP Phone registration. To direct the TR/87 sessions back to the TR/87 FE that corresponds to the home TPS, take one of the following actions:
 - Users must log out and log back onto the TR/87 client (for example, Office Communicator 2007) to force the previous SIP dialog to terminate so that a new dialog can be established, which NRS redirects to the correct TR/87 FE.
 - An administrator issues the SIPCTIStop all command on the Signaling Server on which the TR/87 sessions currently reside to terminate the SIP dialogs. This forces the clients to send another association request (for example, SIP INVITE), which the NRS redirects to the correct TR/87 FE, as depicted in [Table 16 "SIPCTIStop all command" \(page 85\)](#).

Table 16
SIPCTIStop all command

Command	Description
SIPCTIStop all	De-acquire all AST DNs and terminate all TR/87 SIP sessions.

Branch Office redundancy (MG 1000B/SRG)

Branch Office scenarios can be supported; however, SIP CTI support and Telephony Gateway and Services are available for Branch User IP Phones in Local mode (registered in the Branch Office) only when the following conditions are met:

- The Branch Office has SIP CTI and Telephony Gateway and Services enabled and has a Signaling Server dedicated to each branch.
- The network dialing plan is a Coordinated Dialing Plan (CDP).
- The IP Phone (Branch User) has the same domain name configured in both the Main Office and Branch Office.

- The Branch Office has access to the NRS and Office Communications Server (OCS). If access is disrupted, failure cases may not be supported if the NRS and OCS are located in close proximity to the Main Office, which is no longer available. For example, when the WAN link to the Main Office is down, the NRS and OCS are out-of-service.
- The SIP Gateway in the Main Office is out -of-service (in which case the SIP Gateway in the Branch Office is used).

The Microsoft Office Communicator client has no automated mechanism to register to the branch. Users must wait for the existing dialog to time out (30 minutes) or manually log out and log on again after the IP phones change to local mode.

Digital and analog telephones in the Branch Office can have Remote Call Control (RCC) and PBX Integration Enabled support when the Branch Office has access to the NRS and OCS.

Feature Interactions

This section describes the interactions of the Remote Call Control with SIP CTI component.

Table 17
Feature Interactions of RCC

Feature Operation	Description
Call Forwarding	Office Communicator does not reflect call forward state changes made to the CS 1000 telephone itself. WARNING Call Forward state changes Office Communicator does not reflect Call Forward state changes made to the CS 1000telephone. When Office Communicator is active and controls a DN, make Call Forward changes through Office Communicator to ensure that it is in the correct state. When a user logs on to the OCS 2007 from their Office Communicator client, the forwarding status saved within Office Communicator overrides the forwarding status configured from the telephone. For example, if forwarding is off within Office Communicator, it is turned off following log on, regardless of the phone forwarding status at the time.

Feature Operation	Description
Analog telephone usage	As a general rule, Office Communicator in phone mode can only control and invoke telephony features supported by the telephone. If a feature is not supported or configured on a particular telephone (either Analog, IP, or Digital), it is not supported by Office Communicator. An Office Communicator in phone mode that supervises an analog phone (2500) has the following limitations: • Make Call - cannot be made through Office Communicator if the analog phone (2500) phone does not go off-hook prior to placing the call. • Answer Call - cannot be performed through Office Communicator. Answer Call must be performed through the analog phone (2500). • Conference Call - cannot be performed through Office Communicator. • Call Hold - can be performed through Office Communicator. • Call Transfer - Analog telephones do not support the Conference and Transfer key features. As a result, Call Conference and Call Transfer (Announced and Blind) cannot be performed through Office Communicator. Flexible Feature Code (FFC) is not supported by AML and RCC. • Send DTMF digits - DTMF digits work with both Voice Mail and Conferencing.
Multiple Customer operation	Multiple Customer operation is not supported within a single Signaling Server; a separate Signaling Server is required for each customer. Multi-customer support is a consideration for future releases. For more information about how to configure a Multi-Customer environment, see "Multiple customer network" (page 46).
TR/87 Front End application	The TR/87 FE application on a Signaling Server can support only a single Call Server.
UDP Location Code	Only one UDP Location Code can be associated with each Signaling Server TR/87 interface. For example, a different HLOC cannot be used inside the same customer for SIP CTI feature. When using UDP, local calls are represented as CDP, so there is no possibility to define which HLOC to insert into a calling DN.
AML interaction	CS 1000 has an Application Module Link (AML) limitation where only one application can acquire a DN or TN at any time. For example, the TR/87 FE application and IP Call Recording feature cannot coexist on the same DN or TN. This also applies to the interaction between Symposium and Office Communicator Remote Call Control. Symposium uses the AML to acquire and control telephones on the CS 1000 Call Server.
Office Communicator Web Access	Converged Office requires that the client support RCC. The Web version of Office Communicator, called Office Communicator Web Access, does not support RCC.

Feature Operation	Description
Office Communicator Mobile (COMO)	Converged Office requires the client to support Remote Call Control, but the Mobile version of Office Communicator, called Office Communicator Mobile, has limited support for Remote Call Control. Outgoing VoIP calls to telephone numbers for Office Communicator Mobile are not supported. Remote Call Control only permits telephone status updates (for example, on a call or not) when you use Office Communicator Mobile. Remote Call Control supports Call Forward with COMO.
Virtual Server 2005	Virtual Server 2005 is not supported as part of Nortel Converged Office.
Office Communicator 2007 Call Forward All Calls	When the CS 1000 Call Forward All Calls feature is enabled, only calls to the Prime DN or any single-appearance DN on the telephone are forwarded. Therefore, if an Office Communicator 2007 acquires a MADN, and it is not the Multiple Appearance Redirection Prime (MARF), the call is not forwarded even if the Call Forward feature is enabled. For more information, see <i>Features and Services</i> (NN43001-106).
Office Communications Server and MCS coexistence	ATTENTION All Converged Office users must have their extension configured as CLS CDMR. A user cannot have both Office Communications Server and MCS enabled for their extension (all TN's that have a particular number and extension). If any of the TN's have CLS CDMV or CLS CDMO configured, the extension is treated as having MCS enabled. When MCS (SIP CD) is enabled on an extension, Office Communications Server Converged Office is not supported for that extension in Release 5.5.
CallPilot configuration	For PBX Integration Enabled (Computer Mode) calls to access the CallPilot mailbox, the Pound key (#) is pressed. Every mailbox must have the optional messaging network configured. In a normal CS 1000 - CallPilot scenario, this configuration is optional. For PBX Integration Enabled (Computer Mode) calls to CallPilot to work properly, this extra configuration is required. For more information about the configuration of CallPilot, see <i>CallPilot Network Planning Guide</i> (NN44200-201).
Conference Call and Do Not Disturb (DND) features	Conference Call and DND features in RCC mode are not supported by Microsoft.
Flexible Feature Code (FFC)	All Flexible Feature Codes (FFC) are not supported by RCC. Though FFC codes cannot be performed through Office Communicator in RCC mode, they can be used from a converged phone.

LCS 2005 and OCS 2007 coexistence

This section describes the coexistence limitations of LCS 2005 and OCS 2007.

Client considerations

Features hosted on Office Communications Server 2007 are not supported by the OC 2005 client. After a user is configured for enhanced presence, the account can no longer use previous versions of OC 2005, Communicator Web Access 2005, or Communicator Mobile 2005. Microsoft recommends that you upgrade all client computers for a particular user at the same time. Communicator 2007 clients cannot log on to Live Communications Server 2005. Verify that any user whose client is upgraded to Communicator 2007 is already provisioned on an Office Communications Server.

Converged Office functionality

An upgrade from the LCS Application Proxy to the OCS Proxy Server and MCS 2.0 to MCM 3.5 is required to manage CS 1000 telephones by the OC 2007 client in either VOIP or RCC mode. Inter-working of MCM 2.0 with OCS Proxy Server or MCM 3.5 with LCS Application Proxy is not a supported configuration because of incompatible underlying libraries. The same CS 1000 can be connected to two or more different communication servers (LCS 2005 or OCS 2007).

The following must be considered for coexistence of LCS 2005 and OCS 2007:

- The CS 1000 must be upgraded to Release 5.5.
- OCS 2007 patches from Microsoft must be in service. For more information, see the Attention box under [“OCS 2007 component installation” \(page 111\)](#).
- NRS is required to appropriately route a call to the Communication Server.
- Different server DNs (Hot Ps) are assigned for each Communications Server (LCS or OCS). The TLSV for each user is configured with the corresponding server DN as a target DN
- LCS 2005 and OCS 2007 can share the same Active Directory but you can only have one OC client user account on either LCS 2005 or OCS 2007.
- For Remote Call Control (RCC) support, a single Signaling Server cannot be used for both LCS 2005 and OCS 2007 as the configuration of the SIP CTI FE is different for both. In this case, the following options can be considered:
 - RCC supported for both LCS 2005 and OCS 2007. Upgrade the existing Communication Server 1000 to support OCS 2007 RCC users. Configure an additional SIP CTI FE Signaling Server for LCS 2005 RCC users. An additional AML ELANs is defined on the Call Server. Change the static routing rule on the LCS 2005 Home

server to route RCC traffic directly to the SIP CTI FE for LCS 2005. Geographic Redundancy is not supported for LCS 2005 RCC users in this case.

- RCC supported for only LCS 2005 users. Enable RCC only for LCS users in the Active Directory, on the OC clients, or both. The SIP CTI FE should be configured according to the document *Nortel Converged Office Fundamentals* (NN43001-525) for LCS 2005. For example, the Phone context=dialstring configuration on the Signaling Server is used.
- RCC supported only for OCS 2007 users. Enable RCC only for OCS users in the Active Directory, on the OC clients, or both. The SIP CTI FE should be configured according to this document. For example, the Phone-context=<SIP URI Map Entries> configuration on the Signaling Server is used.

MCM 2.0 or 3.0 to MCM 3.5

There is no direct upgrade path from MCM 2.0 or 3.0 to MCM 3.5. MCM 3.5 must be installed on the OCS Proxy server. The OCS Proxy install is done from command line and not from the install wizard. It is still possible to preserve the configuration data from a previous installation by first performing a backup operation on MCM 2.0 or 3.0 and restore the data to MCM 3.5 on the OCS Proxy server. However, this will cause the new configuration parameters to be set to default values as follows:

Table 18
Default configuration parameters

Parameter	Default value
Call Server	CS1000
MediationServer	enabled
RoutingTable	empty
DialPlan	CDP
AccessCode	empty

For more information on MCM 3.5 configuration, see [“MCM 3.5 configuration” \(page 142\)](#)

Load balancer considerations

You cannot use a single logical load balancer for LCS 2005 and OCS 2007. For example, if you have an LCS 2005 application proxy with MCM 2.0 attached to a logical load balancer, you cannot simultaneously attach an OCS Proxy server with MCM 3.5 to the same one. This same restriction applies to all other server roles.


Migration planning from LCS 2005 to OCS 2007

Live Communications Server 2005 with SP1 can only be upgraded to Office Communications Server 2007 by using a side-by-side migration. This involves deploying an Office Communications Server 2007 Standard Edition or Enterprise pool alongside existing Live Communications Server 2005 with SP1 Standard Edition or Enterprise pool thus allowing the two environments to coexist with minimal service disruption.

When migrating servers, Office Communications Server 2007 servers should be deployed using a phased, outside-in approach. This involves replacing the Access Proxies with Office Communications Server 2007 Access Edge Servers before you migrate to Office Communications Server 2007 in your internal environment. Upgrading all the servers of a particular type at one time will help to minimize service disruptions.

The following flow chart depicts the migration phases:

Figure 24
LCS to OCS migration task flow



Prerequisites

Upgrading to Office Communications Server 2007 assumes the following:

- An understanding of the basic migration process.
- An understanding of the coexistence interactions. For more information, see [“LCS 2005 and OCS 2007 coexistence”](#) (page 88).
- An understanding of CS 1000, Signaling Server, and networks.
- An understanding of the user migration process.

Determine your deployment options

There are two deployment options depending on whether you are migrating a small or large client base.

For a small client base, Office Communicator client users can be migrated from LCS to OCS inside a set maintenance window. No extra servers are required.

For a large client base, Office Communicator client users need to be migrated over multiple maintenance windows using a phased approach. The following choices must be made:

1. If using one SIP CTI FE Signaling Server
 - Only LCS users have RCC
- OR**
2. If deploying an additional SIP CTI FE Signaling Server
 - RCC is supported for both LCS and OCS. One Signaling Server for LCS RCC and the other for OCS RCC

ATTENTION

Before migrating to Office Communications Server 2007, existing Live Communications Servers must have Live Communications Server 2005 SP1 installed.

Migration process

The following table breaks down the migration process using a phased, outside-in approach and defines the impact for the user at each phase.

Table 19
User experience

Phase	Description	User experience
1. Upgrade your perimeter network.	Introduce a new Office Communications Server (OCS) 2007 Access Edge Servers and Directors into your Live Communications Server (LCS) 2005 SP1 environment.	No changes. Users continue to use the Microsoft Office Communicator (OC) 2005 client and have the same IM and presence functionality.
2. Deploy OCS 2007 and begin moving users to the new server or pool.	Deploy a new Office Communications Server 2007 Enterprise pool or Standard Edition server. If required, deploy an Archiving and CDR Server. Users are moved to the new server or pool but will continue to use OC 2005 .	No changes. OC 2007 client is not rolled out at this phase so users continue to use OC 2005 and have the same IM and presence functionality.
3. Upgrade CS 1000 and if determined for your migration, add an additional Signaling Server as the SIP CTI FE.	Upgrade Call Server and Signaling Server. The feature is provided in Release 5.5 Call Server and Signaling Server. If you have a large client base, add an additional Signaling Server as the SIP CTI FE so both LCS 2005 and OCS 2007 can have RCC.	No changes. Users continue to use OC 2005 and have the same IM and presence functionality.
4. Deploy OCS 2007 Mediation Server.	Deploy OCS 2007 Mediation Servers.	No changes. Users continue to use OC 2005 and have the same IM and presence functionality
5. Deploy OCS Proxy server with MCM 3.5 .	Deploy OCS Proxy Server with MCM 3.5 .	No changes. Users continue to use OC 2005 and have the same IM and presence functionality
6. Enable enhanced presence, roll out OC 2007 client, and continue migrating users	Enable users for enhanced presence, roll out the OC 2007 client, and the Live Meeting 2007 client to the users.	- The migrated users can use the full functionality of OC 2007 when communicating with other migrated users. - Once enabled for enhanced presence, these users can no longer sign in to a OC 2005 client or previous Communicator Web Access or Communicator Mobile Access clients.

Phase	Description	User experience
7. Configure TLSV routing for new OC 2007 client users on the CS 1000.	Configure TLSV on the CS 1000. Change NRS and SPS routing.	Migrated users are able to use Telephony Gateway and Services functionality (VoIP) and RCC.
8. Continue migrating users.	Migrate remaining users. Enable users for enhanced presence. Roll out the OC 2007 client and the Live Meeting 2007 client to the users.	- OC 2007 users can use the full functionality of OC 2007 when communicating with other OC 2007 users. - When OC 2007 client users are communicating with OC 2005 users, they cannot use the new features in OC 2007. - After Live Meeting 2007 is rolled out to your users, they can participate in on-premise conferences internally and connect to these conferences remotely by using the Web Conferencing Edge Server. - RCC is only available to either OCS 2007 or LCS 2005 users when one SIP CTI FE Signaling Server is deployed. For more information, see “Converged Office functionality” (page 89).
9. Decommission all Live Communications 2005 servers and MCM 2.0 after all users have been migrated to OCS 2007	Remove Live Communications Server 2005 and MCM 2.0 from your environment.	All users are on OC 2007, enabled for enhanced presence and have full functionality of OC 2007. If Live Meeting is deployed, users can participate in on-premise conferences internally and connect to these conferences remotely by using the Web Conferencing Edge Server.
10. Decommission the SIP CTI FE for LCS (if installed)	Remove the SIP CTI FE for LCS (if an additional Signaling Server was deployed).	None.

Description of Migration Phases

To deploy OCS 2007 in an existing Live Communications Server 2005 topology, Nortel recommends the following phases:

Migrating users from LCS to OCS

Step	Action
1	Upgrade your perimeter network by deploying an Access Edge Server that communicates with Live Communications Server 2005 Director. When Director is not deployed, the edge server communicates directly with your internal Live Communications Server 2005 Standard Edition servers or Enterprise pool and the new Access Edge Server is configured as the next hop server to which existing pools and Standard Edition Servers will route external traffic. Next, an Office Communications Server 2007 Director is deployed to replace Live Communications Server 2005 Director. Incoming and outgoing traffic is configured to go through the new Director (if a Director was previously not used and you do not want to use one now, this step can be skipped). For more information, download Microsoft technical documentation from the Download Center at www.microsoft.com .
2	In this phase, an internal Office Communications Server 2007 Standard Edition Server or Enterprise pool is deployed. Move an initial group of users to the new server or pool but they will continue to use OC 2005 as their client. If required, deploy an Archiving and CDR Server. DNS update is required next. For more details, see " LCS 2005 and OCS 2007 coexistence " (page 88).
3	Upgrade CS 1000 and if determined for your migration, add an additional Signaling Server as the SIP CTI FE. Upgrading Call Sever and Signaling Server according to standard procedures. For more information, see " LCS 2005 and OCS 2007 coexistence " (page 88).
4	Deploy OCS 2007 Mediation Server. For more information on deploying Mediation Server, download Microsoft technical documentation from the Download Center at www.microsoft.com .
5	Deploy OCS Proxy server with MCM 3.5 . For more information, see " OCS Proxy server installation " (page 113) and " MCM installation " (page 115).
6	Enable enhanced presence and continue migrating users. Start to move users from Live Communications Server 2005 to Office Communications Server 2007. By enabling enhanced presence, users are allowed to use Office Communicator 2007 and the new functionality that it provides. After enabling the users for enhanced presence, roll out OC 2007 client to each computer for these users. Once a user is enabled for enhanced presence, they can no longer use any previous client versions. For more

- information on enhanced presence, download Microsoft technical documentation from the Download Center at www.microsoft.com.
- 7 Configure TLSV routing for new OC client users on the CS 1000. After configuration of TLSV routing, users will be allowed to use Telephony Gateway and Services (VoIP) and RCC functionality. A Server URI field should be changed for migrated users to enable SIP CTI functionality. Change NRS and SPS routing.
 - 8 Continue migrating users. Enable users for enhanced presence. Roll out the OC 2007 client and the Live Meeting 2007 client to the users. For more information on enhanced presence, download Microsoft technical documentation from the Download Center at www.microsoft.com.
 - 9 Decommission all Live Communications 2005 servers and MCM 2.0 after all users have been migrated to OCS 2007.
 - 10 Decommission the SIP CTI FE for LCS (if installed).

--End--

Unified Messaging

This section describes the interactions and inter-workings of Unified Messaging (UM) with Converged Office. Office Communications Server (OCS) 2007 users can access Unified Messaging capabilities using CallPilot or Exchange Server 2007. Features that are accessible to the OCS 2007 users from CallPilot or Exchange depend on how the deployment is performed. The following sections describe the user experience based on deployments when using CallPilot, Exchange integrated with OCS, and Exchange non-integrated with OCS. For more information on the signaling that takes place in an integrated or non-integrated configuration, see [“Signaling with integrated Voice Mail” \(page 105\)](#) and [“Signaling with non-integrated Voice Mail” \(page 105\)](#).

Unified Messaging navigation

- [“OCS 2007 users using CallPilot” \(page 97\)](#)
- [“OCS 2007 users using UM 2007—integrated” \(page 99\)](#)
- [“OCS 2007 users using UM 2007—non-integrated” \(page 103\)](#)
- [“Signaling with integrated Voice Mail” \(page 105\)](#)
- [“Signaling with non-integrated Voice Mail” \(page 105\)](#)

OCS 2007 users using CallPilot

The table depicts Voice Mail access for OCS 2007 users using CallPilot in the following configurations.

Table 20
CallPilot configurations

	OC User (VoIP) with RCC and CS 1000 Phone	OC User (VoIP) with no RCC and CS 1000 Phone	OC User (VoIP) with no RCC and no CS 1000 Phone	LG-Nortel 8540 (VoIP) with no RCC and no CS 1000 Phone	OC User RCC only, with CS 1000 Phone
CS 1000 configuration	TLSV + SIP CTI	TLSV	TLSV	TLSV	SIP CTI
VM access from phone	Dial CP DN	Dial CP DN	N/A	N/A	Dial CP DN
Login from phone	p/w only	p/w only	N/A	N/A	p/w only
MWI on phone	Yes	Yes	N/A	N/A	Yes
VM access from OC	Dial CP DN	Dial CP DN	Dial CP DN	Dial CP DN	N/A
Login from OC	p/w only	p/w only	p/w only	p/w only	N/A
MWI on OC	No	No	No	No	No
Outlook	New msg on CP Mailbox	New msg on CP Mailbox	New msg on CP Mailbox	New msg on CP Mailbox	New msg on CP Mailbox
Phone CFNA	CP DN	CP DN	TLSV CFNA	TLSV CFNA	CP DN
Phone CFB	CP DN	CP DN	TLSV CFB	TLSV CFB	CP DN
Phone CFAC	CP DN	CP DN	N/A	N/A	CP DN
OC client FC	On Phone (RCC to CP DN)	CP DN	Not recommended	Not recommended	Not recommended
OC client Re-direct	N/A	Not recommended	Not recommended	Not recommended	N/A
OC client sim-ring	N/A	Not recommended	Not recommended	Not recommended	N/A
OC fwd to UM	N/A	N/A	N/A	N/A	N/A

ATTENTION**CallPilot**

For Converged Office users using a Nortel telephone

Deploying Converged Office without configuring Remote Call Control (RCC) is not recommended. If RCC is not deployed for these users, the Office Communicator (OC) 2007 client provides call forwarding and call redirection options that can result in undesirable behaviors. For example, calls forwarded or redirected to the CallPilot DN, will be answered by the CallPilot logon prompt of "CallPilot from Nortel Networks. Mailbox ?", instead of receiving the user's mailbox greeting.

ATTENTION**CallPilot**

For Converged Office users not using a Nortel telephone. For Converged Office users who use voice communications through the OC client or from an LG-Nortel 8540 telephone (or both) and are configured with a Telephony Services (TLSV), the following cautions apply:

- Ensure that the Call Forward No Answer and Call Forward Busy settings for the TLSV are properly set to the CallPilot DN.
- Advise users not to use the Office Communicator 2007 settings for forwarding or redirecting calls to Voice Mail. For example, calls forwarded or redirected to the CallPilot DN, will be answered by the CallPilot logon prompt of "CallPilot from Nortel Networks. Mailbox ?", instead of receiving the user's mailbox greeting.
- Callers experience different call-answering behavior depending upon the state of the user's TLSV . If the TLSV is in a ringing state such as a call waiting to be answered by the user, a second caller will be forwarded immediately to the user's Voice Mail. If the user has already answered a call, a second caller will be forwarded to the user's Voice Mail only after the number of rings specified by the TLSV's Call Forward No Answer setting.

OCS 2007 users using UM 2007—integrated

The following tables depict Voice Mail access for OCS 2007 users using UM 2007 in integrated mode for Option 1 and 2.

Table 21
Unified Messaging 2007 integrated Option 1

	OC User (VoIP) with RCC and CS 1000 Phone	OC User (VoIP) with no RCC and CS 1000 Phone	OC User (VoIP) with no RCC and no CS 1000 Phone	LG-Nortel 8540 (VoIP) with no RCC and no CS 1000 Phone	OC User RCC only, with CS 1000 Phone
CS 1000 configuration	TLSV + SIP CTI	TLSV	TLSV	TLSV	SIP CTI

VM access from phone	Dial SA DN	Dial SA DN	N/A	N/A	Dial SA DN
Logon from phone	Logon and password	Logon and password	N/A	N/A	Logon and password
MWI on phone	No	No	N/A	N/A	No
VM access from OC	Dial SA DN	Use Voice Mail option	Use Voice Mail option	Use Voice Mail option	N/A
Logon from OC	Logon and password	direct	direct	direct	N/A
MWI on OC	Yes	Yes	Yes	Yes	Yes
Outlook	New msg in inbox	New msg in inbox	New msg in inbox	New msg in inbox	New msg in inbox
Phone CFNA	SA DN	SA DN	Not Required	Not Required	SA DN
Phone CFB	SA DN	SA DN	Not Required	Not Required	SA DN
Phone CFAC	SA DN	SA DN	N/A	N/A	SA DN
OC client FC	On Phone (RCC to SA DN)	No	No	No	On Phone (RCC to SA DN)
OC client Re-direct	N/A	No	No	No	N/A
OC client sim-ring	N/A	N/A	N/A	N/A	N/A
OC fwd to UM	N/A	Yes	Yes	Yes	N/A

ATTENTION**UM 2007 Integrated Option 1**

For converged office users using any telephone

In this deployment, the PBX integration cannot be selected if a user wants to have the capability of accessing voicemail from the OC client or Outlook. Doing so causes the call to be automatically routed to voice mail if the OC client is not logged in. In turn, the call to the IP phone is automatically terminated as it has been answered by Exchange. On the other hand, if PBX integration is selected, the voice mail option from the OC client and Outlook would not be available but the IP phone in this case would ring.

ATTENTION**UM 2007 Integrated Option 1**

For Converged Office users using a Nortel telephone

Deploying Converged Office without configuring Remote Call Control (RCC) is not supported. If RCC is not deployed for these users, the Office Communicator (OC) 2007 client provides call forwarding and call redirection options that if selected by the end user, will result in forward or redirected calls being answered by the Exchange logon prompt instead of the user's mailbox greeting. For example, using Call Forward or redirect to the Exchange Unified Messaging System Access number, will result in calls being answered by the Exchange logon prompt, "Welcome, you are connected to Microsoft Exchange", instead of receiving the user's mailbox greeting.

ATTENTION**UM 2007 Integrated Option 1**

For Converged Office users not using a Nortel telephone

For Converged Office users who use voice communications through the OC client, an 8540 telephone, or both and are configured with a Telephony Services (TLSV), the following cautions apply:

The Voice Mail option is not available. Users cannot use the Office Communicator 2007 Voice Mail setting for forwarding or redirecting calls to Voice Mail. Calls Forwarded or redirected to the Exchange Unified Messaging System by the OC client are answered by the Exchange Unified Messaging logon prompt instead of the user's mailbox greeting. For example, using Call Forward or redirect to the Exchange Unified Messaging, results in calls being answered by the Exchange Unified Messaging logon prompt, "What is the prompt?", instead of receiving the user's mailbox greeting. The Exchange UM Call Sender feature will not work properly.

Table 22
Unified Messaging 2007 integrated Option 2

	OC User (VoIP) with RCC and CS 1000 Phone	OC User (VoIP) with no RCC and CS 1000 Phone	OC User (VoIP) with no RCC and no CS 1000 Phone	LG-Nortel 8540 (VoIP) with no RCC and no CS 1000 Phone	OC User RCC only, with CS 1000 Phone
CS 1000 configuration	TLSV + SIP CTI	TLSV	TLSV	TLSV	SIP CTI
VM access from phone	Dial SA DN	Dial SA DN	N/A	N/A	Dial SA DN
Login from phone	p/w	p/w	N/A	N/A	p/w
MWI on phone	No	No	N/A	N/A	No
VM access from OC	Dial SA DN	User Voice Mail option	Use Voice Mail option	Use Voice Mail option	N/A

Login from OC	p/w	direct	direct	direct	N/A
MWI on OC	Yes	Yes	Yes	Yes	Yes
Outlook	New msg in inbox	New msg in inbox	New msg in inbox	New msg in inbox	New msg in inbox
Phone CFNA	SA DN	SA DN	Not required	Not required	SA DN
Phone CFB	SA DN	SA DN	Not required	Not required	SA DN
Phone CFAC	SA DN	SA DN	N/A	N/A	SA DN
OC client FC	On Phone (RCC to SA DN)	Voice Mail option only DN not recommended	Voice Mail option only DN not recommended	Voice Mail option only DN not recommended	On Phone (RCC to SA DN)
OC client Re-direct	N/A	Voice Mail option only DN not recommended	Voice Mail option only DN not recommended	By default set to Voice Mail after 20 seconds	N/A
OC client sim-ring	N/A	N/A	N/A	N/A	N/A
OC fwd to UM	N/A	Yes	Yes	Yes	N/A

ATTENTION**UM 2007 Integrated Option 2**

For converged office users using any telephone

In this deployment, the PBX integration cannot be selected if a user wants to have the capability of accessing voicemail from the OC client or Outlook. Doing so causes the call to be automatically routed to voice mail if the OC client is not logged in. In turn, the call to the IP phone is automatically terminated as it has been answered by Exchange. On the other hand, if PBX integration is selected, the voice mail option from the OC client and Outlook would not be available but the IP phone in this case would ring.

ATTENTION**UM 2007 Integrated Option 2**

For Converged Office users using a Nortel telephone

Converged Office users who internally access the Exchange Unified Messaging Auto Attendant or use the Call Sender feature, are unable to use the Auto Attendant to call other users. Any attempts to call another user will result in the caller being disconnected.

ATTENTION**UM 2007 Integrated Option 2**

For Converged Office users not using a Nortel telephone

For Converged Office users who use voice communications through the OC client, an 8540 telephone, or both and are configured with a Telephony Services (TLSV), the following cautions apply:

- Ensure users only use the OC 2007 client Voice Mail settings for forwarding or redirecting calls to Voice Mail. For example, calls forwarded or redirected to the Voice Mail option are answered with the user's personal greeting.
- Calls should not be forwarded or redirected to the Unified Messaging System Access number. Calls forward or redirected to the Exchange Unified Messaging by the OC client 2007 are answered by the Exchange Unified Messaging logon prompt instead of the user's mailbox greeting. For example, using Call Forward or redirect to the Exchange Unified Messaging System Access number, results in calls being answered by the Exchange Unified Messaging logon prompt, "What is the prompt?", instead of receiving the user's mailbox greeting.
- Users using the Play on Phone feature are required to update the Play on Phone destination with their telephone number for the first time they use the Play on Phone option. The default SIP URI will not work.

OCS 2007 users using UM 2007—non-integrated

The table depicts Voice Mail access for OCS 2007 users using UM 2007 in non-integrated mode for the following configurations.

Table 23
Unified Messaging 2007 non-integrated

	OC User (VoIP) with RCC and CS 1000 Phone	OC User (VoIP) with no RCC and CS 1000 Phone	OC User (VoIP) with no RCC and no CS 1000 Phone	LG-Nortel 8540 (VoIP) with no RCC and no CS 1000 Phone	OC User RCC only, with CS 1000 Phone
CS 1000 configuration	TLSV + SIP CTI	TLSV	TLSV	TLSV	SIP CTI
VM access from phone	Dial SA DN	Dial SA DN	N/A	N/A	Dial SA DN
Login from phone	p/w only	p/w only	N/A	N/A	p/w only
MWI on phone	Yes	Yes	N/A	N/A	Yes
VM access from OC	Dial SA DN	Dial SA DN	Dial SA DN	Dial SA DN	N/A
Login from OC	p/w only	p/w only	p/w only	p/w only	N/A

MWI on OC	Yes	Yes	Yes	Yes	Yes
Outlook	New msg in inbox	New msg in inbox	New msg in inbox	New msg in inbox	New msg in inbox
Phone CFNA	SA DN	SA DN	TLSV CFNA	TLSV CFNA	SA DN
Phone CFB	SA DN	SA DN	TLSV CFB	TLSV CFB	SA DN
Phone CFAC	SA DN	SA DN	N/A	N/A	SA DN
OC client FC	On Phone (RCC to SA DN)	Not recommended	Not recommended	Not recommended	On Phone (RCC to SA DN)
OC client Re-direct	N/A	Not recommended	Not recommended	Not recommended	N/A
OC client sim-ring	N/A	Not recommended	Not recommended	Not recommended	N/A
OC fwd to UM	N/A	N/A	N/A	N/A	N/A

ATTENTION**UM 2007 non-integrated**

For Converged Office users using a Nortel telephone

Deploying Converged Office without configuring Remote Call Control (RCC) is not recommended. If RCC is not deployed for these users, the Office Communicator (OC) 2007 client provides call forwarding and call redirection options that can result in undesirable behaviors. For example, using Call Forward or redirect to the Exchange Unified Messaging System Access number, will result in calls being answered by the Exchange logon prompt, "Welcome, you are connected to Microsoft Exchange", instead of receiving the user's mailbox greeting.

ATTENTION**UM 2007 non-integrated**

For Converged Office users not using a Nortel telephone

For Converged Office users who use voice communications through the OC client, an 8540 telephone, or both and are configured with a Telephony Services (TLSV), the following cautions apply:

- Ensure that the Call Forward No Answer and Call Forward Busy settings for the TLSV are properly set to the Exchange Unified Messaging System Access number.
- Ensure users do not use the Office Communicator 2007 settings for forwarding or redirecting calls to Voice Mail. For example, using Call Forward or redirect to the Exchange Unified Messaging System Access number, results in calls being answered by the Exchange Unified Messaging logon prompt, "What is the prompt?", instead of receiving the user's mailbox greeting.
- Callers can experience different call-answering behavior depending upon the state of the user's TLSV. If the TLSV is in a ringing state such as a call waiting to be answered by the user, a second caller will be forwarded

immediately to the user's Voice Mail. If the user has already answered a call, a second caller will be forwarded to the user's Voice Mail only after the number of rings specified by the TLSV's Call Forward No Answer setting.

For more information on configuring Voice Mail access for OCS 2007 users using UM 2007, see ["OCS 2007 users using UM 2007 in integrated mode" \(page 229\)](#).

Signaling with integrated Voice Mail

In an integrated configuration, the Office Communicator (OC) client has the capability of selecting a Voice Mail option and the dialing plan is TLS secure. The following diagram depicts the signaling between OCS 2007, Exchange, and the CS 1000 components in an integrated configuration.

Signaling with non-integrated Voice Mail

In a non-integrated configuration, the Office Communicator (OC) client does not have the capability of selecting a Voice Mail option, the signaling between Exchange and the OC client is not defined. The following diagram depicts the signaling between OCS 2007, Exchange, and the CS 1000 components in a non-integrated configuration.

Installation


This chapter contains the procedures necessary to install CS 1000 components and Office Communications Server (OCS) 2007 on a CS 1000system.

The first step is to install the necessary CS 1000components (if you do not already have a working CS 1000system in place), and then install the Microsoft server components. After all hardware and software is installed, you can then configure the Telephony Gateway and Services or Remote Call Control components.

After configuration is complete, normalization of telephone numbers, SIP routing, and redundancy help you integrate the Nortel and Office Communications Server 2007 domains. [Figure 25 "Installation and configuration flow" \(page 108\)](#) illustrates this process.

Installation navigation

Figure 25
Installation and configuration flow




- [“CS 1000 and Signaling Server installation” \(page 111\)](#)
- [“OCS 2007 component installation” \(page 111\)](#)
- [“OCS Proxy server installation” \(page 113\)](#)
- [“Load Balancer installation” \(page 114\)](#)
- [“MCM installation” \(page 115\)](#)

OCS 2007 installation preparation and deployment

The following [Figure 26 "OCS 2007 installation preparation and deployment flow chart" \(page 110\)](#) depicts the high-level topics required to deploy OCS 2007. After your internal deployment is complete, you can then deploy Edge Servers for external user access.

Figure 26
OCS 2007 installation preparation and deployment flow chart



CS 1000 and Signaling Server installation

The first step in the installation and configuration process is to install the CS 1000 and Signaling Server.

Installing the CS 1000 system

To install and configure a CS 1000 system, see the following documents:

- *Communication Server 1000M and Meridian 1 Small System Installation and Commissioning* (NN43011-310)
- *Communication Server 1000M and Meridian 1 Large System Installation and Commissioning* (NN43021-310)
- *Communication Server 1000E Installation and Commissioning* (NN43041-310)

ATTENTION

Converged Office requires the Call Server and Signaling Server to have Release 5.5 installed.

See the Nortel Converged Office Product Bulletin to ensure that you are using the most current versions of the Call Server and Signaling Server PEPs.

Installing the Signaling Server

The Signaling Server must be installed. If it is not installed, see *Signaling Server Installation and Commissioning* (NN43001-312).

For information about configuring the Signaling Server, see “[Signaling Server checklist](#)” (page 292).

OCS 2007 component installation

After all CS 1000 components are installed, go to the Microsoft Web site www.microsoft.com for information about installing the OCS components, beginning with the Active Directory.

ATTENTION

The following is a list of the required patches for the Microsoft OCS 2007 installation:

- OCS 2007 – Standard Edition RTM KB 942872 Version 6362.0 plus hotfix
- Description of the Office Communicator 2007 hotfix package: December 17, 2007 KB 943083 Version 2.0.6362.36
- Description of Office Communications Server 2007, Unified Communications Managed API v1.0 Redist: December 17, 2007 KB 944285 Version 3.0.6362.36
- Description of the Update for Office Communication Server 2007, Mediation Server: December 17, 2007 KB 943086 Version 3.0.6362.36

- OCS Application Proxy Server: OCS 2007 – Standard Edition RTMKB 942872Version 6362.0 plus hotfix

Microsoft SR1 RTM documentation can be obtained from the Microsoft Web site. Go to www.microsoft.com.

Prerequisite OCS 2007 information

The following section describes the prerequisite information.

Active Directory

The Office Communications Server 2007 and Office Communicator 2007 environment have a strong dependency on Active Directory to authenticate, authorize, provision, and configure Office Communications Server 2007.

With the OC 2007 client, Active Directory supplies the enterprise address list to facilitate search-based lookups.

Ensure that you install Active Directory in accordance with Microsoft documentation. For more information about Active Directory planning, see *Office Communications Server 2007 Document: Active Directory Guide*. Download Microsoft technical documentation from the Download Center at www.microsoft.com.

Office Communications Server (OCS) 2007 Enterprise Pool

OCS 2007 Enterprise Edition is designed for large-scale deployment where multiple Office Communications Server Enterprise Edition servers are deployed as a pool, typically behind a load balancer. Servers in the pool share a central SQL back end database server that stores user data.

If your pool consists of more than one server, a Load Balancer is required. If your pool consists of only one server, which is connected to a separate SQL back end database server, a Load Balancer is not required.

OC clients register on an Enterprise pool. The client user is directed to a specific server within the pool by a hardware load balancer that distributes the load to these servers. Static data, such as contact lists and access control lists (ACLs), are stored as persistent data on the back end database server.

A client can have multiple concurrent connection instances and can register on multiple servers at the same time. Each device to which the client is logged on (called an endpoint) can be connected through a different server at the same time.

The load balancer exposes a single Virtual Internet Protocol (VIP) address that is used by the clients to access the pool. Each Enterprise Edition server within the pool is responsible for connection processing, security and authentication, protocol processing, and server applications. The user data resides in the back end database server. The database contains records that hold static data and dynamic user data (such as endpoints and active descriptions for a user). The database runs a set of stored procedure calls that form the core of the operational software. Office Communications Servers within the pool are networked to the back end database server using a high-speed network. These Office Communications Servers also run User Replicator (UR) software to provide a connection to the Microsoft Active Directory service so that user account information can be synchronized between the back end database server and the Active Directory.

For more information about Office Communications Server 2007 Enterprise Edition, see the *Office Communications Server 2007 Document: Enterprise Edition Deployment Guide*. Download Microsoft technical documentation from the Download Center at www.microsoft.com.

OCS Proxy server installation

The following section describes the OCS Proxy server installation procedures.

Installing the OCS Proxy server

Step	Action
1	On the Windows Start menu, choose Run .
2	Navigate to the C:\Office Communications Server_Eval\se_eval\setup\i386\ folder.
3	For OCS Standard Edition: server.msi SERVER=PROXY SKU=SE OR For OCS Enterprise Edition: server.msi SERVER=PROXY SKU=EE A new Windows wizard opens prompting you to install the Forwarding Proxy. You must complete all the steps in the wizard before continuing.
4	Activate the proxy server using command line (from Office Communications Server_Eval\StandardEdition\setup\i386 folder). Activate on domain: <code>lscmd /server /password: <password> /action: activate /role:proxy</code> Activate on workgroup: <code>LcsCmd.exe /server /action:activate /role:workgroupProxy /password <password></code> OR For Office Communications Server Enterprise Edition:

```
Activate on domain: lcs cmd /server /user: <user>
                  /password:<password> /action: activate
                  /role:proxy
Activate on workgroup: lcsCmd.exe /server /user:
<user> /password:<password> /action: activate
                  /role:workgroupProxy
The user is the service user on the domain that is used by the
OCS Proxy service. You can enter any user and password.
```

Note: For TLS connection between OCS FE and OCS Proxy/MCM "Activate on workgroup" must be used.

- 5 Type:
Exit on the command line.
- 6 Run the Installation wizard and select the defaults.
- 7 To get Proxy to appear in OCS, navigate to Admin tools/Computer Management and select **Services and applications**.
- 8 Select Microsoft Office Communications 2007 and then Proxy (for example, ocs2007a-proxy.ocs2007a.corp.nortel.com).

--End--

Load Balancer installation

The following section describes the Load Balancer installation procedures.

Installing the Load Balancer

Step	Action
1	Go to the Start menu and select Settings .
2	Select Network Connections .
3	Select TCP/IP properties and add DNS server IP. For example, 47.11.108.50.
4	Go to My Computer , right-click and select System Properties .
5	Enter the Computer Name of each FE server. For example, ocs-fe-1.
6	Click domain. For example, ocs2007a.corp.nortel.com.
7	Restart server.

--End--

MCM installation

Prerequisite MCM information

- Ensure MS Windows Server 2003 operating system is installed with SP1 or R2.
- Ensure the OCS Proxy server is installed.
- Uninstall previous versions of MCM (if any previous versions exist).
 - Stop MCM service. On the MCM management console window and from the **Actions** menu, select **Stop**.
 - Use the Windows **Add/Remove Programs** utility to uninstall MCM.
- To use the Use an existing account option, you require a domain user account and password to install the MCM. The domain user account is a member of the local groups RTC Server Applications and Group. The user account must also have full control permissions on the MCM folder. For example, c:\program files\Nortel\MCM.
- To use the Create a new account option, you can log on to the server with a user ID and permissions to create users in the Active Directory
- To create a new account during the MCM installation, the new user is added to all the necessary groups automatically by the MCM.

Installing MCM 3.5

Step	Action
1	To install the MCM 3.5 software, run the MCM Installation wizard.
2	Select Use an existing account and enter your user ID and password OR select Create a new account .
3	Open the MCM Console window and select the Actions menu.
4	On the Actions menu, choose Start to start the MCM service.
--End--	


MCM must be installed on the OCS Proxy Server. See [“MCM menu options” \(page 146\)](#) for more information about using the MCM menu options.

MCM has two main components: **MCM Service**, which handles call processing, and **MCM Management Console**, which interfaces with the MCM Service component for configuration, administration, and maintenance.

Configuration

The following flow chart depicts the configuration order of the components.

Figure 27
Configuration flow chart



Active Directory configuration


Active Directory configuration takes place in the Active Directory Users and the Computers (ADUC) window. Selecting the Users folder reveals the list of users as depicted in [Figure 28 "Active Directory \(Microsoft LDAP server\)" \(page 119\)](#). All users are defined in this folder.

By default MCM uses GC LDAP server which contains partial information about all objects in the Active Directory domain forest. It requires replication from all Domain controllers to the GC domain controller to be performed after changes made in the Active Directory User's configuration "Active Directory Sites and Services" snap-in.

ATTENTION

All CS 1000 phones must be added in the Active Directory even when there is no Office Communicator user associated with the CS 1000 phone. The administrator can create a user account with the Enterprise Voice and PBX Integration enabled in the Active Directory for every CS 1000 phone. For example, a lab phone or a lobby phone. Some feature interactions will apply. See "Active Directory configuration" (page 79) in the Feature Interactions section.

Figure 28
Active Directory (Microsoft LDAP server)



Defining users

Step	Action
1	Select a user from the list in the Users folder.
2	Right-click the user, and select Properties .
3	The Properties window opens as depicted in Figure 29 "User properties" (page 120).

Figure 29
User properties

The screenshot shows the 'Chris Smith Properties' dialog box with the 'General' tab selected. The dialog has a title bar with a question mark and close button. Below the title bar are several tabs: 'Member Of', 'Dial-in', 'Environment', 'Sessions', 'Remote control', 'Terminal Services Profile', 'COM+', 'Communications', 'General', 'Address', 'Account', 'Profile', 'Telephones', and 'Organization'. The 'General' tab is active, showing a user icon and the name 'Chris Smith'. Below this are input fields for 'First name' (containing 'Chris'), 'Last name' (containing 'Smith'), 'Display name' (containing 'Chris Smith'), 'Description', and 'Office'. There are also fields for 'Telephone number' (containing '2070') and 'E-mail' (containing 'ChrisSmith@ocs2007a.corp.nortel.com'), each with an 'Other...' button next to it. At the bottom are buttons for 'OK', 'Cancel', 'Apply', and 'Help'.

- 4 Enter the user's information (first name, last name, telephone number, and so on) in the appropriate fields in the **General** tab.
- 5 Select the **Communications** tab.

- 6 Click the check box next to **Enable user for Office Communications Server**.
- 7 In the fields provided, define the user **Sign-in name** and the **Server or pool**). Office Communicator 2007 uses these addresses to place calls.

Figure 30
Enable Office Communications Server connectivity for a user in Active Directory

Chris Smith Properties

Published Certificates | Member Of | Dial-in | Object

Security | Environment | Sessions | Remote control

General | Address | Account | Profile | Telephones | Organization

Terminal Services Profile | COM+ | Communications

☒ **Enable user for Office Communications Server**

Sign-in name:
 sip:chrissmith @ ocs2007a.corp.nortel.com

Server or pool:
 ocs2007apool.ocs2007a.corp.nortel.com

Meetings
☒ Allow anonymous participants
 Policy: Default Policy [View...](#)

Note: Meeting settings cannot be changed unless the global setting allows per user configuration.

Additional options: [Configure...](#)

OK Cancel Apply Help

- 8 Click the **Configure** button.
- 9 For enabling Remote Call Control only, select **Enable Remote Call Control** and configure the Server URI and Line URI. See [Figure 31 "Enable Remote call control" \(page 123\)](#).

- 10 For enabling Enterprise Voice and PBX integration only (without RCC), select **Enable Enterprise Voice** and the **Enable PBX integration** check box. See [Figure 32 "Enable Enterprise Voice and PBX integration" \(page 124\)](#).
- 11 For enabling both Remote call control and Enterprise Voice, you must select **Enable Enterprise Voice** and the **Enable PBX integration** check box and specify the Server URI. See [Figure 33 "Enable both RCC and Enterprise Voice" \(page 125\)](#).
- 12 Specify the MCM/App Proxy FQDN in the Server URI field. This must be in the format of sip:CDP or UDP;phone-context=CDP domain or UDP domain@MCM/APP Proxy FQDN. For example:
- Sip:5001;phone-context=cdp.udp@proxy.ocs2007.corp.nortel.com – CDP format
 - Sip:3435001;phone-context=udp@proxy.ocs2007.corp.nortel.com – UDP format

Specify the URI of the user's telephone in the Line URI field. The Line URI must be in the format tel:E164;ext=CDP or UDP. For example:

- tel:+16139675000;ext=5001 – CDP format
- tel:+16139675000;ext=3435001– UDP format.

ATTENTION

It is important to note that the chosen numbering plan must be applied to the TLSV and MCM configurations.

--End--

Figure 31
Enable Remote call control

User Options

Telephony
Select a telephony option. These settings affect only those calls that are routed through IP-PSTN or remote call control gateways.

☐ Enable PC-to-PC communication only

☒ Enable Remote call control

☐ Enable Enterprise Voice

☐ Enable PBX integration

Note: To enable both remote call control and PBX integration, you must specify a Server URI below.

Policy: Default Policy View...

Server URI: sip:2070;phone-context=cdp.udp@test.com

Line URI: tel+16139675000;ext=2070

Federation

☐ Enable federation

☐ Enable remote user access

☐ Enable public IM connectivity

Archiving

☐ Archive internal IM conversations

☐ Archive federated IM conversations

Note: Archiving settings cannot be changed unless the global setting allows per user configuration.

☒ Enable enhanced presence

Note: Enhanced presence cannot be changed once it has been set.

OK Cancel Help

Figure 32
Enable Enterprise Voice and PBX integration

The screenshot shows a 'User Options' dialog box with a close button (X) in the top right corner. The dialog is divided into three main sections: 'Telephony', 'Federation', and 'Archiving'.
Telephony Section:
- Text: 'Select a telephony option. These settings affect only those calls that are routed through IP-PSTN or remote call control gateways.'
- Radio buttons: 'Enable PC-to-PC communication only', 'Enable Remote call control', and 'Enable Enterprise Voice' (which is selected and has a dashed border around it).
- Check box: 'Enable PBX integration' (checked).
- Note: 'Note: To enable both remote call control and PBX integration, you must specify a Server URI below.'
- Fields: 'Policy:' with a dropdown menu showing 'Default Policy' and a 'View...' button; 'Server URI:' with an empty text box; 'Line URI:' with the text 'tel:+16139675000;ext= 2070'.
Federation Section:
- Check boxes: 'Enable federation', 'Enable remote user access', and 'Enable public IM connectivity' (all are unchecked).
Archiving Section:
- Check boxes: 'Archive internal IM conversations' and 'Archive federated IM conversations' (both are checked).
- Note: 'Note: Archiving settings cannot be changed unless the global setting allows per user configuration.'
- Check box: 'Enable enhanced presence' (checked).
- Note: 'Note: Enhanced presence cannot be changed once it has been set.'
At the bottom right, there are three buttons: 'OK', 'Cancel', and 'Help'.

Figure 33
Enable both RCC and Enterprise Voice

User Options

Telephony
Select a telephony option. These settings affect only those calls that are routed through IP-PSTN or remote call control gateways.

☐ Enable PC-to-PC communication only

☐ Enable Remote call control

☒ Enable Enterprise Voice

☒ Enable PBX integration

Note: To enable both remote call control and PBX integration, you must specify a Server URI below.

Policy: Default Policy View...

Server URI: sip: 2070 ;phone-context=cdp.udp@test.com

Line URI: tel: +16139675000;ext= 2070

Federation

☐ Enable federation

☐ Enable remote user access

☐ Enable public IM connectivity

Archiving

☒ Archive internal IM conversations

☒ Archive federated IM conversations

Note: Archiving settings cannot be changed unless the global setting allows per user configuration.

☒ Enable enhanced presence

Note: Enhanced presence cannot be changed once it has been set.

OK Cancel Help

Office Communications Server configuration

The starting point for Telephony Gateway and Services configuration is the Office Communications Server 2007 component.

Load Balancer configuration

The pool of Front End servers is organized to process inbound and outbound traffic. The role of the Load Balancer in this architecture is to route incoming SIP-messages to the less busy server on the base of configured algorithm. Load Balancer's VIP-address is used by clients as a single point of connection to the pool. This address is listed in DNS and has a FQDN. Internal OCS clients require a DNS server to establish connection with an Enterprise Edition Pool.

Voice Properties configuration

When introducing telephony support to an OCS 2007 the following OCS FE entities must be configured:

Step	Action
1	Location profiles. A location profile defines all phone numbers that can be dialed from a named location. A location contains one or, typically, more normalization rules. Normalization rules should be defined in the Location Profile to convert the dialstrings to the E.164 International format for all types of PSTN calls. For example, NXX, NPA and International. For all calls using private dialing plan (CDP or UDP), normalization rules must be defined in the Location Profile to convert the dialstrings to the Line URI format. For example, E.164;ext=xxxxxxx format.
2	Normalization rules. Normalization rules are .NET regular expressions that define a phone number pattern. A set of normalization rules associated with a particular location constitute a location profile.
3	Phone usage records. A phone usage record specifies a class of call (internal, local, long distance, or whatever) that can be made by various users, or groups of users, in an organization.
4	Voice policy. A voice policy associates one or more phone-usage records with one or a group of users.
5	Route. A voice route associates target phone numbers with particular IP-PSTN gateways and phone usage records. Source-based routing must be used for CS 1000 and OCS 2007 integration.
6	Define users and enable their Voice and RCC capabilities.
--End--	

Voice mail must always be configured on the CS 1000 and not Office Communicator. Configuring communication to the CS 1000 gateway is performed at the Mediation Server.

Dual forking is configured based on OCS Voice Policies, which in turn may be applied globally or on a per user basis. For more information on configuring Voice Policies, see *Microsoft Office Communications Server 2007 Enterprise Voice Planning and Deployment Guide*. Download Microsoft technical documentation from the Download Center at www.microsoft.com.

Enabling dual forking–globally

Step	Action
1	Click Forest and then Properties .
2	Select Voice Properties in the OCS management console.
3	Under Global Policy , select the desired policy and click Edit . This policy will be applied for all users.
4	In the Edit Policy window, click the Allow simultaneous ringing of phones box.
--End--	

Enabling dual forking–by user

When applying voice policies on a per user basis, dual forking can be enabled for the user by selecting an appropriate policy.

Step	Action
1	Click Forest and then Properties .
2	Select Voice Properties in the OCS management console.
3	Under Use per user policy , select the desired policy and click Edit . This policy will be applied on a user basis.
4	In the Edit Policy window, click the Allow simultaneous ringing of phones box.
5	Go to Users in the OCS configuration console.
6	Select a user and click Properties .
7	In the properties window, click Additional Options configure .
8	Select the desired policy.
--End--	

Applying policy

Step	Action
1	In the User Options window, click Enable Enterprise Voice .
2	Select Another Policy . The policy can be assigned simultaneously to several users using the Configure Users wizard.
--End--	

OCS configuration procedures

Download Microsoft technical documentation from the Download Center at www.microsoft.com.

Configuration of Static Routes

Configuration of the Office Communications Server involves the configuration of static routes and host authorization.

You must configure static routes between the client and server. For information about configuring static routes (Enterprise Edition pool behind a Load Balancer), see *Office Communications Server 2007 Administration Guide*, and the *Microsoft Office Communications Server 2007 Enterprise Edition Deployment Guide*. Download Microsoft technical documentation from the Download Center at www.microsoft.com.

Host Authorization and Routing configuration

For one Office Communications Server to communicate with another Office Communications Server, each server must have authorization to speak to the other. The Host Authorization tab as depicted in [Figure 35 "Office Communications Server Front Ends" \(page 130\)](#) is where you establish this authorization.

The Host Authorization tab, located in the OCS Proxy with MCM is where all the CS 1000 endpoints are configured. These endpoints must be configured as authorized endpoints in the OCS Proxy with MCM. Configure the CS 1000IP addresses which, in turn, talk to the Office Communications Server. The same authorization must take place for both OCS to OCS authorization and OCS to CS 1000authorization.

Configuring the Host Authorization and Routing for the OCS Front End server

Step	Action
1	Open Office Communications Server (accessed from the Windows server that runs the OCS server) as shown in Figure

34 "Opening Office Communications Server " (page 129). Click on the **Start** menu and then select **Administrative Tools, Office Communications Server 2007**.


Figure 34
Opening Office Communications Server



2


Click on the Office Communications Server (the server to which you want to add Host Authorization and change the Routing), right-click on **Front Ends** and choose **Properties**. See [Figure 35 "Office Communications Server Front Ends"](#) (page 130).

Figure 35
Office Communications Server Front Ends



- 3 Click on the **Host Authorization** tab and select the **Edit** button.
- 4 In the Server section, click on the **IP Address** button and enter the IP address of the OCS Proxy server. For details, see [Table 25 "Routing rules"](#) (page 136).
- 5 In the Settings section, select **Throttle As Server** and the **Treat as Authenticated** check boxes.
- 6 Click **OK**.
- 7 On the Routing tab of the Front End server, a Routing rule is defined to route the SIP message in which the Request URI matches the Server URI as defined in the Active Directory for each user to the OCS Proxy server where MCM is running.
For an example, see [Figure 36 "Routing tab"](#) (page 131).

Figure 36
Routing tab



- 8** In the Add Static Route window, For Domain: enter the domain defined in the Server URI. For Next Hop: enter the IP address of the OCS Proxy.


--End--

For each OCS Proxy with MCM, Host Authorization is required for the Node IP address of all CS 1000 servers that the Office Communications Server interacts with, as well as the TLAN IP address of the Primary, Secondary, and all possible collaborative NRS.

Configuring host authorization for the OCS Proxy


Step	Action
1	Open the OCS Proxy server, click the Windows Start button, point to Administrative Tools , and then click Computer Management .

Figure 37
Opening the Computer Management console




2	Choose Microsoft Office Communications Server and right-click to select Properties .

Figure 38
Office Communications Server Management Console




- 3 For the OCS Proxy, no static route is required. MCM routes inbound calls to the proper Mediation Server based on the Routing Table settings on the MCM.
- 4 Click the **Routing** tab to confirm no route is configured.

Figure 39
Routing tab



- 5 Click the **Host Authorization** tab.
- 6 Click **Edit** to open the Edit Authorized Host window.
- 7 In the Edit Authorized Host window, enter the **IP address**, select both the **Throttle As Server** and **Treat As Authenticated** check boxes, and then click **OK**. The IP addresses that require authorization on the OCS Proxy are the Node IP addresses of all the CS 1000s in the network, IP address of the NRS (SRS or SPS), all the IP addresses of the OCS Front End servers, IP addresses of the Mediation Servers, and the IP addresses of all Front End Servers. For more details, see [Table 25 "Routing rules"](#) (page 136).

Figure 40
Edit Authorized Host



--End--

The following table shows a number of possible configurations of OCS 2007 and the required entries for each. The transport to CS 1000 is TCP for all configuration types.

Table 24
OCS Servers Routing and Host Authorization Summary

	OCS Front End Servers Pool	OCS Mediation Server	OCS Proxy Server
Routing	Domain: OCS Proxy Server's FQDN Next hop IP: IP Address of the OCS Proxy Server Transport: TCP Port: 5060	None	None

	OCS Front End Servers Pool	OCS Mediation Server	OCS Proxy Server
	Phone URI: No Replace host in request URI: No		
Host Authorization	IP Address of the OCS Application Proxy Server Outbound Only: No Throttle as Server: Yes Treat as Authenticated: Yes	None	- NRS/SPS IP Address - Signaling Server Node IP Address - All IP Addresses of Mediation Servers - IP Address of all Front End Servers

Table 25
Routing rules

Configuration Type	Component	Host Authorization	Destination	User / Domain	Phone URI	Transport	Port
1. Single Front End server and single OCS Proxy. All TCP	Front End server	OCS Proxy IP	OCS Proxy IP	<domain name>	No	TCP	5060
	OCS Proxy	Front End server IP					
		SPS/SRS IP					
		Node IP					
		Mediation Servers IP					
2. Single Front End server and single OCS Proxy. SIP CTI TLS	Front End server	OCS Proxy FQDN	OCS Proxy FQDN	<domain name>	No	TLS	5061

Table 25
Routing rules (cont'd.)

Configurat ion Type	Comp- onent	Host Authorizat ion	Dest- ination	User / Domain	Ph one URI	Tran s- port	Por t
	OCS Proxy	Front End server FQDN					
		SPS/SRS FQDN					
		Node FQD N					
		Mediation Servers IP					
3. Pool of Front End servers and Single OCS Proxy . All TCP	Front End servers Pool	OCS Proxy IP	OCS Proxy IP	<domai n name >	No	TLS	506 1
		Load Balan cer IP					
	OCS Proxy	Front End servers IP					
		Load Balan cer IP					
		SPS/SRS IP					
		Node IP					
		Mediation Servers IP					
4. Pool of Front End servers and Single OCS Prox y. SIP CTI TLS	Front En d server Pool	OCS Proxy FQDN	OCS Proxy FQDN	<domai n name >	No	TLS	506 1
	OCS Proxy	Pool FQDN					
		SPS/SRS FQDN					

Table 25
Routing rules (cont'd.)

Configurat ion Type	Comp- onent	Host Authorizat ion	Dest- ination	User / Domain	Ph one URI	Tran s- port	Por t
		Node FQD N					
		Mediation Servers IP					
5. Single Front End server and Pool of OCS Proxies, All TCP	Front En d server	Proxy Load Balancer IP	Proxy Load Ba lancer IP	<domai n name >	No	TCP	506 0
		OCS Proxi es IP	Load Balance r IP	CS 100 0 SIP address	NO	TCP	506 0
	OCS Proxies	Front End server IP					
		Proxy Load Balancer IP					
		SPS/ SRS IP					
		Node IP					
		Mediation Servers IP					
6. Single Front End server and Pool of OCS Proxies, SIP CTI TLS	Front En d server	Proxy Load Balancer FQDN	Proxy Load Ba lancer FQDN	<domai n name >	No	TLS	506 1
	OCS Proxies	Front End server FQDN					
		Proxy Load Balancer FQDN					

Table 25
Routing rules (cont'd.)

Configurat ion Type	Comp- onent	Host Authorizat ion	Dest- ination	User / Domain	Ph one URI	Tran s- port	Por t
		SPS/SRS FQDN					
		Node FQD N					
		Mediation Servers IP					
7. Pool of Front End servers and Pool of OCS Proxies. All TCP	Front En d server Pool	Proxy Load Balancer IP	Proxy Load Ba lancer IP	<domai n name >	No	TCP	506 0
		Front End Load Balan cer IP					
		OCS Proxi es IP					
	OCS Proxies IP	Front End servers IP					
		Proxy Load Balancer IP					
		Front End Load Balan cer IP					
		SPS/SRS IP					
		Node IP					
		Mediation Servers IP					

Table 25
Routing rules (cont'd.)

Configurat ion Type	Comp- onent	Host Authorizat ion	Dest- ination	User / Domain	Ph one URI	Tran s- port	Por t
8. Pool of Front End servers and Pool of OCS Proxies. SIP CTI TLS	Front End servers Pool	Proxy Load Balancer FQDN	Proxy Load Ba lancer FQDN	<domai n name >	No	TLS	506 1
	OCS Proxies	Proxy Load Balancer FQDN					
		Front End Load Balan cer FQDN (Pool FQD N)					
		SPS/SRS FQDN					
		Node FQD N					
		Mediation Servers IP					

Mediation Server configuration

Use the following procedures for configuring a Mediation Server.



WARNING

The Microsoft configuration procedures in this document are provided for your convenience and are based on Microsoft OCS technical documentation. For more information about configuring OCS and the most recent configuration instructions, go to www.microsoft.com.

Configuring a Mediation Server

Step	Action
1	Log on to a Communications Server 2007 Mediation Server.
2	Click Start , point to Administrative Tools, and then click Office Communications Server 2007 .
3	Expand the appropriate forest node.

- 4 Expand the Mediation Servers node, right-click on the Mediation Server to be configured, click **Properties**, and then click the **General** tab.
- 5 In the FQDN box, make sure the FQDN listed matches that of the Mediation Server you have selected.
- 6 Open a command prompt, change to the root directory, and type **nslookup** and (FQDN of the server) using the FQDN displayed on the Mediation Server General tab, and then press Enter.
- 7 From the list of IP addresses displayed in the Communications Server listening IP address list, select the IP address returned in [Step 6](#). If the IP address selected, does not match the IP address in [Step 6](#), Communications Server traffic will be directed toward an interface that is not listening for such traffic and away from the one that is.
- 8 From the list of two IP addresses displayed in the Gateway listening IP address list, select the other IP address (can be a media gateway or the Communication Server 1000).
- 9 From the A/V Edge Server list, select the A/V Edge Server that hosts the A/V Authentication Service for this Mediation Server.
- 10 In the Default location profile list, select the default location profile for this Mediation Server
- 11 In Media port range accept the default range of 60,000 to 64,000.
- 12 Click the **Next Hop Connections** tab.
- 13 On the Next Hop Connections tab under Office Communications Server next hop. In the FQDN list, select the FQDN of the next-hop internal server. This server could be a Director or pool. In the Port box, accept the default of 5061 for TLS.
- 14 On the Next Hop Connections tab under PSTN Gateway next hop. In the IP address box, specify the IP address of the OCS Proxy where the MCM runs. In the Port box, accept the default of 5060 for TCP.
- 15 Click OK.

--End--

MCM 3.5 configuration

The Multimedia Convergence Manager (MCM) is a software component that Nortel provides to enable voice connectivity between CS 1000 clients and the Office Communications Server (OCS) 2007 clients. MCM consists of the following modules:

- Call Processing Service
- Management Console

The MCM Call Processing Service handles the Session Initiation Protocol (SIP) telephony traffic between the CS 1000 and the Office Communications Server. The Management Console provides real-time status of the MCM, Office Communications Server, Primary Network Routing Service (NRS), and Secondary NRS. It also provides Administrative, Maintenance, and Configuration tools.


Office Communications Server 2007 provides multimedia and collaboration features such as Video, Internet Messaging (IM), Presence, White Board, Application Sharing, and Voice over Internet Protocol (VoIP) capability. MCM enables SIP VoIP connectivity between the CS 1000 and the Office Communications Server 2007 and TR/87 authorization functionality required for the Office Communicator (OC) 2007 Remote Call Control capability.

Telephones in a CS 1000 system can make direct SIP calls to OCS clients when the dialed number maps to a corresponding user's Line URI using LDAP queries to the corporate Active Directory. MCM also allows Office Communications Server clients to originate ESN and trunk calls to corporate and external users.

MCM architecture

MCM 3.5 is situated between the Mediation Server and the CS 1000. 3.5 must run on top of the OCS Proxy server with Windows 2003 as depicted in [Figure 41 "MCM architecture" \(page 143\)](#).

Figure 41
MCM architecture



The following examples illustrate how MCM handles call information. Understanding the role of MCM in the Telephony Gateway and Services component helps you to determine the configuration.

Example 1: Outgoing calls from Office Communicator

In this example, an invite travels from the client to the OCS Front End server, and then to the Office Communications Server MCM Proxy through the Mediation Server. MCM checks which NRS is active, and then sends an invite to that SIP Redirect Service (SRS). In this case, the invite is qualified. To return from the SRS, 302 is used. The invite is then sent unqualified to the CS 1000 associated with the originator's location code and DN.

Example 2: Incoming calls to Office Communicator

In this example, the user has a desktop telephone and a Telephony Services (TLSV) that points to an Office Communications Server 2007 server. The TLSV sends a DN or Routing DN. The call was originally made to 6 231 3052, but the TLSV hot key is configured with 6 344 5000. This is a "dummy" routing DN; it can be configured with all hot keys in the network.

In a CDP network, the dummy routing DN (for example, 6 231 3052) must also be configured by a DSC (for example, 8200). The DSC is configured on the NRS as a routing entry for the MCM Gateway endpoint.

The call is routed to the NRS. The invite is sent to the NRS, which returns a 302, and the CS 1000 sends an invite to the MCM Proxy. At this stage, the invite includes a special header called x-nt-ocn that contains the actual number called. Use this header to compare against the Active Directory map for the user's Line URI. This method is used to prevent you from having to program the for each user to determine the correct DN upon which to terminate the call. The MCM then routes this call to the proper Mediation Server based on the SIP GW ID provided in the INVITE and the Routing Table configured on the MCM.

You need not configure each user. Configure only the routing DN, and the header is automatically injected to identify the called party.

MCM Direct configuration

For small CS 1000 deployments (without NRS), MCM supports Direct configuration. In this mode, MCM sends an invite from the client directly to the CS 1000 node IP address specified in the MCM configuration. MCM does not check CS 1000 availability in Direct mode configuration.

For more information about the various MCM configuration fields, see [Figure 43 "MCM configuration form" \(page 148\)](#).


MCM management console

The following list contains possible statuses for the various MCM components:

- MCM
 - Running
 - Pending
 - Stopped
- OCS
 - Running
 - Pending
 - Stopped
- Primary SRS/SPS (the IP address of the Primary SRS/SPS server)
 - Active - Primary SRS/SPS is active. All messages are sent through the Primary NRS.
 - Standby - Primary SRS/SPS is alive. The Secondary SRS/SPS is active.

- Not responding - Primary SRS/SPS is not responding. For normal processing, the Secondary SRS/SPS must be switched to an Active state.
- Unknown - An unknown response is received by the SRS or SPS.
- Secondary SRS/SPS (the IP address of the Secondary SRS/SPS server)
 - Active - Secondary SRS/SPS is active, which is possible only if the Primary SRS/SPS is down.
 - Standby - Secondary SRS/SPS is alive, which is the normal state if the Primary SRS/SPS is active.
 - Not responding - Secondary SRS/SPS is not responding. You cannot switch to it.
 - Unknown - An unknown response is received by the Secondary SRS or SPS.

Figure 42
MCM



MCM menu options

The following list describes the function of each MCM menu command:

- Actions
 - Start - start MCM service
 - Stop - stop MCM service
 - Restart - stop and start MCM service
 - Exit - close current GUI for MCM service
- Tools
 - Configuration
 - Active Calls Count
 - Active Directory Query

- Backup
- Restore
- Set Log Level
- Help
 - Get help and general information about MCM

MCM command line parameters

The MCM console application can be run with command line parameters to configure some advanced settings. The following parameters are available.

Parameter	Description and example
/h	show help about using command line parameters For example: MCMConsole.exe /h
/MedSrvHealth Check	enable/disable Mediation server health checking process For example: MCMConsole.exe /MedSrvHealthCheck:true
/Remove100rel	indicate whether the 100rel from Supported header needs to be deleted For example: MCMConsole.exe /Remove100rel:true
/VoIPChange	allow a change of the anonymous FROM header value to another specified number. For example: MCMConsole.exe "/VoIPChange:<sip:anonymous@anonymous.invalid><sip:+1234567777@domain.com; user=phone>
/RCCChange	allow a change of the RCC anonymous calling number to another specified number. For example: MCMConsole.exe "/RCCChange:<tel:anonymous><tel:+12345 67777>

ATTENTION

/VoIPChange and /RCCChange parameters can be used repeatedly to create mapping table. Use these two parameters to resolve most scenarios that involve double pop-ups when there is a call from an unknown user. See example, as shown below.

Unknown calling number example

If the calling number is unknown, Office Communicator cannot merge VoIP and RCC pop-ups into one pop-up.

In the following scenario, if you have:

- VoIP address: sip:anonymous@anonymous.invalid
- RCC number: <tel:anonymous>

The mapping must be defined on the MCM as:

- MCMConsole "/VoIPChange:<sip:anonymous@anonymous.invalid><sip:+1234567777@domain.com;user=phone>
- MCMConsole "/RCCChange:<tel:anonymous><tel:+1234567777>

The expected result is:

Communicator has one merged pop-up with CLID "+71237777"

MCM Configuration

To access the MCM Configuration window, go to the MCM console window, select the **Tools** menu and then select **Configuration**.

Figure 43
MCM configuration form

The screenshot shows the 'Configuration' window with the following sections:

- Network Topology:**
 - Call Server: CS 1000
 - ☐ SRS
 - ☒ SPS
 - Primary IP: 47.11.56.25
 - Secondary IP: 0.0.0.0
 - Registration ID: MCM@ocs2007a.corp.nortel.com
 - Registration IP: 192.168.25.129
 - Mode: Proxy All
 - ☐ Direct Connect
 - CS1000 SIP GW IP: 0.0.0.0
 - Transport: TCP, Port: 5060
 - ☒ Mediation Server, Routing Table
 - Default codec: G711 U-Law
- Active Directory Configuration:**
 - ☒ Query Server, Synchronize at: 03:00
 - ☐ Local Cache, Synchronize Now
 - ☐ Local Cache then Query Server
 - ☐ AD/LDAP SSL encryption
 - ☐ Non Default AD/LDAP Server
 - Server IP: 0.0.0.0, Port:
- Network Dial Plan:**
 - Dial Plan: CDP
 - Access Code:
- SIP/CTI Authorization:**
 - ☐ Enable RCC Authorization
- Incoming Call Processing Parameters:**
 - Called Phone Context: cdp:udp
 - Called Phone Prefix Delete: 0
 - Called Phone Prefix Insert:
 - Caller Phone Prefix Delete: 0
 - Caller Phone Prefix Insert:
- Outgoing CLID Number Parameters:**
 - Prefix Delete: 0
 - Prefix Insert:
- Outgoing CLID Name Parameters:**
 - ☐ "FirstName LastName"
 - ☐ "LastName, FirstName"
 - ☐ "LastName FirstName"
 - ☒ AD Display Name
- OCS Application parameters:**
 - ☐ Critical

Buttons at the bottom: Ok, Cancel, Help.

Network Topology section The following is a description of some of the configuration fields in the Network Topology section of the MCM configuration window.

Table 26
Network topology fields

Configuration field	Description
Call Server	Type of call server CS 1000, CS 2000, CS 2100
SRS	Outgoing SIP messages from the MCM will use the SIP Redirect Server for routing.
SPS	Outgoing SIP messages from the MCM will go through the SIP Proxy Server.
Direct	Outgoing SIP messages from the MCM will terminate directory to a CS 1000 SIP GW.
Primary IP	IP address of primary SRS/SPS. Not used in the case of Direct SIP Routing.
Secondary IP	IP address of secondary SRS/SPS. Not used in the case of Direct SIP Routing.
Registration ID	MCM endpoint ID. This ID is in the format of host@domain. The host must match the endpoint name as defined in the NRS/SPS for MCM.
Registration IP	Select the MCM proxy IP to register with the SRS/SPS.
Mode	Proxy mode for SPS. The SIP Proxy Server (SPS) acts as a redirect server as well as a proxy server: • Proxy All—SPS will proxy/route all messages from the MCM. • Proxy SIP and Re-direct SIP-CTI—SPS will proxy/route SIP calls and redirect SIP-CTI calls. In this mode, traffic going through the SPS is reduced. This can also be useful for administration purposes. • Redirect All—SPS will redirect all messages. In this mode, SPS will work in the same way as SRS. If this mode is selected, ensure that DNS server IP addresses have been configured on the SIP Proxy Server.
CS 1000 SIP GW IP	IP address of the CS 1000 Node. Used only for Direct SIP routing with the CS 1000.
Transport	Only TCP is supported.
Port	SIP Port on SRS, SPS, and CS 1000. Default values are 5060 for TCP and 5061 for TLS connections.
Mediation Server	Select the check box to use Mediation Server.
Routing table	Click the Routing Table button when using Mediation Server.
Default codec	The default companding law configured on the corresponding CS1000 system. If the CS1000 deployment consists of CS1000 systems configured with different companding laws, a separate server with MCM is required for each law.

Mediation Server routing table Several Call Servers from different geographic locations may be connected to one MCM with one SIP Gateway. For each geographic location, one or several Mediation Servers

forming Mediation Servers pool can be used. The sip-gw-id parameter is passed as an INVITE request providing information about which dedicated Mediation Server or Mediation Server pool to process this message. The parameter value for SIP Gateway Endpoint Name is configured in Element Manager under **System, IP Network, Nodes: Servers, Media Cards, Signaling Server Properties**.

The Routing Table must be configured with Mediation Pool ID as **Gateway ID/Service DN**. For example, if Gateway ID is "cs1k_sppm" and the Service DN is "7294000", then the Mediation Pool ID has to be "cs1k_sppm/7294000". The MCM is then able to determine what pool is used.

Click the **Add** button to configure the Mediation Server pool's IP address.

Click **OK**.

Configure the IP address of the Mediation Server and add it to the pool. See [Figure 44 "Add Route" \(page 151\)](#).

- Configure Mediation Server Pool ID—ensure this is the same as the sip-gw-id header.
- Location—Description of the pool.
- Count—Number of the Mediation Servers in the pool. This gets updated automatically.

When a new Mediation Server is added into the Mediation Server pool, the MCM configuration must be manually updated with the Mediation Server IP address because Mediation Servers do not support an auto discovery mechanism.

The Transport and Port parameters are the SIP transport and TCP port configured on the Mediation Server for the PSTN Gateway Listening Connection. The default values are transport TCP and port 5060. For more information on TLS transport configuration, see ["Transport Layer Security \(TLS\) configuration between OCS Proxy/MCM and Mediation Server" \(page 221\)](#).

Figure 44
Add Route

Add Route

Configure Mediation Server Pool

Mediation Pool Identifier

Location

Mediation Server IP

Address

Incoming Call Processing Parameters This option refers to incoming CS 1000calls to MCM that terminate on Office Communicator. You must specify the phone context. When the telephone context is defined, mapping is performed (using CDP or UDP). In the case of a large network, the telephone context used is UDP, while CDP is used for small networks. You can use Called Phone Prefix Delete and Insert fields to manipulate digits received from the CS 1000prior to mapping.

Table 27
Incoming Call Processing parameters

Configuration field	Description
Called Phone Context	Phone Context of calls to be processed by MCM. This entry depends on the dial-plan (CDP or UDP) and should be the same as Private/CDP domain name entries in the Signaling Server Element Manager.
Called Phone Prefix Delete	Number of prefix digits to be deleted from the called number for mapping to the user ID by MCM
Called Phone Prefix Insert	Prefix digits to be inserted in the called number for mapping to User ID by MCM.
Caller Phone Prefix Delete	Number of Prefix digits to be deleted from the caller number for mapping to a user ID by the Office Communicator client.
Caller Phone Prefix Insert	Prefix digits to be inserted in the caller number for mapping to a User ID by the Office Communicator client.

The Caller Phone Prefix Delete and Insert is used to manipulate the digits in the From header of the INVITE received from the CS 1000. These two kinds of manipulation are generally not necessary, but are available in case a scenario requires this type of manipulation.

Incoming Call Processing Parameters section The MCM requires access rights to certain directories (for example: "Program Files/ MCM..."). Ensure that the user has the Administrators rights to these directories.

The following [Figure 45 "Element Manager SIP URI MAP"](#) (page 153) depicts the Called Phone Context entry in the MCM Configuration screen and the entries for UDP and CDP in the Signalling Server Element Manager. These entries must match.

Figure 45
Element Manager SIP URI MAP

The screenshot shows the 'Element Manager SIP URI MAP' configuration window. It is divided into two main sections: 'Incoming Call Processing Parameters' and '- SIP URI Map'.

Incoming Call Processing Parameters:

- Called Phone Context:** A text field containing 'cdp.udp', which is circled in red.
- Called Phone Prefix Delete:** A numeric field set to '0'.
- Called Phone Prefix Insert:** An empty text field.
- Caller Phone Prefix Delete:** A numeric field set to '0'.
- Caller Phone Prefix Insert:** An empty text field.

- SIP URI Map:

- Public E.164/National domain name:** Text field with '+1'.
- Public E.164/Subscriber domain name:** Text field with '+613'.
- Public E.164/Unknown domain name:** Text field with 'PublicUnknown'.
- Public E.164/Special Number domain name:** Text field with 'PublicSpecial'.
- Private/UDP domain name:** Text field with 'udp'.
- Private/CDP domain name:** Text field with 'cdp.udp', which is circled in red.
- Private/Special Number domain name:** Text field with 'PrivateSpecial'.
- Private/Unknown (vacant number routing) domain name:** Text field with 'PrivateUnknown'.
- Unknown/Unknown domain name:** Text field with 'UnknownUnknown'.

OCS Application parameters Click the Critical checkbox to enable MCM to register as a Critical application on OCS. OCS Proxy service will not start if MCM is registered as a Critical application and MCM fails to start. This option is useful in MCM redundancy deployment, if Load Balancer supports SIP health checking. The health checking fails, when MCM fails to start, and Load Balancer routes all the SIP messages to another functioning MCM.

Active Directory configuration section There are two modes for Active Directory (AD) Configuration: Realtime or Local Cache. Realtime mode is used for end-user ID mapping, which requires a Lightweight Directory Access Protocol (LDAP) query. Local Cache mode involves caching the Active Directory on the MCM server and using that cache information for queries.

Table 28
Active Directory configuration

Configuration Field	Description
Query server	Use this field for real-time LDAP AD queries.

Configuration Field	Description
Local Cache	AD queries are done to a local cache of the AD. The cache is synchronized daily at a preconfigured time. You can force it to synchronize by clicking the Synchronize Now button to start
Local Cache then Query Server	AD queries are done to a local cached of the AD. If the entry is not found in the local cache then the MCM queries the LDAP AD in real-time.
Non default AD/LDAP Server	IP address and port of the LDAP server to be used if different from the default AD/LDAP server.

Active Directory query The Active Directory Query tool is used to check Active Directory mapping configuration. It searches for a user-id (SIP URI) by a given telephone number, and vice versa. This tool is only used for maintenance, and emulates the same algorithm that is used by the MCM service in run-time.


For example: user Brendan McCarthy is defined in the Active Directory as:

SIP URI: sip:brendan@ocs2007a.corp.nortel.com

Line URI: +16239675000;ext=2071


If you type the telephone number in the Query field and click the **Get User-ID** button, the SIP URI appears in the Result field (as shown in [Figure 46 "Get SIP URI" \(page 155\)](#)).

Figure 46
Get SIP URI



If you type the SIP URI in the Query field and press the Get Phone button, the Telephone number appears in the Result field (see [Figure 47 "Get phone" \(page 155\)](#)).

Figure 47
Get phone



Network dial plan section The following table describes the fields for Dial plan and Access code.

Table 29
Network dial plan

Configuration field	Description
Dial plan	Use the dial plan to make calls between the CS 1000 and OCS (CDP or UDP). If the Line URI is configured as UDP, the dial plan will also be UDP.
Access code	Access code for the UDP plan. This code is added to the phone number stored in the OC user's Line URI.

ATTENTION

Only one dialing plan is supported at a time for Office Communication Server 2007 inter-working . All calls between nodes of CS 1000 deployment must be placed using the same dialing plan configured for the Nortel Converged Office feature.

Outgoing CLID Number Parameters section The following table describes the fields for Prefix Delete and Prefix Insert.

Table 30
Outgoing CLID Number Parameters

Configuration field	Description
Prefix Delete	Number of prefix digits to be deleted from the CLID number sent by MCM to the CS 1000.
Prefix Insert	Prefix digits to be inserted in the CLID number sent by MCM to the CS 1000.

Outgoing CLID Name Parameters section If an OC client does not have an UEXT defined in the CS1K then outgoing CLID Name Parameters manipulate the name string to display the name on a CS 1000 configured in the desired format. The name must be defined in the Active Directory in the format Last, First [additional info].

ATTENTION

If an OC client has an UEXT defined in the CS1K then the name is displayed in accordance to CPND configuration for this CS 1000 line. The name will not be displayed if CPND is not configured.

Table 31
Outgoing CLID Name Parameters

Configuration field	Description
FirstName LastName	First name Last name—display name format.
LastName, FirstName	Last name, First name—display name format.

Configuration field	Description
LastName FirstName	Last name First name—display name format.
AD Display Name	Click the check box to use the Display Name value from AD for the calling user name.

SIP CTI Authorization section Click the Enable RCC Authorization check box to enable the authorization of SIP CTI INVITES from Office Communicator (OC). Only the OC user's phone that is configured in the Active Directory is controlled.

For Remote Call Control, the Nortel MCM application that resides within the Office Communications Server domain provides support for authorizing TR/87 service requests and redundancy.

MCM supports authorization of Remote Call Control service requests from Office Communicator clients. The following is a summary of the authorization algorithm:


1. The SIP INVITE "from" header provides the **Requestor Identity** (for example, the Office Communications Server user identity).
2. The CSTA XML message provides the **Controlled Device Identity** (for example, the phone URI).
3. The **Owner Identity** is found by a reverse lookup using the Controlled Device Identity found in ["Item 2" \(page 157\)](#) as a query to Active Directory (Search Active Directory, Find the User whose msRTCSIP-Line equals "Controlled Device ID", then find the msRTCSIP-PrimaryUserAddress of that User).
4. If a result is found in ["Item 3" \(page 157\)](#), the Owner Identity is equal to the Requestor Identity, and msRTCSIP-OptionFlags has RCC enabled, then approve the request. Otherwise, reject the request.

The primary function of MCM when authorization is enabled, is to ensure that an Office Communicator user can use Remote Call Control only for the phone URI, and that Remote Call Control SIP URI as configured in Active Directory for that user by the System Administrator as depicted in [Figure 48 "Enable phone integration on the client" \(page 158\)](#).

Placing control in the hands of the System Administrator is necessary in environments where users must not override their phone integration configuration through the manual phone integration option in Office Communicator.

Note: Disabling TR/87 authorization on the MCM is strongly discouraged. When this functionality is disabled, users can override their active directory configuration and control any DN in the system that is provisioned to support SIP CTI.

Figure 48
Enable phone integration on the client



Redundancy Redundancy of the TR/87 interface is not provided natively with Office Communications Server 2007. Office Communicator does not support multiple Remote Call Control SIP URIs or SIP 300/302 redirection messages. To provide for redundancy of the TR/87 interface, the Nortel MCM application uses the redundancy of NRS and multiple FE endpoints.

MCM redundancy with Load Balancer

OCS Proxy/MCM redundancy is ensured by configuring a Load Balancer. The following must be configured:

- The Front-End server (static route) and Mediation Server (PSTN Gateway next hop) must point to the Load Balancer VIP (Virtual IP address).
- Each MCM is registered to the NRS with dynamic SIP (No Routing Entry configured).
- A static endpoint is configured for the MCM VIP on the NRS. Configure a Routing Entry to point to the static endpoint.

Telephony Gateway and Services configuration

This section describes the process to configure Telephony Gateway and Services.

Office Communications Server, Active Directory and 3.5 must be configured properly prior to configuring the Telephony Gateway and Services component.

Call Server configuration

CS 1000 configuration involves two separate functions: Signaling Server configuration and Call Server Configuration. All of the Signaling Server configuration is performed in Element Manager. Most of the Call Server configuration can also be done in Element Manager, although some can be done at the Call Server prompt. This document assumes that you are already familiar with how to configure a CS 1000.

In ESN networks, you must configure the correct HLOC in both LD 90 (required for ESN calls to work) and LD 15. If not, basic calling functionality does not work. Also, the Caller ID table, Home NPA, and LOC are required for outgoing calls to the Public network (PSTN) to correctly display the outgoing Caller Line ID (CLID) in North America.

Package 408 is required for both Telephony Gateway and Services and Remote Call Control. Phones need not be configured as "AST," or have "T87A" enabled as a class of service; however, Package 408 must be added in order for Telephony Gateway and Services to work properly.

Configuring the Codec

The Mediation Server supports the G.711 (20 milliseconds) codec. The G.711 codec must be enforced in the network by defining only the G.711 codec on the CS 1000. If G.711 is not the only codec used, calls to voice mail (such as CallPilot) or call conferencing bridges (such as MCS MeetMe) do not work. The only codec supported for the short leg of a call (Mediation Server to Call Server) is G.711 and for the long leg (Mediation Server to Office Communications Server) is RT audio.

Other codecs cannot be configured on the CS 1000, as Office Communicator calls that tandem through the CS 1000 to other endpoints cannot be allowed to select a codec other than G.711.

The codec is configured as described in *IP Peer Networking Installation and Commissioning* (NN43001-313). [Figure 49 "Codec configuration" \(page 160\)](#) demonstrates the correct location of Element Manager in which to configure the codec.

Figure 49
Codec configuration

Nortel CS 1000 ELEMENT MANAGER

Save and Transfer Cancel

IP Telephony Node

VGW and IP phone codec profile

Enable Echo canceller ☒

Echo canceller tail delay 128 (milliseconds)

Voice activity detection threshold -17 (-20 - +10 DBM)

Idle noise level -65 (-327 - +327 DBM)

DTMF Tone detection ☒

Enable Modem/Fax pass through mode ☒

Enable V.21 FAX tone detection ☒

FAX maximum rate 14400 (bps)

FAX playback nominal delay 100 (0 - 300 milliseconds)

FAX no activity timeout 20 (10 - 32000 milliseconds)

FAX packet size 30

Codec G711 Select ☒

Codec Name G711

Voice payload size 20 (ms/frame)

Voice playback (jitter buffer) nominal delay 40

Voice playback (jitter buffer) maximum delay 80

Modifications may cause changes to maximal delay settings

Loss Plan configuration

In order for DTMF digits to be transmitted at the correct volume, especially for Office Communicator 2007 to PSTN communications, the Loss Plan for the CS 1000 must be correctly configured. Calls from Office Communicator 2007 to a residential Voice Mail system (VoIP to PSTN) is an example of the necessity of Loss Plan configuration.

The DTI Data Block (DDB) must also be configured for the Loss and Level Plans to be configured correctly. For information on how to configure the Loss Plan and the DTI Data Block, see *Transmission Parameters* (NN43001-282).

ATTENTION

When any kind of in-band signaling is to be used as payload audio packets (for example, DTMF tones) in the egress direction (IP to TDM), the Signal Limiter functionality must be disabled. If problems are encountered with DTMF tones from Office Communicator contact Nortel support to ensure the Signal Limiter functionality is disabled.

Dialing Plan configuration to route to MCM


In order for calls to be extended using TLSV to the Office Communications Server, a dialing plan entry must be entered on the Call Server to send the call to the SIP trunk. This dialing plan entry does not correspond with any number that is dialable within a network, but rather is used to route the call to the MCM. The MCM service running on the OCS Proxy server handles the incoming call and directs the call to the correct Office Communicator client.

The reason for this is that the SIP Invite generated by TLSV has two fields:

- **To:** this field is used for the sole purpose of routing the invite to MCM.
- **Original Called Number (OCN):** this field is used to determine the original number called. The OCN maps to stored information on the Active Directory and sends the call to the correct Office Communicator client.

For example, the CS 1000network can be configured as shown in [Figure 50 "Dialing plan to route to MCM" \(page 161\)](#).

Figure 50
Dialing plan to route to MCM



In this figure, the CS 1000 has a HLOC of 354 and an LOC dialing plan entry of 344. The LOC dialing plan 344 is not dialable, however, calls to the DN: 6712 extend the call to the number 6-344-5000. By TLSV extending the call to 6-344-5000, a SIP Invite is sent to the OCS Proxy server.

The OCS Proxy server runs MCM, which handles the Invite and reads the Original Called Number as 354-6712. The call is sent to the Mediation server and To and RequestURI are mapped to the Line URI. In this diagram the user is mccarthy@ocs2007a.corp.nortel.com

The purpose of configuring is to ensure that the Office Communicator has the same phone number for both incoming and outgoing calls.

For more information about Dialing Plans, see *IP Peer Networking Installation and Commissioning* (NN43001-313).

Configuring Telephony Services

Telephony Services (TLSV) is used to "twin" incoming calls so users can answer the calls on their desktop phone or Office Communicator 2007.

For incoming calls to be extended to the "twinned" Office Communicator client, a UEXT Terminal Number (TN) must be defined for that DN. A new Universal Extension TN is configured as a Telephony Services client. Telephony Services is defined as the prompt TLSV in response to UXTY. It cannot be changed once it has been set. To change UXTY, remove (OUT) and reconfigure (NEW).

Basic Client Configuration (BCC) can program the new TLSV subtype for UEXT TNs. The TLSV subtype will be the required value for all UEXTs associated with OCS 2007. For more information on BCC, see ["Basic Client Configuration" \(page 64\)](#).

The UEXT TN is configured to send the call to another number. In the case of "twinning" to Office Communicator, the call is sent to a number that is not dialable but routes the invite to the Office Communications Server. For more information, see ["Dialing Plan configuration to route to MCM" \(page 161\)](#).

ATTENTION

If SIP CTI control is also enabled for that telephone, the UEXT TN cannot be MARP 0.

When you use a UEXT, the MARP must be on the DN key of the phone itself, not the UEXT. If the MARP is on the UEXT, CTI clients (such as Office Communicator) do not receive Remote Call Control call pop-ups for incoming calls (in addition to other problems).

Note that MARP is assigned to the first DN key created, so if you create the UEXT first and assign a DN key, it becomes the MARP by default. If you add a phone later with the same DN (to twin the phone with Office Communicator) the MARP stays on the UEXT and you encounter this exact situation. The following is an example of a supported configuration:

Table 32
LD 22

Prompt	Response	Description
REQ	prt	
TYPE	dnb	
CUST	0	
DN	2070	
DATE		
PAGE		
DES		

Screen output

```
DN 2070
TYPE I2002
TN > 096 9 08 15 V t y
KEY 00 MARP DES I2002 i F m > 16 APR 2008
(I2002 )
TN 061 0 00 00 KEY 00 DES I2002 16 APR 2008
(UEXT)
```

Table 33
LD 20

Prompt	Response	Description
REQ	prt	
TYPE	tnb	
TN	096 0 08 15	

Screen output

```
DES OCS
TN 096 0 08 15 VIRTUAL
TYPE UEXT
CDEN 8D
CTYP XDLC
CUST 0
UXTY TLSV
NUID
NHTN
ERL 0
ECL 0
FDN
```

TGAR 1
LDN NO
NCOS 0
SGRP 0
RNPG 0
SCI 0
SSU
XLST
SFLT NO
CAC_MFC 0
CLS CTD FBD WTA LPR MTD FND HTD TDD HFD CRPD
MWD LMPN RMMD SMWD AAD IMD XHD IRD NID OLD VCE DRG1
POD DSX VMD SLKD CCSD SWD LND CNDD
CFTD SFD MRD DDV CNID CDCA MSID DAPA BFED RCB
ICDD CDMD LLCN MCTD CLBD AUTU
GPUD DPUD DNDD CFXD ARHD CLTD ASCD
CPFA CPTA ABDD CFHD FICD NAID DNAA BUZZ
UDI RCC HBTD AHA IPND DDGA NAMA MIND PRSD NRWD NRCD NROD
UDI RCC HBTD AHA IPND DDGA NAMA MIND PRSD NRWD NRCD NROD
DRDD EXR0
USMD USRD ULAD CCB
RTDD RBDD RBHD PGND FLXD FTTC DNDY FDSD
NOVD VOLA VOUD CDMR ICRD MCDD T87D MSNV FRA PKCH
CPND_LANG ENG
HUNT
PLEV 02
DANI NO
AST
IAPG 0
AACS NO
ITNA NO
DGRP
MLWU_LANG 0
MLNG ENG
DNDR 0
KEY 00 SCR 2070 0
ANIE 0
01 HOT P 4 8888
ANIE 0
02
03
04
05
06
07
08
09
10

11
12
13
14
15
16
17 TRN
18 AO6
19 CFW 16
20 RGA
21 PRK
22 RNP
23
24 PRS
25 CHG
26 CPN
27
28
29
30
31
DATE 16 APR 2008

Caller ID table configuration

The Caller ID table is used to correctly build the Caller ID (CLID) for both Private network and Public network calls from a number/extension. The Caller ID table is used by all CS 1000 telephones and is required for Office Communicator calls to work.

In Private network calls where the Uniform Dialing Plan (UDP) is used, the Location Code (LOC) is normally prefixed to the Called and Calling number. Therefore, the Active Directory for all users must include the LOC for their number. A telephone number of ESN 354-6712, has an LOC of 354 and an extension of 6712.

For TLSV twinning to work correctly in a UDP environment, the full Original Called Number (OCN) must be sent by the CS 1000 to the Office Communications Server. To have the full OCN sent, the CLID table must be configured with the Home Location (HLOC) of the CS 1000.

Outgoing Office Communicator calls to the Public network must have the Call ID table used by the associated MARP TN (a TN with the same extension used by Office Communicator marked as MARP) correctly configured. The associated MARP TN must point to a Call ID table that has the International Country Code configured. The International Country Code is the prompt INTL (in North America the value is 1). In North

America the associated MARP TN must point to a Call ID table that also has the Home Exchange configured. The Home Exchange is the prompt HLCL and is the '967' in 1-800-967-2070.

For example, a phone with an extension of 2070, an ESN number of 231-2070, and a Public Number of 967-2070 in North America is configured in the following manner:

Table 34
LD 11

Prompt	Response	Description
REQ	prt	
TYPE	i2002	
TN	061 0 00 00	
DATE		
PAGE		

The following is a portion of the screen output:

```
DNDR 0
KEY 00 SCR 2070 0 MARP
DPND_LANG ROMAN
NAME Chris Smith
```

This user is configured to use the default CLID table entry of 0 (the CLID table number is always next to the extension). The CLID table entry 0 must have the correct HLOC of 354, HLCL of 967, and INTL of 1.

The CLID table entry of 0 with an HLOC of 354 is configured in the following manner:

Table 35
LD 15

Prompt	Response	Description
REQ	chg	
TYPE	net	
TYPE NET_DATA		
CUST	0	
OPT		
AC2		
FNP		
CLID	yes	

Prompt	Response	Description
SIZE	5	
INTL	1	
ENTRY	0	
HNTN		
HLCL	967	
HLOC	354	
...		

The response to SIZE must be a number greater than 0. The response to ENTRY must match the CLID table entry for the target telephones. Generally the default is 0.

Home LOC and Home NPA configuration

In order for the correct Caller Line ID (CLID) to be correctly displayed for Office Communicator calls to the Public network, both the HLOC and HNPA can require configuration. All Office Communicators that are part of an ESN network require HLOC configuration. All Office Communicators that make calls to the Public network in North America require that the Area Code be configured.

For more information on the HLOC and HNPA, see *IP Peer Networking Installation and Commissioning* (NN43001-313).

DNS Server configuration

Host Table configuration is replaced in Release 5.5 with DNS configuration. In Element Manager, under LAN configuration (see [Figure 66 "sip configuration" \(page 192\)](#)), you can enter up to three DNS server IP addresses. The DNS server must be correctly configured with the Fully Qualified Domain Name (FQDN) of all OCS and Enterprise Edition Pools. Also, the FQDN must resolve to the IP address of the OCS for all types of DNS queries (not just for the SIP service type).

DNS server must respond with the correct IP for a generic DNS query. There are a number of different types of DNS queries that can be performed.

ATTENTION

The Signaling Server must be rebooted to ensure that all DNS server configurations take effect.

Figure 51
DNS configuration

Nortel CS 1000 ELEMENT MANAGER

LAN configuration

Embedded LAN (ELAN) configuration

Call server IP address: 47.11.56.7

Unistim Signaling port: 15000

Broadcast port: 15001 (1024 - 65535)

Telephony LAN (TLAN) configuration

Unistim Signaling port: 5000

RTP/RTCP Starting port: 5200 (1024 - 65535)

Embedded LAN (ELAN) Routes Add

Host Table Add

DNS Servers

Primary DNS Server IP address: 47.11.56.51

Alternate DNS Server1 IP address: 0.0.0.0

Alternate DNS Server2 IP address: 0.0.0.0

+SNTP

+Virtual Trunk Network Health Monitor configuration

SIP Trunk configuration

For an Office Communications Server to use a CS 1000 as a SIP Gateway, SIP Trunks must be configured on the CS 1000. The configuration of the SIP Trunk requires that configuration be done on both the Call Server and the Signaling Server. For more information on how to configure SIP trunks, see *IP Peer Networking Installation and Commissioning* (NN43001-313).

A CS 1000 with existing SIP trunks requires a configuration change to be compatible with Office Communications Server. In order for a SIP Trunk to communicate with Office Communications Server, the SIP Transport Protocol must be configured as TCP, not UDP (see [Figure 52 "SIP Gateway configuration window" \(page 169\)](#)). However, this is not valid when SPS in Proxy All mode is used, since everything goes through SPS.

The default Local SIP Port of 5060 is required.

Figure 52
SIP Gateway configuration window

Nortel CS 1000 ELEMENT MANAGER

SIP GW Settings

TLS Security

Security Policy: Security Disabled

TLS Security Port: 5061 (1 - 65535)

Client Authentication: ☐

Re-negotiation: ☐

X.509 Certificate Authentication: ☐

Primary Proxy or Re-direct Server

Primary Proxy or Redirect (TLAN) IP address: 47.11.56.25

Port: 5060

Supports Registration: ☒

Primary CDS Proxy or Re-direct server flag: ☒

Transport Protocol: TCP

Secondary Proxy or Re-direct Server

Secondary Proxy or Redirect (TLAN) IP address: 0.0.0.0

Port: 5060

Supports Registration: ☐

Secondary CDS Proxy or Re-direct server flag: ☐

Transport Protocol: TCP

CLID Parameters

Country Code (CCC): 1

ATTENTION

The Route Data Block (RDB) must have the prompts NCNA and NCRD configured to Yes. Otherwise, calls that are "Twinned" to Office Communicator using TLSV do not work.

ATTENTION

The Route Data Block (RDB) must not have a value configured for the prompt INST. Otherwise, incoming calls from Office Communicator to the CS 1000 do not work.

ATTENTION

When configuring the D Channel used by the SIP Trunk for Converged Office Telephony Gateway and Services, configure the NASA prompt to Yes. Failure to do so can result in limited call transfers through Office Communicator.

The CS 1000 SIP trunk that receives Office Communicator calls must be configured to ESN5, and all associated Virtual trunks must be configured to WNK/WNK. These settings are required so that Office Communicator calls to the Public Network display the correct CLID and have the same Network Class of Service (NCOS) as a call from the associated CS 1000 IP Phone.

The Virtual trunk is WNK/WNK if the output from Element Manager, or a terminal window, is:

```
DES IPTIE
TN 081 0 00 02 VIRTUAL
TYPE IPTI
CDEN 8D
CUST 0
XTRK VTRK
ZONE 000
TRK ANLG
NCOS 0
RTMB 10 3
CHID 3
TGAR 0
STRI/STRO WNK WNK
SUPN YES
AST NO
IAPG 0 *
CLS UNR DIP WTA LPR APN THFD XREP P10 NTC MID
TKID *
AACR NO
```

ATTENTION

All of the SIP Virtual Trunks must be configured to WNK WNK.

The Route Data Block is ESN5 if the output from Element Manager, or a terminal window, is:

```
TYPE RDB
CUST 00
DMOD
ROUT 10
DES IPRROUTE
TKTP TIE
VTRK YES
ZONE 100
PCID SIP
... ANTK
```

SIGO ESN5

STYP SDAT

ATTENTION

If the Route Data Block (RDB) already has associated Virtual Trunks and is configured to SIGO STD, all Virtual Trunks must be removed before the RDB can be changed to ESN5.

Route list data block

The Route List Data Block that is used for Office Communicator SIP trunks must have the prompt DORG configured to No. Otherwise, Office Communicator in dual mode will receive two toasts instead of a merged one. One is with CLID information of the transferring telephone and the other is with CLID information of the original caller. This occurs in some transfer and conference scenarios. The default value for DORG is No.

Changing the value to DORG=YES offers new ISDN CLID enhancements. For more information about this feature, see *New in this Release* (NN43001-115) document.

The Route List Data Block can be checked in LD 86. See [Table 36 "LD 86" \(page 171\)](#).

Table 36
LD 86

Prompt	Response	Description
REQ	PRT	
CUST	00	
FEAT	RLB	
RL1	10	
...		
DORG	NO	
...		


Domain naming

In most configurations where the CS 1000 acts as a SIP Gateway for a Office Communications Server, it is recommended that the SIP Trunk Domain name and the Office Communications Server Domain name be an exact match.

In situations where both the OCS and the CS 1000 have already both been assigned a domain name, and the domain names do not match, there is an alternative. MCM can be configured to register to the NRS using an End_Point_Name@Service_Domain_Name.

The domain is listed under the Domains folder in the Management console for Office Communications Server. For example, in the next figure, the Office Communications Server Domain is ocs2007a-ocsfe1.ocs2007a.corp.nortel.com.

Figure 53
SIP Trunk Domain name



The configuration of the SIP Trunk Domain name describes how to configure the SIP Trunk domain name to match the Office Communications Server domain name.

Configuring the SIP Trunk Domain name

Step	Action
1	Log into the Element Manager page for the Signaling Server.
2	Go to IP Telephony .
3	Click Nodes, Servers, Media Cards .
4	Select Configuration .

- 5 Click **Edit** next to the correct node.
- 6 Open the **Signaling Server Properties** as shown in Figure 54 "siing Server Properties" (page 173).

Figure 54
siing Server Properties

NORTEL CS 1000 ELEMENT MANAGER

Signaling Server 47.11.56.6 Properties [Remove]

Role: **Leader**
Type: **HPDL320G4**

Embedded LAN (ELAN) IP address: 47.11.56.6 *

Embedded LAN (ELAN) MAC address: 00:18:fe:86:49:71 *

Telephony LAN (TLAN) IP address: 47.11.56.23 *

Telephony LAN (TLAN) gateway IP address: 47.11.56.17

Hostname: OCS2007_NODE_A *

H323 ID: OCS2007_NODE_A

Enable Line TPS: ☒

Enable IP Peer Gateway (Virtual Trunk TPS): H.323 and SIP
If Telephony LAN(TLAN) IP address and not in the same subnet as Telephony LAN Peer Gateway is enabled, then the TPS is

Enable SIP Proxy / Redirect Server: ☒

Local SIP TCP/UDP Port to Listen to: 5060

SIP Domain name: ocs2007a.corp.nortel.co

SIP Gateway Endpoint Name: OCS2007_NODE_A

SIP Gateway Authentication Password: ●●●●

Enable Gatekeeper: ☒

Network Routing Service Role: Alternate

- 7 In most cases, the value for the field SIP Domain Name must match the domain of the Office Communications Server. In Figure 54 "siing Server Properties" (page 173), the SIP Domain name is ocs2007a.corp.nortel.com. Only in situations where the MCM is configured to register to the NRS using End_Point_Name@Service_Domain_Name can the two SIP Domain Names not match.

--End--

URI Mapping

The SIP URI Map must be configured in order to correctly register with the NRS. The Private/UDP domain name or Private/CDP domain name is used by MCM to obtain the correct context of the Calling Number.

The SIP URI Map is also configured in Element Manager under Node Configuration.

Figure 55
SIP URI Map

Domain Name	Value
Public E.164/National domain name	+1 *
Public E.164/Subscriber domain name	+613 *
Public E.164/Unknown domain name	PublicUnknown
Public E.164/Special Number domain name	PublicSpecial
Private/UDP domain name	udp
Private/CDP domain name	cdp.udp
Private/Special Number domain name	PrivateSpecial
Private/Unknown (vacant number routing) domain name	PrivateUnknown
Unknown/Unknown domain name	UnknownUnknown

Below the configuration fields are buttons for '+ SIP CD Services', '+ SIP CTI Services', '+ Microsoft Unified Messaging', '+ Cards' (with an 'Add' button), and '- Signaling Servers' (with an 'Add' button).

The SIP URI Map must match the NRS server configuration in the following manner:

- The Private/UDP domain name maps to the L0 Domain on the NRS
- The Private/CDP domain name maps to the L1 Domain on the NRS

MCM must be configured to match one of the domain names.

For example, in a UDP network, the configured domain name is OCS2007_UDP in MCM. Mediation server supports Mediation server routing and Mediation server load balancing. MCM 3.5 manipulates the SIP URI for VoIP and Device URI for RCC to seamlessly integrate with OCS 2007 and the CS 1000. The mapping phone number into SIP URI user id is not required because it is processed internally by the Mediation server. MCM 3.5 should only process "x-nt-ocn-id" header of incoming messages in the same manner as before.

SIP Gateway CLID Parameters configuration

The SIP Gateway CLID parameters are used to adjust the format of telephone numbers for incoming call appearances. For Office Communicator, these settings impact the format of numbers that appear on the incoming call pop-up for Telephony Gateway and Services (the SIP call leg for Office Communicator clients that are twinned with a CS 1000 DN through a TLSV).

Figure 56
SIP GW CLID Parameters

The screenshot shows the 'CS 1000 ELEMENT MANAGER' interface. The 'CLID Parameters' section is highlighted with a red circle. The form includes the following fields and options:

- Port: 5060
- Supports Registration: ☐
- Secondary CDS Proxy or Re-direct server flag: ☐
- Transport Protocol: TCP
- Country Code (CCC): 1
- Area Code (AreaCode):
- # Digits to Strip:
- Prefix to Insert:
- Format of CLID:
 - +<CCC><AreaCode><SN>
 - +<CCC><NN>
 - +<International number>

Note: These settings are independent of the similar SIP CTI CLID parameters to allow independent control of the format of numbers on the incoming call pop-up for telephony gateway and services.

For all public calls (subscriber (for example, NXX in North America), national (for example, NPA in North America), or international) E.164 fully qualified numbers are used to represent the caller. This is made possible through the use of the following parameters:

- Country Code
- Area Code
- Subscriber/Number of Digits to strip
- Subscriber/Prefix to insert
- National/Number of Digits to strip
- National/Prefix to insert

The E.164 format of subscriber calls (for example, NXX in North America) is:

+<countrycode><area code><subscriber number>.

The parameters Subscriber/Number of digits to strip and prefix to insert are used to modify the format of subscriber numbers presented from the PSTN due to region specific requirements.

The E.164 format of national calls (for example, NPA in North America) is:

- +<countrycode><national number>.

The parameters National / Number of digits to strip and prefix to insert are used to modify the format of national numbers presented from the PSTN due to region specific requirements.

Parameter: Country Code

This parameter defines the country code to be used in CLID generation.

Parameter: Area Code

This parameter defines the area code to be used in CLID generation.

Parameter: Subscriber / Number of Digits to strip

For incoming subscriber (NXX) calls this parameter defines the number of digits to strip from the incoming phone number prior to conversion to E.164 format.

Parameter: Subscriber / Prefix to insert

For incoming subscriber (NXX) calls this parameter defines the prefix to insert after stripping any digits necessary from the incoming phone number prior to conversion to E.164 format.

Parameter: National / Number of Digits to strip

For incoming national (NPA) calls this parameter defines the number of digits to strip from the incoming phone number prior to conversion to E.164 format.

Parameter: National / Prefix to insert

For incoming national (NPA) calls this parameter defines the prefix to insert after stripping any digits necessary from the incoming phone number prior to conversion to E.164 format.

SPS configuration

SIP Proxy Server (SPS) is configured through MCM (see [Figure 43 "MCM configuration form" \(page 148\)](#)).

SPS options include:

- **Primary and Secondary IP addresses**
- **Three different modes:** Proxy All, Redirect, and Proxy SIP Gateway Calls
- **Transport:** TLS (5061) and TCP (5060)

NRS configuration

The Server IP running the MCM application (generally an Office Communications Server 2007 Proxy) must be configured on the NRS as a dynamic SIP endpoint, or gateway, and not as a collaboration server.

An Office Communications Server Service Domain must be created for the Signaling Server and MCM. The Signaling Server and MCM register to the Office Communications Server Service Domain on the NRS. The Service Domain between the NRS and the Office Communication Server may or may not match the domain name of the Office Communications Server.

The MCM is configured to register with End_Point_Name@Service_Domain_Name, where the 'Service Domain Name' matches the Service Domain configured on the NRS

Figure 57
Office Communications Server Service Domain

The screenshot shows the Nortel Network Routing Service Manager (NRS) web interface. The top navigation bar includes links for Home, Configuration, Tools, Reports, Administration, and a status indicator for the Active DB view. The left sidebar lists various configuration options: Service Domains, L1 Domains (UDP), L0 Domains (CDP), Gateway Endpoints, User Endpoints, Routing Entries, Default Routes, and Collaborative Servers. The main content area displays the 'Service Domains' configuration page, which includes a table with the following data:

#	ID	Description	# of L1 domains	# of L0 domains	# of gateway endpoints
1	Test	Not available	0	0	0
2	ocs2007a.corp.nortel.com	NRS_SPS	1	1	4

In Figure 57 "Office Communications Server Service Domain" (page 177), the NRS is configured with the matching Service Domain of ocs2007a.corp.nortel.com.

The L1 and L0 Domains must also be configured and match what the CS 1000 is configured under SIP URI Map. Dynamic Gateway endpoints must be configured for the CS 1000 and the MCM with appropriate dialing plan entries.

The NRS must have the same UDP or CDP dialing plan prefix to route calls to the MCM endpoint. This UDP or CDP dialing plan prefix is the same one configured for the TLSV calls.

For example, the Location Code (LOC) 354 from the TLSV example appears as:

```
01 HOT P 8 63545000
```

The NRS must be configured to analyze and qualify numbers dialed from the Office Communications Server (for example, if you configure prefixes to identify the call type, then you might use 6011 for International, 61 for National, and 6 for UDP).

For more information on how to configure the NRS, see *IP Peer Networking Installation and Commissioning* (NN43001-313).

CDR configuration

Call Detail Recording (CDR) is supported for outgoing calls from Office Communicator. Office Communicator CLID is included in the CDR record. From Office Communicator, when a call is made, the Office Communicator CLID (extracted from the Active Directory) is identified.

The following is an example of an outgoing call:

```
N 024 00 A030 001 T012 023 09/12 10:48:23 00:00:02.0  
614165558888&2452070XXXXXXXXXX
```

The dialed number appears at the end (XXXXXXXXXX) and the Office Communicator CLID and the CDR records appear after the ampersand (&); a location code of 245 is followed by 2070 (a location code of 245 followed by 2070). Again, MCM supports redundant NRS configurations.

E.164 International Format Numbers from Office Communicator - Computer Calls (SIP Gateway)

The dialed number sent from Office Communicator to the CS 1000 for SIP GW calls follows the same format as those dialed on the station. As such, there is no distinction within or outside North America for the handling of computer (SIP Gateway) calls.

Calls to International format numbers are handled by the SIP Gateway and arrive with a request URI in the SIP INVITE for the following call:

sip: +CCCCXXXXXXXX@domain; user=phone

In order to support these calls, placed through the SIP Gateway, you must configure the parameters CNTC, NATC, and INTC in LD 15. These parameters ensure that fully qualified numbers within the same country are dialed as national numbers by stripping the country code and adding the national dial prefix.

Example 1 (Outside of North America)

AC1=0, CNTC=31, NATC=0, INTC=00

The URI incoming for the SIP INVITE for the call is:

sip:+31123456789@domain.com;user=phone

The digits sent to the outgoing trunk are: 00123456789

The digits seen on the DCH for the outgoing trunk are: 0123456789

Example 2 (North America)

AC1=8, CNTC=1, NATC=1, INTC=011

The URI incoming for the SIP INVITE for the call is:

sip: +12125551212@domain.com;user=phone

The digits sent to the outgoing trunk are: 812125551212

The digits seen on the DCH for the outgoing trunk are: 12125551212


Phone number normalization

Now that you have completed the installation and configuration of Telephony Gateway and Services, proceed directly to the next step in the process: ["Normalizing phone numbers" \(page 222\)](#).

Direct-SIP configuration

This section describes the process to configure Routes, Dialing Plan and Users. On the SIP Gateway used to communicate directly with a Mediation Server that serves non-converged users, the IP address of that Mediation Server must be specified in the Primary Proxy or Redirect Server field under the SIP Gateway Settings as shown in [Figure 58 "Edit Node Configuration" \(page 180\)](#)

Figure 58
Edit Node Configuration




On the Mediation Server that serves non-converged users and to communicate directly with a SIP Gateway, the node IP address of the SIP Gateway must be specified when configuring the Microsoft Mediation Server, as shown in [Figure 59 "Next Hop Connections" \(page 181\)](#)

ATTENTION


In the SIP-direct networked setup, the IP address of the NRS should be given instead in the same field.

Figure 59
Next Hop Connections




For SIP-direct networked setup, the IP address of the NRS must be specified in the Primary Proxy or Redirect Server field under the SIP Gateway Settings as shown in the figure [Figure 60 "SIP Gateway Settings"](#) (page 181).

Figure 60
SIP Gateway Settings



In NRS, the Mediation Server should be added as a Static Endpoint as shown in the figure below [Figure 61 "Edit Gateway Endpoint"](#) (page 182).

Figure 61
Edit Gateway Endpoint



Dialing Plan Configuration

This dialing plan is a standard tandem SIP/PRI dialing plan. Therefore the number coming from OCS will be in the E.164 format and the number that is sent to OCS must be in the E.164 format.

The dialing plan on PRI to PSTN and incoming call from PSTN is configured as per individual customer requirements.

Remote Call Control configuration

This section describes the process to configure the Remote Call Control with the SIP CTI component.

Office Communications Server, Active Directory and MCM 3.5 must be configured properly prior to configuring the Remote Call Control component.

Remote Call Control and PBX integration

By default users are configured for PC-to-PC communications. Configuring Remote Call Control and PBX integration is done from the User properties in Active Directory and on the Office Communicator client.

Enabling Remote Call Control and PBX integration

Step	Action
1	On the OCS configuration console, go to Users.
2	Choose a user, right-click and select Properties .

- 3 In the properties window, in the **Advanced Options** section, click the **configure** button.
- 4 Choose **Enable Remote call control** to enable clients control of the PBX phone or **Enable Enterprise Voice** and click the **Enable PBX integration** box to enable both Remote Call Control and Enterprise Voice.

--End--


RCC and PBX integration on OC client

After phone integration options are enabled for a user on the server, they are enabled on the OC client.

Step	Action
1	Go to the Office Communicator menu.
2	Choose Tools and then select Options .
3	Go to the Phones tab.
4	Click Enable integration with your phone system box to integrate Communicator to control your desktop phone. See Figure 62 "Enable integration with your phone system" (page 184) .
5	Click on the Advanced button and select Automatic configuration . Click OK .

--End--

Figure 62
Enable integration with your phone system



CS 1000 configuration

Application Module Link (AML) is the main interface used to support call control requests from SIP CTI clients between the SS TR/87 FE application and the CS 1000.

Per-TN configuration is required to define which TNs are used for SIP CTI and to define the specific DN keys on each TN that are available for control by SIP CTI applications.

Configuring the AML

The following tables ("[Configuring the AML](#)" (page 184) and [Table 38 "LD 17: Configure VAS \(Value Added Server\)"](#) (page 185)) display the prompts used for AML link configuration:

Table 37
LD 17: Configure AML Link

Prompt	Response	Description
REQ	CHG	Change existing data.
TYPE	ADAN	A new AML link; the link is an ELAN type. The link number can be from 32 to 47 on a small system and from 32 and 127 on a large system. An AML link number within the above range implies that the transport is over a TCP link.
ADAN	<new ELAN #>	
CTYP	ELAN	
		Card Type: ELAN

To verify that the AML link is up and running, use the STAT ELAN command from LD 48:

```
LD 48
STAT ELAN
ELAN #: 032 DES: CDLCS
APPL_IP_ID: 47 .164 .116 .43 : 0000F600 Lyr7: ACTIVE EMPTY
APPL ACTIVE
```

For more information on the STAT ELAN command, see *Software Input Output Reference — Maintenance* (NN43001-711).

ATTENTION

For redundancy, one AML link is required for each Front End within the node, regardless of whether the Front End is a leader or a follower.

Table 38
LD 17: Configure VAS (Value Added Server)

Prompt	Response	Description
REQ	CHG	Change existing data
TYPE	VAS	Value Added Server
VAS	NEW	VAS ID, ranges from 32 to 47 on a small system and from 32 to 127 on a large system
VSID	<VAS#>	
ELAN	<LINK #>	
SECU	YES	Security For Meridian Link Applications. Enable this for the TR/87 FE application on the Signaling Server to acquire DNS

TLSV ISM

Incremental Software Management (ISM) is a flexible mechanism that allows the telephone provider company to charge for the Telephony Services feature independently of other related available features. The ISM also gives the telephone service provider the flexibility to charge for the Telephony Services units that are configured on the system on per user basis.

A new ISM for the TLSV type of UEXT is available. The TLSV ISM count will be incremented when UXTY prompt is configured as TLSV.

Configuring the SIP CTI TR/87 ISM limit

Incremental Software Management (ISM) (SIP CTI TR/87) is used to define the number of TNs that can be configured with the T87A class of service. The TR/87 configuration for a given TN requires that in addition to the existence of the CLS T87A, the controlled line itself must also be identified as an AST DN. This implies that AST ISMs are also required.

As part of the ordering process, a corresponding AST license is provided for each SIP CTI TR/87 license. This ISM limit is prompted only if package 408 (MS_CONV) is unrestricted (requires level 2 packages).

The SIP CTI TR87 ISM is an instant ISM and does not require a cold start of the Call Server to take effect (see [Figure 63 "ISM Limit printout" \(page 186\)](#))

Table 39
LD 22

Prompt	Response	Description
REQ	prt	
TYPE	slt	

Figure 63
ISM Limit printout

TYPE	slt	Print System Limits			
<...>					
PCA	32767	LEFT 32767	USED	0	
ITG ISDN TRUNKS	32767	LEFT 32767	USED	0	
H.323 ACCESS PORTS	32767	LEFT 32767	USED	0	
AST	32767	LEFT 32767	USED	0	
SIPCONVERGED DESKTOPS	32767	LEFT 32767	USED	0	
SIP CTI TR_87	32767	LEFT 32767	USED	11	
RAN CON	32767	LEFT 32767	USED	0	
MUS CON	32767	LEFT 32767	USED	0	
SURVIVABILITY	0	LEFT 0	USED	0	
<...>					

Configuring a station

SIP CTI control of a DN key can be supported on IP, digital, and analog stations.

ATTENTION

Features such as Make Call and Answer Call depend on the hands-free capability of the station and the on-hook default path configuration on the station. Therefore the use of certain features on stations without hands-free support is limited.

A new CLS (T87A) is introduced to allow a TN to support the SIP CTI application.

The AST prompt is used to configure which DN key on the TN is controlled or monitored by the SIP CTI application. A maximum of two keys per TN can be configured as AST keys.

CLID information is sent, or suppressed, to Office Communicator based on the CLS CNDA/CNDD consistent with the presentation of the CLID information on the station display itself.

This affects whether CLID information (that can be available for calls that do not map to Active Directory users) appears on the Office Communicator call toast (for example, PSTN calls).

Considering MADN (Multiple Appearance DN)

When you configure a station, you must consider certain issues if Office Communicator is used in a MADN environment:

- When multiple TNs exist in a MADN group, the T87A CLS and AST configuration are configured only on the MARP TN
- When "twinning" a station with Office Communicator using a TLSV, the MARP TN within the MADN group must be on a station and not on the TLSV. For more information, see [Table 40 "LD 11–Twinning a station" \(page 187\)](#).

Table 40
LD 11–Twinning a station

Prompt	Response	Description
REQ	prt	
TYPE	dnb	
CUST	0	
dn	2070	

Screen Output

```
DN 2070
CPND
XPLN 15
DISPLAY_FMT FIRST, LAST
TYPE SL1
TN 100 0 03 04 V KEY 00 MARP DES DLOCS2 3 DEC 2007 (2004P2)
TN 100 0 03 05 V KEY 00 DES OCS 16 APR 2008 (UEXT)
NACT
```

- Any Remote Call Control service request sent by Office Communicator, such as Make Call or Answer Call, always apply to the device defined as the MARP TN.
- For SCR keys telephony, presence updates (for example, on the phone) are supported for all TNs within a MADN group
Example: Answering a call on a wireless station SCR key on a non-MARP TN shows the Office Communications Server user as "On the Phone".
- Incoming calls to Multiple Appearance Directory Numbers (MADNs) in the MSB mode are still signified by the indicator next to the Directory Number (DN) key, and can be answered even while MSB is active. Calls to any Single Appearance Directory Number on the telephone receive a busy indication.
- For MCR keys telephony, presence is supported only for the MARP TN within a MADN group.
Example: Answering a call on a wireless station MCR key on a non-MARP TN does not show the Office Communications Server user as "On the Phone". Only calls answered on the MARP TN affect the presence status of that user.

NRS configuration

Using NRS is optional. If NRS is used, MCM and TR/87 FE must be configured on the NRS as the Gateway Endpoints.

The corresponding Routing Entries must be defined to support SIP gateway calls.

Signaling Server configuration

The TR/87 FE application shares the TPS master/follower mechanism to provide redundancy within a node. The TR/87 FE application shares one instance of the SIP stack with the SIP GW and correspondingly uses some of the existing SIP GW configuration parameters:

- SIP Transport Protocol, Local SIP Port, SIP Domain Name
- The SIP URI map

The IP address and domain name of any Office Communications Server proxy responsible for forwarding TR/87 traffic to the Signaling Server must be added to the Signaling Server Host Table in Element Manager. Configure SIP CTI-specific parameters in Element Manager.

ATTENTION

When the SIP CTI service is enabled and any dependent configuration parameter is modified in Element Manager, all active SIP CTI sessions are terminated so the configuration data can be updated.

Node parameter configuration

The node IP is the IP address of the TR/87 FE:

- You can configure multiple nodes to support TR/87 applications for additional capacity. The Remote Call Control SIP URI of users determines which node they use.
- An AML restriction dictates that only one application can acquire a given DN on a Call Server.

ATTENTION

When you add additional nodes to balance TR/87 load, SIP routing must be configured so that all clients that attempt to control a DN terminate on the same node.

The TR/87 FE application can run within a TPS node as well as a non-TPS node as shown in [Figure 64 "TR/87 Node configuration" \(page 190\)](#).

Figure 64
TR/87 Node configuration

NORTEL CS 1000 ELEMENT MANAGER

Navigation Tree:

- Home
- Links
 - Virtual Terminals
 - Bookmarks
- System
 - + Alarms
 - Maintenance
 - + Core Equipment
 - Peripheral Equipment
 - IP Network
 - [Nodes: Servers, Media Cards](#)
 - Maintenance and Reports
 - Media Gateways
 - Zones
 - Host and Route Tables
 - Network Address Translation
 - QoS Thresholds
 - Personal Directories
 - + Interfaces
 - Engineered Values
 - + Emergency Services
 - Geographic Redundancy
 - Database Replication Control
 - State Control
 - Software
 - File Upload
 - IP Phone Firmware
 - Voice Gateway Media Card
 - Servers, Media Cards PEPs
- Customers
 - Routes and Trunks
 - Routes and Trunks
 - D-Channels
 - Digital Trunk Interface
 - Dialing and Numbering Plans
 - Electronic Switched Network
 - Network Routing Service
 - Flexible Code Restriction
 - Incoming Digit Translation

Configuration Fields:

- + SIP CD Services
- + SIP CTI Services
- + Microsoft Unified Messaging
- + Cards
- Signaling Servers
- [Signaling Server 47.11.56.69 Properties](#)

Role: Leader
Type: IBMX306M

Embedded LAN (ELAN) IP address: 47.11.56.69 *

Embedded LAN (ELAN) MAC address: 00:14:5e:83:93:24 *

Telephony LAN (TLAN) IP address: 47.11.56.87 *

Telephony LAN (TLAN) gateway IP address: 47.11.56.81

Hostname: OCS2007NODEB *

H323 ID: OCS2007NODEB

Enable Line TPS: ☒ (highlighted with a red circle)

Enable IP Peer Gateway (Virtual Trunk TPS): H.323 and SIP ▼

If Telephony LAN(TLAN) IP address and Telephony LAN(TLAN) Gateway is enabled, then the TPS and/or VTF

Enable SIP Proxy / Redirect Server: ☒

Local SIP TCP/UDP Port to Listen to: 5060

SIP Domain name: ocs2007a.corp.nortel.co

SIP Gateway Endpoint Name: OCS2007NODEB

SIP Gateway parameter configuration

The SIP Gateway application must be enabled. To enable the SIP Gateway, TR/87 FE uses the following SIP Gateway configuration parameters (see [Figure 65 "SIP Gateway configuration" \(page 191\)](#)):

- SIP Transport Protocol (must be TCP for Office Communications Server 2007 deployments)
- Local SIP Port (default 5060)
- SIP Domain Name

Figure 65
SIP Gateway configuration

NORTEL CS 1000 ELEMENT MANAGER

- Home
- Links
 - Virtual Terminals
 - Bookmarks
- System
 - + Alarms
 - Maintenance
 - + Core Equipment
 - Peripheral Equipment
 - IP Network
 - **Nodes: Servers, Media Cards**
 - Maintenance and Reports
 - Media Gateways
 - Zones
 - Host and Route Tables
 - Network Address Translation
 - QoS Thresholds
 - Personal Directories
 - + Interfaces
 - Engineered Values
 - + Emergency Services
 - Geographic Redundancy
 - Database Replication Control
 - State Control
 - Software
 - File Upload
 - IP Phone Firmware
 - Voice Gateway Media Card
 - Servers, Media Cards PEPs
- Customers
 - Routes and Trunks
 - Routes and Trunks
 - D-Channels
 - Digital Trunk Interface
 - Dialing and Numbering Plans
 - Electronic Switched Network
 - Network Routing Service
 - Flexible Code Restriction
 - Incoming Digit Translation
- Tools
 - + Backup and Restore
 - Call Server Initialization

+ SIP CTI Services

+ Microsoft Unified Messaging

+ Cards

- Signaling Servers

+ Signaling Server 47.11.56.69 Properties

Signaling Server 47.11.56.74 Properties

Role Unknown
Type UnknownSS

Embedded LAN (ELAN) IP address 47.11.56.74 *

Embedded LAN (ELAN) MAC address 00:19:bb:25:9b:7b *

Telephony LAN (TLAN) IP address 47.11.56.89 *

Telephony LAN (TLAN) gateway IP address 47.11.56.81

Hostname NODEB_NRS *

H323 ID NODEB_NRS

Enable Line TPS ☒

Enable IP Peer Gateway (Virtual Trunk TPS) SIP only

If Telephony LAN(TLAN) IP address and Telephony LAN(TLAN) gateway IP address are in the same subnet as Telephony LAN(TLAN) Node IP address when Gateway is enabled, then the TPS and/or VTRK applications will not work.

Local SIP TCP/UDP Port to Listen to 5060

SIP Domain name ocs2007a.corp.nortel.co

SIP Gateway Endpoint Name NODEB_NRS

SIP Gateway Authentication Password

DNS Server configuration

Host Table configuration is replaced in Release 5.5 with DNS configuration. The DNS server must be correctly configured with the Fully Qualified Domain Name (FQDN) of all OCS servers and Enterprise Edition Pools. Also, the FQDN must resolve to the IP address of the OCS server for all types of DNS queries (not just for the SIP service type). (see [Figure 66 "sip configuration"](#) (page 192))

DNS server must respond with the correct IP for a generic DNS query. There are a number of different types of DNS queries that can be performed.

Step	Action
1	Log on to Element Manager and navigate to LAN configuration.

2 Enter the FQDN of up to three DNS servers.

--End--

Figure 66
sip ctiuration

NORTEL CS 1000 ELEMENT MANAGER

LAN configuration

Embedded LAN (ELAN) configuration

Call server IP address: 47.11.56.66

Unistern Signaling port: 15000

Broadcast port: 15001 (1024 - 65535)

Telephony LAN (TLAN) configuration

Unistern Signaling port: 5000

RTP/RTCP Starting port: 5200 (1024 - 65535)

Embedded LAN (ELAN) Routes Add

Host Table Add

DNS Servers

Primary DNS Server IP address: 47.11.56.114

Alternate DNS Server 1 IP address: 0.0.0.0

Alternate DNS Server 2 IP address: 0.0.0.0

+ SNTP

+ Virtual Trunk Network Health Monitor configuration

+ H323 GW Settings

+ Firmware

+ SIP GW Settings

+ SIP URI Map

+ SIP CD Services

SIP CTI Services configuration settings

In Element Manager, under SIP CTI services, the Calling Device URI Format must be configured as **phone-context=<SIP URI Map Entries>** to support OCS 2007 RCC. Ensure the **Dial Plan prefix** section values under SIP CTI Services are configured. Click **Save and Transfer** the configuration and then reboot the Signaling Server.

For each of the SIP CTI settings, if a configuration change is made and a save and transfer is performed, all active SIP CTI sessions are terminated to apply the change. Office Communicator automatically reestablishes the session without user intervention.

There is a limitation where you cannot configure SIP CTI for two or more customers on a single node.

See Figure 67 "SIP CTI Services settings" (page 193) for the settings in Element Manager.

Figure 67
SIP CTI Services settings

NORTEL CS 1000 ELEMENT MANAGER

- SIP CTI Services

Service Enabled ☒

Support TLS Endpoints Only ☐

CTI Settings

Customer Number (0 - 99)

Maximum Associations per DN

Place International Calls Within This Country As National Calls ☒

Dial Plan Prefix

National Prefix

International Prefix

Location Code Call Prefix

Special Number Prefix

Subscriber Prefix

CLID Parameters

Dialing Plan

Calling Device URI Format

Home Location Code

Country Code (CCC)

Area Code (AreaCode) Note: The NPA in North America

#Digits to Strip Prefix to Insert Format of CLID

Parameter: Service Enabled

The default state of the SIP CTI service is disabled. To enforce the change of state for this parameter, you must reboot. The SIP CTI service consumes approximately 140 MB of RAM on the Signaling Server when enabled.

ATTENTION

The configuration change to enable or disable the SIP CTI service is propagated to all Signaling Servers within the node. Ensure that engineering guidelines are considered for all Signaling Servers within the node before you enable this feature.

Parameter: Customer Number

The customer number parameter defines the customer on the Call Server to which SIP CTI service requests apply. Each TR/87 FE can support one customer number. Additional customers can be supported by adding additional Signaling Servers.

Parameter: Maximum Associations Per DN

This parameter defines the maximum number of simultaneous TR/87 SIP dialogs that can be active for a single DN. Multiple instances of Office Communicator (for example, home, office, laptop) are active and each of them can have its own active TR/87 session. This parameter limits the number of simultaneous client sessions for a single DN.

Parameter: International Calls As National

This parameter is used in combination with the following parameters:

- SIP CTI Dial Plan Prefix - National Prefix
- SIP CTI Dial Plan Prefix - International Prefix
- SIP CTI CLID Parameters - Country Code

When enabled this feature monitors all SIP CTI calls made using the E.164 international number format. For E.164 called numbers that are within the local country the SIP CTI national dial prefix is used to originate the call from the Call Server. For E.164 called numbers that are outside the local country the international dial prefix is used to originate the call from the Call Server.

When this feature is disabled all SIP CTI calls made using the E.164 number format uses the international dial prefix when originating the call from the Call Server.

Two scenarios are provided using the following example parameters:

- SIP CTI Settings - International Calls As National = Enabled
- SIP CTI Dial Plan Prefix - National Prefix = 61
- SIP CTI Dial Plan Prefix - International Prefix = 6011
- SIP CTI CLID Parameters - Country Code - 1
- AC1 = 6

Scenario 1 A call is placed from Office Communicator to +14167008000. The TR/87 Front End application on the Signaling Server uses the above SIP CTI settings to determine that the E.164 destination is within the local country. The call originates through AML from the Call Server using the national dial string 614167008000.

Scenario 2 A call is placed from Office Communicator to +31123456789. The TR/87 Front End application on the Signaling Server uses the following SIP CTI settings to determine that the E.164 destination is not within the local country. The call originates through AML from the Call Server using the international dial string 601131123456789.

SIP CTI Dial Plan prefixes

The SIP CTI dial plan prefixes configuration settings are used to prefix phone numbers sent to the Call Server as a result of SIP CTI call attempts.

Parameter: National Prefix When calls are made to E.164 fully qualified numbers this parameter is used in combination with the “International Calls as National” setting in the CTI IP settings section. When a call to an E.164 destination contains the same country code as the local country the call is placed from the Call Server as a national call using this prefix rather than the international call prefix.

This parameter is also used to prefix calls that are made with a URI that contains a phone-context equal to the Public E.164/National domain in the SIP URI map.

Refer to the section [“Parameter: International Calls As National” \(page 194\)](#) for an example of the use of this parameter.

Parameter: International Prefix When calls are made to E.164 fully qualified numbers this parameter is used in combination with the “International Calls as National” setting in the CTI settings section. If the “International Calls as National” feature is disabled, all calls to any E.164 number are prefixed with this prefix. If the “International Calls as National” feature is enabled, only calls to E.164 destinations outside of the local country are dialed with this prefix.

Refer to the section [“Parameter: International Calls As National” \(page 194\)](#) for an example of the use of this parameter.

Parameter: Location Code Call Prefix This parameter is used to prefix calls that are made with IRAs with a phone-context equal to the Private/UDP domain in the SIP URI map.

This parameter is also used in conjunction with the Calling Device URI Format setting. Refer to the section [“Parameter: Calling Device URI Format” \(page 197\)](#) for an example of the use of this parameter.

Parameter: Special Number Prefix This parameter is used to prefix calls that are made with a URI that contains a phone-context equal to the Public/E.164 Special Number domain in the SIP URI map.

Parameter: Subscriber Prefix This parameter is used to prefix calls that are made with a URI that contains a phone-context equal to the Public E.164/Subscriber domain in the SIP URI map.

SIP CTI CLID configuration parameters

The SIP CTI CLID parameters are used to adjust the format of phone numbers for incoming call appearances. For Office Communicator these settings impact the format of numbers that appear on the incoming call pop-up for Remote Call Control.

ATTENTION

These settings are independent of the similar SIP GW CLID parameters to allow independent control of the format of numbers on the incoming call pop-up for Remote Call Control.

For all public calls (subscriber (for example, NXX in North America), national (for example, NPA in North America), or international) E.164 fully qualified numbers are used to represent the caller. This is made possible through the use of the following parameters:

- Country Code
- Area Code
- Subscriber/Number of Digits to strip
- Subscriber/Prefix to insert
- National/Number of Digits to strip
- National/Prefix to insert

The E.164 format of subscriber calls (NXX) is:

+<countrycode><area code><subscriber number>.

The parameters Subscriber/Number of digits to strip and prefix to insert are used to modify the format of subscriber numbers presented from the PSTN due to region specific requirements.

The E.164 format of national calls (NPA) is:

+<countrycode><national number>.

The parameters National/Number of digits to strip and prefix to insert are used to modify the format of national numbers presented from the PSTN due to region specific requirements.

Parameter: Dialing Plan

When configured to CDP, no changes are made to CDP numbers from the Call Server. However, when configured to UDP, the location code prefix and location code are added as a prefix to CDP numbers to aid in normalization. When this setting is enabled all user phone numbers in the active directory can be entered using the home location code to ensure a consistent unique format throughout the enterprise. Two scenarios are provided using the following example parameters:

- SIP CTI Dial Plan Prefix - Location Code Call Prefix = 6
- SIP CTI CLID Parameters - Home Location Code = 343

Scenario 1 - SIP STI Dial Plan = CDP

A call is placed to the DN controlled by Office Communicator for RCC from DN 3000 on the same Call Server. The call pop-up that appears on the users desktop shows call from 3000.

Scenario 2 - SIP CTI Dial Plan = UDP

A call is placed to the DN controlled by Office Communicator for RCC from DN 5000 on the same Call Server. The call pop-up that appears on the users desktop shows call from 634353000.

Parameter: Calling Device URI Format

This configuration setting defines the phone-context=<SIP URI Map Entries>.

ATTENTION

For Office Communications Server installations, phone-context=<SIP URI Map Entries> must be used to ensure compatibility with Office Communicator.

The combination of the URIs generated by the TR/87 FE and the normalization rules available to Office Communicator 2007 define the ability for Office Communicator to match incoming phone numbers to Office Communications Server user identities (for example, on the incoming call pop-up window).

The CSTA-delivered event contains a parameter called callingDevice that notifies the Office Communicator when a call is presented to the Remote Call Control controlled line. This field contains a TEL URI that is generated based on the combination of the SIP CTI dialing plan and Calling Device URI format parameters. Four scenarios are provided where a call is placed to the DN controlled by Office Communicator for RCC from DN 5000 using the following example parameters:

- SIP CTI Dial Plan Prefix - Location Code Call Prefix = 6
- SIP CTI CLID Parameters - Home Location Code = 343

**Scenario 1, Dial Plan = UDP, Calling Device URI Format =
phone-context= SIP GW URI map entries:**

The TEL URI generated for the caller is:

"tel:3435000;phone-context=udp.nortel.com"

**Scenario 2, Dial Plan = CDP, Calling Device URI Format =
phone-context= SIP GW URI map entries:**

The TEL URI generated for the caller is:

"tel:3000;phone-context=cdp.nortel.com"

Parameter: Home Location Code

This parameter defines the home location code to be used in CLID generation in combination with the SIP CTI dial plan setting.

See section "Parameter: Dial Plan" for an example of the use of this parameter.

Parameter: Country Code

This parameter defines the country code to be used in CLID generation.

Parameter: Area Code

This parameter defines the area code to be used in CLID generation.

Parameter: Subscriber/Number of Digits to strip

For incoming subscriber (for example, NXX in North America) calls this parameter defines the number of digits to strip from the incoming phone number prior to conversion to E.164 format.

Parameter: Subscriber/Prefix to insert

For incoming subscriber (for example, NXX in North America) calls this parameter defines the prefix to insert after stripping any digits necessary from the incoming phone number prior to conversion to E.164 format.

Parameter: National/Number of Digits to strip

For incoming national (for example, NPA in North America) calls this parameter defines the number of digits to strip from the incoming phone number prior to conversion to E.164 format.

Parameter: National/Prefix to insert

For incoming national (for example, NPA in North America) calls this parameter defines the prefix to insert after stripping any digits necessary from the incoming phone number prior to conversion to E.164 format.

North American SIP CTI configuration example

With the configuration defined as in [Figure 68 "North American CLID manipulation"](#) (page 199), the following occurs:

- An incoming Subscriber Call with phone number 4005000 produces tel:+16134005000 on the Office Communicator incoming call pop-up.
- An incoming National Call with phone number 4169008000 produces tel:+14169008000 on the Office Communicator incoming call pop-up.
- An RCC call from Office Communicator to the E.164 number +16135006000 produces a call from the controlled DN to 616135006000.

An RCC call from Office Communicator to the E.164 number +3312345678 9 produces a call from the controlled DN to 601133123456789.

Figure 68
North American CLID manipulation

The screenshot shows the 'CS 1000 ELEMENT MANAGER' configuration window. The 'SIP CTI Services' section is expanded, showing various settings. The 'CTI Settings' section includes 'Service Enabled' (checked), 'Support TLS Endpoints Only' (unchecked), 'Customer Number' (0), 'Maximum Associations per DN' (10), and 'Place International Calls Within This Country As National Calls' (checked). The 'Dial Plan Prefix' section includes 'National Prefix' (61), 'International Prefix' (6011), 'Location Code Call Prefix' (6), 'Special Number Prefix' (6), and 'Subscriber Prefix' (9). The 'CLID Parameters' section includes 'Dialing Plan' (CDP), 'Calling Device URI Format' (phone-context=<SIP URI Map Entries>), 'Home Location Code' (343), 'Country Code (CCC)' (1), 'Area Code (AreaCode)' (613), and '#Digits to Strip' (0). The 'Format of CLID' section includes 'Prefix to Insert' and 'Format of CLID' (Note: The NPA in North America). The 'Subscriber Number (SN)' is 0, and the 'National Number (NN)' is 0.

Section	Parameter	Value	Notes
SIP CTI Services	Service Enabled	☒	
	Support TLS Endpoints Only	☐	
	Customer Number	0	(0 - 99)
	Maximum Associations per DN	10	
	Place International Calls Within This Country As National Calls	☒	
Dial Plan Prefix	National Prefix	61	
	International Prefix	6011	
	Location Code Call Prefix	6	
	Special Number Prefix	6	
	Subscriber Prefix	9	
CLID Parameters	Dialing Plan	CDP	
	Calling Device URI Format	phone-context=<SIP URI Map Entries>	
	Home Location Code	343	
	Country Code (CCC)	1	
	Area Code (AreaCode)	613	Note: The NPA in North America
	#Digits to Strip	0	
	Prefix to Insert		
Format of CLID	Subscriber Number (SN)	0	+<CCC><AreaCode><SN>
	National Number (NN)	0	+<CCC><NN>

Non-North American SIP CTI configuration example

With the configuration defined as in [Figure 69 "Non-North American CLID Manipulation"](#) (page 200) the following occurs:

- An incoming Subscriber Call with phone number 4005000 produces +311234005000 on the Office Communicator incoming call pop-up.
- An incoming National Call with phone number 00123456789 produces +31123456789 on the Office Communicator incoming call pop-up.
- An RCC call from Office Communicator to the E.164 number +31123456789 produces a call from the controlled DN to 00123456789.
- An RCC call from Office Communicator to the E.164 number +33123456789 produces a call from the controlled DN to 00033123456789.

Figure 69
Non-North American CLID Manipulation

CS 1000 ELEMENT MANAGER Help

- SIP CTI Services

Service Enabled ☒

Support TLS Endpoints Only ☐

CTI Settings

Customer Number (0 - 99)

Maximum Associations per DN

Place International Calls Within This Country As National Calls ☒

Dial Plan Prefix

National Prefix

International Prefix

Location Code Call Prefix

Special Number Prefix

Subscriber Prefix

CLID Parameters

Dialing Plan

Calling Device URI Format

Home Location Code

Country Code (CCC)

Area Code (AreaCode) Note: The NPA in North America

#Digits to Strip

Prefix to Insert

Format of CLID

Subscriber Number (SN)

National Number (NN)

Configuring the SIP URI Map

The existing SIP URI map (see [Figure 70 "SIP URI Map" \(page 201\)](#)) configured for SIP GW application is also used by the TR/87 FE application to parse incoming URIs within SIP CTI service requests.

Figure 70
SIP URI Map

CS 1000 ELEMENT MANAGER	
+ SIP GW Settings	
SIP URI Map	
Public E.164/National domain name	+1
Public E.164/Subscriber domain name	+613
Public E.164/Unknown domain name	PublicUnknown
Public E.164/Special Number domain name	PublicSpecial
Private/UDP domain name	udp
Private/CDP domain name	cdp.udp
Private/Special Number domain name	PrivateSpecial
Private/Unknown (vacant number routing) domain name	PrivateUnknown
Unknown/Unknown domain name	UnknownUnknown
+ SIP CD Services	

Configuring CDR

Call Detail Recording (CDR) records are produced for calls controlled using the Remote Call Control feature. The format of these CDR records is the same as those of calls dialed directly from a telephone's keypad.

Dialing E.164 International Format Numbers from Office Communicator - Phone Calls (SIP CTI)

When a call is originated from Office Communicator to an E.164 number (such as +14163005000) through Remote Call Control, the make call service request arrives at the TR/87 FE within a SIP INFO message as per the TR/87 specification. See [Figure 71 "SIP INFO message" \(page 202\)](#).

Figure 71
SIP INFO message

```
<?xml version="1.0" encoding="UTF-8"?><DeliveredEvent
xmlns="http://www.ecma-international.org/standards/ecma-323/csta/ed3">
<monitorCrossRefID>37</monitorCrossRefID>

<connection>
  <callID>19806</callID>
  <deviceID>tel:+16139675000;ext=3050</deviceID>
</connection>

<alertingDevice>
  <deviceIdentifier>tel:+16139675000;ext=3050</deviceIdentifier>
</alertingDevice>

<callingDevice>
  <deviceIdentifier>tel:+16139675000;ext=2014</deviceIdentifier>
</callingDevice>

<calledDevice>
  <deviceIdentifier>tel:+16139675000;ext=3050</deviceIdentifier>
</calledDevice>

<lastRedirectionDevice>
  <notRequired />
</lastRedirectionDevice>

<localConnectionInfo>alerting</localConnectionInfo>

<cause>normal</cause>

</DeliveredEvent>
01/21/2008|15:02:18.898 1E498:1E494 INFO :: End of Data Received -
47.11.56.51:5061 (To Local Address: 47.11.56.165:2968) 2113 bytes
```

The TR/87 FE that resides on the Signaling Server contains a feature to insert the appropriate dial plan prefix, either national or international, depending on the location of the Call Server and destination of the call. This ensures calls within the country use the national dial format and calls outside the country use the international dial format. This feature is enabled or disabled in Element Manager in the SIP CTI Settings section. When “All International Calls As National” is enabled, any calls within the local country have the country code stripped from the E.164 number and the national dial prefix applied. The format of the number presented by the TR/87 FE to the Call Server through AML in this scenario is:

<SIP CTI national prefix><national subscriber number>.

Any calls outside the country have only the international dial prefix applied to the E.164 phone number. The format of the number presented by the TR/ 87 FE to the Call Server through AML in this scenario is:

<SIP CTI international prefix><international number>.

When “All International Calls As National” is disabled, all calls to any E.164 destination use the international dial format. See section [“Parameter: International Calls As National” \(page 194\)](#) for additional detail on the configuration of this feature and an illustrative example.

Transport Layer Security (TLS) configuration between OCS Proxy/MCM and CS1000

Interactions and requirements

The following provides information on product interactions and requirements.

End-to-end security

End-to-end security is not supported for Converged Office solution and CS 1000 node configuration.

Issue To (subject) parameter

The Issued To (subject) parameter must be a Fully Qualified Domain Name (FQDN) for all certificates used by Converged Office solutions. For example, Office Communications Server, SPS, SIP Gateway).

Security options

The Security Option "System cryptography: Use FIPS compliant algorithms for encryption, hashing and signing" must be enabled on the Office Communications Server that talks to the CS 1000 using TLS. This option is automatically enabled by MCM if TLS transport is configured. Enabling this option affects other system components (Terminal Services, Encrypting File System Service). For example, Remote Desktop Client cannot connect to the server from a Windows 2000 PC because it does not support FIPS. New Remote Desktop Client must be installed on the Windows XP PC (Windows 2003 Server %SystemRoot%\System32\Clients\tsclient).

Local host IP Address

Local host IP Address 127.0.0.1 must be authorized on the Office Communications Server that talks to the CS 1000 using TLS. Authorization is performed by MCM automatically if TLS transport is configured.

DNS server

The DNS server used by Office Communications Server must resolve the SPS FQDN to its IP address and vice versa.

Private Certificate Authority (Nortel ECM)

Certificates signed by the Private CA (Nortel ECM) cannot be used on the Office Communications Server. For example, certificates for OCS servers must be issued by either Microsoft CA or another external CA. For more information about Microsoft security and the Microsoft Office Communications Server Security Guide on the Microsoft Web site, go to www.microsoft.com.

OCS certificate

Certificates used by OCS for TLS connection has to meet the following requirements:

- Enhanced Key Usage (EKU): Server Authentication (1.3.6.1.5.5.7.3.1), Client Authentication (1.3.6.1.5.5.7.3.2)
- Key Usage (KU): Digital Signature, Key Encipherment, Data Encipherment (b0)

For more information about configuring the OCS certificate and how to configure a certificate that is compliant with the above requirements, see [“Configuring OCS certificate” \(page 216\)](#).

Using the OCS certificate wizard to request a certificate for the OCS Application Proxy (where MCM runs) is not supported if the Microsoft Enterprise CA is used. Microsoft Enterprise CA running Microsoft Windows Server 2003 in Standard or Web Edition are not supported.

Example TLS configuration

- A Office Communications Server Application Proxy running MCM with:
 - IP Address – 192.168.72.15
 - FQDN – ocs2007serv5s.OCS2007
- A SIP Proxy Server (SPS):
 - IP Address – 192.168.75.100
 - FQDN – ocs-sps.ocs2007
- Office Communications Server uses certificates issued by the Microsoft Certification Authority. CS 1000 components use the Private CA (Nortel ECM) signed certificates.

Configuring TLS for Converged Office

The following section describes the TLS configuration procedures for Converged Office.

ATTENTION


The network addresses used in the example figures in this section are different than the examples used throughout this document.

Step	Action

- 1 Configure the DNS server used by Office Communications Server to resolve SPS FQDN to its IP Address and vice versa. See [Figure 72 "nslookup" \(page 205\)](#).


Note: If SPS is used by MCM in a Redirect mode (Redirect All, Proxy SIP, and Redirect SIP-CTI) then FQDNs of all SIP Gateways with TLS enabled must be resolved to IP Addresses by DNS and vice versa.

Figure 72
nslookup




- 2 Add Private CA certificate to the Trusted Root Certification Authorities. Copy and Save Private CA certificate to a file on the OCS server. See [Figure 73 "Private Certificate Authority" \(page 206\)](#).

Figure 73
Private Certificate Authority




- 3** Open MMC on the Office Communication Server and add the Certificates (local computer) snap-in, See [Figure 74 "Certificate snap-in"](#) (page 207).

Figure 74
Certificate snap-in




- 4 Import the saved file to the Trusted Root Certification Authorities. See [Figure 75 "Import to Trusted Certificate Authorities"](#) (page 208).

Figure 75
Import to Trusted Certificate Authorities




- 5 Enable incoming TLS connections on the Office Communications Server. See [Figure 76 "Enable incoming TLS connections" \(page 208\)](#).

Figure 76
Enable incoming TLS connections




- 6 Configure the default certificate used for TLS connections by the Office Communications Server. See [Figure 77 "Configure default certificate" \(page 209\)](#).

Figure 77
Configure default certificate



- 7 Add SPS FQDN to the Host Authorization table on the Office Communication Server. See [Figure 78 "Add SPS FQDN" \(page 210\)](#).


Figure 78
Add SPS FQDN



Note: If SPS is used by MCM in a Redirect mode (Redirect All, Proxy SIP, and Redirect SIP-CTI) the FQDNs of all SIP Gateways with TLS enabled must be added to the table.

- 8 Add Microsoft CA certificate to the Trusted Certificate Authorities on SPS. See [Figure 79 "Add Microsoft CA Certificate" \(page 211\)](#). Download Microsoft CA certificate and save it to file on the Office Communications Server in Base-64 encoding.

Figure 79
Add Microsoft CA Certificate



- 9 Open the saved file in Notepad and copy its content to the clipboard. Add the copied content to the Trusted Certificate Authorities. See [Figure 80 "Add a CA to the Service"](#) (page 212).

Figure 80
Add a CA to the Service





Figure 81 "Certificate Endpoints" (page 213) shows the newly added Certificate Authority.

Figure 81
Certificate Endpoints




10 Configure TLS transport on the MCM. See [Figure 82 "TLS Transport configuration"](#) (page 214).

Figure 82
TLS Transport configuration

- 11** Check that MCM is registered with SPS. See [Figure 83 "MCM status"](#) (page 215).

Figure 83
MCM status



If the SPS status is not responding, it may take up to five minutes until all the Office Communications Server changes are applied.

--End--

For more information about TLS, see the:

- *Nortel Security Management (NN43001-604) document*
- *Microsoft Office Communications Server 2007 Security Guide*

Note:

- ***Microsoft Enterprise CA running Microsoft Windows Server 2003 either Standard or Web Editions are not supported.***
- ***Using OCS Certificate wizard to request certificate for OCS Application Proxy, where MCM runs, is not supported.***

Configuring OCS certificate

This section covers the following topics for configuring the certificate used by the OCS Application Proxy for TLS connection to the CS 1000.

- [“Step 1: Configuring \(duplicating\) the Web certificate template” \(page 216\)](#)
- [“Step 2: Downloading the CA certification path” \(page 218\)](#)
- [“Step 3: Installation of the CA certification path” \(page 218\)](#)
- [“Step 4: Requesting a certificate” \(page 219\)](#)
- [“Step 5: Configuring OCS to use the certificate” \(page 220\)](#)

Enterprise CA

Step 1: Configuring (duplicating) the Web certificate template

To duplicate the Computer certificate template for a Windows Server 2003 Enterprise CA, perform the following steps.

Step	Action
1	Log on to the CA server as a member of the DomainAdmins group.
2	Click Start and select Run . In the Open box, type mmc , and then click OK .
3	On the File menu, click Add/Remove Snap-in .
4	Click Add .
5	In the Add Standalone Snap-in dialog box, click Certificate templates , and then click Add .
6	Click Certification Authority , and then click Add .
7	In Certification Authority, accept the default option, Local computer (the computer this console is running on).
8	Click Finish .
9	Click Close , and then click OK .
10	The console pane of MMC, verify that the Certificate Templates and Certification Authority snap-ins appear.
11	Click Certificate Templates .
12	In the details pane, right-click Web Server , and then click Duplicate Template .
13	On the General tab, change the template name to a meaningful name for your organization.

- 14 In the **Validity period** box, verify that the validity period meets your organization's requirements.
- 15 On the **Request Handling** tab, select the **Allow private key to be exported** check box.
- 16 On the **Subject name** tab, in the **Request** area, click **Supply**.
- 17 Click the **Security** tab.
- 18 Grant **Enroll** permissions for the following groups in all domains: Authenticated users, Domain Admins, Domain Computers, and Enterprise Admins.
- 19 Click **Apply**, and then click **OK**.
- 20 To verify settings, expand **Certificate Templates**.
- 21 In the details pane, right-click the template that you configured. Click **Properties** and verify your settings, and then click **OK**.
- 22 Expand **Certification Authority (local)**, and then expand your **CA**.
- 23 In the console tree, right-click **Certificate Templates**, point to **New**, and then click **Certificate Template to Issue**.
- 24 Select the new template, and then click **OK**.
- 25 Verify that the new template appears in the details pane, then under Intended Purpose, verify that **Server Authentication** and **Client Authentication** appear, and under Key Usage, verify that Digital signature, **Allow key exchange only with key encryption** and **Allow encryption of user data** appear.
- 26 Close MMC.
- 27 Click **Start**, and then click **Run**. In the Open box, type **gpupdate /force**, and then click **OK**. The gpupdate program forces an update of the Group Policy on the domain controller and replicates these changes throughout the forest.
- 28 Click **Start**, and then click **Run**. In the Open box, type **http://<domain controller name>/certserv**, and then click **OK**.
- 29 Enter the user name and password of an account that is a member of the **DomainAdmins** group.
- 30 On the Certificate Services Web page, under **Select a task**, click **Request a certificate**.
- 31 Click **Advanced certificate request**.
- 32 Click **Create and submit a request to this CA**.
- 33 Verify that your new certificate template appears in the **Certificate template** list.

--End--

Step 2: Downloading the CA certification path

Use the following procedures to download the CA certification path.

Step	Action
1	With the enterprise root CA offline and the enterprise subordinate (issuing) CA Server online, log on to Office Communications Server. Click Start, Run , and then type http://<name of your Issuing CA Server>/certsrv and then click OK .
2	Under Select a task , click Download a CA certificate, certificate chain, or CRL .
3	Under Download a CA Certificate, Certificate Chain, or CRL , click Download CA certificate chain .
4	In the File Download dialog box, click Save .
5	Save the file to the hard disk drive on your server. This file has an extension of .p7b. If you open this .p7b file, the chain will have the following two certificates: • <name of enterprise root CA> certificate. • <name of enterprise subordinate CA> certificate
--End--	

Step 3: Installation of the CA certification path

Use the following procedures for installation of the CA certification path.

Step	Action
1	Click Start, Run , type mmc , and then click OK .
2	On the File menu, click Add/Remove Snap-in .
3	In the Add/Remove Snap-in dialog box, click Add .
4	In the list of Available Standalone Snap-ins , select Certificates .
5	Click Add .
6	Select Computer account and click Next .
7	In the Select Computer dialog box, ensure Local computer: (the computer this console is running on) is selected, and then click Finish .
8	Click Close , and then click OK .

- 9 In the left pane of the Certificates console, expand **Certificates (Local Computer)**.
- 10 Expand **Trusted Root Certification Authorities**.
- 11 Right-click **Certificates**, point to **All Tasks**, and then click **Import**.
- 12 In the Import Wizard, click **Next**.
- 13 Click **Browse** and go to where you saved the certificate chain, select the p7b file, and then click **Open**.
- 14 Click **Next**.
- 15 Leave the default value **Place all certificates in the following store** and ensure **Trusted Root Certification Authorities** appears under the Certificate store.
- 16 Click **Next**.
- 17 Click **Finish**.

--End--

Step 4: Requesting a certificate

Use the following procedures to request a certificate.

Step	Action
1	Open a Web browser, type the URL http://<name of your Issuing CA server>/certsrv , and then press ENTER.
2	Click Request a Certificate .
3	Click Advanced certificate request .
4	Click Create and submit a request to this CA .
5	In Certificate Template , select the name you gave to your duplicated Web certificate template.
6	In Identifying Information for Offline Template , type the FQDN of either the pool or the server.
7	In Key Options , click the Store certificate in the local computer certificate store check box.
8	Click Submit .
9	Click Yes on the potential scripting violation dialog.
10	After the requested certificate is issued by the CA go to the URL http://<name of your Issuing CA server>/certsrv again.
11	Click View the status of a pending certificate request .
12	Click the request you just submitted.

- 13 Click **Install this certificate**.
- 14 Click **Yes** on the potential scripting violation dialog.

--End--

Step 5: Configuring OCS to use the certificate

Use the following procedures to configure OCS to use the certificate.

Step	Action
1	Open Computer Management snap-in.
2	Navigate and right-click on Microsoft Office Communications Server 2007 .
3	Click Properties .
4	Click Certificate tab.
5	Click Select Certificate .
6	Select the certificate you just installed.
7	Click OK .
8	Click Apply .
--End--	

Standalone CA

OCS Certificate wizard can be used in case of Standalone CA with the only comment: client ECU must be included.

Figure 84
Certificate Wizard for standalone CA

For more details about certificate configuration, see the Microsoft Office Communications Server 2007 Security Guide. Download Microsoft documentation from the Microsoft Web site at www.microsoft.com.

Transport Layer Security (TLS) configuration between OCS Proxy/MCM and Mediation Server

Follow these steps to configure the mediation server:

Mediation Server configuration

Step	Action
1	Make sure that the Certification Authority (CA) certificate issued the OCS Proxy certificate is trusted. Normally the certificates for Mediation Server and OCS Proxy are issued by one and the same CA. Therefore, this step can be ignored.
2	Configure 5061 for PSTN Gateway next hop port.

- 3 Create a text file with name "MediationServerSvc.exe.config" in the Mediation Server's directory. For example, "C:\Program Files\Microsoft Office Communications Server 2007\Mediation Server\MediationServerSvc.exe.config". This file should have the following content:

```
<?xml version="1.0" encoding="utf-8" ?>
<configuration>
<appSettings>
<add key="GatewayTLS" value="On" />
<add key="GatewayFqdn" value="OCS-Proxy.FQDN" />
</appSettings>
</configuration>
```

Where "OCS-Proxy.FQDN" is FQDN of your OCS Proxy server. This FQDN has to be resolved to the IP Address configured as PSTN Gateway Next hop.

- 4 Restart the Mediation Server.

--End--

For more information, see Microsoft web site at <http://technet.microsoft.com/en-us/library/bb803598.aspx>

OCS Proxy server configuration

Step	Action
1	Add the Mediation Server's FQDN to the Authorized hosts on OCS Proxy.
2	Configure TLS transport on MCM for the Mediation Server connections (MCM Console\Configuration\Routing Table).
--End--	

Note: OCS Mediation Server listens to the TCP port 5060 for incoming connections from Gateway even if TLS is configured. Therefore, the same 5060 port should be configured on MCM.

Normalizing phone numbers

Office Communicator 2007 requires that all phone numbers be in standard TEL URI format as defined in RFC 3966 for dialing and for reverse number lookup.

Office Communicator 2007 uses phone numbers that are provisioned (Active Directory and Outlook) and that are adhoc from the user through the user interface. All sources can be free format—a convention that is not in compliance with TEL URI.

The phone numbers configured for the Office Communicator user in the Active Directory are normalized. The PBX private dialing plan phone number is normalized to the Line URI format. For example, E.164;ext=CDP number or UDP number, based on the dialing plan.

The following lists some examples of normalization:

- The number ESN 343-5555 would be normalized to +16139620100;ext=3435555.
- The number +1 (425) 7066340 would be normalized to +14257066340.
- A number 1-800-368-3908 would be normalized to +18003683908.

Phone numbers are normalized in Active Directory. Each user can have multiple phone numbers such as Office, Mobile, and Home. Two options are available to normalize these numbers: **Offline** and **Address Book Service**. See *Microsoft Office Communications Server 2007 Planning Guide* for more information on normalization.

ATTENTION

All normalization rules must be in Generic script.

Normalizing Offline (Recommended)

The user's phone number is read from the Active Directory user object, original fields. These numbers are normalized offline to TEL URI format and stored in Active Directory in a different field named proxy address (multi value). Microsoft provides a reference on how to build a tool for this task.

If you use this option, then Address Book Service must not normalize the phone numbers and must instead publish only normalized phone numbers in the proxy address.

Each number in the proxy address is attached with an attribute that describes the phone number (for example: Office, Home, and so on).

For example:

tel:+14255551212;ext=5551212;ad-rdn=telephoneNumber;displayName=(425)555-1212

The ad-rdn = telephoneNumber is a proprietary parameter describes the type of the phone number and displayName, which is a proprietary parameter that holds the display format of this phone number (by default, the original phone number before normalization).

By default, the msRTCSIP-RCC Line is copied from the proxy address (attribute ad-rdn=telephoneNumber). The phone number is copied without ad-rdn and display name parameters.

For example:

```
tel:+14257771234;ext=1234;ad-rdn=telephoneNumber;display-name="(425) 7771234 * 1234"
```

is shown as:

```
tel:+14257771234;ext=1234
```

Normalizing using the Address Book Service

The Run time: Address Book service normalizes the original phone numbers in Active Directory. In this case, the normalized phone numbers are not stored in Active Directory and the output cannot be analyzed before it is used by Office Communicator. Having Address Book Service properly setup for an OC client is essential in receiving correct CLID info on call pop-ups.

Creating Normalization rules

Matching incoming calling numbers to the phone numbers for a Office Communications Server user, and transforming free-form dialstrings to URIs that can be called through TR/87, is performed by Office Communications Server 2007 and Office Communicator 2007 through a process called Normalization.

Normalization rules, according to Microsoft guidelines, must be defined to make use of the integration of Office Communicator 2007 Remote Call Control and Office Communications Server 2007 Multimedia functionality.

Each Office Communications Server user that uses Office Communicator Remote Call Control capability must have appropriate Office Communications configuration (in addition to the per-TN configuration discussed previously).

You must consider and define SIP routing for TR/87 sessions for each Office Communications Server user.

MCM provides authorization of Remote Call Control service requests based on the configuration defined in Active Directory for each Office Communications Server user.

Office Communicator requires that all phone numbers be in the standardized TEL URI format (RFC 3966) for reverse number lookup (matching the phone number of an incoming call to a known Office Communications Server user) and for dialing (either through an adhoc interface or through a menu from a user object).

Matching an incoming phone number to a Office Communications Server user identity is used to establish multimedia sessions. If the Office Communications Server user identity cannot be determined from a phone number, then Office Communications Server multimedia sessions cannot be established with the calling or called party.

See the *Microsoft Office Communicator Planning and Deployment Guide*. Download Microsoft technical documentation from the Download Center at www.microsoft.com.

For more in-depth information about deploying the Address Book Service, see the *Address Book Service Planning and Deployment Guide*. Microsoft documentation can be found at the Download Center, www.microsoft.com.

Example

A Office Communications Server user accesses an Active Directory phone number for Jim (in Outlook, for example) to make a Remote Call Control phone call. Office Communicator uses normalization to map the free-form phone number to a TEL URI prior to sending the TR/87 Make Call service request. You can assume the following points for normalizing phone numbers:

- The normalization method chosen is Address Book Service – Run time as opposed to using the offline method
- An Active Directory entry exists for Jim with business phone number ESN 343-2356
- A normalization rule exists that defines a regular expression (as defined in [Figure 85 "Normalization rule example for UDP dial plan" \(page 226\)](#)) to map ESN 343-2356 to +16239675000;ext=3432356.

Figure 85
Normalization rule example for UDP dial plan

```
#
# ESN ddd-dddd
#

.*ESN\s* (\d\d\d) [\s () \- \. /] * (\d\d\d\d)
+16139675000;ext=$1$2
```

- The normalized version (tel:+16139675000;ext=\$1\$2) of the business number in Active Directory entries is stored in the Global Address List (GAL) and downloaded at login by the Office Communicator 2007 client from the Address Book Service.

Result When you use a contact in a buddy list for Jim, or any other Microsoft Office Application that makes use of Active Directory phone numbers, the URI sent to the TR/87 FE for a TR/87 Make Call service request is:

tel:+16139675000;ext=\$1\$2


Adding a new Normalization rule

The procedure, [“Adding a new normalization rule” \(page 226\)](#) describes the process of adding a new normalization rule.

Adding a new normalization rule

Step	Action
1	Add an appropriate rule to the beginning of the “%ProgramFiles%\Microsoft OC 2007\Address Book Service\Company_Phone_Number_Normalization_Rules.txt” file. This ensures that the email notification provides the correct link.


Figure 86
Company phone number normalization rules for CDP



- 2 Refresh the Address Book on the server by issuing the following command on the server running ABService as shown in the example [Figure 87 "Refresh Address Book on the server"](#) (page 228):


```
%ProgramFiles%\Microsoft Office Communications
2007\Server\Core\ABServer.exe -syncNow
```

Figure 87
Refresh Address Book on the server



- 3 Exit from Office Communicator 2007.
- 4 Refresh Address Book on the client as shown in [Figure 88 "Refresh Address Book on the client" \(page 228\)](#). Issue the following command on the PC running Office Communicator 2007:
`Del "%UserProfile%\Local Settings\Application Data\Microsoft\Communicator\*" /q`

Figure 88
Refresh Address Book on the client



- 5 Launch Office Communicator 2007.

--End--

SIP Routing and Redundancy configuration

Office Communicator is a soft phone application as well as a SIP User Agent (UA). Office Communications Server Front End server (Standard Edition Server or Enterprise Edition Server) hosts Office Communicator .

The TR/87 FE within the Communication Server 1000 is also a SIP UA. Office Communicator 2007 establishes a SIP dialog in one direction only: from the application to the TR/87 FE. The Office Communications Server Front End, which functions as a SIP Proxy, is a required component. The Nortel Multimedia Convergence Manager (MCM) is also required to provide support for authorization and the use of an NRS.

ATTENTION

Due to the inability of the Office Communicator client to support the SIP 302 redirect message (a fundamental requirement for the basic operation of the NRS), the MCM application installed on the Office Communications Server to support Telephony Gateway and Services functionality is also a required component for Remote Call Control support when using Office Communicator. The MCM application handles the 302 redirect message on behalf of Office Communicator clients.

Configuring Remote Call Control SIP Routing Using Phone Addressing

When an NRS is used with SIP addressing, based on the phone address format, the Communication Server 1000 TR/87 FE used to support a Remote Call Control session for a user must be co-resident with the SIP GW. This is essential, as the URI that is present in the INVITE to establish a TR/87 session is identical to the URI used to place a SIP call to the user. Thus, the NRS redirects the INVITE based on the request URI only (and not the mime content type within the INVITE).

The TR/87 FE recognizes the TR/87 mime type within an INVITE and intercepts the TR/87 INVITE if it is co-resident with the SIP Gateway. This ensures that both TR/87 sessions and phone calls with the same request URI are handled appropriately — either by the TR/87 FE or SIP Gateway, on the same Signaling Server.

Redundancy configuration

For information about Redundancy, see [“Redundancy” \(page 84\)](#).

OCS 2007 users using UM 2007 in integrated mode**Option 1 adding user Alias as Exchange UM**

These procedures assume the installation procedures for Exchange UM have already been completed. Download Microsoft documentation from the Download Center at www.microsoft.com.

Configuring a basic mailbox for the UM user

Step	Action
1	Configure the OCS user mailbox in Exchange UM.
2	Configure SIP URI. For example, ocs2007a.corp.nortel.com


- 3 Add the Exchange UM Address (Extension) for every Exchange UM user.
- 4 Select Manually enter mailbox extension and enter the CS 1000 DN xxxx.

--End--

Adding user Alias as Exchange UM


Step	Action
1	From the Exchange Management Console, click on Recipient Configuration , and select Mailbox .
2	Select a user. For example, Brendan McCarthy
3	Right-click on the user and select Properties .

Figure 89
User Properties window for Exchange UM




- 4 Click on the **E-mail Addresses** tab.
- 5 Click on the **Add** menu and select **EUM Address**.
- 6 In the UM Address (Extension) window, enter the useralias@domain of the user in the Address/Extension field . For example, brendanmccarthy@ocs2007a.corp.nortel.com

Figure 90
UM Address



- 7 Click on the **Browse** button to find the associated Dial plan for the user. Click **OK** and then click **Apply** from the E-Mail Addresses tab of the Properties window.

Figure 91
Dial plan window




8

The new EUM address is added. To find the new UM Extension, click on the **Mailbox Features** tab, right-click on **Unified Messaging**, and select **Unified Messaging Properties**. In the **UM Addresses (Extensions)** field, there are three addresses.

- CS 1000 DN
- CS 1000 DN@domain
- useralias@domain

Figure 92
Unified Messaging Properties window



--End--

Option 2 adding CS 1000 DN as Exchange UM

These procedures assume the installation procedures for Exchange UM have already been completed. Download Microsoft documentation from the Download Center at www.microsoft.com.

Configuring a basic mailbox for the UM user


Step	Action
1	Configure the OCS user mailbox in Exchange UM.
2	Add the Exchange UM Address (Extension) as CS1000DN@do main for every Exchange UM user.
3	Select Manually enter mailbox extension and the CS 1000 DN XXXX.

--End--

Adding Exchange UM


Step	Action
1	From the Exchange Management Console window, click on Recipient Configuration , and select Mailbox .
2	Select a user. For example, Brendan McCarthy
3	Right-click on the user and select Properties .

Figure 93
User Properties window for Exchange UM




- 4 Click on the **E-mail Addresses** tab.
- 5 Click on the **Add** menu and select **EUM Address**.
- 6 In the UM Address (Extension) window, enter the CS1000DN@domain of the user in the **Address/Extension** field . For example, 2071@ocs2007a.corp.nortel.com

Figure 94
UM Address




- 7 Click on the **Browse** button to find the associated Dial plan for the user. Click **OK** and then click **Apply** from the E-Mail Addresses tab of the Properties window.

Figure 95
Dial Plan window



- 8 The new EUM address is added. To find the new UM Extension, click on the **Mailbox Features** tab, right-click on **Unified Messaging**, and select **Unified Messaging Properties**. In the **UM Addresses (Extensions)** field, there are three addresses.
- CS 1000 DN
 - CS 1000 DN@domain
 - useralias@domain

Figure 96
Unified Messaging Properties window



--End--

Maintenance

Introduction

The following are maintenance tips for MCM 3.5. For more information on troubleshooting tips, see [“Troubleshooting” \(page 245\)](#) section.

Communication Server 1000

No new SIP tracing capabilities are available on the Communication Server 1000. Existing SIP Trunk and Gateway tracing capabilities are used.

MCM 3.5

MCM 3.5 provides the following maintenance features:

Tools

MCM provides the following commands on the Tools menu:

- Active Directory Query: Check phone to user-id mapping. DNs can be entered, and found user-ids are displayed
- Backup Data: Back up a configuration file to the user specified location.
- Restore Data: Restore configuration files from user specified location.
- Set Log Level: Determine (configure) which information is logged in the MCM log file.
- Get Active Calls Count: Show how many calls are connected through Office Communications Server. You can use the Traffic tool to capture SIP and SIP CTI calls and transactions per hour.
 - The Multimedia Convergence Manager 3.0 service provides a test capability to retrieve user ID by phone number.
 - The Primary and Secondary NRS status utility is available from the application main window.
 - You can deploy Ethereal software on the OCS Proxy to provide call traces. MCM also provides full SIP-tracing capability. MCM SIP tracing is important particularly when MTLS (Mutual Transport

Layer Security) is enabled in future Communication Server 1000 releases- where SIP traces cannot be captured by a tool like Ethereal. MCM SIP tracing can be filtered by DN number. MCM SIP tracing is implemented as part of the application logging functionality. Special commands are not required. For more information on tracing, see [“Capturing traces and logs” \(page 255\)](#)

- You can remotely access the Office Communications Server application using the Windows 2003 server remote access capability.
- Task Manager is supported in Windows 2003 Server for MCM.

Patches and upgrades

Patching is not supported in MCM 3.5. Fixes are provided in up-issues and maintenance releases.

ATTENTION

All customer configured MCM application data is retained during an MCM application upgrade.

Remote Call Control

Signaling Server OAM Level CLI Commands

The Signaling Server OAM Level CLI commands are used to query active TR/87 sessions to turn on tracing at the SIP level. You can use these commands to terminate either a session for a specific DN or to terminate all TR/87 sessions that are currently active on the server.

Table 41
Signaling Server OAM Level CLI commands

Prompt	Response	Description
>	SIPCTISessionShow	Show the total number of TR87 SIP sessions.
>	SIPCTITraceShow	Display the trace settings for SIP CTI application, including the trace filter setting and output setting.
>	SIPCTIShow	Show SIP CTI application status and configuration.
>	SIPCTIClientShow	Show information about the all the soft clients associated.

Table 41
Signaling Server OAM Level CLI commands (cont'd.)

Prompt	Response	Description
>	SIPCTITraceLevel <level>	Configure the TR87 SIP message Trace Level. The level can be one of the following: 0 –TR87 SIP message body (ECMA 323) only 1 – TR87 SIP message body (ECMA 323) and message headers
>	SIPCTITrace on	Turn on SIP CTI trace for all soft clients in both incoming and outgoing directions.
>	SIPCTITrace off	Turn off SIP CTI trace for all soft clients in both incoming and outgoing directions.
>	SIPCTITrace <MsgRcv> <MsgSend>	Turn on SIP CTI trace for all soft clients in incoming and/or outgoing. The parameter is either on or off.
>	SIPCTITrace sc <soft client SIP/Tel URI/DN> <MsgRcv> <MsgSend>	Turn on SIP CTI trace for a specific soft client in incoming and/or outgoing direction(s). This may result in a number of sessions as a single URI could be used for multiple active sessions.
>	SIPCTIOutput <Dest> <"fileName">	Redirecting the SIP CTI trace to a specific output destination. The destination can be one of the following: 1. TTY 2. RPTLOG 3. File If File is selected as the output destination, the filename must be given.

Table 41
Signaling Server OAM Level CLI commands (cont'd.)

Prompt	Response	Description
>	SIPCTIStop all	De-acquire all AST DNs and terminate all the TR87 SIP sessions.
>	SIPCTIStop <dn>	De-acquire one specific AST DN and terminate all the TR87 SIP sessions associated with this AST DN.

Operational Measurements for SIP CTI

The following Operational Measurements (OM) details are collected for SIP CTI:

- SIPCTITotalSoftClientLoginAttempts
- SIPCTITotalSoftClientLoginSuccesses
- SIPCTITotalAnswerCallRequests
- SIPCTITotalAnswerCallSuccesses
- SIPCTITotalClearConnectionRequests
- SIPCTITotalClearConnectionSuccesses
- SIPCTITotalConsultationCallRequests
- SIPCTITotalConsultationCallSuccesses
- SIPCTITotalDeflectCallRequests
- SIPCTITotalDeflectCallSuccesses
- SIPCTITotalHoldCallRequests
- SIPCTITotalHoldCallSuccesses
- SIPCTITotalMakeCallRequests
- SIPCTITotalMakeCallSuccesses
- SIPCTITotalRetrieveCallRequests
- SIPCTITotalRetrieveCallSuccesses
- SIPCTITotalSingleStepTransferRequests
- SIPCTITotalSingleStepTransferSuccesses
- SIPCTITotalTransferCallRequests
- SIPCTITotalTransferCallSuccesses
- SIPCTITotalMonitorStartRequests

- SIPCTITotalMonitorStartSuccesses
- SIPCTITotalMonitorStopRequests
- SIPCTITotalMonitorStopSuccesses
- SIPCTITotalConferenceCallRequests
- SIPCTITotalConferenceCallSuccesses
- SIPCTITotalSetForwardingRequests
- SIPCTITotalSetForwardingSuccesses
- SIPCTITotalGetForwardingRequests
- SIPCTITotalGetForwardingSuccesses
- SIPCTITotalSessionTerminated

For information on how to access these OM's through Element Manager, see *Element Manager System Administration* (NN43001-632).

Signaling Server Expert Level CLI Commands

Using Signaling Server Expert Level CLI commands, as shown in [Table 42 "Signaling Server Expert Level CLI commands" \(page 243\)](#), you can trace AML commands that are sent by the TR/87 FE to the Call Server on behalf of the Office Communicator clients that may be active.

Table 42
Signaling Server Expert Level CLI commands

Prompt	Response	Description
	SIPCTIAmlTrace level	Configure AML Trace level for SIP CTI application.
		The level can be one of the following:
		0—Turn off trace.
		1—Print all input and output AML data buffer.
		2—Print all input and output AML data buffer except POLLING message.
		3—Print all input and output AML data buffer except POLLING message, with IE type decoding.

Prompt	Response	Description
		4—Print all input and output AML data buffer except POLLING message with IE type and data decoding.
		ATTENTION This trace prints out AML messages to and from CS at the transport layer. Because sending and receiving AML messages are per AML link instead of per DN or TN, no good solution exists to filter on this AML trace tool. Nortel recommends that you do not turn on the trace in a busy system.

Troubleshooting

Use the following procedures to assist in troubleshooting general Converged Office problems.

Checking Telephony Gateway (SIP Gateway) configuration

Checking Telephony Gateway configuration

Step	Action
1	Check all required Communication Server 1000 resources (packages, license, and Communication Server 1000 patches).
2	Check the DN, telephone TN and TLSV configuration.
3	Check the DNS on the Signaling Server.
4	Verify the Signaling Server SIP and the MCM endpoint registration on the NRS.
5	Ensure that MCM is registered to the NRS.
6	Verify the Host Authorization and Certificates for Office Communications Servers and Pool.

ATTENTION

Improper configuration of Host Authorization and Certificates for Office Communications Servers and Pool is the primary reason Converged Office does not function properly in the Enterprise Edition configuration.

--End--

Checking Remote Call Control (SIP CTI) configuration

Checking Remote Call Control configuration

Step	Action
1	Check all required Communication Server 1000 resources (packages, license, and Communication Server 1000 patches).

- 2 Check the DN, telephone TN, and TLSV configuration.
- 3 Verify that AST, IAPG, and CLS (CDMR/TR87A) are configured correctly (SIP CTI only).
- 4 Verify that the AML Link status is up. Make sure that the ELAN ID is greater or equal to 32 (SIP CTI only).
- 5 Check the SIP CTI status (on the Signaling Server, under PDT, issue the command SIPCTIShow). Make sure the SIP CTI status reads **Application status: Active** (SIP CTI only).
- 6 Check the DNS on the Signaling Server.
- 7 Verify the Signaling Server SIP and the MCM endpoint registration on the NRS.
- 8 Ensure that MCM is registered to the NRS.
- 9 Verify the MCM configuration for the Called Phone Context and check it against the Signaling Server configuration for the SIP URI map and Private/CDP domain name parameter (SIP CTI only).
- 10 Verify the Routing, Host Authorization, and Certificates inside OCS servers and Pool.

Note: Improper configuration of Routing, Host Authorization, and Certificates on OCS Servers and Pool is the primary reason Converged Office does not function properly in the Enterprise Edition configuration.

- 11 If the problem still exists, go to the section [“Capturing traces and logs” \(page 255\)](#) to assist further.

--End--

Lack of memory on Signaling Server

Problem:

Lack of memory on Signaling Server.

Symptom:

After SIP CTI services are activated, you are unable to log on to the Signaling Server through Element Manager. When rebooting, some HTTP tasks are not up.

Possible cause:

Insufficient memory.

Solution:

Check the memory and upgrade the memory to 1 gigabyte (GB), if required. The Signaling Server (running Converged Office) requires 1 GB of memory. Release 4.5 only required 512 megabytes (MB).

SIP CTI services does not come up
SIP Dialog not established**Problem:**

Phone integration is enabled in Office Communicator and a SIP dialog for TR/87 was attempted and not established successfully.

Symptom:

When logged into the Office Communicator, the phone icon is not displayed.


Possible cause 1:

The Server URI or the Line URI is incorrect.

Possible cause 2:

Use Microsoft's nslookup tool to verify the DNS configuration on the Signaling Server and the Host Name resolution for each IP address. For more information on the nslookup tool, see [Figure 97 "nslookup tool" \(page 247\)](#), or visit the Microsoft Web site at <http://support.microsoft.com/kb/200525>.

Figure 97
nslookup tool



Solution 1: Check configuration parameters in AD

Check the configuration parameters in Active Directory for this user. Run a SIPCTITrace on the Signaling Server and check the MCM logs. For more information on activating the trace, see [“SIP CTI traces on the Signaling Server” \(page 256\)](#).

Solution 2: Confirm FQDN and the IP address are correct**Solution 2:**

Confirm that the FQDN (case sensitive) and the IP address are correct.

For causes (not mentioned), the following actions may help identify the problem:

- Activate AML traces on the Call Server to check if the IACR/IACS (TN acquire) is correct. For more information on capturing traces, see [“AML traces on the Call Server \(SIP CTI only\)” \(page 255\)](#)
- Activate SIPCTITrace. For more information on capturing traces, see [Table 46 “SIP CTI trace in PDT” \(page 256\)](#)
- Activate OCS Front End server and Proxy server traces
- Activate MCM logs
- Capture Ethereal traces

SIP CTI service is down**Problem:**

SIP CTI service down.

Symptom:

After SIP CTI services are activated, SIP CTI services does not come up.

Possible cause:

VSID or ELAN ID is lower than 32.

Solution:

Follow the procedure [“Reconfigure SIP CTI service” \(page 248\)](#) to solve this issue.

Reconfigure SIP CTI service

Step	Action
1	Reconfigure the VSID and ELAN IDs so both are greater than 32. Confirm that the SIP CTI service is up.
2	Check the SIP CTI status on the Signaling Server.

Table 43
Check the SIP CTI status

Prompt	Response	Description
pdt	SIPCTIShow	show SIP CTI status and settings

See [Figure 98 "Screen output example for SIP CTI status"](#) (page 249).

Figure 98
Screen output example for SIP CTI status

<pre> pdt> SIPCTIShow SIP CTI Status and Settings: ----- Application status: Active Customer number: 0 Dialing plan: CDP SIP URI format: FQDN Maximum number of associations per DN: 10 Support TLS Endpoints Only: FALSE ----- CTI Dial Plan Information ----- Home Location Code: "Not Configured" Country Code: "Not Configured" NPA Prefix: "6" INTL Prefix: "6" LOC Prefix: "9" SPN Prefix: "6" NXX Prefix: "6" ----- CTI CLID Information ----- International Calls As National: TRUE Subscriber / Number of digits to strip: 0 National / Number of digits to strip: 0 Area Code: "Not Configured" Subscriber / Prefix to insert: "Not Configured" National / Prefix to insert: "Not Configured" pdt> </pre>

3

In LD 48, check the ELAN status on the Call Server

Table 44
LD 48

Prompt	Response	Description
.stat	elan	Check the ELAN status on the Call Server

Screen output:

```

SERVER TASK: ENABLED
ELAN #: 032 DES: CDLCS
APPL_IP_ID: 47.11.157.112 : 0000F600 LYR7: ACTIVE EMPTY
APPL ACTIVE

```

--End--

MCM not synchronizing new users in AD Cache mode

Problem:

MCM cannot synchronize new users in AD Cache Mode.

Symptom:

Several new users are configured in AD, but MCM did not download them to its AD Cache during synchronization and cannot find them.

Possible cause 1:

The changes made to those users in AD is not replicated to the Global Catalog (GC) server used by MCM.

Possible cause 2:

MCM Service credentials are not sufficient to view the msRTCSIP properties.

Possible cause 3:

The Active Directory field is not enabled for propagation to the Global Catalog.

Solution 1: Check the Global Catalog content manually

Consult with the Network Administrator about the schedule of replications between Domain Controllers (DCs).

Alternatively, check the GC content. Follow the steps in [“Checking the Global Catalog content manually” \(page 250\)](#).

Checking the Global Catalog content manually

Step	Action
1	Install the Operating System Support Tools on the server (usually the Tools setup is on the MS Windows 2003 Server setup disk).
2	Run the LDP tool (%ProgramFiles%\Support Tools\ldap.exe).
3	Connect to the GC server IP address at the port 3268 (Connection -> Connect ...).
4	Bind with the MCM service account credentials (Connection -> Bind ...).
5	Download the AD structure tree (View -> Tree).
6	Navigate to the object of one of those just configured users.
7	Confirm that the object contains the properties: • msRTCSIP-UserEnabled and it is configured to TRUE • msRTCSIP-PrimaryUserAddress and it is configured with correct User

- SIP URI
- with correct phone number
- msRTCSIP-OptionFlags
- msRTCSIP-Line
- msRTCSIP-LineServer

If some of those properties are not presented, or configured with old values, then the GC server is not replicated. The user must wait for the next automatic replication or run the replication manually.

If you are unsure that the replication is complete, or that the properties msRTCSIPUserEnabled and/or msRTCSIP-OptionFlags are not presented, see Possible cause 2 and [“Solution 2: Access permissions for the AD object properties” \(page 251\)](#).

--End--

Solution 2: Access permissions for the AD object properties

Solution 2:

Check the access permissions for the AD object properties by following the steps in [“Accessing permissions for the AD object properties” \(page 251\)](#).

Accessing permissions for the AD object properties

Step	Action
1	Install the Operating System Support Tools on the server (usually the Tools setup is on the MS Windows 2003 Server setup disk).
2	Run the ADSIEdit tool (%ProgramFiles%\Support Tools\adsiedit.msc).
3	Navigate to the users object container or the specific user's object.
4	Right-click the item and open Properties .
5	Go to the Security tab and click the Advanced button.
6	Search for the permission entry specific for the msRTCSIP properties group or RTCPropetySet. If there is a specific user group that has access rights to that property group, then the best solution is to add the MCM service account to this user group. Otherwise, you have to allow MCM Service account to read the properties msRTCSIP-UserEnabled , msRTCSIP-PrimaryUserAddress , msRTCSIPOptionFlags , msRTCSIP-Line , and msRTCSIP-LineServer .

- 7 Click **Add**.
- 8 Choose the **MCM service account** and click **OK**.
- 9 Go to the **Properties** tab.
- 10 Select **User objects** in the field **Apply onto**.
- 11 In the **Permissions** list box select the Allow check boxes across the Read permission of necessary properties and RTCPropertySet.
- 12 Click **OK**.

--End--

Solution 3: Enable propagation of the AD to the Global Catalog

Enable propagation of the Active Directory field to the Global Catalog. Be sure to specify a Domain Controller LDAP server (port 389) to reduce the search scope to only one domain. Follow the procedure in [“Enabling propagation of the Active Directory field to the Global Catalog”](#) (page 252).

Enabling propagation of the Active Directory field to the Global Catalog

Step	Action
1	Open the Active Directory Schema snap-in.
2	Select the Attributes folder on the left pane.
3	Find and the right-click the necessary field (otherTelephone).
4	Click the Property menu item.
5	Enable Replicate this attribute to the Global Catalog .
6	Click OK .

--End--

OC client not registered

The following is a list of areas to troubleshoot when only one client is unable to register:

- Check to ensure that all clients are registered.
- Look in the client options for Active Directory for a mistake in SIP URI or Line URI.
- For RCC enabled user, ensure that the T87A class of service is configured for this client and a session is established.
- Remove RCC to see if VOIP functionality is present.

The following is a list of areas to troubleshoot when all clients are unable to register:

- Ensure all component configuration information is correct on the Front End server, Mediation Server, MCM, Signaling Server, SPS, Call Server, and DNS.
- Capture logs starting with the client logs. SIP messages between the Mediation Server and the Front End server cannot be seen as this is a secure leg.

Pop-up not displayed

Problem:

Pop-up not displayed.

Symptom:

When a Office Communicator user receives a call, the called telephone rings, but no pop-up appears for the user to click on to answer the call.

Possible causes:

The Phone Context may be not correct. Address Book Service may not be properly setup. Phone integration is not activated.

Solutions:

- Ensure that the user's name is in Active Directory, the MCM, and the Signaling Server (L1 parameter) have the correct Phone Context.
- Ensure Address Book Service properly setup for an OC client is essential in receiving correct CLID info on call pop-ups
- Ensure PBX Integration is marked for an OC client in Active Directory and Server URI line is filled with valid info
- Ensure User has activated Phone integration on OC client
- Ensure TLSV is configured properly for the called user.

Two pop-ups are displayed

Problem:

Two toasts appear.

Symptom:

In some transfer and conference scenarios, the user receives two toasts instead of a merged one. One is with CLID information of the transferring telephone and the other is with CLID information of the original caller.

Solution:

The Route List Data Block must have the prompt DORG configured to No. The default value for DORG is No. For more information, see ["Route list data block" \(page 171\)](#).

Delay for a SIP Gateway call

Problem:

Delay for a SIP Gateway call.

Symptom:

Office Communicator users observe a delay at the beginning of a call.

Possible cause:

Missing Office Communicator patch.

Solution:

Ensure that the Office Communicator patch is up-to-date.

Call Forward is cancelled by Office Communicator

Problem:

Office Communicator cancels the Call Forward configured on the telephone.

Symptom:

The telephone is on Call Forward to another number. When the Office Communicator user who is associated to this telephone logs in (this telephone is controlled by the Office Communicator user through SIP CTI), the Office Communicator cancels the Call Forward.

Possible cause:

This is a Microsoft issue that Nortel has escalated to Microsoft.

Solution:

No solution yet.

Office Communicator disconnecting from the network

Problem:

Office Communicator user cannot control the telephone after having been disconnected several times.

Symptom:

Customers using smart telephones or Mobile Communicators cannot take control of the telephone after having been disconnected abruptly three or more times. This disconnection could be due to your network (for example, GPRS or WLAN).

Possible cause:

This problem occurs because the SIP CTI link is disconnected abnormally and the Association is out of service for 30 minutes (1800 seconds). This timer is hard-coded by Office Communicator and cannot be changed.

Solution:

Increase the **Maximum Associations per DN** on the Signaling Server through Element Manager. This field is configured to 3 by default. Increase this parameter to allow more network disconnections.

Capturing traces and logs

Use the following procedures to capture traces and logs to assist in troubleshooting Converged Office problems. When a problem is encountered, traces and logs can be activated on different components.

- Communication Server 1000 traces
- MCM logs
- OCS logs
- OC logs

Note: MCM logs are used for debugging purposes only. Use the Event Viewer to determine if any Error Events were logged. A detailed description of an Event can be seen by right-clicking on the Event and selecting Properties from the pop-up menu. Report any problems listed in the Event description.

Communication Server 1000 traces

Use the following procedures for capturing traces.

AML traces on the Call Server (SIP CTI only)

In LD 48, activate AML traces on the Call Server (SIP CTI only):

Table 45
LD 48

Prompt	Response	Description
EDD000	enl msgi 32	Enable incoming AML traces for ELAN 32
EDD000	enl msgo 32	Enable outgoing AML traces for ELAN 32

Screen output:

```
ELAN32 I MTYP=3B IACR TN=0 TIME=18:07:34
ELAN32 IN B1B1BE7A OUT B1B1BE7C QSIZE 00000000
ELAN32 03 20 00 00 00 00 1E 3B 00 0B 00 00 95 01 05 36 02 72 14 E6
ELAN32 0C BF EE 01 FF FF FF 00 00 0F FF 00 00
```

ELAN32 O MTYP=3C IACS TN=0 TIME=18:07:34
ELAN32 IN B1B1BE8B OUT 00000000 QSIZE 00000000
ELAN32 03 27 00 00 00 00 1E 3C 00 0B 00 00 95 01 05 36 02 72 14 E6
ELAN32 0C BF EE 01 FF FF FF 00 00 0F FF 00 00 37 02 98 C2 AA 01 00

ELAN32 I MTYP=1D SETFTR TN=0 TIME=18:07:34
ELAN32 IN B1B1C6E8 OUT B1B1C6EA QSIZE 00000000
ELAN32 03 16 00 00 00 00 16 1D 00 0B 00 00 46 01 08 36 02 72 14 3F
ELAN32 02 00 00

ELAN32 O MTYP=1D SETFTR TN=0 TIME=18:07:34
ELAN32 IN B1B1C6EE OUT 00000000 QSIZE 00000000
ELAN32 03 1D 00 00 00 00 16 1D 00 0B 00 00 3F 02 98 C2 46 01 08 36
ELAN32 02 72 14 71 01 01 78 02 20 0E

SIP CTI traces on the Signaling Server

In PDT, activate **SIP CTI** traces on the Signaling Server.

Table 46
SIP CTI trace in PDT

Prompt	Response	Description
pdt	SIPCTITrace on	activate SIP CTI trace
pdt	SIPCTITraceLevel 1	

Figure 99
Example of screen output for SIP CTI Traces on the Signaling Server

```

===== PUTTY log 2008.01.23 22:37:58
=====
[SIPCTITrace:] (23/01/08 23:39:39) <?xml version="1.0" encoding="UTF-
8"?>
[SIPCTITrace:] (23/01/08 23:39:39) <deliveredEvent
xmlns="http://www.ecma-international.org/standards/ecma
[SIPCTITrace:] (23/01/08 23:39:39) -323/csta/ed3">
[SIPCTITrace:] (23/01/08 23:39:39)
<monitorCrossRefID>37</monitorCrossRefID>
[SIPCTITrace:] (23/01/08 23:39:39)
<connection><callID>19797</callID><deviceID>tel:+16139675000;ext=3050</
[SIPCTITrace:] (23/01/08 23:39:39) deviceID></connection>
[SIPCTITrace:] (23/01/08 23:39:39)
<alertingDevice><deviceIdentifier>tel:+16139675000;ext=3050</deviceIden
[SIPCTITrace:] (23/01/08 23:39:39) tifier></alertingDevice>
[SIPCTITrace:] (23/01/08 23:39:39)
<callingDevice><deviceIdentifier>tel:2014;phone-context=cdp.udp</device
[SIPCTITrace:] (23/01/08 23:39:39) Identifier></callingDevice>
[SIPCTITrace:] (23/01/08 23:39:39)
<calledDevice><deviceIdentifier>tel:+16139675000;ext=3050</deviceIdent
[SIPCTITrace:] (23/01/08 23:39:39) fier></calledDevice>
[SIPCTITrace:] (23/01/08 23:39:39)
<lastRedirectionDevice><notRequired/></lastRedirectionDevice>
[SIPCTITrace:] (23/01/08 23:39:39)
<localConnectionInfo>alerting</localConnectionInfo><cause>normal</cause>
[SIPCTITrace:] (23/01/08 23:39:39) >
[SIPCTITrace:] (23/01/08 23:39:39) </deliveredEvent>
[SIPCTITrace:] (23/01/08 23:39:46) <?xml version="1.0" encoding="UTF-
8"?>
[SIPCTITrace:] (23/01/08 23:39:46) <ConnectionClearedEvent
xmlns="http://www.ecma-international.org/standa
[SIPCTITrace:] (23/01/08 23:39:46) rds/ecma-323/csta/ed3">
[SIPCTITrace:] (23/01/08 23:39:46)
<monitorCrossRefID>37</monitorCrossRefID>
[SIPCTITrace:] (23/01/08 23:39:46)
<droppedConnection><callID>19797</callID><deviceID>tel:+16139675000;ext
[SIPCTITrace:] (23/01/08 23:39:46) =3050</deviceID></droppedConnection>
[SIPCTITrace:] (23/01/08 23:39:46)
<releasingDevice><deviceIdentifier>tel:+16139675000;ext=3050</deviceIde
[SIPCTITrace:] (23/01/08 23:39:46) ntifier></releasingDevice>
[SIPCTITrace:] (23/01/08 23:39:46)
<localConnectionInfo>null</localConnectionInfo><cause>normal</cause>
[SIPCTITrace:] (23/01/08 23:39:46) </ConnectionClearedEvent>

```

SIP Gateway traces on the Signaling Server

In PDT, activate **Gateway** traces on the Signaling Server.

Table 47
SIP Gateway trace in PDT

Prompt	Response	Description
pdt	SIPCallTrace on	
pdt	SIPTraceLevel 1	

Figure 100
Example of screen output for SIP Gateway trace

```

===== PUTTY log 2008.01.23 22:45:59
=====
24/01/2008 03:41:16 LOG0006 SIPNPM: ->Content-Type:
application/sdp;charset=utf-8
24/01/2008 03:41:16 LOG0006 SIPNPM: ->Content-Length: 299
24/01/2008 03:41:16 LOG0006 SIPNPM: ->
24/01/2008 03:41:16 LOG0006 SIPNPM: ->v=0
24/01/2008 03:41:16 LOG0006 SIPNPM: ->o=- 0 0 IN IP4 47.11.56.52
24/01/2008 03:41:16 LOG0006 SIPNPM: ->s=session
24/01/2008 03:41:16 LOG0006 SIPNPM: ->c=IN IP4 47.11.56.52
24/01/2008 03:41:16 LOG0006 SIPNPM: ->b=CT:1000
24/01/2008 03:41:16 LOG0006 SIPNPM: ->t=0 0
24/01/2008 03:41:16 LOG0006 SIPNPM: ->m=audio 60094 RTP/AVP 97 101 0 8
24/01/2008 03:41:16 LOG0006 SIPNPM: ->c=IN IP4 47.11.56.52
24/01/2008 03:41:16 LOG0006 SIPNPM: ->a=rtcp:60095
24/01/2008 03:41:16 LOG0006 SIPNPM: ->a=label:Audio
24/01/2008 03:41:16 LOG0006 SIPNPM: ->a=rtpmap:97 RED/8000
24/01/2008 03:41:16 LOG0006 SIPNPM: ->a=rtpmap:101 telephone-event/8000
24/01/2008 03:41:16 LOG0006 SIPNPM: ->a=fmtp:101 0-16
24/01/2008 03:41:16 LOG0006 SIPNPM: ->a=rtpmap:0 PCMU/8000
24/01/2008 03:41:16 LOG0006 SIPNPM: ->a=rtpmap:8 PCMA/8000
24/01/2008 03:41:16 LOG0006 SIPNPM: ->a=ptime:20
24/01/2008 03:41:16 LOG0006 SIPNPM: ->
24/01/2008 03:41:16 LOG0006 SIPNPM: This message is OUTGOING ---
24/01/2008 03:41:16 LOG0006 SIPNPM: ->SIP/2.0 100 Trying
24/01/2008 03:41:16 LOG0006 SIPNPM: ->From: <sip:2014;phone-
context=cdp.udp@ocs2007a-
med.ocs2007a.corp.nortel.com;user=phone>;tag=c0d6342d
24/01/2008 03:41:16 LOG0006 SIPNPM: ->>ec;epid=93883CDE01
24/01/2008 03:41:16 LOG0006 SIPNPM: ->To: <sip:3050;phone-
context=cdp.udp@47.11.56.54;user=phone>
24/01/2008 03:41:16 LOG0006 SIPNPM: ->Call-ID: 178c6ba6-817e-4415-8619
-555b6699d90b
24/01/2008 03:41:16 LOG0006 SIPNPM: ->CSeq: 260 INVITE
24/01/2008 03:41:16 LOG0006 SIPNPM: ->via: SIP/2.0/TCP
47.11.56.25:5060;branch=z9hg4bk6374d2a8716e971b8129ba3b.6
24/01/2008 03:41:16 LOG0006 SIPNPM: ->Via: SIP/2.0/TCP
47.11.56.54:1904;received=47.11.56.54;branch=z9hg4bkD4DB5B54.5F8572DF;b
ranch=TRUE
24/01/2008 03:41:16 LOG0006 SIPNPM: ->via: SIP/2.0/TCP
47.11.56.52:2778;branch=z9hg4bk7f583134;ms-received-port=2778;ms-
received-cid=2FD00
24/01/2008 03:41:16 LOG0006 SIPNPM: ->Supported: 100rel,x-nortel-
sipvc,replaces,timer
24/01/2008 03:41:16 LOG0006 SIPNPM: ->User-Agent: Nortel CS1000 SIP GW
release_5.0 version_sse-5.00.31
24/01/2008 03:41:16 LOG0006 SIPNPM: ->Contact:
<sip:3050@ocs2007a.corp.nortel.com;user=phone;x-nt-net-feature=x-nt-
home>
24/01/2008 03:41:16 LOG0006 SIPNPM: ->Allow:
INVITE,ACK,BYE,REGISTER,REFER,NOTIFY,CANCEL,PRACK,OPTIONS,INFO,SUBSCRIB
E,UPDATE
24/01/2008 03:41:16 LOG0006 SIPNPM: ->Content-Length: 0

```

MCM logs

MCM 3.5 generates a daily log file with no maximum size restrictions and no cleanup procedures are implemented. The contents of the existing log file remain in all cases.


SNMP is not supported on the MCM 3.5 application. Alarms are logged to an MCM log file in addition to the Windows 2003 Event Viewer.

MCM 3.5 logging has the following levels:

- **None:** No messages or alarms are logged to the file. (Alarms are still logged to Windows Event Viewer).
- **SIP:** SIP messages (filtered by distinct DN) are logged further to alarms. Only one DN can be specified at the same time in MCM.
- **Debug:** Debug information is logged to the MCM log file.
- **SIP and Debug**

To clear a log, click on the **Clear Log** button. The backup file is stored as MCMlog.bak. See [Figure 101 "MCM logs" \(page 259\)](#) for an example of the Logs window.

Figure 101
MCM logs



Activating MCM logging

The following section details how to turn on MCM logging. MCM Logs can be enabled from MCM Console. Log files are stored in MCM.log file which is located in the MCM application installation directory (?:\Program Files\Nortel\MCM\MCM.log).

Step	Action
1	On the MCM console interface, to activate MCM logs, select Tools and then choose Logs from the menu.

2 Go to Log Level and choose Debug.

--End--

To turn off MCM logging, see [“Resetting MCM debug trace”](#) (page 261).

MCM log file output


The following shows a snippet from the log output file:

```
12/14/2007 11:11:37 AM: 3.0.1.76: Debug: OnCustomCommand
: got command:
update config data
12/14/2007 11:11:38 AM: 3.0.1.76: Debug: ConfigurationDa
ta:
ReadConfigFile: Invalid secondary NRS address: 0.0.0.0
12/14/2007 11:11:38 AM: 3.0.1.76: Debug: ConfigurationDa
ta:
ReadConfigFile: Invalid LDAP server IP address: 0.0.0.0
12/14/2007 11:11:38 AM: 3.0.1.76: Debug: ServerEventHand
ler: got Event #2
12/14/2007 11:11:38 AM: 3.0.1.76: SIP and Debug:
NRSPolling:
sendPolling: request sent to the Primary NRS
12/14/2007 11:11:38 AM: 3.0.1.76: Debug: AD Cache:
turning off
12/14/2007 11:11:38 AM: 3.0.1.76: Debug: AD Cache: it
has been turned off
12/14/2007 11:11:38 AM: 3.0.1.76: Debug: ServerEventHand
ler: got Event #3
12/14/2007 11:11:38 AM: 3.0.1.76: SIP and Debug:
NRSPolling: pollingResponseHandler
SIP/2.0 200
via: SIP/2.0/TCP 47.11.56.54:4616;branch=z9hG4bK-422726
df-8d69b1-2ac0;received=47.11.56.54
from: <sip:MCM@ocs2007a.corp.nortel.com>;tag=a7fdb8be-c
10b-44ef-9bf8-b9f6233cecb5
to: <sip:MCM@ocs2007a.corp.nortel.com>;tag=18892
call-id: 00000000-00000000-0000-00000000-000002-0000
cseq: 6 REGISTER
contact: <sip:MCM@ocs2007a.corp.nortel.com:5060>;expir
es=300;maddr=47.11.56.54;Transport=TCP
expires: 300
content-length: 0
```

MCM Event log

MCM Exceptions and failures are reported in System Event Log. The following shows an example event log:

Figure 102
Event Viewer window



Resetting MCM debug trace

Use the following procedures to reset the MCM debug trace.

Resetting MCM debug trace

Step	Action
1	On the MCM interface, select Tools and then choose Logs from the menu.
2	Go to Log Level and choose None .
3	Delete the MCM.log file from the directory where MCM is installed.

--End--

OCS logs

Use the following procedures to activate an OCS log.


Activating OCS logs

Step	Action
1	Right-click on the OCS pool and select Logging Tool and then choose New Debug Session .

- 2 In the OCS 2007 Logging Tool window, specify the Components to trace, Severity level, and other log file options. See example [Figure 103 "OCS debugging tool" \(page 262\)](#).
- 3 Click the **Start Logging** button.
- 4 To view the log file, click the **Analyze Log Files** button. The log file is stored as a .txt file in c:\WINDOWS\Tracing folder.

--End--

Figure 103
OCS debugging tool



OC logs

The following procedures describe how to enable logs for OC client. The tracing log folder is stored in the user's Documents and Settings sub folder with the .uccplog extension.


Enabling OC logs

Step	Action
1	From the OC client, select the Options menu.
2	Choose the General tab.
3	Select the Turn on logging in Communicator and the Turn on Windows Event Logging for Communicator checkboxes. See Figure 104 "Turn on Logging and Windows Event Logging" (page 263) .

4 Click OK.

--End--


Figure 104
Turn on Logging and Windows Event Logging



OC client start-up debugging

To determine if there is a PBX connection, a handset icon will be present in the upper right of the OC client window. The example in [Figure 105 "No PBX connection for OC client"](#) (page 264) shows an OC client window where the handset icon is not present. For more information on troubleshooting an OC client registration, see ["OC client not registered"](#) (page 252).

Figure 105
No PBX connection for OC client



Case checklists

Use the following checklists prior to opening a case to ensure that all relevant information is collected:

Table 48
Signaling Server information

	Check
The patches list installed on the Signaling Server: pdt>mdp issp	
The configuration on the Signaling Server: - pdt>cd /u/config - pdt>copy config.ini	
Are you connected to the Signaling Server with Telnet and under pdt? pdt>SIPCTIShow	

Table 49
Call Server information

	Check
Provide the patches list installed on the Call Server - LD 22 - issp	
Capture the print out for the user DN in LD 11	
Capture the print out for the TN configured for this DN (do both for all TNs, including the TLSV)	
Capture the DSC configuration for the TLSV (configured for the Hot P 1)	
In LD 48, perform the command stat elan	
Provide the print out for the SIP Route and all related RLI/DMI	

Table 50
NRS configuration information

	Check
NRS configuration	
Print capture of the Signaling Server endpoint configuration	
Print capture of the MCM endpoint configuration	
Print capture of the Routing Entries for the MCM endpoint	

Table 51
MCM configuration information

	Check
Send the MCM.ini file	

Table 52
OCS configuration information

	Check
The FQDN name of the Proxy server and the IP address	
The FQDN name of the Pool and the IP name	
The VIP of the Load Balancer	
On the Proxy Server capture Routing and for each route, Edit it and capture the screen	
On the Pool, capture Routing for each route, Edit it and get a screen capture	
On the Proxy Server, get a screen capture of Host Authorization	
On the Pool, get a screen capture of Host Authorization	
Front End server Properties, General tab, Mutual TLS/TLS row, Edit	
Front End server Properties, Security tab	
OCS Proxy Properties, General tab, Mutual TLS/TLS row, Edit	
OCS Proxy Properties, Security tab	

Table 53
Active Directory configuration information

	Check
Print Capture of the OCS user for the General Tab	
Print Capture of the OCS user for the Office Communications Server	
Print Capture of the OCS user for the Office Communication, Advanced Settings	

Table 54
Tracing information

	Check
An example AML trace on the Call Server (if it is a problem regarding the RCC feature not able to control the telephone)	
An example Signaling Server trace: SIPCallTrace (For problem related to SIP Gateway)	
An example Signaling Server trace: SIPCallTrace (For problem related to SIP Gateway)	
An example Signaling Server trace: SIPCTITrace (For problem related to SIP CTI)	
An example MCM.log with the log level = SIP + Debug for the failed call scenario (to reset the trace: put the trace level to none, delete the MCM.log file and put back the level to Debug)	

Appendix

Call Flow and protocol details

Contents

This section contains information about the following topics:

[“Overview” \(page 267\)](#)

[“Message sequence” \(page 268\)](#)

[“Call flow” \(page 269\)](#)

Overview

The Converged Office feature provides interworking between Nortel and Microsoft products. It addresses the market need of our customers who want to use Microsoft client software for their multimedia needs while continuing to use the Business Grade Telephony of the Nortel IP PBX.

The software component introduced to implement this functionality is the TR/87 Front End application that resides on the Signaling Server.

The same TR/87 FE that supports the Office Communicator client also serves as a core component of the SIP Contact Center architecture.

From the perspective of the TR/87 FE, all client types are transparent, whether Office Communicator, a TR/87 session initiated by the Contact Center Manager server (CCMS), or some other SIP UA.

Within the scope of Communication Server 1000 TR/87 supported services and events noted in this document, all operations performed on the telephone are directly reflected in the client and vice versa. Similarly, all phone restrictions applicable to a physical TN also apply to the soft client that is issuing commands on behalf of a controlled DN.

Message sequence

TR/87(4) is an ECMA Technical Report that describes the use of SIP as a transport of service requests and events defined by the ECMA-269(5) specification as XML bodies within SIP messages. The ECMA-323(6) specification defines the XML format of ECMA-269 services and events.

The Front End (FE) application conforms to the minimum subset of the TR/87 specification defined for Office Communications Server 2007 interworking and those components necessary to support the next generation SIP Contact Center requirements.

Figure 106 "Message sequence diagram - CSTA Session Establishment and Monitor Start" (page 268) shows the expected message flow for establishing and monitoring a CSTA session as defined by TR/87.

Figure 106
Message sequence diagram - CSTA Session Establishment and Monitor Start




Figure 107 "SIP INFO message with ECMA-323 content" (page 269) is an example of a SIP INFO message with ECMA-323 content.

Figure 107
SIP INFO message with ECMA-323 content

```

INFO fe1_cs1000@lcs2005s.corp.nortel.com
Via: SIP/2.0/TCP 157.56.66.156:16714
Max-Forwards: 70
From:<sip:alice@microsoft.com>;tag=0d9280080ada4a1ea504f7d78d434336;epid=5fc880096d
To:<sip:fe1_cs1000@lcs2005s.corp.nortel.com>;tag=3f181801fc9d4fab27ef7d89bd28f9f
Call-ID: fdbcb6a6184a4e92a5f001865f84a2c6@157.56.66.156
CSeq: 2 INFO
Contact: <sip:alice@microsoft.com:16714>
Contact:<sip:alice@microsoft.com:9609;maddr=47.130.16.136;transport=tcp>;proxy=replace
User-Agent: RTC/1.2
Content-Type: application/csta+xml
Content-Disposition: signal; handling=required
Content-Length: 189
<?xml version="1.0" encoding="UTF-8"?>
<MakeCall
xmlns="http://www.ecma-international.org/standards/ecma-323/csta/ed3.">
<callingDevice>tel:+14257777777</callingDevice>
<calledDirectoryNumber>tel:65000;phone
context=microsoft.com</calledDirectoryNumber>
</MakeCall>

```

Call flow

This section illustrates the call flow sequence for the Telephony Gateway and Services and Remote Call Control with Mediation Server present.


Telephony Gateway and Services call flow

This section explores dual forking call flows in different scenarios when Mediation Server is present.

This scenario as illustrated in [Figure 108 "Inbound call to OC client with SPS, OC client answers"](#) (page 270) depicts a configuration of a UDP dialing plan on the Communication Server 1000 and the presence of an SPS component on the network. A Communication Server 1000 user dials 5555 which is the phone belonging to user Bob in the demo.com domain. Bob accepts the call from his OC client.

Note: This scenario would also apply if the inbound call originated from the PSTN.

Figure 108
Inbound call to OC client with SPS, OC client answers



Incoming calls to OC 2007 can originate directly from a phone behind the Communication Server 1000 where the request URI represents the destination.

Incoming calls can also come from a TLSV, where the Request URI is a service DN used to route the call to OCS 2007, and the actual destination is determined by a special header (x-nt-ocn) that contains the destination DN. MCM checks for the x-nt-ocn and routes the call accordingly.

Telephony Services (TLSV) configuration provides additional Office Communicator features such as forwarding to voice mail, and so on. Configuration of TLSV is performed through station administration tools.

This scenario as illustrated in [Figure 109 "Inbound call to OC client with SRS, phone answers"](#) (page 271) depicts the presence of an SRS component on the network (instead of SPS).


For example, A Communication Server 1000 user dials 5555 which is the phone belonging to user Bob in the demo.com domain. Bob accepts the call from his phone (instead of the OC client).

ATTENTION

This scenario would also apply if the inbound call originated from the PSTN.

Figure 109

Inbound call to OC client with SRS, phone answers




The next scenario as illustrated in [Figure 110 "Direct inbound call to OC client, OC client answers"](#) (page 272) depicts a limited deployment configuration where the MCM is pointing directly to the Communication Server 1000. The deployment of SPS or SRS are not present. A Communication Server 1000 user dials 5555 which is the phone belonging to user Bob in the demo.com domain. Bob accepts the call from his OC client.

ATTENTION

This scenario would also apply if the inbound call originated from the PSTN.

Figure 110
Direct inbound call to OC client, OC client answers




This scenario as illustrated in [Figure 111 "Outbound call from OC client to another client, phone answers"](#) (page 273) depicts the prevention of dual forking in a configuration where both users are registered to the same Communication Server 1000 with the presence of SPS. Joe calls Bob from his OC client. Bob accepts the call from his phone.

ATTENTION

In this call flow scenario, homing operation is performed on the Communication Server 1000 to validate the caller's (Joe) permissions before proceeding with the call.

Figure 111
Outbound call from OC client to another client, phone answers




This scenario as illustrated in [Figure 112 "Outbound call from OC client to another OC client, OC client answers"](#) (page 274) depicts a configuration with a CDP dialing plan and the presence of the SRS component on the network. Joe calls Bob from his OC client. Bob accepts the call from his OC client.

ATTENTION

For the CDP dialing plan to work, the entire network must be configured with CDP. Therefore, it can only be deployed on small networks.


Figure 112
Outbound call from OC client to another OC client, OC client answers



Call Forward by OC client

This scenario depicts a situation where the Communication Server 1000 phone dials the phone number of an OC client Bob and is forwarded to another client Joe. Bob's twin phone number is x5555 and Joe's number is X3333.


Figure 113
Call Forward call flow by OC client



Remote Call Control Call Flow

Figure 114 "Remote Call Control Session Establishment through SRS" (page 276) illustrates the Remote Call Control Session Establishment through SRS.

Figure 114
Remote Call Control Session Establishment through SRS



Supported features

Table 55
SIP CTI supported features

Feature	Supported by CS 1000 TR/87 FE	Supported by Office Communicator 2007
Call Control Events		
17.2.3 - Conference	X	X
17.2.4 - Connection Cleared	X	X
17.2.5 - Delivered	X	X
17.2.7 - Diverted	X	X
17.2.8 - Established	X	X
17.2.9 - Failed	X	X
17.2.10 - Held	X	X
17.2.14 - Originated	X	X
17.2.16 - Retrieved	X	X
17.2.18 - Transferred	X	X
Call Associated Services		
18.1.4 - Generate Digits	X	X

Table 55
SIP CTI supported features (cont'd.)

Feature	Supported by CS 1000 TR/87 FE	Supported by Office Communicator 2007
Call Associated Events		
18.2.5 - Service Completion Failure	X	X
Logical Device Features		
22.1.9 - Get Do Not Disturb	X (Release 5.5)	
22.1.10 - Get Forwarding	X	X
22.1.17 - Set Do Not Disturb		
22.1.18 - Set Forwarding	X	X
Logical Device Feature Event		
22.2.12 - Do Not Disturb	X	
22.2.13 - Forwarding	X	X
Capability Exchange Services		
13.1.1 - Get CSTA Features	X	X
System Services		
14.2.1 - Request System Status	X	X
Monitoring Services		
15.1.2 - Monitor Start	X	X
15.1.3 - Monitor Stop	X	X
Call Control Services		
17.1.2 - Alternate Call		X
17.1.3 - Answer Call	X	X
17.1.8 - Clear Connection	X	X
17.1.9 - Conference Call	X	
17.1.10 - Consultation Call	X	X

Table 55
SIP CTI supported features (cont'd.)

Feature	Supported by CS 1000 TR/87 FE	Supported by Office Communicator 2007
17.1.11 - Deflect Call	X	X
17.1.15 - Hold Call	X	X
17.1.18 - Make Call	X	X
17.1.21 - Reconnect Call		X
17.1.22 - Retrieve Call	X	X
17.1.25 - Single Step Transfer Call	X	X
17.1.26 - Transfer Call	X	X

Appendix

Configuration Examples

Contents

- [“Introduction” \(page 279\)](#)
- [“Standard Edition” \(page 279\)](#)
- [“Enterprise Edition” \(page 305\)](#)
- [“Host Authorization” \(page 313\)](#)
- [“Routing” \(page 314\)](#)
- [“Configuring DNS” \(page 316\)](#)
- [“Active Directory configuration” \(page 318\)](#)
- [“Installing and configuring MCM” \(page 319\)](#)
- [“Signaling Server checklist” \(page 322\)](#)
- [“Configuring NRS” \(page 323\)](#)

Introduction

As described in the Planning and Engineering chapter, small, medium, and large networks require different editions of Office Communications Server (OCS) 2007. This appendix contains configuration examples for both Standard Edition and Enterprise Editions of OCS 2007.

Standard Edition

This section provides information on how to configure and troubleshoot the Converged Office solution running the Standard Edition OCS 2007. This sample configuration is for a small network deployment.

Setting up the lab


Follow these steps to ensure the lab is set up correctly:

Setting up the lab

Step	Action
1	Confirm that the CS 1000 server is version 5.5 with the Product Enhancement Package or a later version.
2	Confirm that the Signaling Server is version 5.5 or later with all patches as required in the Product Bulletin
3	Confirm that you have the OCS 2007 Standard Edition server .
4	Confirm that you have MCM 3.5.
--End--	

Figure 115 "Overview of lab setup" (page 280) illustrates how to set up a lab for Converged Office.

Figure 115
Overview of lab setup



Collecting required data

Collect the required data listed in the following three tables before you begin to configure the Converged Office solution. The information entered here can be used to verify configuration settings later on.

Table 56
Microsoft Active Directory

Required information	Record your information	For example
User SIP URI		chrissmith@ocs2007a.corp.nortel.com
Server URI		sip:2070;phone-context=cdp.udp@test.com
Line URI		tel:+16139675000;ext=2070

Table 57
Network Routing Service (NRS)

Required information	Record your information	For example
IP-address Primary SPS		47.11.56.25
IP-address Secondary SPS		Not used
Node IP-address		47.11.56.24
MCM endpoint name		mcm@ocs2007a.corp.nortel.com
Communication Server 1000 SIP gateway endpoint name		ocs2007_node_A@ocs2007a.corp.nortel.com
Routing Entry for UEXT		CDP: 888-MCM CDP: 20 and 21 > OCS2007_node A
Service domain		ocs2007a.corp.nortel.com
Level 1 domain		udp
Level 0 domain		cdp.udp

Table 58
Element Manager for Signaling Server

Required information	Record your information	For example
Communication Server 1000 SIP gateway endpoint name		ocs2007_node_A@ocs2007a.corp.nortel.com
SIP Domain name		ocs2007a.corp.nortel.com
SIP URI map, Private/UDP domain name		udp
SIP URI map, Private/CDP domain name		cdp.udp
SIP CTI Service, Service enabled		Yes
SIP CTI Service, Customer Number		0

SIP CTI Service, International Calls As National		Yes
SIP CTI Service, National Prefix		0
SIP CTI Service, International Prefix		00
SIP CTI Service, Dialing Plan		cdp
SIP CTI Service, Calling Device URI Format		sip:2070;phone-context=cdp.udp@test.com
SIP CTI Service, Country Code		33
SIP CTI Service, National/ Number of digits to strip		1

Table 59
MCM

Required Information	Record your information	For example
Registration ID		mcm@ocs2007a.corp.nortel.com
Called Phone Context		cdp.udp

Configuring the Call Server

Use the following procedure to check the configuration of the Call Server.

Checking the Call Server configuration

Step	Action
1	Check the version of the Communication Server 1000 Call Server. The Communication Server 1000 Call Server version must be release 5.5.
2	Check the Product Bulletin .
3	In LD 22, confirm that AST , TLSV , and SIP CTI TR87 licenses are available.

Table 60
LD 22---check for licenses

Prompt	Response	Description
REQ	slt	

Screen output:

```

ANALOGUE TELEPHONES 32767 LEFT 32767 USED 0
CLASS TELEPHONES 32767 LEFT 32767 USED 0
DIGITAL TELEPHONES 32767 LEFT 32767 USED 0
DECT USERS 32767 LEFT 32767 USED 0
IP USERS 32767 LEFT 32756 USED 11
BASIC IP USERS 32767 LEFT 32767 USED 0
TEMPORARY IP USERS 32767 LEFT 32767 USED 0
DECT VISITOR USER 10000 LEFT 10000 USED 0
ACD AGENTS 32767 LEFT 32767 USED 0
MOBILE EXTENSIONS 32767 LEFT 32767 USED 0
TELEPHONY SERVICES 32767 LEFT 32761 USED 6
CONVERGED MOBILE USERS 32767 LEFT 32767 USED 0
NORTEL SIP LINES 32767 LEFT 32767 USED 0
THIRD PARTY SIP LINES 32767 LEFT 32767 USED 0
PCA 32767 LEFT 32762 USED 5

AST 32767 LEFT 32756 USED 11
ITG ISDN TRUNKS 32767 LEFT 32767 USED 0
H.323 ACCESS PORTS 32767 LEFT 32767 USED 0
AST 32767 LEFT 32761 USED 6
SIP CONVERGED DESKTOPS 32767 LEFT 32767 USED 0
SIP CTI TR87 32767 LEFT 32760 USED 7
SIP ACCESS PORTS 32767 LEFT 32753 USED 14
RAN CON 32767 LEFT 32767 USED 0
MUS CON 32767 LEFT 32767 USED 0
TNS 32767 LEFT 32639 USED 128
ACDN 24000 LEFT 24000 USED 0
AML 16 LEFT 14 USED 2 IDLE_SET_DISPLAY NORTEL
LTID 32760 LEFT 32760 USED 0
RAN RTE 512 LEFT 512 USED 0
ATTENDANT CONSOLES 32767 LEFT 32767 USED 0
BRI DSL 10000 LEFT 10000 USED 0
MPH DSL 100 LEFT 100 USED 0
DATA PORTS 32767 LEFT 32767 USED 0
PHANTOM PORTS 32767 LEFT 32767 USED 0
TRADITIONAL TRUNKS 32767 LEFT 32767 USED 0
DCH 255 LEFT 254 USED 1

```

- 4 Also in LD 22, confirm that the MS_CONV and TLSV package is present (this package is required).

Table 61
LD 22-MS_CONV and TLSV packages

Prompt	Response	Description
REQ	prt	
TYPE	pkg 408	
TYPE	pkg 413	

Screen output:

MS_CONV 408

TLSV 413

- 5 Ensure that the VSID and the ELAN ID are **greater than or equal to 32** and that the SECU parameter is configured to **YES** for ELAN and for VAS configuration.

Table 62
LD 22–Check VSID and ELAN ID configuration

Prompt	Response	Description
REQ	prt	
TYPE	vas	

Screen output:

ELAN 032
SECU YES
INTL 0001
MCNT 9999

- 6 In LD 20, confirm that STRI/STRO is **WNK** for SIP Trunk configuration.

ATTENTION

The screen output shown here may differ, depending on the setup used.

Table 63
LD 20–SIP Trunk configuration

Prompt	Response	Description
REQ	prt	
TYPE	tnb	
TN	156 0 0 0	
DATE	<enter>	
PAGE	<enter>	
DES	<enter>	

Screen output:

DES SIP
TN 156 0 00 00 VIRTUAL
TYPE IPTI
CDEN 8D
CUST 0
XTRK VTRK
ZONE 000
TRK ANLG
NCOS 0
RTMB 62 1

```

CHID 1
TGAR 0
STRI/STRO WNK WNK
SUPN YES
AST NO
IAPG 0
CLS UNR DTN WTA LPR APN THFD XREP P10 NTC
TKID
AACR NO
DATE 5 DEC 2006

```

- 7 In LD 21, check that NCNA and NCRD are configured to **YES** and that SIGO is **ESN5** in the SIP Route Configuration. For example:

Table 64
LD 21–SIP Route configuration

Prompt	Response	Description
REQ	prt	
TYPE	rdb	
CUST	0	
ROUT	62	

Screen output:

```

TYPE RDB
CUST 00
ROUT 62
DES SIP
TKTP TIE
NPID_TBL_NUM 0
ESN NO
RPA NO
CNVT NO
SAT NO
RCLS EXT
VTRK YES
ZONE 000
PCID SIP
CRID YES
NODE 81
DTRK NO
ISDN YES
MODE ISLD
DCH 63
IFC SL1
PNI 00001
NCNA YES
NCRD YES

```

TRO YES
FALT NO
CTYP UKWN
INAC YES
ISAR NO
DAPC NO
PTYP ATT
...
DEXT NO
ANTK
SIGO ESN5
MFC NO
...

- 8 For TN configuration in LD 20, confirm configuration of **AST, TR87A, TLSV, and CDMR Class of Service**. Confirm configuration of **MARP** for the telephone.

ATTENTION

The screen output shown here may differ depending on the setup used.

Table 65
LD 20–TN configuration

Prompt	Response	Description
REQ	prt	
TYPE	dnb	
CUST	0	
DN	2070	
DATE	<enter>	
PAGE	<enter>	
DES	<enter>	

Screen output:

DN 2070
CPND
CPND_LANG ROMAN
XPLN 16
DISPLAY_FMT FIRST, LAST
TYPE SL1
TN 100 0 03 04 V KEY 00 MARP DES DLOCS2 3 DEC 2007
(2004P2)
TN 100 0 03 05 V KEY 00 DES OCS 16 APR 2008
(UEXT)
NACT

Table 66
LD 20

Prompt	Response	Description
REQ	prt	
TYPE	tnb	
TN	152 0 0 14	
DATE	<enter>	
PAGE	<enter>	
DES	<enter>	

Screen output:

```

DES CDLCS
TN 152 0 00 14 VIRTUAL
TYPE I2004
CDEN 8D
CTYP XDLC
CUST 0
ZONE 000
FDN
TGAR 0
LDN NO
NCOS 0
SGRP 0
RNPG 0
SCI 0
SSU
LNRS 16
XLST 0
SCPW 2070
SFLT NO
CAC_MFC 0
CLS CTD FBD WTA LPR MTD FND HTD TDD HFD CRPD
MWD LMPN RMMD SMWD AAD IMD XHD IRD NID OLD VCE DRG1
POD DSX VMD CMSD SLKD CCSA-CSI SWD LNA CNDA
CFTD SFD MRD DDV CNID CDCA MSID DAPA BFED RCBF
ICDD CDMD LLCN MCTD CLBD AUTU
GPUD DPUD DNDA CFXD ARHD FITD CLTD ASCD
CPFA CPTA HSPD ABDD CFHD FICD NAID BUZZ
UDI RCC HBTD AHA IPND DDGA NAMA MIND PRSD NRWD NRCD
NROD
DRDD EXR0
USRD ULAD CCBD RTDD RBDD RBHD PGND OCBD FLXD FTTC
DNDY DNO3 MCBN
FDSD NOVD VOLA VOUD CDMR ICRD MCDD T87A KEM2
CPND_LANG ENG
BFTN 152 0 01 00
HUNT
PLEV 02

```

CSDN
AST 00
IAPG 0

- 9 Check LD 20 to confirm that UEXT with TLSV subtype is activated. If not, configure LD 15 to PCA **ON** This allows the incoming call to twin the UEXT and make the SIP Gateway call work. Use LD 11 to configure each user with UEXT.

Table 67
LD 20–Confirm UEXT is activated

Prompt	Response	Description
REQ	prt	
TYPE	FTR_DATA	
CUST	0	

Screen output

...
PCA ON
...

Table 68
LD 11–Confirm configuration of UEXT with TLSV subtype for SIP Gateway

Prompt	Response	Description
REQ	prt	
TYPE	UEXT	
TN	96 0 8 15	
UXTY	TLSV	
DATE	<enter>	
PAGE	<enter>	
DES	<enter>	

The screen output shown here may differ depending on the setup used.

Screen output:

DES OCS
TN 096 0 08 15 VIRTUAL
TYPE UEXT
CDEN 8D
CTYP XDLC
CUST 0
UXTY TLSV
UXID
NUID
NHTN

CFG_ZONE 000
CUR_ZONE 000
NCOS 0
ERL 0
ECL 0
FDN
TGAR 1
LDN NO
NCOS 0
SGRP 0
RNPG 0
SCI 0
SSU
XLST
SFLT NO
CAC_CIS 0
CAC_MFC 0
CLS CTD FBD WTA LPR MTD FND HTD TDD HFD CRPD MWD LMPN RMMD
SMWD AAD IMD XHD IRD NID OLD VCE DRG1 POD DSX VMD SLKD CCSD
SWD LND CNDD CFTD SFD MRD DDV CNID CDCA MSID DAPA BFED
RCBD ICDD CDMD LLCN MCTD CLBD AUTU GPUD DPUD DNDD CFXD
ARHD CLTD ASCD CPFA CPTA ABDD CFHD FICD NAID DNAA BUZZUDI
RCC HBTB AHA IPND DDGA NAMA MIND PRSD NRWD NRCD NROD UDI
RCC HBTB AHA IPND DDGA NAMA MIND PRSD NRWD NRCD NROD DRDD
EXR0USMD USRD ULAD CCBF RTDD RBDD RBHD PGND FLXD FTTC DNDY
DNO3 MCB FDSF NOVD VOLA VOUD CDMR ICRD MCDD T87D MSNV FRA
PKCH
CPND_LANG ENG
HUNT
PLEV 02
DANI NO
AST
IAPG 0
AACS NO
AACS NO
ITNA NO
DGRP
MLWU_LANG 0
MLNG ENG
DNDR 0
KEY 00 SCR 2070 0
CPND
ANIE 0
01 HOT P 3 888
02
03
04
05
06
07
08

09
10
11
12
13
14
15
16
17 TRN
18 AO6
19 CFW 16
20 RGA
21 PRK
22 RNP
23
24 PRS
25 CHG
26 CPN
27
28
29
30
31

Date 16 APR 2008

Table 69
LD 11 — Configure UEXT with subtype TLSV

Prompt	Response	Description
REQ	CHG/NEW	Change or create a new mobile universal extension.
TYPE	UEXT	Universal Extension—This parameter indicates this is a universal extension unit.
TN	L S C U	Universal Extension TN
CUST	0-99	Customer number
UXTY	TLSV	UEXT subtype, this is prompted only for TYPE=UEXT. TLSV – Telephony Services unit Note: the UXTY cannot be changed for a UEXT. The unit must be removed and reconfigured. MOBX units cannot be copied.

Prompt	Response	Description
KEY 0 SCR	<SCR DN>	Prime DN can be up to seven-digits
KEY 01 HOT P	nn yyyzzzz	<nn> is the maximum number of digits for HOTP DN yyyzzzz is the access code and phone number of OCS target DN. This can be up to 31-digits.

Screen Output:

```

....
TYPE UEXT
CDEN 8D
CTYP XDLC
CUST 0
UXTY TLSV
....
KEY 00 SCR 2070 0
01 HOT P 3 888

```

- 10 Confirm that AST is not configured.
- 11 Configure TR87D and CDMR Class Of Service.
- 12 Confirm that this UEXT is not configured as MARP.
- 13 Configure Hot P for SIP Gateway calls.
- 14 Configure CLS PCAM.
- 15 Confirm **DSC** configuration. Create a DSC to route the call to the SIP route using the RL1.

Table 70
LD 87–Confirm DSC configuration

Prompt	Response	Description
REQ	prt	
CUST	0	
FEAT	cdp	
TYPE	dsc	
DSC	888	

ATTENTION

The screen output shown here may differ depending on the setup used.

Screen Output

```

FLEN 3
DSP LSC

```

RRPA NO
RLI 1
CCBA NO
NPA
NXX

--End--


Signaling Server checklist

Use the following procedure to confirm the correct configuration of the Signaling Server.

Checking the configuration of the Signaling Server


Step	Action
1	Confirm that the Signaling Server is version 5.5. Refer to the Product Bulletin for any required patches for Converged Office.
2	Confirm that your installation meets the memory requirements. The maximum number of SIP CTI/TR87 users on a single Signaling Server is 5000. The Standard Signaling Server memory is 1 gigabyte (minimum requirement) and is required in the following scenarios: a if SIP CTI/TR87 is co-resident with PD/RL/CL application b if SIP CTI/TR87 is co-resident with H.323/SIP GW serving more than 200 ports, or co-resident with Terminal Proxy Server serving more than 1000 IP users
3	Confirm the configuration of the Front End server and OCS Proxy server. Right-click on My Computer and choose the Computer Name tab. For more information, see Figure 116 "FQDN of the OCS 2007 Front End server" (page 293).

Figure 116
FQDN of the OCS 2007 Front End server



- 4 Define the IP address of the server acting as DNS. For example, in [Figure 117 "DNS configuration on the Signaling Server" \(page 293\)](#), the IP address is **47.11.56.114**.

Figure 117
DNS configuration on the Signaling Server



- 5 Ensure that the SIP GW settings match the settings as shown in [Figure 118 "SIP GW Settings" \(page 294\)](#).

Figure 118
SIP GW Settings

NORTEL CS 1000 ELEMENT MANAGER

SIP GW Settings

TLS Security

Security Policy: Security Disabled

TLS Security Port: 5061 (1 - 65535)

Client Authentication: ☐

Re-negotiation: ☐

X.509 Certificate Authentication: ☐

Primary Proxy or Re-direct Server

Primary Proxy or Redirect (TLAN) IP address: 47.11.56.25

Port: 5060

Supports Registration: ☒

Primary CDS Proxy or Re-direct server flag: ☐

Transport Protocol: TCP

Secondary Proxy or Re-direct Server

Secondary Proxy or Redirect (TLAN) IP address: 0.0.0.0

Port: 5060

Supports Registration: ☐

Secondary CDS Proxy or Re-direct server flag: ☐

Transport Protocol: TCP

CLID Parameters

Country Code (CCC):

6

Confirm that the SIP URI Map settings match the settings as shown in [Figure 119 "SIP URI Map" \(page 295\)](#).

Figure 119
SIP URI Map

The screenshot shows the 'CS 1000 ELEMENT MANAGER' interface with the 'SIP URI Map' tab selected. The configuration table lists various domain names and their corresponding values. The 'Public E.164/National domain name' and 'Public E.164/Subscriber domain name' fields have a green asterisk to their right, indicating they are required or validated. The 'Public E.164/Unknown domain name' field is highlighted with a blue selection bar.

CS 1000 ELEMENT MANAGER	
+ SIP URI Settings	
SIP URI Map	
Public E.164/National domain name	+1 *
Public E.164/Subscriber domain name	+613 *
Public E.164/Unknown domain name	PublicUnknown
Public E.164/Special Number domain name	PublicSpecial
Private/UDP domain name	udp
Private/CDP domain name	cdp.udp
Private/Special Number domain name	PrivateSpecial
Private/Unknown (vacant number routing) domain name	PrivateUnknown
Unknown/Unknown domain name	UnknownUnknown
+ SIP CD Services	

7

Confirm that the SIP CTI Services settings match the settings as shown in [Figure 120 "SIP CTI Services" \(page 296\)](#).

Figure 120
SIP CTI Services

CS 1000 ELEMENT MANAGER

Help

- SIP CTI Services

Service Enabled☒

Support TLS Endpoints Only☐

CTI Settings

Customer Number

(0 - 99)

Maximum Associations per DN

Place International Calls Within This Country As National Calls☒

Dial Plan Prefix

National Prefix

International Prefix

Location Code Call Prefix

Special Number Prefix

Subscriber Prefix

CLID Parameters

Dialing Plan

Calling Device URI Format

Home Location Code

Country Code (CCC)

Area Code (AreaCode)

Note:The NPA in North America

#Digits to Strip

Prefix to Insert

Format of CLID

Subscriber Number (SN)

National Number (NN)

International number

+<CCC><AreaCode><SN>

+<CCC><NN>

+<International number>

--End--

Configuring Network Routing Service (NRS)

Use the following procedure to check the configuration of NRS.

Checking NRS configuration

Step	Action
1	Check the Signaling Server and MCM Endpoints Status as shown in Figure 121 "Signaling Server and MCM Endpoints status on NRS" (page 297).

Nortel Communication Server 1000
Nortel Converged Office Fundamentals — Microsoft Office Communications Server 2007
NN43001-121 02.15 9 September 2009

Copyright © 2007-2009 Nortel Networks. All Rights Reserved.

Figure 121
Signaling Server and MCM Endpoints status on NRS

NETWORK ROUTING SERVICE MANAGER [Help](#) | [Logout](#)

Managing: ☒ Active database **47.11.56.25**
☐ Standby database [Numbering Plan](#) » Endpoints

Search for Endpoints

Enter an endpoint ID (use * for all) and click Search. You may narrow the search by specifying a particular domain.

Endpoint ID:

Limit results to Domain: All service domains / All L1 domains / All L0 domains

Results per page: 100

Gateway Endpoints (18) **User Endpoints (0)**

[Refresh](#)

ID	Supported Protocols	Call Signaling IP	Description	# of Routing Entries	Context
1 ☐ MCM	Dynamic SIP endpoint	47.11.56.54	MCM on OCS Proxy	1	ocs2007a.corp.nortel.com / udp / cdp
2 ☐ MCM-Proxy2	Dynamic SIP endpoint	47.11.236.39		1	ocs2007a.corp.nortel.com / udp / cdp
3 ☐ OCS2007NODEB	RAS H.323 endpoint / Dynamic SIP endpoint	Not registered / 47.11.56.88		1	ocs2007a.corp.nortel.com / udp / cdp
4 ☐ OCS2007_NODE_A	RAS H.323 endpoint / Dynamic SIP endpoint	Not registered / 47.11.56.24	OCS2007NODEA	2	ocs2007a.corp.nortel.com / udp / cdp
5 ☐ OCSProxy	Dynamic SIP endpoint	Not registered	OCS2007	2	lcs2005s.corp.nortel.com /

1 - 18 of 18 Gateway Endpoint(s) [First](#) | [Previous](#) | [Next](#) | [Last](#)

Ensure that all the endpoints are registered (the endpoints must be listed as "Dynamic Sip" under the Supported Protocols column and have an IP address under the Call Signaling IP column in [Figure 121 "Signaling Server and MCM Endpoints status on NRS" \(page 297\)](#).

- 2 Check the UEXT Routing Entry as shown in [Figure 122 "Routing Entry" \(page 298\)](#) (refer to the information you recorded in [Table 57 "Network Routing Service \(NRS\)" \(page 281\)](#)). To configure UEXT for SIP Gateway, see step 9 in "Checking the Call Server configuration" (page 282).

Figure 122
Routing Entry

NETWORK ROUTING SERVICE MANAGER

Help | Logout

Managing: ☒ Active database 47.11.56.25

☐ Standby database

[Numbering Plan > Routes](#)

Search for Routing Entries

Enter a DnPrefix and Dn Type (use * for all) and click Search. You may narrow the search by specifying a particular domain.

DN Prefix: *

DN Type: All DN Types

Limit results to Domain: All service domains

/ All L1 domains

/ All L0 domains

Endpoint Name: All gateway endpoints

Results per page: 100

Search

Routing Entries (25)

Default Routes (0)

Routing test...

Refresh

☐ DN Prefix	DN Type	Route Cost	SIP URI Phone Context	Context
1 ☐ 10	Private level 0 regional (CDP steering code)	1	cdp1.udp1	lcs2005s.corp.nortel.com / udp1 / cdp1 / node3228
2 ☐ 11	Private level 0 regional (CDP steering code)	1	cdp1.udp1	lcs2005s.corp.nortel.com / udp1 / cdp1 / um_node134
3 ☐ 2	Private level 0 regional (CDP steering code)	1	cdp1.udp1	lcs2005s.corp.nortel.com / udp1 / cdp1 / node1220
4 ☐ 20	Private level 0 regional (CDP steering code)	1	cdp.udp	ocs2007a.corp.nortel.com / udp /


1 - 25 of 25 Routing Entry(ies)

First | Previous | Next | Last

- 3
- Check the OCS 2007 Standard Edition configuration.

In Host Authorization for an OCS 2007 Standard Edition, configure the IP Address of the OCS Proxy server. (see [Figure 123 "Host Authorization"](#) (page 299).

Figure 123
Host Authorization



- 4 Check the OCS Proxy server configuration. See [Table 57 "Network Routing Service \(NRS\)" \(page 281\)](#), the OCS Proxy IP is 47.11.56.54, and the Node IP is 47.11.56.24.

--End--

Active Directory user configuration

Use the following procedure to check the Active Directory user configuration.

Checking the settings of Active Directory user configuration

Step	Action
1	Check the user configuration by going to Active Directory, select the user and right-click on User Properties. Select the General tab. Complete the following actions: Compare and match your user properties settings with those in Figure 124 "General user properties" (page 300). The

telephone number in the Telephone Number field must be the same as the information recorded in [Table 56 "Microsoft Active Directory" \(page 281\)](#).

Figure 124
General user properties

The screenshot shows the 'Chris Smith Properties' dialog box with the 'General' tab selected. The 'Telephone number' field is circled in red and contains the value '2070'. The 'E-mail' and 'Web page' fields are empty. The 'OK', 'Cancel', 'Apply', and 'Help' buttons are at the bottom.

Member Of	Dial-in	Environment	Sessions
Remote control	Terminal Services Profile	COM+	Communications
General	Address	Account	Profile
Telephones	Organization		

Chris Smith

First name: Initials:

Last name:

Display name:

Description:

Office:

Telephone number:

E-mail:

Web page:

- b** Click on the **Communications** tab. Compare and match your settings in OCS 2007 Office Communications user properties with those in [Figure 125 "Communications properties" \(page 301\)](#). Ensure the SIP Sign-in name is the same as the information recorded in [Table 56 "Microsoft Active Directory" \(page 281\)](#).

Figure 125
Communications properties

Chris Smith Properties

General | Address | Account | Profile | Telephones | Organization
 Member Of | Dial-in | Environment | Sessions
 Remote control | Terminal Services Profile | COM+ | **Communications**

☒ **Enable user for Office Communications Server**

Sign-in name:
 sip:chrissmith @ ocs2007a.corp.nortel.com

Server or pool:
 ocs2007a-ocsfe1.ocs2007a.corp.nortel.com

Meetings
☒ Allow anonymous participants
 Policy: Default Policy
 View...

Note: Meeting settings cannot be changed unless the global setting allows per user configuration.

Additional options: Configure...

OK Cancel Apply Help

- c Click the **Communications** tab and click the **Configure** button. Compare and match your settings with those in [Figure 126 "User Options" \(page 302\)](#). The Server URI and the Line URI must be the same as the information recorded in [Table 56 "Microsoft Active Directory" \(page 281\)](#).

Figure 126
User Options

User Options

Telephony

Select a telephony option. These settings affect only those calls that are routed through IP-PSTN or remote call control gateways.

☐ Enable PC-to-PC communication only

☐ Enable Remote call control

☒ Enable Enterprise Voice

☐ Enable PBX integration

Note: To enable both remote call control and PBX integration, you must specify a Server URI below.

Policy:

Default Policy

View...

Server URI:

sip:2070;phone-context=cdp.udp@test.com

Line URI:

tel+16139675000;ext=2070

Federation

☐ Enable federation

☐ Enable remote user access

☐ Enable public IM connectivity

Archiving

☐ Archive internal IM conversations

☐ Archive federated IM conversations

Note: Archiving settings cannot be changed unless the global setting allows per user configuration.

☒ Enable enhanced presence

Note: Enhanced presence cannot be changed once it has been set.

OK

Cancel

Help

Checking the MCM installation and configuration

Check that the MCM is properly installed and configured.

Checking the MCM installation and configuration

Step	Action
1	On the MCM, check that the user is a member of the RTC Server Applications and RTC Server Local Group.
2	For MCM Application, confirm that MCM running and for the Default OCS applications, confirm that IM URL Filter and Routing


Application are running (see [Figure 127 "MCM Application" \(page 303\)](#)).

If the MCM application is not running:

Confirm that MCM is configured with the MCM user groups RTC Server Local Group and RTC Server Applications.

- Confirm that the MCM user password is correct.
- Check the Event logs to find out why MCM is not running.

Figure 127
MCM Application



3

See [Figure 128 "MCM Gateway Endpoint configuration" \(page 304\)](#) and [Figure 129 "MCM Configuration screen" \(page 305\)](#) to check for proper MCM configuration on NRS.

--End--

Figure 128
MCM Gateway Endpoint configuration

NORTEL NETWORK ROUTING SERVICE MANAGER

«Common Manager

- System
 - NRS Server
 - Database
 - System Wide Settings
- Numbering Plans
 - Domains
 - Endpoints
 - Routes
 - Network Post-Translation
 - Collaborative Servers
- + Tools

Managing: ☒ Active database 47.11.56.25
☐ Standby database [Numbering Plan > Endpoints > Gateway Endpoint](#)

Edit Gateway Endpoint (ocs2007a.corp.nortel.com / udp / cdp)

End point name: *

Description:

Trust Node: ☒

Tandem gateway endpoint name:

Endpoint authentication enabled:

Authentication password:

E.164 country code:

E.164 area code:

E.164 international dialing access code:

E.164 international dialing code length:

E.164 national dialing access code:

E.164 national dialing code length:

E.164 local (subscriber) dialing access code:

* Required value

Figure 129
MCM Configuration screen

The screenshot shows the 'Configuration' window with the following sections:

- Network Topology:**
 - Call Server: CS 1000
 - ☐ SRS
 - ☒ SPS
 - Primary IP: 47 . 11 . 56 . 25
 - Secondary IP: 0 . 0 . 0 . 0
 - Registration ID: MCM@ocs2007a.corp.nortel.co
 - Registration IP: 47.11.56.54
 - Mode: Proxy All
 - ☐ Direct Connect
 - CS1000 SIP GW IP: 47 . 11 . 56 . 24
 - Transport: TCP Port: 5060
 - ☒ Mediation Server Routing Table
- Active Directory Configuration:**
 - ☒ Query Server Synchronize at: 03:00
 - ☐ Local Cache Synchronize Now
 - ☐ Local Cache then Query Server
 - ☐ Non Default AD/LDAP Server
 - Server IP: 0 . 0 . 0 . 0 Port:
- Network Dial Plan:**
 - Dial Plan: CDP
 - Access Code:
- SIP-CTI Authorization:**
 - ☐ Enable RCC Authorization
- Incoming Call Processing Parameters:**
 - Called Phone Context: cdp.udp
 - Called Phone Prefix Delete: 0
 - Called Phone Prefix Insert:
 - Caller Phone Prefix Delete: 0
 - Caller Phone Prefix Insert:
- Outgoing CLID Number Parameters:**
 - Prefix Delete: 0
 - Prefix Insert:
- Outgoing CLID Name Parameters:**
 - ☐ "FirstName LastName"
 - ☐ "LastName, FirstName"
 - ☐ "LastName FirstName"
 - ☒ AD Display Name

Buttons at the bottom: Ok, Cancel, Help

Enterprise Edition

This section describes the configuration of the OCS Enterprise Edition.


Overview of general lab set-up

Figure 130 "OCS Enterprise Edition General Overview" (page 306), illustrates the lab set-up, which includes:

- Call Server version 5.5
- Signaling Server version 5.5
- MCM version 3.5
- 1 DNS/Active Directory Server

- Mediation Servers
- OCS FE Server with a Pool and a Microsoft Software Load Balancer
- 1 OCS Proxy server

Figure 130
OCS Enterprise Edition General Overview



Collecting Data for Enterprise Edition

Collect the required data listed in the following four tables before you begin to configure the Converged Office solution.

ATTENTION

The FQDN field is case sensitive. Enter the exact FQDN.

ATTENTION

The Certificate is complex and its correct configuration is not described in this section. Confirm that you have configured the Certificate correctly.

Table 71
Microsoft Active Directory

Required information	Record your information	For example
User SIP URI		chrissmith@ocs2007a.corp.nortel.com
Server URI		sip:2070;phone-context=cdp.udp@test.com

Line URI		tel:+16139675000;ext=2070
Telephone number		2070

Table 72
OCS

Required information	Record your information	For example
OCS 2007 Proxy server		ocs2007a-proxy.ocs2007a.corp.nortel.com 47.11.56.54
Load Balancer Pool		ocs2007apool 47.11.56.51
OCS Enterprise Edition Front End server 1		ocs2007a-ocsfe1.ocs2007a.corp.nortel.com 47.11.56.51
OCS Enterprise Edition Front End server 2		ocs2007ocsfe2.ocs2007a.corp.nortel.com 47.11.56.52

Table 73
NRS

Required information	Record your information	For example
IP-address Primary SPS		47.11.56.25 (standalone)
IP-address Secondary SPS		Not used
Node IP-address		47.11.156.24
OCS endpoint name		mcm@ocs2007a.corp.nortel.com
Communication Server 1000 SIP gateway endpoint name		ocs2007_node_A
Routing Entry for UEXT		LOC: CDP: 888 - MCM LOC: 20 and 21 - OCS2007_node_A
Service domain		ocs2007asps.ocs2007a.corp.nortel.com
Level 1 domain		udp
Level 0 domain		cdp.udp

Table 74
Element Manager

Required information	Record your information	For example
LAN configuration, FQDN (OCS Proxy and OCS Pool)		ocs2007a-proxy.ocs2007a.corp.nortel.com
LAN configuration, IP Address (OCS Proxy and OCS Pool)		47.11.56.54

Communication Server 1000 SIP gateway endpoint name		ocs2007_node_A
SIP Domain name		ocs2007a.corp.nortel.com
SIP Gateway Endpoint name		ocs2007_node_A
SIP URI map, Private/UDP domain name		udp
SIP URI map, Private/CDP domain name		cdp.udp
SIP CTI Service, Service enabled		Yes
SIP CTI Service, Customer Number		0
SIP CTI Service, International Calls As National		Yes
SIP CTI Service, National Prefix		0
SIP CTI Service, International Prefix		00
SIP CTI Service, Dialing Plan		CDP
SIP CTI Service, Calling Device URI Format		Phone-context=<sip URI map entries)
SIP CTI Service, Country Code		33
SIP CTI Service, National/ Number of digits to strip		1

OCS Management Console

The OCS Management Console, shown in [Figure 131 "OCS Management Console" \(page 309\)](#), provides an overview of OCS configuration:

- The OCS Enterprise Edition Pool: **ocs2007apool**
- The OCS Enterprise Edition FE server(s): **ocs2007a-ocsfe1.ocs2007a.corp.nortel.com**
The Enterprise edition can have multiple FE Servers.
- The OCS Enterprise Edition Proxy Server: **ocs2007a-proxy-ocs2007a.corp.nortel.com**

ATTENTION

The OCS GUI is always displayed in lower case. To determine the correct FQDN, right-click on pool, and the correct FQDN displays under Display Name as depicted in [Figure 132 "Determining the exact FQDN of the pool" \(page 310\)](#).

Figure 131
OCS Management Console





Figure 132
Determining the exact FQDN of the pool




OCS Default Applications Running

Use the following procedure to determine which default applications are running.

Identifying the active default applications

Step	Action
1	To determine the exact FQDN of Pool, confirm that the two default applications, IM URL Filter Application Setting and Routing Application Setting are running.
2	In OCS 2007, click on Applications. See Figure 133 "Default applications" (page 311) for an example window.

Figure 133 Default applications



--End--


General tab settings

Use the following procedure to confirm the correct settings in the General tab.

Step	Action
1	Right-click on OCS 2007 Front End server and select Properties .
2	Choose the General tab and click the Edit button. Confirm you have the correct settings for the Front End server. For an example, see Figure 134 "General settings" (page 312) .

--End--

Figure 134
General settings



Security/Certificates

Prior to the setup of Converged Office, configure certificates.

ATTENTION


Certificate configuration is not covered in this section.

Use the following procedure to check your configuration settings of Certificates.

Checking the configuration of Certificates

Step	Action
1	Right-click on the OCS 2007 Front End server, select Properties .
2	Choose the Certificate tab. The Certificate must be issued to the FDQN of the Pool, not to FQDN of the Front End server (see Figure 135 "Front End server Certificate" (page 313)).
3	Click the Select Certificate button to confirm the settings of the Front End server Certificate.

Figure 135
Front End server Certificate



--End--


Host Authorization

Use the following procedure to check your configuration settings of Host Authorization.

Checking the configuration of Host Authorization

Step	Action
1	Right-click on the OCS 2007 Front End server and select Properties .
2	Choose the Host Authorization tab.
3	Click the Edit button to confirm the settings of the Host Authorization for the Front End server (see Figure 136 "Host Authorization for Front End server" (page 314)).

Figure 136
Host Authorization for Front End server



--End--


Routing

Use the following procedure to check that Routing is correctly configured.

Checking that Routing is correctly configured


Step	Action
1	Right-click on Front Ends and select Properties . Compare the Routing settings of the Front End server Enterprise Pool with the Routing settings in Figure 137 "Routing for Enterprise Pool" (page 315) .

Figure 137
Routing for Enterprise Pool



- 2 Choose the **Routing** tab.
- 3 Click the **Edit** button to confirm the Matching URI and Next hop settings. (see [Figure 138 "Edit Static Route " \(page 316\)](#)). Forward all requests with the specified Domain.

Figure 138
Edit Static Route



--End--


Configuring DNS

Use the following procedure to check the settings for DNS Configuration. Checking these settings assumes that the DNS service is enabled on the Windows 2003 server. The OCS servers are also using this DNS server.

Checking that DNS is correctly configured


Step	Action
1	On the DNS server, select _tcp .
2	Select _sipinternaltls .
3	Right-click and select Properties .
4	Click on the Service Location (SRV) tab.
5	Check that the sipinternal SRV records are configured properly. See example Figure 139 "sipinternaltls SRV records" (page 317) for the settings for sipinternaltls SRV records.

Figure 139
sipinternaltls SRV records



- 6 On the DNS server, right-click on **ocs2007apool** and select **Properties**.
- 7 Select the **Host (A)** tab and check the Host A record for the Pool (see [Figure 140 "Host \(A\) record for the Pool"](#) (page 318))..

Figure 140
Host (A) record for the Pool



For more information on these configurations, see the *Microsoft Office Communications Server 2007 Enterprise Edition Deployment Guide* . Download Microsoft documentation from the Download Center at www.microsoft.com.

--End--

Active Directory configuration


Step	Action
1	On the Active Directory server, right-click on Users and select the name of the user to configure in the right pane.
2	Right-click and select Properties .
3	Choose the Communications tab.

4 Click the **Configure** button.

--End--

See [Figure 141 "User Advanced Settings" \(page 319\)](#) to check the settings for Server URI and Line URI.

Figure 141
User Advanced Settings



ATTENTION

For more information on the user configuration of Active Directory, see the Standard Edition section ["Active Directory user configuration" \(page 299\)](#).

Installing and configuring MCM

Use the following procedure to check that MCM is correctly installed and configured.

Checking that MCM is correctly installed and configured.


Step	Action

1	Assign the required Local group to the MCM user.

Prior to installation of MCM, an MCM user inside the Active Directory is created and the RTC Server Local Group and RTC Server Application local group is assigned to this user.


- 2 On the Proxy Server, right-click on **My Computer** and choose **Manage**. This assigns the MCM user to the RTC Server Local Group and RTC Server Application.
- 3 Under Local Users and Groups, select **Groups**.
- 4 Right-click on **RTC Server Local Group** and select **Properties**. Confirm that the settings are correct . See [Figure 142 "RTC Server Local Group"](#) (page 320) for an example.

Figure 142
RTC Server Local Group



- 5 Right-click on **RTC Server Applications** and select **Properties**. Confirm that the settings of the RTC Server Application group are correct (see [Figure 143 "RTC Server Application group"](#) (page 321)).

Figure 143
RTC Server Application group



ATTENTION

- MCM may not run if the MCM user is not configured to belong to the required groups.
- MCM may not run if an incorrect password is entered during the MCM installation.

- 6 On the MCM server, choose the **Tools** menu and select **Configuration**. See [Figure 144 "MCM configuration"](#) (page 322) for an example.

Figure 144
MCM configuration

The screenshot shows the 'Configuration' window for MCM. It is divided into several sections:

- Network Topology:**
 - Call Server: CS 1000
 - SRS, SPS, Direct Connect: Radio buttons (SPS is selected).
 - Primary IP: 47.11.56.25
 - Secondary IP: 0.0.0.0
 - Registration ID: MCM@ocs2007a.corp.nortel.co
 - Registration IP: 47.11.56.54
 - Mode: Proxy All
 - CS1000 SIP GW IP: 47.11.56.24
 - Transport: TCP
 - Port: 5060
 - Mediation Server: Checked
 - Routing Table: Button
- Active Directory Configuration:**
 - Query Server: Selected
 - Synchronize at: 03:00
 - Local Cache: Unselected
 - Synchronize Now: Button
 - Local Cache then Query Server: Unselected
 - Non Default AD/LDAP Server: Unchecked
 - Server IP: 0.0.0.0
 - Port:
- Network Dial Plan:**
 - Dial Plan: CDP
 - Access Code:
- SIP-CTI Authorization:**
 - Enable RCC Authorization: Unchecked
- Incoming Call Processing Parameters:**
 - Called Phone Context: cdp.udp
 - Called Phone Prefix Delete: 0
 - Called Phone Prefix Insert:
 - Caller Phone Prefix Delete: 0
 - Caller Phone Prefix Insert:
- Outgoing CLID Number Parameters:**
 - Prefix Delete: 0
 - Prefix Insert:
- Outgoing CLID Name Parameters:**
 - "FirstName LastName": Unchecked
 - "LastName, FirstName": Unchecked
 - "LastName FirstName": Unchecked
 - AD Display Name: Checked

Buttons at the bottom: Ok, Cancel, Help.

7

Ensure that the correct **Called Phone Context** is entered. The Called Phone Context must correspond to what is configured for the **user inside Active Directory** and the **SIP URI map** (Private/CDP or UDP domain name) configured in Element Manager.

--End--

Signaling Server checklist

Use the following procedure to check that the Signaling Server is correctly configured.

Checking that the Signaling Server is correctly configured

Step	Action
1	Check the settings of SIP URI (see Figure 145 "SIP URI" (page 323)).

Figure 145
SIP URI

CS 1000 ELEMENT MANAGER

+ SIP URI Settings

SIP URI Map

Public E.164/National domain name	+1	*
Public E.164/Subscriber domain name	+613	*
Public E.164/Unknown domain name	PublicUnknown	
Public E.164/Special Number domain name	PublicSpecial	
Private/UDP domain name	udp	
Private/CDP domain name	cdp.udp	
Private/Special Number domain name	PrivateSpecial	
Private/Unknown (vacant number routing) domain name	PrivateUnknown	
Unknown/Unknown domain name	UnknownUnknown	

+ SIP CD Services

--End--

Configuring NRS

Use the following procedure to check that the NRS is correctly configured.

Checking that NRS is correctly configured

Step	Action
1	Go to Network Routing Service (NRS) and select Endpoints . Confirm that the settings are correct (see Figure 146 "MCM endpoints" (page 324)).

Figure 146
MCM endpoints

The screenshot displays the 'Edit Gateway Endpoint' configuration page in the Nortel Network Routing Service Manager. The interface includes a left-hand navigation menu with sections like 'Common Manager', 'System', 'Numbering Plans', and 'Tools'. The main content area shows the configuration for the endpoint 'MCM'. Key settings include: 'End point name' set to 'MCM' (marked as required), 'Description' set to 'MCM on OCS Proxy', 'Trust Node' checked, 'Tandem gateway endpoint name' set to 'Not configured', 'Endpoint authentication enabled' set to 'Authentication off', and an empty 'Authentication password' field. Below these are several empty input fields for E.164 dialing codes (country, area, international access, national access, and local access codes). The top of the page shows the 'Managing' status as 'Active database' and the IP address '47.11.56.25'. The breadcrumb trail indicates the path: 'Numbering Plan > Endpoints > Gateway Endpoint'.

2

From the **Routing Entries** tab, confirm that the settings are correct (see [Figure 147 "Routing Entries for Endpoints"](#) (page 325)).

Figure 147
Routing Entries for Endpoints

The screenshot shows the 'NETWORK ROUTING SERVICE MANAGER' interface. At the top, there's a header with 'Help' and 'Logout' links. Below the header, the 'Managing' section shows 'Active database' selected and the IP address '47.11.56.25'. A link 'Numbering Plan > Routes' is also present. The main section is titled 'Search for Routing Entries'. It contains a search form with fields for 'DN Prefix' (with an asterisk), 'DN Type' (set to 'All DN Types'), 'Limit results to Domain' (with three dropdowns: 'All service domains', 'All L1 domains', and 'All L0 domains'), and 'Endpoint Name' (set to 'All gateway endpoints'). There are 'Results per page' and 'Search' buttons. Below the search form, there are two tabs: 'Routing Entries (25)' and 'Default Routes (0)'. The 'Routing Entries (25)' tab is active, showing a table of routing entries. The table has columns: 'DN Prefix', 'DN Type', 'Route Cost', 'SIP URI Phone Context', and 'Context'. The first four entries are listed, each with a checkbox and a number in the first column. The last entry is partially visible. At the bottom of the table, it says '1 - 25 of 25 Routing Entry(ies)'. There are 'First', 'Previous', 'Next', and 'Last' navigation links.

DN Prefix	DN Type	Route Cost	SIP URI Phone Context	Context
10	Private level 0 regional (CDP steering code)	1	cdp1.udp1	lcs2005s.corp.nortel.com / udp1 / cdp1 / node3228
11	Private level 0 regional (CDP steering code)	1	cdp1.udp1	lcs2005s.corp.nortel.com / udp1 / cdp1 / um_node134
2	Private level 0 regional (CDP steering code)	1	cdp1.udp1	lcs2005s.corp.nortel.com / udp1 / cdp1 / node1220
20	Private level 0 regional (CDP steering code)	1	cdp.udp	ocs2007a.corp.nortel.com / udp /

--End--

Normalizing Phone Numbers

When normalizing phone numbers, the **Telephone Number** field can be different from what is configured in the OCS user configuration for the **Line URI** field. However, a corresponding normalization rule should be defined in the "Company_Phone_Number_Normalization_Rules.txt" file to convert the Telephone Number to the Line URI format.

For example:

```
##
## CDP 4 digits
##
(d\d\d\d)
+16139675000;ext=$1
```

If the Telephone Number is normalized to the Line URI format, you can use the "Click to Call" feature to show the caller's user name when the Address Book Service is available.

Appendix Abbreviations

ACD	Automatic Call Distribution
AD	Active Directory
AML	Application Module Link
ATS	Activity Tracking System
AUX	Auxiliary
B2BUA	Back 2 Back User Agent
BCC	Basic Client Configuration
BRSC	Basic Rate Signaling Concentrator
CAST	Customer Assurance and Serviceability Test
CCMS	Contact Center Manager Server
CCR	Customer Controlled Routing

CDP	Coordinated Dialing Plan
CDR	Call Detail Recording
CS	Communication Server
CSTA	Computer Supported Telecommunications Applications
DC	Domain Controllers
DORG	Display Call Originator Information
DRAM	Dynamic Random Access Memory
DN	Directory Number
DNIS	Dialed Number Identification Services
EC	Enterprise Configurator
EMS	Enterprise Multimedia Systems
EPROM	Erasable Programmable Read-Only Memory
FS	Feature Specification
FQDN	Fully Qualified Domain Name
GC	Global Catalog

GNTS	Global Network Technical Support
IP	Internet Protocol
IPSec	Secure Internet Protocol
IVR	Interactive Voice Response
LDAP	Lightweight Directory Access Protocol
MISP	Multipurpose ISDN Signaling Processor
MCM	Multimedia Convergence Manager
MMC	Microsoft Management Console
MNM	Meridian Network Management
MSDL	Multi-purpose Serial Data Link
NAS	Nortel Application Switch
NCR	Number of Call Registers
NRS	Network Routing Service
OC	Office Communicator
OCS	Office Communications Server

P	Pentium
PSTN	Public Switched Telephone Network
PRD	Product Requirements Document
RCC	Remote Call Control Provides full Microsoft Office integration of telephony to control business-grade telephony phones from within Microsoft Office applications, as well as support for a standards-based CTI interface defined by the TR/87 protocol.
RDB	Route Data Block
RTP	Real-Time Transport Protocol
SA	StrongARM
SDP	Session Description Protocol
SIP CTI	Session Initiation Protocol Computer Telephony Integration The SIP CTI (TR/87) protocol is on the Communication Server 1000 Signaling Server. TR/87 is the specification that OC 2007 uses to implement phone integration throughout the suite of Microsoft Office applications.
SISP	Small System ISDN Signaling Processor
SPS	SIP Proxy Server
SRS	SIP Redirect Service

SRTP	Secure Real-Time Transport Protocol
TLSV	Telephony Services
TN	Terminal Number
UEXT	Universal Extension
URI	Uniform Resource Identifier
VIP	Virtual Internet Protocol
VoIP	Voice over Internet Protocol
VTRK	Virtual Trunk
XPEC	Expanded Peripheral Equipment Controller Pack

Nortel Communication Server 1000

Nortel Converged Office Fundamentals — Microsoft Office Communications Server 2007

Release: 5.5

Publication: NN43001-121

Document revision: 02.15

Document release date: 9 September 2009

Copyright © 2007-2009 Nortel Networks. All Rights Reserved.

While the information in this document is believed to be accurate and reliable, except as otherwise expressly agreed to in writing NORTEL PROVIDES THIS DOCUMENT "AS IS" WITHOUT WARRANTY OR CONDITION OF ANY KIND, EITHER EXPRESS OR IMPLIED. The information and/or products described in this document are subject to change without notice.

Nortel, Nortel Networks, the Nortel logo, and the Globemark are trademarks of Nortel Networks.

All other trademarks are the property of their respective owners.

To provide feedback or to report a problem in this document, go to www.nortel.com/documentfeedback.

www.nortel.com

