

0 1 2 3 4 5 6 7 8 9

CONTENTS	SHEET NO.	SHEET ISSUE NO.
SHEET INDEX	A1	6
OPTION INDEX		
SIDE 0 AND 1 POWER	B1	5
SIDE 0 AND 1 CIRCUIT A	B2	5
SIDE 0 AND 1 CIRCUIT B	B3	5
CABLING DIAGRAM	B4	5
CABLING DIAGRAM	B5	5
CIRCUIT CONNECTIVITY	BC1	2,3
CIRCUIT CONNECTIVITY	BC2	2,3
CIRCUIT CONNECTIVITY	BC3	2,3
CIRCUIT CONNECTIVITY	BC4	2,3
CIRCUIT CONNECTIVITY	BC5	2,3
CIRCUIT CONNECTIVITY	BC6	2,3
CIRCUIT CONNECTIVITY	BC7	2,3
CIRCUIT CONNECTIVITY	BC8	2,3
CIRCUIT CONNECTIVITY	BC9	2,3
CIRCUIT CONNECTIVITY	BC10	2,3
CIRCUIT CONNECTIVITY	BC11	2,3
CIRCUIT CONNECTIVITY	BC12	2,3
CIRCUIT CONNECTIVITY	BC13	2,3
CIRCUIT CONNECTIVITY	BC14	2,3
CIRCUIT CONNECTIVITY	BC15	2,3
CIRCUIT CONNECTIVITY	BC16	2,3
CIRCUIT CONNECTIVITY	BC17	2,3
CIRCUIT CONNECTIVITY	BC18	2,3
CIRCUIT CONNECTIVITY	BC19	2,3
CIRCUIT CONNECTIVITY	BC20	2,3
CIRCUIT CONNECTIVITY	BC21	2,3
CIRCUIT CONNECTIVITY	BC22	2,3
CIRCUIT CONNECTIVITY	BC23	2,3
CIRCUIT CONNECTIVITY	BC24	2,3
APPARATUS FIGURES	C1	4

CONTENTS	SHEET NO.	SHEET ISSUE NO.
CIRCUIT NOTES	D1	4
EQUIPMENT NOTES		
INFORMATION NOTES	D2	5
	D3	4
SHT CANCELED ON DWG ISS 2M	GA1	
CIRCUIT ACCESS REFERENCE DATA	GB1	2
UNIT SYMBOL	GB2	2,3
SHT CANCELED ON DWG ISS 2M	GB3	
BD1 ORM NCT LINKS (DSX-3 CABLING)	H1	5
BD2 ORM NCT LINKS (LIGHT WAVE CABLING)	H2	5
BD3 & 4 DS3 CONNECT OPTIONS	H3	5
BD5 & 6 FIBER CONNECT OPTIONS	H4	5
TRCU2 BACKPLANE - OPTION (Y) WIRING	H5	5
TRCU2 BACKPLANE - OPTION (Q) WIRING (SM2000 ORM APPLICATION)	H6	5

OPTION INDEX			
APP OR WRG	RATED ON ISSUE	REF NOTES	LOCATION
Z	STD 3		B1/B5/B2/B0,B9
Y	STD 3		B1/B4,B4/G2,B5/B3
X	STD 3		B2,3/B4
W	STD 3		B2,3/B4
V	STD 3		B2,3/B4
U	STD 3		B2,3/B4
T	STD 3		B2,3/B4
S	STD 4		B2,3/B4
R	STD 4		B2,3/B4
Q	STD 5		B2,3/A0,A1,A8,A9
P	STD 5		B2,3/B3,B7

DWG ISS	CD ISS	DWG ISS	CD ISS	DWG ISS	CD ISS
1	1	2M	2	3B	2
APPR	APPR	APPR	APPR	APPR	APPR
DWG ISS	CD ISS	DATE ISSD	DRN	APP	
4M	2	02-09-93			
5B	2	04-05-94			
6M	2	9-11-96			

SUPPORTING INFORMATION

SYSTEM USED ON	DESIGN CONTROL	CATEGORY	NO.
5ESS	IH		

SHEET INDEX NOTES

- ONLY THE LATEST ISSUE, OR ISSUES IF CONCURRENT, ARE SHOWN IN THE INDEX.
- FOR REISSUES, A CHANGED OR NEW SHEET IS ASSIGNED THE SAME ISSUE NUMBER AS SHEET 1.
- THE ISSUE NUMBER OF SHEET 1 IS RECOGNIZED AS THE ISSUE NUMBER OF THE WHOLE DRAWING.

Copyright (C) 1996 Lucent Technologies, Inc.
All Rights Reserved

BT13

**5ESS[®] SWITCHING EQUIPMENT
TRANSMISSION RATE CONVERTER
UNIT MODEL 2
CIRCUIT**

(TRCU2)


DWG SIZE	ISSUE
C2	6M

Lucent Technologies, Inc. SD-5D086-02 SHEET A1
42

0 1 2 3 4 5 6 7 8 9 PRINTED IN U.S.A.

SIDE 0 AND 1 POWER


NOTES:
 1. THIS SCHEMATIC SHOWS CIRCUITS 0 AND 1 COMPRESSED.
 NAMES OF THE FORM ID:1NAME EXPAND TO QNAME FOR
 CIRCUIT 0 AND INAME FOR CIRCUIT 1.



Copyright (C) 1994 AT&T All Rights Reserved		
TRANSMISSION RATE CONVERTER UNIT MODEL 2		DWG SIZE C2
		ISSUE 5B
AT&T	SD-5D086-02	SHEET 81

B

A




A

B

SIDE 0 AND 1 CIRCUIT B

THE FOLLOWING CONNECTIONS ARE ISOLATED BACKPLANE PINS
WHEN OPTION (C) IS IN EFFECT: 04-038-038 04-154-038
04-038-150 04-154-150



CODE	OPT
18E	X
18F	N
18G	V
18K	T
18E2	S
18F2	R

NOTES:
1. THIS SCHEMATIC SHOWS CIRCUITS 0 AND 1 COMPRESSED.
NAMES OF THE FORM (0:1)NAME EXPAND TO (0:1)NAME FOR
CIRCUIT 0 AND 1 NAME FOR CIRCUIT 1.


Copyright (C) 1994 AT&T
All Rights Reserved

TRANSMISSION RATE CONVERTER UNIT MODEL 2		DWG SIZE C2	ISSUE 5B
AT&T	SD-5D086-02	SHEET 83	


PRINTED IN U.S.A.

CABLING DIAGRAM

NOTES:
 1. THIS SCHEMATIC SHOWS CIRCUITS 0 AND 1 COMPRESSED.
 NAMES OF THE FORM (0:1)NAME EXPAND TO (NAME FOR
 CIRCUIT 0 AND 1NAME FOR CIRCUIT 1.



(0:1)TFL
 04-017 04-173
 TF



(0:1)TFR
 04-018,04-174
 TF

(0:1)DLIS0

Copyright (C) 1994 AT&T All Rights Reserved		
TRANSMISSION RATE CONVERTER UNIT MODEL 2	DWG SIZE C2	ISSUE 5B
AT&T	SD-5D086-02	SHEET B4

PRINTED IN U.S.A.


B

A

A

B





Copyright (C) 1994 AT&T
 All Rights Reserved

TRANSMISSION RATE CONVERTER
 UNIT MODEL 2

DWG SIZE	ISSUE
C2	5B

AT&T	SD-5D088-02	SHEET
		B5


PRINTED IN U.S.A.

B

A

A

B



LEAD	CODE	494RA	494RA	TN1345	TN1345	TN1345	TN1345	AKM3	16E	AKM3	16E	AKM3	16E	AKM3	16E	TN1345	TN1345	TN1345	TN1345	494RA	494RA	WRG OPT	SEE NOTE OR REFERENCE
	EQL	04-006	04-014	04-022	04-030	04-038	04-046	04-063	04-069	04-082	04-088	04-101	04-107	04-120	04-126	04-138	04-146	04-154	04-162	04-170	04-178		
	DESIG	APP OPT						U		U		U		U									
0-5	<D> 018 045 046 047 048 049 050 051 052 053 054 055 056 145 146 147 148 149 150 151 152 153 154 155 156			<P> 000 001 006 010 014 018 023 024 051 055 056 100 101 106 110 112 114 118 123 124 134 155 156	<D> 011 -P> 000 001 006 010 014 018 023 024 051 055 056 100 101 106 110 112 114 118 123 124 134 155 156	-P> 000 001 006 010 014 018 023 024 051 055 056 100 101 106 110 112 114 118 123 124 134 155 156	<D> 000 001 006 010 014 018 023 024 051 055 056 100 101 106 110 112 114 118 123 124 134 155 156		<P> 100 200 300		<P> 100 200 300												
0-CRPR	<D> 017		<D> 102	<D> 102	<D> 102	<D> 102																	
0-CRPRM		<D> 017	<D> 103	<D> 103	<D> 103	<D> 103																	
0-48	<D> 006 007 008 106 107 108	<D> 006 007 008 106 107 108	<P> 049	<P> 049	<P> 049	<P> 049																	
0-48RTN	<D> 003 004 005 103 104 105	<D> 003 004 005 103 104 105																					
0-5		<D> 032 033 034 035 036 037 038 039 040 041 042 043 119 132 133 134 135 136 137 138 139 140 141 142 143	<P> 012 032 033 044 132 133 144	<P> 012 032 033 044 132 133 144	<P> 012 032 033 044 132 133 144	<P> 012 032 033 044 132 133 144		<P> 049 148 249		<P> 049 148 249													
0-CRPR	<D> 117		<D> 002	<D> 002	<D> 002	<D> 002																	

Copyright (C) 1991 AT&T
All Rights Reserved

TRANSMISSION RATE CONVERTER UNIT MODEL 2		DWG SIZE C2	ISSUE 3B
AT&T	SD-5D086-02	SHEET BC1	

PRINTED IN U.S.A.

0 1 2 3 4 5 6 7 8 9

A
B
C
D
E
F
G
H

A
B
C
D
E
F
G
H

LEAD	CODE	494RA	494RA	TN1345	TN1345	TN1345	TN1345	AKM3	16E	AKM3	16E	AKM3	16E	AKM3	16E	TN1345	TN1345	TN1345	TN1345	494RA	494RA	WRG OPT	SEE NOTE OR REFERENCE
	EQL	04-006	04-014	04-022	04-030	04-038	04-046	04-063	04-069	04-082	04-088	04-101	04-107	04-120	04-126	04-138	04-146	04-154	04-162	04-170	04-178		
DESIG	APP OPT							U		U		U		U									
0-CRPRM			<0> 117	<0> 003	<0> 003	<0> 003	<0> 003																
0AEC45DN				<0> 251					<0> 219														
0AEC45DP				<0> 351					<0> 319														
0AEC45MN				<0> 247					<0> 231														
0AEC45MP				<0> 347					<0> 331														
0AEC48N				<0> 243					<0> 211														
0AEC45P				<0> 343					<0> 311														
0AEC90N				<0> 253					<0> 223														
0AEC90P				<0> 353					<0> 323														
0AED3				<0> 337				<0> 048															
0AED45DN				<0> 249					<0> 215														
0AED45DP				<0> 349					<0> 315														
0AED45MN				<0> 245					<0> 227														
0AED45MP				<0> 345					<0> 327														
0AEDN0F				<0> 047					<0> 038														
0AEDS3				<0> 335				<0> 119															
0AEEQP				<0> 205					<0> 134														
0AEMST0				<0> 005											<0> 105								
0AEMSYNC				<0> 317					<0> 136														
0AEQP				<0> 304	<0> 304			<0> 023															
0AEST0				<0> 105											<0> 005								
0ALPO				<0> 203	<0> 303																		
0ALPOM				<0> 303	<0> 203																		
0AMSTR				<0> 039	<0> 039																		

Copyright (C) 1991 AT&T All Rights Reserved		
TRANSMISSION RATE CONVERTER UNIT MODEL 2	DWG SIZE	ISSUE
	C2	3B
AT&T	SD-5D086-02	SHEET BC2

0 1 2 3 4 5 6 7 8 9

PRINTED IN U.S.A.

0 1 2 3 4 5 6 7 8 9

A
B
C
D
E
F
G
H

LEAD	CODE	494RA	494RA	TN1345	TN1345	TN1345	TN1345	AKM3	16E	AKM3	16E	AKM3	16E	AKM3	16E	TN1345	TN1345	TN1345	TN1345	494RA	494RA	WRG OPT	SEE NOTE OR REFERENCE
	EQL	04-006	04-014	04-022	04-030	04-038	04-046	04-063	04-069	04-082	04-088	04-101	04-107	04-120	04-126	04-138	04-146	04-154	04-162	04-170	04-178		
DESIG	APP OPT							U		U		U		U									
0AOC45DN				<D> 251					<D> 217														
0AOC45DP				<D> 351					<D> 317														
0AOC45MN				<D> 247					<D> 229														
0AOC45MP				<D> 347					<D> 329														
0AOC45N				<D> 243					<D> 209														
0AOC45P				<D> 343					<D> 309														
0AOC90N				<D> 253					<D> 221														
0AOC90P				<D> 353					<D> 321														
0AOD3				<D> 337				<D> 138															
0AOD45DN				<D> 249					<D> 213														
0AOD45DP				<D> 349					<D> 313														
0AOD45MN				<D> 245					<D> 225														
0AOD45MP				<D> 345					<D> 325														
0AODNOF				<D> 047					<D> 137														
0AODS3				<D> 335				<D> 006															
0AOEQP				<D> 205					<D> 034														
0AOMST0				<D> 005													<D> 105						
0AOMSYNC				<D> 317					<D> 135														
0AOST0				<D> 105														<D> 005					
0ASDS3A								<D> 015 117															
0ASDS3B								<D> 002 004															
0ASELREF				<D> 150	<D> 150																		
0BEC45DN						<D> 251						<D> 219											

Copyright (C) 1991 AT&T
All Rights Reserved

TRANSMISSION RATE CONVERTER
UNIT MODEL 2

DWG SIZE: C2 ISSUE: 3B

AT&T SD-5D086-02 SHEET BC3

PRINTED IN U.S.A.

0 1 2 3 4 5 6 7 8 9

0 1 2 3 4 5 6 7 8 9

A
B
C
D
E
F
G
H

A
B
C
D
E
F
G
H

LEAD DESIG	CODE	494RA	494RA	TN1345	TN1345	TN1345	TN1345	AKM3	16E	AKM3	16E	AKM3	16E	AKM3	16E	TN1345	TN1345	TN1345	TN1345	494RA	494RA	WRG OPT	SEE NOTE OR REFERENCE
	EQL	04-006	04-014	04-022	04-030	04-038	04-046	04-063	04-069	04-082	04-088	04-101	04-107	04-120	04-126	04-138	04-146	04-154	04-162	04-170	04-178		
OBEC45DP						<> 351						<> 319											
OBEC45MN						<> 247						<> 231											
OBEC45MP						<> 347						<> 331											
OBEC48N						<> 243						<> 211											
OBEC45P						<> 343						<> 311											
OBEC90N						<> 253						<> 223											
OBEC90P						<> 353						<> 323											
OBED3						<> 337				<> 048													
OBED45DN						<> 248						<> 215											
OBED45DP						<> 348						<> 315											
OBED45MN						<> 245						<> 227											
OBED45MP						<> 345						<> 327											
OBEDNOF						<> 047						<> 038											
OBEDS3						<> 335					<> 119												
OBEEQP						<> 205						<> 134											
OBEMSTO						<> 005														<> 105			
OBEMSYNC						<> 317						<> 136											
OBEQP						<> 304	<> 304				<> 023												
OBESTO						<> 105															<> 005		
OBLPO						<> 203	<> 303																
OBLPOM						<> 303	<> 203																
OBMSTR						<> 038	<> 039																
OBCC45DN							<> 251					<> 217											
OBCC45DP							<> 351					<> 317											

0 1 2 3 4 5 6 7 8 9

Copyright (C) 1991 AT&T All Rights Reserved		
TRANSMISSION RATE CONVERTER UNIT MODEL 2	DWG SIZE	ISSUE
	C2	3B
AT&T	SD-5D086-02	SHEET BC4

PRINTED IN U.S.A

0 1 2 3 4 5 6 7 8 9

A
B
C
D
E
F
G
H

LEAD DESIG	CODE	494RA	494RA	TN1345	TN1345	TN1345	TN1345	AKM3	16E	AKM3	16E	AKM3	16E	AKM3	16E	TN1345	TN1345	TN1345	TN1345	494RA	494RA	WRG OPT	SEE NOTE OR REFERENCE
	EQL	04-006	04-014	04-022	04-030	04-038	04-046	04-063	04-069	04-082	04-088	04-101	04-107	04-120	04-126	04-138	04-146	04-154	04-162	04-170	04-178		
APP OPT								U		U				U									
OBOD45MN							<0> 247				<0> 229												
OBOD45MP							<0> 347				<0> 329												
OBOD45N							<0> 243				<0> 209												
OBOD45P							<0> 343				<0> 309												
OBOD90N							<0> 253				<0> 221												
OBOD90P							<0> 353				<0> 321												
OBOD3							<0> 337			<0> 138													
OBOD45DN							<0> 249				<0> 213												
OBOD45DP							<0> 349				<0> 313												
OBOD45MN							<0> 245				<0> 225												
OBOD45MP							<0> 345				<0> 325												
OBODNCF							<0> 047				<0> 137												
OBODS3							<0> 335			<0> 006													
OBOD45EQP							<0> 205				<0> 034												
OBOD45ST0							<0> 005													<0> 105			
OBOD45SYNC							<0> 317				<0> 135												
OBOD45ST0							<0> 105													<0> 005			
OBOD45S3A										<0> 015 117													
OBOD45S3B										<0> 002 004													
OBOD45SELREF							<0> 150			<0> 150													
OBOD45LIAM		<0> 014	<0> 014																				
OBOD45LIAMP		<0> 113	<0> 113																				
OBOD45LIQCS		<0> 015	<0> 015																				

Copyright (C) 1991 AT&T
All Rights Reserved

TRANSMISSION RATE CONVERTER
UNIT MODEL 2

DWG SIZE C2	ISSUE 3B
AT&T	SD-5D086-02
SHEET BC5	

PRINTED IN U.S.A.

0 1 2 3 4 5 6 7 8 9

0 1 2 3 4 5 6 7 8 9

A
B
C
D
E
F
G
H

LEAD	CODE	494RA	494RA	TN1345	TN1345	TN1345	TN1345	AKM3	16E	AKM3	16E	AKM3	16E	TN1345	TN1345	TN1345	TN1345	494RA	494RA	WRG	SEE NOTE		
	EQL	04-006	04-014	04-022	04-030	04-038	04-046	04-063	04-069	04-082	04-088	04-101	04-107	04-120	04-126	04-138	04-146	04-154	04-162		04-170	04-178	OR
DESIG	APP OPT							U		U		U										REFERENCE	
1-5													<P> 049 148 149 249		<P> 049 148 149 249	<P> 012 032 033 044 132 133 144	<P> 012 032 033 044 132 133 144	<P> 012 032 033 044 132 133 144		<O> 032 033 034 035 036 037 038 039 040 041 042 043 119 132 133 134 135 136 137 138 139 140 141 142 143			
1-CRPR														<O> 002	<O> 002	<O> 002	<O> 002	<O> 117					
1-CRPRM														<O> 003	<O> 003	<O> 003	<O> 003		<O> 117				
1AEC45DN													<O> 219		<O> 251								
1AEC45DP													<O> 319		<O> 351								
1AEC45MN													<O> 231		<O> 247								
1AEC45MP													<O> 331		<O> 347								
1AEC45N													<O> 211		<O> 243								
1AEC45P													<O> 311		<O> 343								
1AEC90N													<O> 223		<O> 253								
1AEC90P													<O> 323		<O> 353								
1AED3												<O> 048			<O> 337								
1AED45DN													<O> 215		<O> 249								
1AED45DP													<O> 315		<O> 349								
1AED45MN													<O> 227		<O> 245								
1AED45MP													<O> 327		<O> 345								
1AEDNOF													<O> 038		<O> 047								

Copyright (C) 1991 AT&T
All Rights Reserved

TRANSMISSION RATE CONVERTER
UNIT MODEL 2

DWG SIZE: C2 ISSUE: 3B

AT&T SD-5D086-02 SHEET BC7

PRINTED IN U.S.A.

0 1 2 3 4 5 6 7 8 9

0 1 2 3 4 5 6 7 8 9

A
B
C
D
E
F
G
H

LEAD	CODE	494RA	494RA	TN1345	TN1345	TN1345	TN1345	AKM3	16E	AKM3	16E	AKM3	16E	AKM3	16E	TN1345	TN1345	TN1345	TN1345	494RA	494RA	WRG OPT	SEE NOTE OR REFERENCE
	EQL	04-006	04-014	04-022	04-030	04-038	04-046	04-063	04-069	04-082	04-088	04-101	04-107	04-120	04-126	04-138	04-146	04-154	04-162	04-170	04-178		
DESIG	APP OPT							U		U		U											
1AEDS3												<D> 119				<D> 335							
1AEEQP													<D> 134			<D> 205							
1AEMSYNC													<D> 136			<D> 317							
1AEQP												<D> 023				<D> 304	<D> 304						
1ALPO																<D> 203	<D> 303						
1ALPOM																<D> 303	<D> 203						
1AMSTR																<D> 039	<D> 039						
1AOC45DN													<D> 217				<D> 251						
1AOC45DP													<D> 317				<D> 351						
1AOC45MN													<D> 229				<D> 247						
1AOC45MP													<D> 329				<D> 347						
1AOC45N													<D> 209				<D> 243						
1AOC45P													<D> 309				<D> 343						
1AOC90N													<D> 221				<D> 253						
1AOC90P													<D> 321				<D> 353						
1AOD3												<D> 138					<D> 337						
1AOD45DN													<D> 213				<D> 249						
1AOD45DP													<D> 313				<D> 349						
1AOD45MN													<D> 225				<D> 245						
1AOD45MP													<D> 325				<D> 345						
1AODNOF													<D> 137				<D> 047						
1AODS3												<D> 006					<D> 335						
1AOEQP													<D> 034				<D> 205						
1AOSYNC													<D> 135				<D> 317						

Copyright (C) 1991 AT&T
All Rights Reserved

TRANSMISSION RATE CONVERTER
UNIT MODEL 2

DWG SIZE C2	ISSUE 3B
AT&T	SD-5D086-02
SHEET BC8	

PRINTED IN U.S.A.

0 1 2 3 4 5 6 7 8 9

0 1 2 3 4 5 6 7 8 9

A
B
C
D
E
F
G
H

LEAD	CODE	494RA	494RA	TN1345	TN1345	TN1345	TN1345	AKM3	16E	AKM3	16E	AKM3	16E	AKM3	16E	TN1345	TN1345	TN1345	TN1345	494RA	494RA	WRG OPT	SEE NOTE OR REFERENCE
	EOL	04-006	04-014	04-022	04-030	04-038	04-046	04-063	04-069	04-082	04-088	04-101	04-107	04-120	04-126	04-138	04-146	04-154	04-162	04-170	04-178		
DESIG	APP OPT							U		U				U									
1ASDS3A												<O> 015 117											
1ASDS3B												<O> 002 004											
1ASELREF																<O> 150	<O> 150						
1BEC45DN															<O> 219						<O> 251		
1BEC45DP															<O> 319						<O> 351		
1BEC45MN															<O> 231						<O> 247		
1BEC45MP															<O> 331						<O> 347		
1BEC45N															<O> 211						<O> 243		
1BEC45P															<O> 311						<O> 343		
1BEC90N															<O> 223						<O> 253		
1BEC90P															<O> 323						<O> 353		
1BED3															<O> 046						<O> 337		
1BED45DN															<O> 215						<O> 249		
1BED45DP															<O> 315						<O> 349		
1BED45MN															<O> 227						<O> 245		
1BED45MP															<O> 327						<O> 345		
1BEDNOF															<O> 038						<O> 047		
1BEDS3															<O> 119						<O> 335		
1BEEQP															<O> 134						<O> 205		
1BEMSYNC															<O> 136						<O> 317		
1BEQP															<O> 023						<O> 304	<O> 304	
1BLPO																					<O> 203	<O> 303	
1BLPCM																					<O> 303	<O> 203	

Copyright (C) 1991 AT&T All Rights Reserved		
TRANSMISSION RATE CONVERTER UNIT MODEL 2		DWG SIZE C2
		ISSUE 3B
AT&T	SD-5D086-02	SHEET BC9

0 1 2 3 4 5 6 7 8 9

PRINTED IN U.S.A

0 1 2 3 4 5 6 7 8 9

A
B
C
D
E
F
G
H

LEAD	CODE	494RA	494RA	TN1345	TN1345	TN1345	TN1345	AKM3	16E	AKM3	16E	AKM3	16E	AKM3	16E	TN1345	TN1345	TN1345	TN1345	494RA	494RA	WRG OPT	SEE NOTE OR REFERENCE
	EQL	04-006	04-014	04-022	04-030	04-038	04-046	04-063	04-069	04-082	04-088	04-101	04-107	04-120	04-126	04-138	04-146	04-154	04-162	04-170	04-178		
DESIG	APP OPT							U		U			U										
1BMS1R																			<D> 039	<D> 039			
1BOC45DN															<D> 217					<D> 251			
1BOC45DP															<D> 317					<D> 351			
1BOC45MN															<D> 229					<D> 247			
1BOC45MP															<D> 329					<D> 347			
1BOC45N															<D> 209					<D> 243			
1BOC45P															<D> 309					<D> 343			
1BOC90N															<D> 221					<D> 253			
1BOC90P															<D> 321					<D> 353			
1BOD3														<D> 138						<D> 337			
1BOD45DN															<D> 213					<D> 249			
1BOD45DP															<D> 313					<D> 349			
1BOD45MN															<D> 225					<D> 245			
1BOD45MP															<D> 325					<D> 345			
1BODNOF															<D> 137					<D> 047			
1BODS3														<D> 006						<D> 335			
1BOEQP															<D> 094					<D> 205			
1BOMSYNC															<D> 135					<D> 317			
1BSDSSA														<D> 015 117									
1BSDSSB														<D> 002 004									
1BSELREF																			<D> 150	<D> 150			
1DLIALM																				<D> 014	<D> 014		
1DLIAMP																				<D> 113	<D> 113		

Copyright (C) 1991 AT&T
All Rights Reserved

TRANSMISSION RATE CONVERTER
UNIT MODEL 2

DWG SIZE C2	ISSUE 3B
AT&T	SD-5D086-02
SHEET BC10	

PRINTED IN U.S.A.

0 1 2 3 4 5 6 7 8 9

0 1 2 3 4 5 6 7 8 9

A
B
C
D
E
F
G
H

LEAD	CODE	494RA	494RA	TN1345	TN1345	TN1345	TN1345	AKM3	16E	AKM3	16E	AKM3	16E	AKM3	16E	TN1345	TN1345	TN1345	TN1345	494RA	494RA	WRG OPT	SEE NOTE OR REFERENCE	
	EQL	04-006	04-014	04-022	04-030	04-038	04-046	04-063	04-069	04-082	04-088	04-101	04-107	04-120	04-126	04-138	04-146	04-154	04-162	04-170	04-178			
DESIG	APP OPT							U		U		U		U										
1DLI00S																					<O> 015	<O> 015		
1DLIS1																					<O> 011	<O> 011		
1DLIS2																					<O> 110	<O> 110		
1DLIS3																					<O> 109	<O> 109		
1DOOS48																					<O> 115	<O> 115		
1INT																					<O> 112	<O> 012		
GRD04006	<O> 032 033 034 035 036 037 038 039 040 041 042 043 119 132 133 134 135 136 137 138 139 140 141 142 143																							
GRD04014		<O> 045 046 047 048 049 050 051 052 053 054 055 056 118 145 146 147 148 149 150 151 152 153 154 155 156																						

Copyright (C) 1991 AT&T
All Rights Reserved

TRANSMISSION RATE CONVERTER
UNIT MODEL 2

DWG SIZE: C2 ISSUE: 3B

AT&T SD-5D086-02 SHEET BC11

PRINTED IN U.S.A.

0 1 2 3 4 5 6 7 8 9

0 1 2 3 4 5 6 7 8 9

A
B
C
D
E
F
G
H

LEAD	CODE	494RA	494RA	TN1345	TN1345	TN1345	TN1345	AKM3	16E	AKM3	16E	AKM3	16E	AKM3	16E	TN1345	TN1345	TN1345	TN1345	494RA	494RA	WRG OPT	SEE NOTE OR REFERENCE	
	EQL	04-006	04-014	04-022	04-030	04-038	04-046	04-063	04-069	04-082	04-088	04-101	04-107	04-120	04-126	04-138	04-146	04-154	04-162	04-170	04-178			
DESIG	APP OPT							U		U		U		U										
GHDC4022				<G> 004 008 013 016 020 021 034 040 052 104 108 113 116 120 121 139 148 152 200 201 202 204 206 206 210 212 214 216 218 220 222 223 224 232 233 234 236 238 240 242 244 246 248 250 252 254 255 256 300 301 302 306 306 310 312 314 316 316 316 320 322 323 324 332 333 334 336 338 340 342 344 346 348 350 352 354 355 356 <Q> 011																				

Copyright (C) 1991 AT&T All Rights Reserved		
TRANSMISSION RATE CONVERTER UNIT MODEL 2	DWG SIZE	ISSUE
	C2	3B
AT&T	SD-5D086-02	SHEET BC12

0 1 2 3 4 5 6 7 8 9

PRINTED IN U.S.A.

0 1 2 3 4 5 6 7 8 9

A
B
C
D
E
F
G
H

LEAD	CODE	494RA	494RA	TN1345	TN1345	TN1345	TN1345	AKM3	16E	AKM3	16E	AKM3	16E	AKM3	16E	TN1345	TN1345	TN1345	TN1345	494RA	494RA	WRG OPT	SEE NOTE OR REFERENCE		
	EQL	04-006	04-014	04-022	04-030	04-038	04-046	04-063	04-069	04-082	04-088	04-101	04-107	04-120	04-126	04-138	04-146	04-154	04-162	04-170	04-178				
DESIG	APP OPT							U		U		U		U											
GRD04030					<G> 004 008 013 016 020 021 034 040 052 104 108 113 116 120 121 139 148 152 200 201 202 204 206 208 210 212 214 216 218 220 222 223 224 232 233 234 236 238 240 242 244 246 248 250 252 254 255 256 300 301 302 306 308 310 312 314 316 318 320 322 323 324 332 332 333 333 334 336 338 340 342 344 346 348 350 352 354 355 356																				

Copyright (C) 1991 AT&T
All Rights Reserved

TRANSMISSION RATE CONVERTER
UNIT MODEL 2

DWG SIZE C2	ISSUE 3B
AT&T	SD-5D086-02
SHEET BC13	

0 1 2 3 4 5 6 7 8 9

PRINTED IN U.S.A.

0 1 2 3 4 5 6 7 8 9

A
B
C
D
E
F
G
H

A
B
C
D
E
F
G
H

LEAD	CODE	494RA	494RA	TN1345	TN1345	TN1345	TN1345	AKM3	16E	AKM3	16E	AKM3	16E	AKM3	16E	TN1345	TN1345	TN1345	TN1345	494RA	494RA	WRG OPT	SEE NOTE OR REFERENCE
	EQL	04-006	04-014	04-022	04-030	04-038	04-046	04-063	04-069	04-082	04-088	04-101	04-107	04-120	04-126	04-138	04-146	04-154	04-162	04-170	04-178		
DESIG	APP OPT							U		U		U		U									
GRD04038						<G>																	
						004																	
						008																	
						013																	
						016																	
						020																	
						021																	
						034																	
						040																	
						052																	
						104																	
						108																	
						113																	
						116																	
						120																	
						121																	
						139																	
						148																	
						152																	
						200																	
						201																	
						202																	
						204																	
						206																	
						208																	
						210																	
						212																	
						214																	
						216																	
						218																	
						220																	
						222																	
						223																	
						224																	
						232																	
						233																	
						234																	
						236																	
						238																	
						240																	
						242																	
						244																	
						246																	
						248																	
						250																	
						252																	
						254																	
						255																	
						256																	
						300																	
						301																	
						302																	
						306																	
						308																	
						310																	
						312																	
						314																	
						316																	
						318																	
						320																	
						322																	
						323																	
						324																	
						332																	
						333																	
						334																	
						336																	
						338																	
						340																	
						342																	
						344																	
						346																	
						348																	
						350																	
						352																	
						354																	
						355																	
						356																	
						<D>																	
						011																	

Copyright (C) 1991 AT&T
All Rights Reserved

TRANSMISSION RATE CONVERTER
UNIT MODEL 2

DWG SIZE: C2 ISSUE: 3B

AT&T SD-5D086-02 SHEET BC14

PRINTED IN U.S.A.

0 1 2 3 4 5 6 7 8 9

0 1 2 3 4 5 6 7 8 9

A
B
C
D
E
F
G
H

LEAD	CODE	494RA	494RA	TN1345	TN1345	TN1345	TN1345	AKM3	16E	AKM3	16E	AKM3	16E	AKM3	16E	TN1345	TN1345	TN1345	TN1345	494RA	494RA	WRG OPT	SEE NOTE OR REFERENCE			
	EQL	04-006	04-014	04-022	04-030	04-038	04-046	04-063	04-069	04-082	04-088	04-101	04-107	04-120	04-126	04-138	04-146	04-154	04-162	04-170	04-178					
DESIG	APP OPT							U		U		U		U												
GRD04046							<G> 004 008 013 016 020 021 034 040 052 104 108 113 116 120 121 139 148 152 200 201 202 204 206 208 210 212 214 216 218 220 222 223 224 232 233 234 236 238 240 242 244 246 248 250 252 254 255 256 300 301 302 306 308 310 312 314 316 318 320 322 323 324 332 333 334 336 338 340 342 344 346 348 350 352 354 355 356																			

Copyright (C) 1991 AT&T
All Rights Reserved

TRANSMISSION RATE CONVERTER
UNIT MODEL 2

DWG SIZE C2	ISSUE 3B
AT&T	SD-5D086-02
SHEET BC15	

PRINTED IN U.S.A.

0 1 2 3 4 5 6 7 8 9

0 1 2 3 4 5 6 7 8 9

A
B
C
D
E
F
G
H

LEAD DESIG	CODE	494RA	494RA	TN1345	TN1345	TN1345	TN1345	AKM3	16E	AKM3	16E	AKM3	16E	AKM3	16E	TN1345	TN1345	TN1345	TN1345	494RA	494RA	WRG OPT	SEE NOTE OR REFERENCE	
	EQL	04-006	04-014	04-022	04-030	04-038	04-046	04-063	04-069	04-082	04-088	04-101	04-107	04-120	04-126	04-138	04-146	04-154	04-162	04-170	04-178			
APP OPT								U		U		U		U										
GRD04083								<G> 001 017 018 019 020 022 036 038 039 102 103 104 105 106 107 108 114 115 124 140 146 147 212 228 244 304 316 332 348																
GRD04089								<G> 009 017 025 033 046 108 116 124 132 138 140 208 210 212 214 216 218 220 222 224 226 228 230 232 244 304 308 310 312 314 316 318 320 322 324 326 328 330 332 344																

Copyright (C) 1991 AT&T All Rights Reserved		
TRANSMISSION RATE CONVERTER UNIT MODEL 2	DWG SIZE	ISSUE
	C2	3B
AT&T	SD-5D086-02	SHEET BC16

0 1 2 3 4 5 6 7 8 9

PRINTED IN U.S.A

0 1 2 3 4 5 6 7 8 9

A
B
C
D
E
F
G
H

LEAD	CODE	494RA	494RA	TN1345	TN1345	TN1345	TN1345	AKM3	16E	AKM3	16E	AKM3	16E	AKM3	16E	TN1345	TN1345	TN1345	TN1345	494RA	494RA	WRG OPT	SEE NOTE OR REFERENCE		
	EQL	04-006	04-014	04-022	04-030	04-038	04-046	04-063	04-069	04-082	04-088	04-101	04-107	04-120	04-126	04-138	04-146	04-154	04-162	04-170	04-178				
DESIG	APP OPT							U		U		U		U											
GRD04082										<G> 001 017 018 019 020 022 036 038 039 102 103 104 105 106 107 108 114 115 124 140 146 147 212 228 244 304 316 332 348															
GRD04088										<G> 005 017 025 033 046 108 116 124 132 138 140 208 210 212 214 216 218 220 222 224 226 228 230 232 244 304 308 310 312 314 316 318 320 322 324 326 328 330 332 344															

Copyright (C) 1991 AT&T All Rights Reserved		
TRANSMISSION RATE CONVERTER UNIT MODEL 2		DWG SIZE C2
AT&T		ISSUE 3B
SD-5D086-02		SHEET BC17

0 1 2 3 4 5 6 7 8 9

0 1 2 3 4 5 6 7 8 9

A
B
C
D
E
F
G
H

LEAD DESIG	CODE	494RA	494RA	TN1345	TN1345	TN1345	TN1345	AKM3	16E	AKM3	16E	AKM3	16E	AKM3	16E	TN1345	TN1345	TN1345	TN1345	494RA	494RA	WRG OPT	SEE NOTE OR REFERENCE			
	EQL	04-006	04-014	04-022	04-030	04-038	04-046	04-063	04-069	04-082	04-088	04-101	04-107	04-120	04-126	04-138	04-146	04-154	04-162	04-170	04-178					
APP OPT								U		U		U														
GRD04101												<G> 001 017 018 019 020 022 036 038 039 102 103 104 105 106 107 108 114 115 124 140 146 147 212 228 244 304 316 332 348														
GRD04107												<G> 009 017 025 033 046 108 116 124 132 138 140 208 210 212 214 216 218 220 222 224 226 228 230 232 244 304 308 310 312 314 316 318 320 322 324 326 328 330 332 344														

Copyright (C) 1991 AT&T All Rights Reserved		
TRANSMISSION RATE CONVERTER UNIT MODEL 2		DWG SIZE C2
AT&T		ISSUE 3B
SD-5D086-02		SHEET BC18

0 1 2 3 4 5 6 7 8 9

0 1 2 3 4 5 6 7 8 9

A
B
C
D
E
F
G
H

LEAD	CODE	494RA	494RA	TN1345	TN1345	TN1345	TN1345	AKM3	16E	AKM3	16E	AKM3	16E	AKM3	16E	TN1345	TN1345	TN1345	TN1345	494RA	494RA	WRG OPT	SEE NOTE OR REFERENCE								
	EQL	04-006	04-014	04-022	04-030	04-038	04-046	04-063	04-069	04-082	04-088	04-101	04-107	04-120	04-126	04-138	04-146	04-154	04-162	04-170	04-178										
DESIG	APP OPT							U		U		U		U																	
GRD04120														<G> 001 017 018 019 020 022 036 038 039 102 103 104 105 106 107 108 114 115 124 140 146 147 212 228 244 304 316 332 348																	
GRD04126														<G> 009 017 025 033 046 108 116 124 132 138 140 208 210 212 214 216 218 220 222 224 226 228 230 232 244 304 308 310 312 314 316 318 320 322 324 326 328 330 332 344																	

Copyright (C) 1991 AT&T All Rights Reserved		
TRANSMISSION RATE CONVERTER UNIT MODEL 2	DWG SIZE	ISSUE
	C2	3B
AT&T	SD-5D086-02	SHEET BC19

0 1 2 3 4 5 6 7 8 9

PRINTED IN U.S.A

0 1 2 3 4 5 6 7 8 9

A
B
C
D
E
F
G
H

LEAD	CODE	494RA	494RA	TN1345	TN1345	TN1345	TN1345	AKM3	16E	AKM3	16E	AKM3	16E	AKM3	16E	TN1345	TN1345	TN1345	TN1345	494RA	494RA	WRG OPT	SEE NOTE OR REFERENCE												
	EQL	04-006	04-014	04-022	04-030	04-038	04-046	04-063	04-069	04-082	04-088	04-101	04-107	04-120	04-126	04-138	04-146	04-154	04-162	04-170	04-178														
DESIG	APP OPT							U		U		U		U																					
GRD04138																<G> 004 008 013 016 020 021 034 040 052 104 108 113 116 120 121 139 148 152 200 201 202 204 206 208 210 212 214 216 218 220 222 223 224 232 233 234 238 238 240 242 244 246 248 250 252 254 255 256 300 301 302 306 308 310 312 314 316 318 320 322 323 324 332 333 334 336 338 340 342 344 346 348 350 352 354 355 356 <D> 011																			

Copyright (C) 1991 AT&T
All Rights Reserved

TRANSMISSION RATE CONVERTER
UNIT MODEL 2

DWG SIZE C2	ISSUE 3B
AT&T	SD-5D086-02
	SHEET BC20

0 1 2 3 4 5 6 7 8 9

APP. FIG. 1

CIRCUIT PACK					
OPTION	DESIG	EQPT LOC	FS LOC	CLEI CODE	CODE
	0A_PWR	04-008	1F1	PWBQ54AAXX	484RA
	0B_PWR	04-014	1F8	PWBQ54AAXX	484RA
	0AE	04-022	3F0	ESICD01AXX	TN1345
	0AC	04-030	3F8	ESICD01AXX	TN1345
	1AE	04-138	3F0	ESICD01AXX	TN1345
	1AC	04-146	3F8	ESICD01AXX	TN1345
	1A_PWR	04-170	1F1	PWBQ54AAXX	484RA
	1B_PWR	04-178	1F8	PWBQ54AAXX	484RA

PB				
OPTION	DESIG	EQPT LOC	FS LOC	CODE
Y	J1	08-182	5C1	982TR
Y	J2	05-182	5D1	982TR
Y	J3	08-154	5E8	982TR
Y	J4	05-154	5E1	982TR
Y	J5	06-146	5D8	982TR
Y	J7	05-146	5G1	982TR
Y	J8	08-138	5E8	982TR
Y	J11	05-138	5G8	982TR
Y	J13	08-048	5B1	982TR
Y	J14	05-048	5D1	982TR
Y	J15	08-038	5C8	982TR
Y	J16	05-038	5E1	982TR
Y	J17	08-030	5D8	982TR
Y	J19	05-030	5F1	982TR
Y	J21	08-022	5E8	982TR
Y	J23	05-022	5F8	982TR

APP. FIG. 2

CIRCUIT PACK					
OPTION	DESIG	EQPT LOC	FS LOC	CLEI CODE	CODE
Y	04-038	04-038	4F0	ESICD01AXX	TN1345
Y	04-048	04-048	4F8	ESICD01AXX	TN1345
Y	04-154	04-154	4F0	ESICD01AXX	TN1345
Y	04-182	04-182	4F8	ESICD01AXX	TN1345

APP. FIG. 3

CIRCUIT PACK					
OPTION	DESIG	EQPT LOC	FS LOC	CLEI CODE	CODE
U	0A_DSS	04-053	3H3	DMCBAB0EXX	AKM3
U	1A_DSS	04-101	3H3	DMCBAB0EXX	AKM3

APP. FIG. 4

CIRCUIT PACK					
OPTION	DESIG	EQPT LOC	FS LOC	CLEI CODE	CODE
U	0B_DSS	04-082	4H3	DMCBAB0EXX	AKM3
U	1B_DSS	04-120	4H3	DMCBAB0EXX	AKM3

APP. FIG. 5

CIRCUIT PACK					
OPTION	DESIG	EQPT LOC	FS LOC	CLEI CODE	CODE
T	0A_OLJ	04-088	3F4	M3RG3300XX	18K
X	0A_OLJ	04-088	3F4	M3RG3000XX	18E
V	0A_OLJ	04-088	3F4	M3RG3200XX	18G
W	0A_OLJ	04-088	3F4	M3RG3100XX	18F
S	0A_OLJ	04-088	3F4	M3RGZ2TDA	18E2
R	0A_OLJ	04-088	3F4	M3RGZ0TDA	18F2
X	1A_OLJ	04-107	3F4	M3RG3000XX	18E
T	1A_OLJ	04-107	3F4	M3RG3300XX	18K
V	1A_OLJ	04-107	3F4	M3RG3200XX	18G
W	1A_OLJ	04-107	3F4	M3RG3100XX	18F
S	1A_OLJ	04-107	3F4	M3RGZ2TDA	18E2
R	1A_OLJ	04-107	3F4	M3RGZ0TDA	18F2

APP. FIG. 6

CIRCUIT PACK					
OPTION	DESIG	EQPT LOC	FS LOC	CLEI CODE	CODE
V	0B_OLJ	04-088	4E4	M3RG3300XX	18G
W	0B_OLJ	04-088	4E4	M3RG3100XX	18F
X	0B_OLJ	04-088	4E4	M3RG3000XX	18E
T	0B_OLJ	04-088	4E4	M3RG3300XX	18K
S	0B_OLJ	04-088	4E4	M3RGZ2TDA	18E2
R	0B_OLJ	04-088	4E4	M3RGZ0TDA	18F2
T	1B_OLJ	04-128	4E4	M3RG3300XX	18K
W	1B_OLJ	04-128	4E4	M3RG3100XX	18F
V	1B_OLJ	04-128	4E4	M3RG3200XX	18G
X	1B_OLJ	04-128	4E4	M3RG3000XX	18E
S	1B_OLJ	04-128	4E4	M3RGZ2TDA	18E2
R	1B_OLJ	04-128	4E4	M3RGZ0TDA	18F2

Copyright (C) 1993 AT&T All Rights Reserved		
TRANSMISSION RATE CONVERTER UNIT MODEL 2	DWG SIZE	ISSUE
	C2	4M
AT&T	SD-5D086-02	SHEET C1

CIRCUIT NOTES

101.

DESIG	FUSE AMP	POTENTIAL	ONE PER
	5	-48	SIDE

BATTERY SYMBOL	VOLTAGE RANGE

EQUIPMENT NOTES

201.
UNLESS OTHERWISE SPECIFIED, WIRING SHALL
BE PRINTED WIRING PATHS LOCATED IN MULTILAYER
PRINTED WIRING BOARD ED-5D657.

202.

APPARATUS CODE	CIRCUIT PACK REMOVAL PROCEDURE		
	PULL HOT	REMOVE UNIT POWER	SEQUENCED
TN1345 HOST	X		
TN1345 REMOTE		X	
AKMS	X		
18E,E2,F,F2,G,K HOST	X		
18E,F,G,K REMOTE		X	

Copyright (C) 1993 AT&T
All Rights Reserved

TRANSMISSION RATE CONVERTER
UNIT MODEL 2

DWG SIZE
C2

ISSUE
4M

AT&T

SD-5D086-02

SHEET
D1

PRINTED IN U.S.A.

INFORMATION NOTES:

301. UNLESS OTHERWISE SPECIFIED: RESISTANCE VALUES ARE IN OHMS. CAPACITANCE VALUES ARE IN MICROFARADS. VALUES PRECEDED BY THE SYMBOL + (PLUS) OR - (MINUS) ARE IN VOLTS.

FEATURE OR OPTION	PROVIDE		QUANTITY
	APP FIG	APP REQ	
ASSEMBLY WIRING AND EQUIPMENT FOR ONE DIRECT FIBER TRANSMISSION RATE CONVERTER UNIT (EW ONE ACTIVE AND ONE STANDBY CIRCUIT)	1		1 PER UNIT
HOST APPLICATION		Y	
REMOTE APPLICATION		Z	
SM2000 CRM APPLICATIONS		Q	
APPARATUS REQUIRED TO PROVIDE ONE ADDITIONAL ACTIVE AND STANDBY CIRCUIT FOR A HOST INTERFACING WITH TWO REMOTE SITES.	2	Y	1 PER UNIT AS REQUIRED
APPARATUS REQUIRED IN ADDITION TO APPARATUS FIGURE 1 FOR 45 MBIT/SEC ELECTRICAL TRANSMISSION	3	U	1 PER APP FIG. 1 AS REQUIRED
APPARATUS REQUIRED IN ADDITION TO APPARATUS FIGURE 2 FOR 45 MBIT/SEC ELECTRICAL TRANSMISSION	4	U	1 PER APP FIG. 2 AS REQUIRED
APPARATUS REQUIRED IN ADDITION TO APPARATUS FIGURE 1 FOR 90 MBIT/SEC OPTICAL TRANSMISSION	5		1 PER APP FIG. 1 AS REQUIRED
0 TO 18 MILES (0-17.5 DB)		X	
0 TO 28 MILES (0-22.0 DB)		#	
10 TO 38 MILES (7-28.0 DB)		V	
17 TO 44.9 MILES (13.7-28 DB)		T	
0 TO 37.8 MILES (0-29.9 DB)		R	
0 TO 25.1 MILES (0-23.8 DB)	S		
APPARATUS REQUIRED IN ADDITION TO APPARATUS FIGURE 2 FOR 90 MBIT/SEC OPTICAL TRANSMISSION	6		1 PER APP FIG. 2 AS REQUIRED
0 TO 18 MILES (0-17.5 DB)		X	
0 TO 28 MILES (0-22.0 DB)		#	
10 TO 38 MILES (7-28.0 DB)		V	
17 TO 44.9 MILES (13.7-34.0 DB)		T	
0 TO 37.8 MILES (0-28.9 DB)		R	
0 TO 25.1 MILES (0-23.8 DB)	S		
APPARATUS REQUIRED IN ADDITION TO APPARATUS FIGURE 2 FOR 90 MBIT/SEC OPTICAL TRANSMISSION AND 45 MBIT/SEC ELECTRICAL TRANSMISSION	7		1 PER APP FIG. 2 AS REQUIRED
0 TO 18 MILES (0-17.5 DB)		X	
0 TO 28 MILES (0-22.0 DB)		W	
10 TO 38 MILES (7-28.0 DB)		V	
0 TO 100 MILES		U	
17 TO 44.9 MILES (13.7-34.0 DB)		T	
0 TO 37.8 MILES (0-28.9 DB)	R		
0 TO 25.1 MILES (0-23.8 DB)	S		

INFORMATION NOTES: (CONT.)

RECORD OF FIGURES, WIRING AND APPARATUS CHANGES						
CHANGED ON ISS	IF JOB RECORDS DO NOT SPECIFY	THIS OPTION WAS FURN	SEE NOTE	USE IN CIRCUIT		
				STD	ASM	MO
24	ZY	Z	302	ZY		
58	QP	P	302	Q		

304. LIGHTWAVE CABLING: THE TRCU-2 PROVIDES BACKPLANE ACCESS FOR THE OPTICAL FIBER CABLING TO AND FROM THE CABLE INTERCONNECTION POINT (LIGHT GUIDE CROSS CONNECT (LGX)) AS A STANDARD OFFERING. TWO SHORT OPTICAL FIBER PIGTAILS EXIT THE LOWER PORTION OF THE 10E,F AND G CIRCUIT PACKS AND ARE DRESSED BACK TO CONNECT TO A FIBER COUPLER. THE OPTICAL FIBER CABLE FROM THE LGX EQUIPMENT IS DRESSED THRU THE BACKPLANE AND CONNECTED TO THE COUPLER.

TRANSMIT: IF THE OUTSIDE PLANT FIBER IS SINGLE MODE, THE INTRA-OFFICE TRANSMIT DIRECTION USES ONLY SINGLE MODE FIBER. IF THE OUTSIDE PLANT FIBER IS MULTIMODE, THE INTRA-OFFICE DIRECTION CAN USE SINGLE MODE OR MULTIMODE FIBER. THE OLI TRANSMIT PIGTAIL IS ALWAYS SINGLE MODE WITH A BICONIC CONNECTOR (YELLOW) LABELED 'OUT' AND USES A 1012A COUPLER.

RECEIVE: IF THE OUTSIDE PLANT FIBER IS SINGLE MODE, THE INTRA-OFFICE RECEIVE DIRECTION USES SINGLE MODE OR MULTIMODE FIBER. IF THE OUTSIDE PLANT FIBER IS MULTIMODE, THE INTRA-OFFICE DIRECTION USES ONLY MULTIMODE FIBER. THE OLI RECEIVE PIGTAIL IS ALWAYS MULTIMODE WITH A BICONIC CONNECTOR (BLACK) LABELED 'IN' AND USES A 1002A COUPLER.

305. DSX-3 CABLING: THE TRCU-2 PROVIDES BACKPLANE ACCESS FOR THE CABLING TO AND FROM THE DSX-3 CROSS CONNECT. (DSX-3) AS A STANDARD OFFERING, A SHIELDED COAX CABLE FROM THE DSX-3 TERMINATES ON THE AKM3 CIRCUIT PACK. THIS CABLE IS DRESSED THRU THE BACKPLANE. FEMALE BNC CONNECTORS ARE MOUNTED ON THE AKM3 CIRCUIT PACKS AND MATE WITH A RIGHT ANGLED MALE BNC CONNECTOR (28P143-11 CONNECTOR FROM SPECIALTY CONNECTOR CO. OR EQUIVALENT) THAT TERMINATE THE COAX CABLE.

306. WHEN THE ALTERNATE ROUTE OF THE ODD (EVEN) LINK FROM SIDE '0' AND THE ODD (EVEN) LINK FROM SIDE '1' DIFFER IN DELAY BY MORE THAN 20 MICROSECONDS (APPROXIMATELY 2.5 MILES IN LENGTH) A SLIP CAN OCCUR. THE SLIP WILL OCCUR WHEN THE 'TSI' SWITCHES SIDES (LIKE DURING THE DIAGNOSTIC ROUTINE 'FORCE ONTO SWITCH'). A SLIP IS A FRAME OF DATA WHICH IS LOST OR REPEATED. THESE SLIPS ARE ONLY DETECTED BY SUBSCRIBERS WHO ARE TRANSMITTING DATA WHICH IS NON-JSON WITHOUT PROTOCOLS. IF THESE SLIPS CANNOT BE TOLERATED THE FOLLOWING RESTRICTIONS MUST BE ADHERED TO.

THE ODD (EVEN) LINKS FROM SIDE '0' AND THE ODD (EVEN) LINK FROM SIDE '1' MUST NOT DIFFER IN DELAY BY MORE THAN 20 MICROSECONDS (APPROXIMATELY 2.5 MILES IN LENGTH). IF THE INTERFACE IS ELECTRICAL THE ODD (EVEN) LINKS FROM SIDE '0' AND SIDE '1' CAN HAVE THE SAME ROUTE AND THE EVEN (ODD) LINKS AN ALTERNATE ROUTE WHICH WOULD ALLOW THESE ROUTES TO DIFFER BY A DELAY OF MORE THAN 20 MICROSECONDS (2.5 MILES). IF THE INTERFACE IS OPTICAL THE ODD AND EVEN LINKS ARE ON THE SAME FIBER SO THE DIFFERENCE IN DELAY CANNOT BE MORE THAN 20 MICROSECONDS (2.5 MILES) AND THE RESTRICTION IS REQUIRED.

INFORMATION NOTES: (CONT.)

307. AT BOTH THE HOST AND REMOTE LOCATIONS THE CABLING BETWEEN THE TRCU2 AND THE DSX-3 BAY MUST NOT EXCEED 450 FEET IN LENGTH. IN ADDITION THIS CABLING MUST BE ROUTED WITHIN 3 FEET OF THE SESS GROUND WINDOW AT SOME POINT IN ITS LENGTH. THE COAX SHIELD MUST BE GROUNDED AT THE GROUND WINDOW WITH A GROUND LEAD NO GREATER THAN 3 FEET IN LENGTH. (COAX JACK-JACK BULKHEAD CONNECTORS THROUGH A BUS BAR GROUNDED TO THE GROUND WINDOW IS ACCEPTABLE.)

308. THE FIBER OPT LINKS BETWEEN THE CM1 (TMS) OR CM2 AND THE TRCU2 HAVE THE PRESENT 1000 FEET CABLE LENGTH LIMITATION.

309. THE CABLES BETWEEN THE TRCU2 AND THE MCTU2 OR TSIU4 HAVE A CABLE LENGTH LIMITATION OF 4.0 FEET.

PARAMETER	OLI					
	10E	10F	10G	10K	10E2	10F2
WAVELENGTH	1305 +/- 30NM	1305 +/- 20NM	1305 +/- 20NM	1305 +/- 20NM	1305 +/- 30NM	1305 +/- 30NM
TYPE OF TRANSMITTER	SINGLE MODE	SINGLE MODE	SINGLE MODE	SINGLE MODE	SINGLE MODE	SINGLE MODE
TRANSMITTER OUTPUT POWER-HI (1)	-10 DBM	-10 DBM	-4 DBM	+2.0 DBM	-4.1 DBM +/- 1 DB	-4.1 DBM +/- 1 DB
TRANSMITTER OUTPUT POWER-LW (1)	-18 DBM	-18 DBM	-10 DBM	-4.0 DBM	-9.1 DBM +/- 1 DB	-9.1 DBM +/- 1 DB
RECEIVER SENSITIVITY FOR BER=10E-9	-34 DBM	-38.5 DBM	-38.5 DBM	-38.5 DBM	-34.4 DBM	-39.5 DBM
AVAILABLE SYSTEM GAIN	24 DB	28.5 DB	34.5 DB	40.5 DB	30.3 DB	35.4 DB
EYE MARGIN	3.5 DB	3.5 DB	3.5 DB	3.5 DB	3.5 DB	3.5 DB
EQUIPMENT MARGIN	3 DB	3 DB	3 DB	3 DB	3.0 DB	3.0 DB
MAXIMUM FACILITY LOSS	17.5 DB	22 DB	28 DB	34 DB	23.8 DB	28.9 DB
MINIMUM FACILITY LOSS	0 DB	0 DB	7 DB	0 DB	0 DB	0 DB
CONNECTOR LOSS	1.5 DB	1.5 DB	1.5 DB	1.5 DB	1.5 DB	1.5 DB
SINGLE MODE FIBER	OUTSIDE PLANT BUDGET (1305 +/- 30NM)	15 DB	20.5 DB	28.5 DB	32.5 DB	22.3 DB
	SPAN LENGTH (2)	29 KM (18 MI)	45.5 KM (29.3 MI)	53.9 KM (36.3 MI)	72.2 KM (44.8 MI) 1	40.8 KM (25.1 MI)
MULTI MODE FIBER	DISPERSION AND MODAL NOISE ALLOCATION (3)	3 DB	3 DB	3 DB	3 DB	3 DB
	OUTSIDE PLANT BUDGET (1305 +/- 30NM)	13 DB	17.5 DB	23.5 DB	29.5 DB	19.3 DB
	SPAN LENGTH (4)	13 KM (8 MI)	17.5 KM (10.8 MI)	23.5 KM (14.6 MI)	29.5 KM (18.3 MI)	19.3 KM (12.0 MI)

- THE TRANSMITTER HAS A 0 DB SWITCH. POWER OUTPUT MAY BE SELECTED AS HI OR LW. SELECTION IS BASED ON THE INSTALLED CABLE LOSS.
 - ASSUMES 0.56 DB/KM AVERAGE CABLE PLUS SPLICE LOSS (MEDIUM LOSS FIBER) FOR THE 10E AND 0.45 DB/KM AVERAGE CABLE PLUS SPLICE LOSS (LOW LOSS FIBER) FOR THE 10F AND 10G.
 - ASSUMES 90 MHZ END-TO-END FIBER BANDWIDTH.
 - ASSUMES 1.0 DB/KM AVERAGE CABLE PLUS SPLICE LOSS (MEDIUM LOSS FIBER).
311. A MINIMUM OF ONE TRCU2 CAN BE EQUIPPED IN AN EXM2000 REMOTE OFFICE WITH 4 NCT LINKS. MAXIMUM OF 8 TRCU2'S CAN BE EQUIPPED IN AN EXM2000 REMOTE OFFICE WITH 24 NCT LINKS.

Copyright (C) 1994 AT&T
All Rights Reserved

TRANSMISSION RATE CONVERTER
UNIT MODEL 2

AT&T	SD-5D086-02	DWG SIZE C2	ISSUE 5B
			SHEET 02

PRINTED IN U.S.A.

INFORMATION NOTE: (CONT.)

311.

OLI PACK TRANSMITTER SWITCH			
TRANSMITTER	RECEIVER	TRANSMITTER SWITCH	
		LOW	HIGH
FACILITY LOSS			
18E OR 18F	18E	0 TO 9 DB	9 TO 17.3 DB
18E OR 18F	18F OR 18G	0 TO 11 DB	11 TO 22 DB
18G	18E	7 TO 15 DB	15 TO 23.5 DB
18G	18F OR 18G	7 TO 18 DB	18 TO 28 DB
18K	18F,G,K	13 TO 22 DB	22 TO 34 DB
18K	18E	13 TO 21 DB	21 TO 29.5 DB

INFORMATION NOTE: (CONT.)

312. GIVEN:

	18E	18E2	18F	18F2	18G	18K
TX OUTPUT (H)	-10	-4.1	-10	-4.1	-4	-2
TX OUTPUT (L)	-18	-9.1	-18	-9.1	-10	-4
RX OVERLOAD	-15.3	-7	-15	-7	-15	-15
RX SENSITIVITY	-34	-34.4	-38.5	-38.5	-38.5	-38.5

FACILITY LOSS CALCULATIONS:

MIN. FAC. LOSS = TX OUTPUT (L) - RX OVERLOAD + 2 DB TX MARGIN

MAX. FAC. LOSS = TX OUTPUT (H) - RX SENS - 8.5 DB EYE AND EQUIPMENT MARGIN

OLI PACK TRANSMITTER SWITCH			
TRANSMITTER	RECEIVER	TRANSMITTER SWITCH	
		LOW	HIGH
FACILITY LOSS			
18E2	18E2	0 TO 11	11 TO 23.8 DB
18E2	18E	9 TO 18	18 TO 23.4 DB
18E2	18F	8 TO 17	17 TO 27.9 DB
18E2	18F2	0 TO 14	14 TO 28.9 DB
18E2	18G	8 TO 17	17 TO 27.9 DB
18E2	18K	8 TO 17	17 TO 27.9 DB
18E	18E2	0 TO 8	8 TO 17.9 DB
18F	18E2	0 TO 8	8 TO 17.9 DB
18F2	18E2	0 TO 11	11 TO 23.8 DB
18G	18E2	0 TO 11	11 TO 23.8 DB
18K	18E2	5 TO 17	17 TO 29.9 DB

TABLE 1. FACILITY LOSS FOR THE 18E2 OLI.

OLI PACK TRANSMITTER SWITCH			
TRANSMITTER	RECEIVER	TRANSMITTER SWITCH	
		LOW	HIGH
FACILITY LOSS			
18F2	18F2	0 TO 14	14 TO 28.8 DB
18F2	18E	9 TO 18	18 TO 23.4 DB
18F2	18E2	0 TO 11	11 TO 23.8 DB
18F2	18F	8 TO 17	17 TO 27.9 DB
18F2	18G	8 TO 17	17 TO 27.9 DB
18F2	18K	8 TO 17	17 TO 27.9 DB
18E	18F2	0 TO 11	11 TO 23.0 DB
18E2	18F2	0 TO 14	14 TO 28.9 DB
18F	18F2	0 TO 11	11 TO 23.0 DB
18G	18F2	0 TO 14	14 TO 28.0 DB
18K	18F2	5 TO 20	20 TO 35.0 DB

TABLE 2. FACILITY LOSS FOR THE 18F2 OLI.

INFORMATION NOTE: (CONT.)

312. (CONT.)

TABLE 3. 18-TYPE OLI FACILITY LOSS AND SINGLE MODE SPAN LENGTH.

OO	RT	MAX. FAC. LOSS	MAX. SM SPAN LENGTH
18E	18E	17.5 DB	35.6 KM (22.1 MI)
18E	18F	17.5 DB	35.6 KM (22.1 MI)
18E	18E2	17.8 DB	36.5 KM (22.8 MI)
18E	18G	22.0 DB	45.6 KM (28.3 MI)
18E	18F2	23.0 DB	47.8 KM (29.7 MI)
18F	18E	17.5 DB	35.6 KM (22.1 MI)
18F	18E2	17.9 DB	36.5 KM (22.8 MI)
18F	18F	22.0 DB	45.6 KM (28.3 MI)
18F	18G	22.0 DB	45.6 KM (28.3 MI)
18F	18F2	23.0 DB	47.8 KM (29.7 MI)
18G	18E	22.0 DB	45.6 KM (28.3 MI)
18G	18F	22.0 DB	45.6 KM (28.3 MI)
18G	18E2	24.4 DB	50.9 KM (31.6 MI)
18G	18F2	27.9 DB	58.7 KM (36.4 MI)
18G	18G	28.0 DB	59.0 KM (36.3 MI)
18E2	18E	17.9 DB	36.5 KM (22.8 MI)
18E2	18F	17.9 DB	36.5 KM (22.8 MI)
18E2	18E2	23.8 DB	49.8 KM (30.7 MI)
18E2	18F2	23.8 DB	49.8 KM (30.7 MI)
18E2	18G	23.9 DB	49.8 KM (30.9 MI)
18F2	18E	23.0 DB	47.8 KM (29.7 MI)
18F2	18F	23.0 DB	47.8 KM (29.7 MI)
18F2	18E2	23.8 DB	49.8 KM (30.7 MI)
18F2	18G	27.9 DB	58.7 KM (36.4 MI)
18F2	18F2	28.9 DB	60.9 KM (37.8 MI)

Copyright (C) 1993 AT&T
All Rights Reserved

TRANSMISSION RATE CONVERTER UNIT MODEL 2	DWG SIZE	ISSUE
	C2	4M
AT&T	SD-5D086-02	SHEET 03


PRINTED IN U.S.A.

0 1 2 3 4 5 6 7 8 9

A
B
C
D
E
F
G
H

TRCU2
(BACKPLANE)

**SD-5D086-02 (TRCU) UNIT ACCESS
WIRING SIDE**



Copyright (C) 1991 AT&T All Rights Reserved		
TRANSMISSION RATE CONVERTER UNIT MODEL 2	MAY 10, 1989	
	DWG SIZE C2	ISSUE 2M
AT&T	SD-5D086-02	SHEET GB1

0 1 2 3 4 5 6 7 8 9

PRINTED IN U.S.A.

0 1 2 3 4 5 6 7 8 9

A
B
C
D
E
F
G
H

A
B
C
D
E
F
G
H


UNIT SYMBOL				UNIT SYMBOL			
TERM MOD(OPTION)	FUNC	(CONN)TERM	LOC	TERM MOD(OPTION)	FUNC	(CONN)TERM	LOC
0AEDS3N(U)	I	(0A_DS3INA)04-063-J1 1	2G2	1AINT(Z)	0	(J25)04-174-000	4H2
0ADDS3N(U)	I	(0A_DS3INB)04-063-J1 2	2G7	1BINT(Z)	0	(J25)04-174-001	4G2
0AEDS3OT(U)	0	(0A_DS3OUTA)04-063-J9	2G2	1DLIS3(Z)	0	(J25)04-174-002	4G2
0ADDS3OT(U)	0	(0A_DS3OUTB)04-063-J1 0	2G7	1DLIS2(Z)	0	(J25)04-174-003	4F2
0ARCV(X+W+V+T)	I	(0A_LG(IN))04-069-LG(IN)	2B3	1DLIS1(Z)	0	(J25)04-174-004	4F2
0ATRNS(X+W+V+T)	0	(0A_LG(OUT))04-069-LG(OUT)	2B6	1DLIAMP(Z)	0	(J25)04-174-005	4F2
0BEDS3N(U)	I	(0B_DS3INA)04-082-J1 1	3G2	1DLIALM(Z)	0	(J25)04-174-006	4E2
0BODS3N(U)	I	(0B_DS3INB)04-082-J1 2	3G7	1DLIOOS(Z)	0	(J25)04-174-007	4E2
0BEDS3OT(U)	0	(0B_DS3OUTA)04-082-J9	3G2	1DOOS48(Z)	0	(J25)04-174-008	4E2
0BODS3OT(U)	0	(0B_DS3OUTB)04-082-J1 0	3G7	0AINT(Z)	0	(J26)04-018-000	4G2
0BRVC(X+W+V+T)	I	(0B_LG(IN))04-088-LG(IN)	3B2	0BINT(Z)	0	(J26)04-018-001	4G2
0BTRNS(X+W+V+T)	0	(0B_LG(OUT))04-088-LG(OUT)	3B6	0DLIS3(Z)	0	(J26)04-018-002	4G2
1AEDS3N(U)	I	(1A_DS3INA)04-101-J1?KT	2H2	0DLIS2(Z)	0	(J26)04-018-003	4F2
1ADDS3N(U)	I	(1A_DS3INB)04-101-J1 2	2H7	0DLIS1(Z)	0	(J26)04-018-004	4F2
1AEDS3OT(U)	0	(1A_DS3OUTA)04-101-J9	2G2	0DLIAMP(Z)	0	(J26)04-018-005	4F2
1ADDS3OT(U)	0	(1A_DS3OUTB)04-101-J1 0	2G7	0DLIALM(Z)	0	(J26)04-018-006	4E2
1ARCV(X+W+V+T)	I	(1A_LG(IN))04-107-LG(IN)	2C3	0DLIOOS(Z)	0	(J26)04-018-007	4E2
1ATRNS(X+W+V+T)	0	(1A_LG(OUT))04-107-LG(OUT)	2C6	0DOOS48(Z)	0	(J26)04-018-008	4D2
1BEDS3N(U)	I	(1B_DS3INA)04-120-J1 1	3G2	1AODCOF(Z)	I	(J6)04-146-050	2A8
1BODS3N(U)	I	(1B_DS3INB)04-120-J1 2	3G7	GRD04146(Z)	G	(J6)04-146-052	*E1
1BEDS3OT(U)	0	(1B_DS3OUTA)04-120-J9	3G2	GRD04146(Z)	G	(J6)04-146-148	*E1
1BODS3OT(U)	0	(1B_DS3OUTB)04-120-J1 0	3G7	1ASELREF(Z)	I	(J6)04-146-150	2A8
1BRVC(X+W+V+T)	I	(1B_LG(IN))04-126-LG(IN)	3B2	GRD04146(Z)	G	(J6)04-146-152	*F1
1BTRNS(X+W+V+T)	0	(1B_LG(OUT))04-126-LG(OUT)	3B6	1AONCTR(Z)	I	(J6)04-146-153	2A9
1AEDCOF(Z)	I	(J1 0)04-138-050	2A1	GRD04146(Z)	G	(J6)04-146-034	*E1
GRD04138(Z)	G	(J1 0)04-138-052	*D1	1A08KREF(Z)	I	(J8)04-146-035	2A9
GRD04138(Z)	G	(J1 0)04-138-148	*D1	1AMSTR(Z)	I	(J8)04-146-039	2A8
1ASELREF(Z)	I	(J1 0)04-138-150	2A0	GRD04146(Z)	G	(J8)04-146-040	*E1
GRD04138(Z)	G	(J1 0)04-138-152	*E1	GRD04146(Z)	G	(J8)04-146-139	*E1
1AENCTR(Z)	I	(J1 0)04-138-153	2A0	1AONCTT(Z)	I	(J8)04-146-140	2A8
GRD04138(Z)	G	(J1 2)04-138-034	*D1	1BONCTR(Y)	IO	(LG1)06-162-FO	5F7
1AE8KREF(Z)	I	(J1 2)04-138-035	2A0	1AENCTT(Y)	IO	(LG11)05-138-FO	5C3
1AMSTR(Z)	I	(J1 2)04-138-039	2A1	0BONCTR(Y)	IO	(LG13)06-046-FO	5E7
GRD04138(Z)	G	(J1 2)04-138-040	*D1	0BONCTT(Y)	IO	(LG14)05-046-FO	5D7
GRD04138(Z)	G	(J1 2)04-138-137KT	*D1	0BENCTR(Y)	IO	(LG15)06-038-FO	5B7
1AENCTT(Z)	I	(J1 2)04-138-140	2A1	0BENCTT(Y)	IO	(LG16)05-038-FO	5B7
0AODCOF(Z)	I	(J1 8)04-030-050	2A7	0AONCTR(Y)	IO	(LG17)06-030-FO	5E3
GRD04030(Z)	G	(J1 8)04-030-052	*C1	0AONCTT(Y)	IO	(LG19)05-030-FO	5E3
GRD04030(Z)	G	(J1 8)04-030-148	*C1	1BONCTT(Y)	IO	(LG2)05-162-FO	5F7
0ASELREF(Z)	I	(J1 8)04-030-150	2A8	0AENCTR(Y)	IO	(LG21)06-022-FO	5B3
GRD04030(Z)	G	(J1 8)04-030-152	*C1	0AENCTT(Y)	IO	(LG23)05-022-FO	5B3
0AONCTR(Z)	I	(J1 8)04-030-153	2A9	1BENCTR(Y)	IO	(LG3)06-154-FO	5C7
GRD04030(Z)	G	(J2 0)04-030-034	*B1	1BENCTT(Y)	IO	(LG4)05-154-FO	5C7
0A08KREF(Z)	I	(J2 0)04-030-035	2A9	1AONCTR(Y)	IO	(LG5)06-146-FO	5F3
0AMSTR(Z)	I	(J2 0)04-030-039	2A8	1AONCTT(Y)	IO	(LG7)05-146-FO	5F3
GRD04030(Z)	G	(J2 0)04-030-040	*C1	1AENCTR(Y)	IO	(LG9)06-138-FO	5C3
GRD04030(Z)	G	(J2 0)04-030-139	*C1				
0AONCTT(Z)	I	(J2 0)04-030-140	2A8				
0AEDCOF(Z)	I	(J2 2)04-022-050	2A1				
GRD04022(Z)	G	(J2 2)04-022-052	*B1				
GRD04022(Z)	G	(J2 2)04-022-148	*B1				
0ASELREF(Z)	I	(J2 2)04-022-150	2A0				
GRD04022(Z)	G	(J2 2)04-022-152	*B1				
0AENCTR(Z)	I	(J2 2)04-022-153	2A0				
GRD04022(Z)	G	(J2 4)04-022-034	*A1				
0AE8KREF(Z)	I	(J2 4)04-022-035	2A0				
0AMSTR(Z)	I	(J2 4)04-022-039	2A1				
GRD04022(Z)	G	(J2 4)04-022-040	*B1				
GRD04022(Z)	G	(J2 4)04-022-139	*B1				
0AENCTT(Z)	I	(J2 4)04-022-140	2A1				

* NOT SHOWN IN SCHEMATIC

Copyright (C) 1991 AT&T All Rights Reserved		
TRANSMISSION RATE CONVERTER UNIT MODEL 2	DWG SIZE	ISSUE
	C2	3B
AT&T	SD-5D086-02	SHEET GB2

0 1 2 3 4 5 6 7 8 9

PRINTED IN U.S.A.



Copyright (C) 1994 AT&T All Rights Reserved		
TRANSMISSION RATE CONVERTER UNIT MODEL 2	DWG SIZE	ISSUE
	C2	5B
AT&T	SD-5D088-02	SHEET H1

B

A




A

B

BD 2
 SYSTEM APPLICATION DIAGRAM
 ORM NCT LINKS
 (LIGHT WAVE CABLING)

NOTES:

1. THE MCTU(2) CAN BE EQUIPPED WITH MULTIPLE VERSIONS OF THE TN1077, TN1077B, TN1077C, TN1077D, TN1077E.
2. BLOCK DIAGRAM SHOWS PRIMARY LINK EQUIPPAGE WITH ADDITIONAL TRCU2'S IN A SM2000 ORM CONFIGURATION A TOTAL OF 24 NCT LINKS (ELN1'S) CAN BE EQUIPPED.
3. THE DLI (TN1077) RESIDES IN THE MCTU(2) SM. THE ENLJ (BKD3) RESIDES IN THE TSIU4, USED FOR SM2000 ORM APPLICATIONS.




Copyright (C) 1994 AT&T All Rights Reserved		
TRANSMISSION RATE CONVERTER UNIT MODEL 2	DWG SIZE	ISSUE
	C2	5B
AT&T	SD-5D086-02	SHEET H2

PRINTED IN U.S.A.

B



A



A

B


BD 3 & 4
SYSTEM APPLICATION DIAGRAM
(DS3 CONNECT OPTION)



Copyright (C) 1994 AT&T All Rights Reserved		
TRANSMISSION RATE CONVERTER UNIT MODEL 2		DWG SIZE C2
AT&T		ISSUE 5B
SD-5D088-02		SHEET H3
PRINTED IN U.S.A.		

B

A




A

B

BD 5 & 6


SYSTEM APPLICATION DIAGRAM (FIBER CONNECT OPTION)



Copyright (C) 1994 AT&T All Rights Reserved		
TRANSMISSION RATE CONVERTER UNIT MODEL 2		DWG SIZE C2
AT&T	SD-50086-02	ISSUE 5B SHEET H4
		PRINTED IN U.S.A.



EXM2000 ORM TRCU2 BACKPLANE
 VIEW FROM BACK SIDE OF UNIT
 LOWER HALF OF TRCU2 SHELF PINS (X00-X24)
 (USED WITH SM2K TSIU4 UNIT - OPTION (Y) WIRING)




NOTES:
 - CONNECTED PINS ARE MARKED WITH A BOLD DOT
 - CONNECTED PINS EQLS ARE NOTED UNDER THE SIDE HEADINGS

TO POWER UP THE TRCU2
 THESE TWO MARKED PINS MUST BE
 SHORTED OR TIED TOGETHER

Copyright (C) 1994 AT&T All Rights Reserved		
TRANSMISSION RATE CONVERTER UNIT MODEL 2		DWG SIZE C2
AT&T	SD-5D086-02	ISSUE 5B SHEET H5
PRINTED IN U.S.A.		

B


A



A

B

ORM TRCU2 BACKPLANE
 VIEW FROM BACK SIDE OF UNIT
 LOWER HALF OF TRCU2 SHELF PINS (X32-X56)
 (USED WITH SM2K TSU4 UNIT - OPTION (Q) WIRING)



NOTES:

- ISOLATED PINS ARE MARKED WITH A BOLD DOT
- ISOLATED PINS NUMBERS UNDER THE SIDE HEADING

SIDE 0
 022-039
 022-150
 038-039
 038-150


SIDE 1
 138-039
 138-150
 154-039
 154-150

Copyright (C) 1994 AT&T All Rights Reserved		
TRANSMISSION RATE CONVERTER UNIT MODEL 2		DWG SIZE C2
		ISSUE 5B
AT&T	SD-5D086-02	SHEET HG

PRINTED IN U.S.A.

B

A



A

B