




# Zoom H1 Handy Recorder Line-In Port Replacement

This guide will show you how to remove and replace a faulty line-in port.

Written By: Alex



 **TOOLS:**

- [Soldering Iron \(1\)](#)
- [Phillips #00 Screwdriver \(1\)](#)
- [iFixit Opening Tools \(1\)](#)

## Step 1 — Line-In Port



- Flip device over so the display is facing down.

## Step 2



- Remove the battery cover by pressing down on battery cover and sliding it to the right.

## Step 3




- Remove the two 10 mm Phillips #00 screws located below the microphones on the back cover.

## Step 4



- Remove the back cover (using a plastic removal tool around the edges if needed).


## Step 5



- De-solder and remove the heat shield.


**⚠ Be careful while removing this shield, since the copper sheet is very easy to rip.**

## Step 6




- De-solder the line in port from its soldering points.
- These points are located beneath the black shielding on the left side of the blue circuit board.

## Step 7



- Replace Line-in port and re-solder at points specified in Step 6.

## Step 8



- Reattach and re-solder the heat shielding back into place.

**⚠** Again, be careful when soldering as it is very easy to melt through the heat shield and copper sheet beneath.

To reassemble your device, follow these instructions in reverse order.