

OPTION & MICROVERSION SECTION

Contents

1. Relationship between option and micro-program version.....	OPTVER01-10
---	-----------------------------

1. Relationship between option and micro-program version

Before installing one of hardware options described in the below, confirm whether the stored micro-program supports the hardware option or not.

Table 1 Comparison Table of Options & Micro-Versions

No.	Model number	Support item	Micro-program version (*1)
1	DKC-F460I-8ML/8MS	FICON(8ML/8MS)	DKCMAIN: 21-02-2X and higher
2	DKC-F460I-4GSF/4HSF/ 8GSF/8HSF/8HLF	DB Validator (4GSF/4HSF/8GSF/8HSF/8HLF)	DKCMAIN: 21-02-2X and higher
3	DKC-F460I-1PSD/3PSD, DKU-F455I-1PSD/3PSD	30A AC-BOX	DKCMAIN: 21-02-2X and higher
4	DKU450I-14	DKU405I connection	DKCMAIN: 21-02-4X and higher
5	DKC-F460I-SVP	SVP high availability kit	DKCMAIN: 21-02-4X and higher
6	DKC-F460I-16HSF	Fibre 16-port Adapter for Short Wavelength (1-2Gbps support)	DKCMAIN: 21-03-0X and higher
7	DKC460I-5FE	Disk Control frame without doors (NAS support Model)	DKCMAIN: 21-04-XX and higher
8	DKC-F460I-4NS	NAS 4-port Adapter for SX (1.25Gbps support)	DKCMAIN: 21-07-4X and higher
9	DKC-F460I-8SE	Serial 8-port Adapter	DKCMAIN: 21-06-2X and higher
10	DKC-F460I-8IS	iSCSI 8-port Adapter	DKCMAIN: 21-09-0X and higher
11	DKC-F460I-3PS/3PSD, DKU-F455I-3PS/3PSD	3 Phase mixture support	DKCMAIN: 21-07-2X and higher
	DKC-F460I-1PS/1PSD, DKU-F455I-1PS/1PSD	Single mixture support	
12	DKC-F460I-4096/S1024	Additional Cache Memory Module 64GB and over, and Additional Shared Memory Module	DKCMAIN: 21-07-XX and higher
		Additional Cache Memory Module lower than 64GB, and Additional Shared Memory Module	DKCMAIN: 21-08-XX and higher
13	DKU-F455I-146JF/JS, DKU-F455I-146JQ/JM	4 HDD Canisters 1 HDD Canister	DKCMAIN: 21-07-XX and higher

(*1) Refer to the page [SVP03-10](#) to confirm micro-program version.

If the present micro-program versions are lower than the ones in the table above, please exchange or update them first. (Refer to [MICRO-FC04-10](#).)

Non-Disruptive : Go to [INST02-40](#) No.1.

Disruptive : Go to [INST02-70](#) No.1.