

OPTION & MICROVERSION SECTION

Contents

[OPTVER01-10](#) 1. Relationship between option and micro-program version

1. Relationship between option and micro-program version

Before installing one of hardware options described in the below, confirm whether the stored micro-program supports the hardware option or not.

Table 1-1 Comparison Table of Options & Micro-Versions

No.	Model number	Support item	Micro-program version (*1)
1	DKC-F605I-300KS	DKS2E-K300FC	DKCMAIN: 60-01-4X and higher
2	DKC-F605I-0R7HS	DKS2A-H0R7AT	DKCMAIN: 60-02-0X and higher
3	DKC-F610I-C16G/CBEX/DBEX	Cache Memory (16GB) support	DKCMAIN: 60-02-4X and higher
4	DKC-F605I-400JS	DKS2E-J400FC	DKCMAIN: 60-02-4X and higher
5	DKC-F610I-IPV6	IPv6 Upgrade Kit	DKCMAIN: 60-02-4X and higher
6	DKC-F605I-300KM	Multi vendor (DKS2E-K300FC, DKR2G-K300FC)	DKCMAIN: 60-02-04 and higher
7	DKC-F605I-1R0HS	DKR2B-H1R0AT	DKCMAIN: 60-03-0X and higher
8	DKC-F610I-SVPV	SVP High Reliability Support Kit (IPv6)	DKCMAIN: 60-03-2X and higher
9	DKC-F605I-450KS	DKS2F-K450FC	DKCMAIN: 60-04-0X and higher
10	DKC-F610I-EDKA	Encrypt Disk Adapter	DKCMAIN: 60-04-0X and higher
11	DKC-F605I-72S1/146S1	SDT2A-S072FC/S146FC	DKCMAIN: 60-04-0X and higher
12	DKC-F605I-200S1/400S1	SDT2A-S200FC/S400FC	DKCMAIN: 60-05-XX and higher
13	DKC-F610I-8US/1UL/1US	Fibre 8Gbps support	DKCMAIN: 60-06-0X and higher
14	DKC-F605I-600KS	DKS2G-K600FC	DKCMAIN: 60-06-0X and higher
15	DKC-F605I-2R0HS	DKR2C-H2R0AT	DKCMAIN: 60-06-0X and higher

*1: Refer to the page [SVP03-10](#) to confirm micro-program version.

If the present micro-program versions are lower than the ones in the table above, please exchange or update them first. (Refer to [MICRO04-10](#).)

Non-Disruptive : Go to [INST02-40](#) No.3.

Disruptive : Go to [INST02-90](#) No.3.