



Section 4 - BGP and L3VPN

ine.com

Task 4.1

- Configure iBGP neighborship between the edge HQ DATACENTER routers:
 - R1 and R2 belong to BGP AS 12.
 - R1 and R2 must establish iBGP neighborship using their interface Loopback0 interface.
 - Ensure R1 and R2 learn each other's Loopback0 using OSPF AREA 0 as the IGP.
 - R1 must always be the DR as a preference and R2 must be the BDR. SVI 250 on SW1 must never participate in the DR/BDR election.
 - No other links must be activated for OSPF.