

Licensing, Capacity Usage Threshold Reached, Warning

Ericsson Centralized User Database

Operating Instructions

Copyright

© Ericsson AB 2016-2018. All rights reserved. No part of this document may be reproduced in any form without the written permission of the copyright owner.

Disclaimer

The contents of this document are subject to revision without notice due to continued progress in methodology, design and manufacturing. Ericsson shall have no liability for any error or damage of any kind resulting from the use of this document.

Trademark List

All trademarks mentioned herein are the property of their respective owners. These are shown in the document *Trademark Information*.

Contents

1	Introduction	1
1.1	Alarm Description	1
1.2	Prerequisites	3
2	Procedure	4
	Glossary	5



Licensing, Capacity Usage Threshold Reached, Warning



1 Introduction

This instruction concerns alarm handling for the Licensing, Capacity Usage Threshold Reached, Warning alarm.

1.1 Alarm Description

This alarm is raised when the number of reserved capacity in a capacity license approaches the Warning threshold. The default value of the Warning threshold is 80% of the `licensedCapacityLimit` parameter.

The alarm is issued in the following situations:

- The capacity usage has reached the Warning threshold for the active HLR Profile.
- The capacity usage has reached the Warning threshold for the active HSS-IMS Profile.
- The capacity usage has reached the Warning threshold for the active HSS-EPC Profile.
- The capacity usage has reached the Warning threshold for the active AUC Profile.
- The capacity usage has reached the Warning threshold for the Small Generic Profile.
- The capacity usage has reached the Warning threshold for the Medium Generic Profile.
- The capacity usage has reached the Warning threshold for the Large Generic Profile.
- The capacity usage has reached the Warning threshold for the active IoT Profile.
- The capacity usage has reached the Warning threshold for the active HSS-EPC 5G Profile.

The possible alarm causes and the corresponding fault reasons, fault locations, and impacts are described in [Table 1](#).

Table 1 Alarm Causes

Alarm Cause	Description	Fault Reason	Fault Location	Impact
The Warning threshold of the capacity profile has been passed.	The capacity usage threshold has been reached.	The requested capacity has passed the Warning threshold defined	License Manager	Potential violation of license agreements, if the number of reserved



Alarm Cause	Description	Fault Reason	Fault Location	Impact
		in the capacity license.		capacity continues to increase and reaches the limit.

The alarm attributes are listed and explained in [Table 2](#).

Table 2 Alarm Attributes

Attribute Name	Attribute Value
Auto Cease	Yes
Module	LICENSING
Error Code	5
Timestamp First	Date and time when the alarm was raised for the first time.
Repeated Counter	Number which indicates how many times the alarm was raised.
Timestamp Last	Date and time of the most recent alarm raised.
Resource ID	1.3.6.1.4.1.193.169.14.2.3.<# SUB_LICENSE_SUFFIX>
Alarm Model Description	License Management, Licensing
Alarm Active Description	Capacity Usage Threshold Reached for <#LICENSE_TYPE>, Warning
ITU Alarm Event Type	qualityOfServiceAlarm (3)
ITU Alarm Probable Cause	thresholdCrossed (549)
ITU Alarm Perceived Severity	(6) - Warning
Originating source IP	Node IP where the alarm was raised.
Sequence Number	Number which indicates the order in which the alarms are raised.

The available values of the <#SUB_LICENSE_SUFFIX> and <#LICENSE_TYPE> variables shown in [Table 2](#) are listed below. The list follows the below format:

"<#SUB_LICENSE_SUFFIX>" for the <#LICENSE_TYPE>.

- "2" for the HLR Profile.
- "3" for the HSS-IMS Profile.
- "4" for the HSS-EPC Profile.
- "5" for the AUC Profile.
- "6" for the Small Generic Profile.
- "7" for the Medium Generic Profile.
- "8" for the Large Generic Profile.
- "9" for the IoT Profile.
- "10" for the HSS-EPC 5G Profile.



For further information about attribute descriptions, refer to CUDB Node Fault Management Configuration Guide.

1.2 Prerequisites

This section provides information on the documents, tools, and conditions that apply to the procedure.

1.2.1 Documents

This instruction references the following documents:

- CUDB Node Fault Management Configuration Guide
- License Management, Capacity Usage Threshold Reached

1.2.2 Tools

Not applicable.

1.2.3 Conditions

Not applicable.



2 Procedure

If the alarm is raised, then refer to the License Management, Capacity Usage Threshold Reached document for the procedure to perform.

Note: Perform only the actions that are applicable for LM deployments using ELIM license key files. The applicable severity is "Warning".



Glossary

For the terms, definitions, acronyms and abbreviations used in this document, refer to CUDB Glossary of Terms and Acronyms