

# Event List

## Virtual Multimedia Resource Function

---

### Description

**Copyright**

© Ericsson AB 2017. All rights reserved. No part of this document may be reproduced in any form without the written permission of the copyright owner.

**Disclaimer**

The contents of this document are subject to revision without notice due to continued progress in methodology, design and manufacturing. Ericsson shall have no liability for any error or damage of any kind resulting from the use of this document.



# Contents

<b>1</b>	<b>Events</b>	<b>1</b>
1.1	MRF H.248 Link Recovered after Temporary Outage	1
1.2	COM SA, CLM Cluster Node Unavailable	2
1.3	COM SA, AMF SI Unassigned	3



# 1 Events

This section describes the events that can be generated in vMRF.

## 1.1 MRF H.248 Link Recovered after Temporary Outage

The `MRF H.248 Link Recovered after Temporary Outage` event is related to signaling link state changes between vMRF and MTAS.

In case an already established SCTP transport link loss is detected, a 30 second timer is started. If the link recovers before the timer expires, the `MRF H.248 Link Recovered after Temporary Outage` event is reported. The timer is then cancelled. Ongoing traffic is not impacted. If the link does not recover before the timer ends, the `MRF H.248 Link Unavailable` alarm is raised.

### 1.1.1 Information

The event attributes are listed in [Table 1](#).

*Table 1 Event Attributes*

Attribute Name	Attribute Value
Major Type	193
Minor Type	5308420
Managed Object Class	MrfH248Interface
Managed Object Instance	ManagedElement=1,MediaResourceFunction=1,MrfH248Control=1,MrfH248Interface=<MrfH248InterfaceId>
Specific Problem	MRF H.248 Link Recovered after Temporary Outage
Event Type	communicationsAlarms (2)
Probable Cause	x733CommunicationsProtocolError (305)
Additional Text	SCTP association recovered
Perceived Severity	Warning (6)
isStateful	false



## 1.2 COM SA, CLM Cluster Node Unavailable

The COM SA, CLM Cluster Node Unavailable event is related to failed communication with a connected node. The event is raised by the middleware Cluster Membership (CLM) service.

The event is reported in the following cases:

- The CLM has lost contact with a node and has been unable to re-establish contact for 15 minutes.
- After a cluster start, the CLM has been unable to establish contact with a node for 15 minutes.

### 1.2.1 Information

The event attributes are listed in [Table 2](#).

*Table 2 Event Attributes*

Attribute Name	Attribute Value
Major Type	193
Minor Type	849346561
Source	One of the following: <ul style="list-style-type: none"><li>• safNode=&lt;PL_name&gt;, safCluster=myClmCluster</li><li>• safNode=&lt;SC_name&gt;, safCluster=myClmCluster</li></ul>
Specific Problem	COM SA, CLM Cluster Node Unavailable
Event Type	Other (1)
Probable Cause	x736UnspecifiedReason (418)
Additional Text	CLM Cluster Node Unavailable
Perceived Severity	Warning (6)
isStateful	false

**Note:** Depending on the system configuration, the `uuid` for the affected node can be appended to Additional Text.

## 1.3 COM SA, AMF SI Unassigned

The event is reported by the middleware Availability Management Framework (AMF) service.

The AMF is responsible for assigning active or standby workloads to software components in the managed element through Service Units (SUs). The SUs are logical aggregations of several software components. The event is raised when a particular workload can no longer be assigned to any SU.

### 1.3.1 Information

The event attributes are listed in [Table 3](#).

*Table 3 Event Attributes*

Attribute Name	Attribute Value
Major Type	18568
Minor Type	131077
Source	safApp=<*>, safSi=<*>
Specific Problem	COM SA, AMF SI Unassigned
Event Type	Other (1)
Probable Cause	x736UnspecifiedReason (418)
Additional Text	SI designated by <LDAP DN of the SI> has no current active assignments to any SU
Perceived Severity	Warning (6)
isStateful	false