

# Show Supported and Enabled TLS Ciphers

## OPERATING INSTRUCTIONS

**Copyright**

© Ericsson AB 2016, 2017. All rights reserved. No part of this document may be reproduced in any form without the written permission of the copyright owner.

**Disclaimer**

The contents of this document are subject to revision without notice due to continued progress in methodology, design and manufacturing. Ericsson shall have no liability for any error or damage of any kind resulting from the use of this document.

**Trademark List**

All trademarks mentioned herein are the property of their respective owners. These are shown in the document Trademark Information.



# Contents

<b>1</b>	<b>Description</b>	<b>1</b>
<b>2</b>	<b>Procedure</b>	<b>1</b>
2.1	Show Supported and Enabled TLS Ciphers	1



Show Supported and Enabled TLS Ciphers



# 1 Description

This instruction describes how to show the supported Transport Layer Security (TLS) and enabled cipher suites for the Managed System (MS).

## 2 Procedure

### 2.1 Show Supported and Enabled TLS Ciphers

#### Prerequisites

- No documents are required.
- No tools are required.
- The following conditions must apply:
  - The user has the System Security Administrator or System Administrator role.
  - An Ericsson Command-Line Interface (ECLI) session in Exec mode is in progress.

#### Steps

1. Navigate to `Tls` managed object, for example:

```
>dn ManagedElement=NODE06ST,SystemFunctions=1,SecM=1,Tls=1
```

2. Show the supported ciphers:

```
(Tls=1)>show supportedCiphers
```

The following is an example output:

```
[...]  
supportedCiphers="DES-CBC-MD5"  
  authentication="aRSA"  
  encryption="DES"  
  export=""  
  keyExchange="kRSA"  
  mac="MD5"  
  protocolVersion="SSLv2"  
[...]
```



3. Show the enabled ciphers, for example:

```
(Tls=1)>show enabledCiphers
```

The following is an example output:

```
enabledCiphers="PSK-AES256-CBC-SHA"  
  authentication="aPSK"  
  encryption="AES"  
  export=""  
  keyExchange="kPSK"  
  mac="SHA1"  
  protocolVersion="SSLv3"  
enabledCiphers="DES-CBC3-SHA"  
  authentication="aRSA"  
  encryption="3DES"  
  export=""  
  keyExchange="kRSA"  
  mac="SHA1"  
  protocolVersion="SSLv3"
```

**Note:** The result depends on the configuration of `cipherFilters` and can vary depending on systems.