

Prepared (Subject resp) XMRDMFI Dmitry Filushin		No. 26/1543-ANA 901 37 Uen		
Approved (Document resp) BDGSGHDD [Hans Fernqvist]	Checked	Date 2018-05-16	Rev C	Reference

**SS7 CAF Link Unavailable for UP**

**Contents**

1	Overview	2
1.1	Description	2
2	Procedure	2

Prepared (Subject resp) XMRDMFI Dmitry Filushin		No. 26/1543-ANA 901 37 Uen		
Approved (Document resp) BDGSGHDD [Hans Fernqvist]	Checked	Date 2018-05-07	Rev C	Reference

## 1 Overview

**Note:** This alarm is deprecated.

### 1.1 Description

The alarm is issued when the signaling link has become unavailable to all signaling traffic due to link failure, blocking or inhibiting.

Major type	193
Minor type	1586562651
MO Class	N/A
Specific Problem	SS7 CAF Link Unavailable For UP
Severity	SEVERITY_WARNING
Additional Text	Link Unavailable For UP

The possible causes are as follows:

- Incorrect SS7 configuration.
- The signaling link was blocked or inhibited as a result of an error that occurred in M3 or lower layer.
- Problem with hardware or network connection.

**Note:** The link is automatically restarted by M3. This is a timer-controlled process and the link should come back into service. Traffic carried by the link is transferred to one or more alternative links by means of a changeover procedure.

## 2 Procedure

Perform the following actions to find out root cause of wrong state:

1. Exclude errors in SS7 configuration.
2. If the link doesn't come back in service (the alarm wasn't cleared) check cables, connections and SS7 boards to exclude connection problems.
3. Check if there is "Remote Processor Outage" alarm and solve concerned problem if it is.
4. Verify that NMM process is up and running, see Signaling Manager User Guide for details.

If the NMM process is down or alarm is not cleared contact the next level of maintenance support, see SS7 CAF Troubleshooting Guide for details.