

Stop Threshold Monitoring Job

OPERATING INSTRUCTIONS

Copyright

© Ericsson AB 2016, 2017. All rights reserved. No part of this document may be reproduced in any form without the written permission of the copyright owner.

Disclaimer

The contents of this document are subject to revision without notice due to continued progress in methodology, design and manufacturing. Ericsson shall have no liability for any error or damage of any kind resulting from the use of this document.

Trademark List

All trademarks mentioned herein are the property of their respective owners. These are shown in the document Trademark Information.



Contents

1	Description	1
2	Procedure	1
2.1	Stop Threshold Monitoring Job	1





1 Description

This instruction describes how to stop a threshold monitoring job. In maintenance situations, the user can suspend a threshold monitoring job to avoid forwarding threshold alarms to the management system when the Managed Element (ME) is unstable and already given specific attention. This is also a way to reduce the load on the ME.

2 Procedure

2.1 Stop Threshold Monitoring Job

Prerequisites

- No documents are required.
- No tools are required.
- The following conditions must apply:

- The job name is known.

In this instruction, the job name example is POT_Thr_Job.

- An Ericsson Command-Line Interface (ECLI) session in Exec mode is in progress.

Steps

1. Navigate to the PmJob managed object, for example:

```
>dn ManagedElement=NODE06ST,SystemFunctions=1,Pm=1,PmJob=POT_Thr_Job
```

2. Enter Config mode:

```
(PmJob=POT_Thr_Job)>configure
```

3. Set the PmJob state to STOPPED:

```
(config-PmJob=POT_Thr_Job)>requestedJobState=STOPPED
```

4. Commit the PmJob configuration:

```
(config-PmJob=POT_Thr_Job)>commit
```



5. Verify the result:

(PmJob=POT_Thr_Job)>**show -v**

The following is an example output:

```
PmJob=POT_Thr_Job
compressionType=[] <empty>
currentJobState=STOPPED <read-only>
granularityPeriod=FIFTEEN_MIN <default>
jobControl=FULL <default> <read-only>
jobGroup=[] <empty>
jobPriority=MEDIUM <default>
jobType=THRESHOLDJOB
pmJobId="POT_Thr_Job"
reportContentGeneration=CHANGED_ONLY <default>
reportingPeriod=FIFTEEN_MIN <default>
requestedJobState=STOPPED
MeasurementReader=POT_mr
```