

# BRM, Auto Export Backup Failed

## OPERATING INSTRUCTIONS

**Copyright**

© Ericsson AB 2016, 2017. All rights reserved. No part of this document may be reproduced in any form without the written permission of the copyright owner.

**Disclaimer**

The contents of this document are subject to revision without notice due to continued progress in methodology, design and manufacturing. Ericsson shall have no liability for any error or damage of any kind resulting from the use of this document.

**Trademark List**

All trademarks mentioned herein are the property of their respective owners. These are shown in the document Trademark Information.



# Contents

<b>1</b>	<b>Alarm Description</b>	<b>1</b>
<b>2</b>	<b>Procedure</b>	<b>2</b>
2.1	Handle Alarm BRM, Auto Export Backup Failed	2
2.2	Handle Reason Authentication Failure	3
2.3	Handle Reason Directory Not Exist	4
2.4	Handle Reason Server Unreachable	5
2.5	Handle Reason Permission Denied	6
2.6	Handle Undetermined Reason	6



BRM, Auto Export Backup Failed



# 1 Alarm Description

The alarm is raised when an auto-export backup has failed.

Table 1 BRM, Auto Export Backup Failed Alarm Causes

Alarm Cause	Description	Fault Reason	Fault Location	Impact
An auto-export backup has failed	A Backup and Restore Management (BRM) scheduled export to the configured backup storage server has failed	The external file storage fails to authenticate the SSH File Transfer Protocol (SFTP) user used by the Managed Element (ME)	ME configuration	The scheduled export fails. The next successful scheduled export clears the alarm.
		The ME attempts to store SFTP files in a directory that does not exist in the external file storage	ME configuration	
		The ME cannot reach the external file storage over SFTP	Network problems	
		The SFTP user used by the ME does not have the permission to write files in the specified external file directory	External file storage directory permissions	

**Note:** This alarm can appear as a result of a maintenance activity.



## 2 Procedure

### 2.1 Handle Alarm BRM, Auto Export Backup Failed

#### Prerequisites

— This instruction references the following documents:

- [Data Collection Guideline](#)
- [Schedule Single Backup](#)

**Note:** This Operating Instruction describes only the System Data backup instructions. To apply them to a User Data backup, navigate to the User Data backup manager in the first step, as follows:

```
>dn ManagedElement=<node_name>,SystemFunctions=1,BrM=1,BrmBackupManager=USER_DATA
```

— No tools are required.

— The following conditions must apply:

- The alarm is raised.
- The address, SFTP username, and password for the external file storage are known. In this instruction, the username is `hostuser1` and the password is `hostuser1pw` in `host1`.
- An Ericsson Command-Line Interface (ECLI) session in Exec mode is in progress.

#### Steps

1. Check the alarm attribute `Additional Text`.

2. Select action based on the attribute value:

- If `Additional Text` contains `Auto Export for <backup_type> failed due to authentication failure`, proceed with [Section 2.2 Handle Reason Authentication Failure](#) on page 3.
- If `Additional Text` contains `Auto Export for <backup_type> failed due to directory not exist`, proceed with [Section 2.3 Handle Reason Directory Not Exist](#) on page 4.
- If `Additional Text` contains `Auto Export for <backup_type> failed due to server unreachable`, proceed with [Section 2.4 Handle Reason Server Unreachable](#) on page 5.



- If Additional Text contains Auto Export for <backup\_type> failed due to permission denied, proceed with Section 2.5 Handle Reason Permission Denied on page 6.
- If Additional Text contains Auto Export for <backup\_type> failed, proceed with Section 2.6 Handle Undetermined Reason on page 6. This Additional Text is displayed when an export of a scheduled backup fails for an undetermined reason.

## 2.2 Handle Reason Authentication Failure

### Steps

1. Navigate to the `BrmBackupScheduler` Managed Object (MO), for example:

```
>dn ManagedElement=N0DE06ST, SystemFunctions=1, BrM=1, BrmBackupMa
nager=SYSTEM_DATA, BrmBackupScheduler=SYSTEM_DATA
```

2. Check that the SFTP user configured in the ME is the correct one to export backup files to the external file storage:

```
(BrmBackupScheduler=SYSTEM_DATA)>show autoExportUri
```

3. Obtain the password associated to this SFTP user (contact the external file storage administrator, if necessary).

4. Enter Config mode:

```
(BrmBackupScheduler=SYSTEM_DATA)>configure
```

5. Is it needed to change the configured username?

Yes: Continue with the next step.

No: Proceed with Step 7.

6. Change the configured username in attribute `autoExportUri`, for example:

```
(config-BrmBackupScheduler=SYSTEM_DATA)>autoExportUri=sftp://ho
stuser1@host1/home/hostuser1/
```

**Note:** Only SFTP URIs are supported. The syntax is `sftp://<user_id>@<hostname_or_ip_address>/<remote_destination_directory>`

7. Change the configured password, for example:

```
(config-BrmBackupScheduler=SYSTEM_DATA)>autoExportPassword="hos
tuser1pw" cleartext
```

8. Commit the changes:

```
(config-BrmBackupScheduler=SYSTEM_DATA)>commit
```



9. Schedule a single backup.

For information on how to schedule a single backup, refer to [Schedule Single Backup](#).

**Note:** It is assumed that there are no scheduled backup events left in the ME, or the existing scheduled backup events are too far in time and therefore not appropriate to wait for to clear the alarm.

10. Is the alarm cleared?

Yes: Proceed with Step 13.

No: Continue with the next step.

11. Perform data collection, refer to [Data Collection Guideline](#).

12. Consult the next level of maintenance support. Further actions are outside the scope of this instruction.

13. Job is completed.

## 2.3 Handle Reason Directory Not Exist

### Steps

1. Check which directory is meant to be used in the external file storage for export of backup files (contact the external file storage administrator, if necessary).

2. Navigate to the `BrmBackupScheduler` MO, for example:

```
>dn ManagedElement=NODE06ST,SystemFunctions=1,BrM=1,BrmBackupManager=SYSTEM_DATA,BrmBackupScheduler=SYSTEM_DATA
```

3. Enter Config mode:

```
(BrmBackupScheduler=SYSTEM_DATA)>configure
```

4. Change the directory configured in the ME:

```
(config-BrmBackupScheduler=SYSTEM_DATA)>autoExportUri=sftp://hostuser1@host1/home/hostuser1/
```

**Note:** Only SFTP URIs are supported. The syntax is `sftp://<user_id>@<hostname_or_ip_address>/<remote_destination_directory>`

5. Commit the change:

```
(config-BrmBackupScheduler=SYSTEM_DATA)>commit
```

6. Schedule a single backup.





For information on how to schedule a single backup, refer to [Schedule Single Backup](#).

**Note:** It is assumed that there are no scheduled backup events left in the ME, or the existing scheduled backup events are too far in time and therefore not appropriate to wait for to clear the alarm.

7. Is the alarm cleared?

Yes: Proceed with Step 10.

No: Continue with the next step.

8. Perform data collection, refer to [Data Collection Guideline](#).

9. Consult the next level of maintenance support. Further actions are outside the scope of this instruction.

10. Job is completed.

## 2.4

### Handle Reason Server Unreachable

#### Steps

1. Check the connection to the external file storage using `ping` and `traceroute`.

In this instruction, the external file system is called `host1`.

2. Can the external system be reached with a delay less than 10 seconds?

Yes: Continue with the next step.

No: The network can have a configuration fault. Request the network administrator to act on the fault. Proceed with Step 7.

3. Schedule a single backup.

For information on how to schedule a single backup, refer to [Schedule Single Backup](#).

**Note:** It is assumed that there are no scheduled backup events left in the ME, or the existing scheduled backup events are too far in time and therefore not appropriate to wait for to clear the alarm.

4. Is the alarm cleared?

Yes: Proceed with Step 7.

No: Continue with the next step.

5. Perform data collection, refer to [Data Collection Guideline](#).



6. Consult the next level of maintenance support. Further actions are outside the scope of this instruction.
7. Job is completed.

## 2.5 Handle Reason Permission Denied

### Steps

1. Navigate to the `BrmBackupScheduler` MO, for example:

```
>dn ManagedElement=NODE06ST,SystemFunctions=1,BrM=1,BrmBackupMa  
nager=SYSTEM_DATA,BrmBackupScheduler=SYSTEM_DATA
```

2. Check the SFTP user and the directory configured in the ME:

```
(BrmBackupScheduler=SYSTEM_DATA)>show autoExportUri
```

3. Has the SFTP user proper write permissions in the external file storage directory (contact the external file storage administrator, if necessary)?

Yes: Proceed with Step 6.

No: Continue with the next step.

4. Schedule a single backup.

For information on how to schedule a single backup, refer to [Schedule Single Backup](#).

**Note:** It is assumed that there are no scheduled backup events left in the ME, or the existing scheduled backup events are too far in time and therefore not appropriate to wait for to clear the alarm.

5. Is the alarm cleared?

Yes: Proceed with Step 8.

No: Proceed with Step 6.

6. Perform data collection, refer to [Data Collection Guideline](#).
7. Consult the next level of maintenance support. Further actions are outside the scope of this instruction.
8. Job is completed.

## 2.6 Handle Undetermined Reason

### Steps

1. Schedule a single backup.



For information on how to schedule a single backup, refer to [Schedule Single Backup](#).

**Note:** It is assumed that there are no scheduled backup events left in the ME, or the existing scheduled backup events are too far in time and therefore not appropriate to wait for to clear the alarm.

2. Is the alarm cleared?

Yes: Proceed with Step 5.

No: Continue with the next step.

3. Perform data collection, refer to [Data Collection Guideline](#).
4. Consult the next level of maintenance support. Further actions are outside the scope of this instruction.
5. Job is completed.