

Configure Ericsson Filter Version

OPERATING INSTRUCTIONS

Copyright

© Ericsson AB 2016. All rights reserved. No part of this document may be reproduced in any form without the written permission of the copyright owner.

Disclaimer

The contents of this document are subject to revision without notice due to continued progress in methodology, design and manufacturing. Ericsson shall have no liability for any error or damage of any kind resulting from the use of this document.

Trademark List

All trademarks mentioned herein are the property of their respective owners. These are shown in the document Trademark Information.



Contents

1	Introduction	1
1.1	Prerequisites	1
2	Procedure	3





1 Introduction

This document describes how to configure the Ericsson Filter version. Such change can be triggered by the organization security policy.

1.1 Prerequisites

This section describes the prerequisites, which must be fulfilled before using the procedure.

1.1.1 Conditions

The following conditions must apply:

- The user has the System Security Administrator role.
- The Managed Element (ME) is configured to connect with remote LDAP server, refer to *Configure LDAP Basic Connection* and *Configure TLS for LDAP*.
- The LDAP server is configured for the ME.
- `profileFilter` is set to `ERICSSON_FILTER`, refer to *Configure Ericsson LDAP Filter*.
- The ME Target Type is set and TBAC is enabled, refer to *Configure Target-Based Access Control*.
- The user profiles are updated with target qualifiers.
- An Ericsson Command-Line Interface (ECLI) session in Exec mode is in progress.





2 Procedure

To set the `version` attribute in *EricssonFilter* Managed Object (MO):

1. Navigate to the *EricssonFilter* MO, for example:

```
>dn ManagedElement=NODE06ST,SystemFunctions=1,SecM=1,UserManagement=1,LdapAuthenticationMethod=1,Ldap=1,EricssonFilter=1
```

2. Enter Config mode:

```
(EricssonFilter=1)>configure
```

3. Set the desired Ericsson Filter version, for example:

```
(config-EricssonFilter=1)>version=1
```

4. Commit the settings:

```
(config-EricssonFilter=1)>commit
```

5. Verify the result:

```
(EricssonFilter=1)>show -r ..
```

The following is an example output:

```
Ldap=1
  baseDn="dc=my-domain,dc=com"
  fallbackLdapIpAddress="192.168.0.11"
  ldapIpAddress="192.168.0.10"
  profileFilter=ERICSSON_FILTER
  EricssonFilter=1
    targetBasedAccessControl=UNLOCKED
    version=1
```