

Change Password Policy

OPERATING INSTRUCTIONS

Copyright

© Ericsson AB 2015, 2017. All rights reserved. No part of this document may be reproduced in any form without the written permission of the copyright owner.

Disclaimer

The contents of this document are subject to revision without notice due to continued progress in methodology, design and manufacturing. Ericsson shall have no liability for any error or damage of any kind resulting from the use of this document.

Trademark List

All trademarks mentioned herein are the property of their respective owners. These are shown in the document Trademark Information.



Contents

1	Description	1
2	Procedure	1
2.1	Change Password Policy	1





1 Description

This instruction describes how to change attributes in an existing password policy applicable for local Operation and Maintenance (O&M) user accounts.

2 Procedure

2.1 Change Password Policy

Prerequisites

- No documents are required.
- No tools are required.
- The following conditions must apply:
 - The user has sufficient access rights to perform the task, for example, the user has System Security Administrator role.
 - The user is familiar with the security policy of the organization.
 - An Ericsson Command-Line Interface (ECLI) session in Exec mode is in progress.
 - The password policy is known.

Steps

1. Navigate to the *PasswordPolicy* Managed Object (MO), for example:

```
>dn ManagedElement=NODE06ST, SystemFunctions=1, SecM=1, UserManagement=1, LocalAuthenticationMethod=1, PasswordPolicy=1
```

2. Enter Config mode:

```
(PasswordPolicy=1) >configure
```

3. Set the *PasswordPolicy* attributes according to operators password policy, for example:

```
(config-PasswordPolicy=1) >minLength=12
```



4. Commit the settings:

```
(config-PasswordPolicy=1) > commit
```

5. Verify the settings:

```
(PasswordPolicy=1) > show -v
```

The following is an example output:

```
PasswordPolicy=1
  expireWarning=7 <default>
  failureCountInterval=1800 <default>
  historyLength=12 <default>
  lockoutDuration=[] <empty>
  maxAge=90 <default>
  maxFailure=3 <default>
  minAge=15 <default>
  minLength=12
  passwordPolicyId="1"
  passwordQuality="ManagedElement=1,=>
SystemFunctions=1,SecM=1,UserManagement=1,=>
LocalAuthenticationMethod=1,PasswordQuality=1"
  reservedByAccount=[] <empty> <read-only>
  userLabel=[] <empty>
```