

# Delete Upgrade Package

---

## OPERATING INSTRUCTIONS

**Copyright**

© Ericsson AB 2016, 2017. All rights reserved. No part of this document may be reproduced in any form without the written permission of the copyright owner.

**Disclaimer**

The contents of this document are subject to revision without notice due to continued progress in methodology, design and manufacturing. Ericsson shall have no liability for any error or damage of any kind resulting from the use of this document.

**Trademark List**

All trademarks mentioned herein are the property of their respective owners. These are shown in the document Trademark Information.



# Contents

<b>1</b>	<b>Description</b>	<b>1</b>
<b>2</b>	<b>Procedure</b>	<b>1</b>
2.1	Delete Upgrade Package	1



Delete Upgrade Package



# 1 Description

This instruction describes how to delete an upgrade package managed object. It can be done once an upgrade package has been applied and is no longer needed on the Managed Element (ME).

**Note:** If the upgrade file initially was retrieved from a Uniform Resource Identifier (URI), this operation deletes it together with the managed object. If the upgrade package file initially was downloaded with the SSH File Transfer Protocol (SFTP), this operation does not delete it from the ME.

## 2 Procedure

### 2.1 Delete Upgrade Package

#### Prerequisites

- No documents are required.
- No tools are required.
- The following conditions must apply:
  - An *UpgradePackage* managed object for which the corresponding software version or a later software version is present exists.
  - An Ericsson Command-Line Interface (ECLI) session in Exec mode is in progress.

#### Steps

1. Navigate to the *SwM* managed object, for example:

```
>dn ManagedElement=NODE06ST,SystemFunctions=1,SwM=1
```

2. Check the available upgrade packages:

```
(SwM=1) >show -v
```

The following example output shows an upgrade package managed object targeting an upgrade of the software version to the revision already



activated is visible. The upgrade package is no longer applicable to the current software version and can be deleted.

```
SwM=1
[...]  
UpgradePackage=UpgradePackage=ERIC_UP-CXP9020355_1-R7F01
```

3. Delete the *UpgradePackage* managed object, for example:

```
(SwM=1) >removeUpgradePackage ManagedElement=NODE06ST, SystemFunctions=1, SwM=1, UpgradePackage=ERIC_UP-CXP9020355_1-R7F01
```

The system returns output `true` or `false`.

4. Verify the success of the deletion operation and that the *UpgradePackage* managed object is deleted:

```
(SwM=1) >show -v
```

The following example output shows the final result. If `state=RUNNING`, the operation is not yet completed. Result `result=FAILURE` means that the deletion failed.

```
SwM=1
[...]  
  reportProgress <read-only>  
    actionName="RemoveUpgradePackage" <read-only>  
[...]  
  result=SUCCESS <read-only>  
[...]  
  state=FINISHED <read-only>  
[...]
```

**Note:** If the *UpgradePackage* managed object has been created with operation `createUpgradePackageLocal`, then the upgrade package file that was downloaded in *Prepare Upgrade Package* still exists in the file system of the ME. The deletion of the upgrade package file is outside the scope of this document.