

RELAYS
PAPER ARMATURE STOPS, BACKSTOPS, AND SEPARATORS
APPLICATION AND LIST OF RELAYS

	PAGE		PAGE
1. GENERAL	1	TOLL SYSTEM	9
2. UNRESTRICTED APPLICATION — NO CHANGES IN ELECTRICAL OR MECHANICAL REQUIREMENTS	2	Table R No. 3 Switchboard Trunk Circuits	9
3. UNRESTRICTED APPLICATION — WITH CHANGES IN ELECTRICAL AND MECHANICAL REQUIREMENTS	3	Table S Miscellaneous Circuits	9
Table A Unrestricted Application	3	COMMON SYSTEMS	10
4. RESTRICTED APPLICATION	3	Table T Miscellaneous Circuits	10
PANEL SYSTEM	3	PBX SYSTEMS	11
Table B Senders — Subscribers	3	Table U Miscellaneous Circuits	11
Table C Senders — Local Tandem, Full Selector Tandem, Call Distributing "B" Switchboard, and Semi-mechanical "A" Switchboard (Suburban)	5	1. GENERAL	
Table D Incoming Selectors	5	1.01 This section indicates whether or not removable D-93568 and D-97950 paper armature stops, D-95367 removable paper backstop, D-159461 backstop nut, or KS-7246 or KS-7743 separators may be applied to certain relays for the purpose of relieving sticking conditions; and lists the relays on which separators shall be applied by the Western Electric Company.	
Table E Line Finder and District Selectors	5	1.02 This section is reissued to include additional relays in Table D.	
Table F Decoders and Decoder Connectors	6	1.03 Armature stops or separators shall be applied by the Western Electric Company to all relays listed in Parts 2 and 3 when these relays have a zinc-plate finish on the core, and to the E1325, R132, and No. 149P relays as listed in Part 4. Armature stops or separators are not required on relays having chromium-plated cores and zinc-plated armatures with stop pins, nor on relays having chromium finish on both the armature and the core, unless otherwise stated in this section. The B1071 relay shall have paper stops applied to the core, regardless of finish.	
Table G Line, Trip, Start, and Link Circuits	6	1.04 The procedures for applying removable paper armature stops, backstops, or separators to relays are covered in the sections covering the particular type of relay.	
Table H Panel "A" and "B" Switchboard Cord Circuits	6		
Table J Miscellaneous Circuits	6		
MANUAL SYSTEM	7		
Table K Panel Call Indicator Trunks	7		
Table L Miscellaneous Trunk and Trunk Applique Circuits	7		
Table M Panel Call Indicator Control and Lamp Circuits	7		
Table N "A" Switchboard Cord Circuits	8		
Table O Miscellaneous Circuits	8		
STEP-BY-STEP SYSTEM	8		
Table P Call Indicator and "A" Switchboard Trunk Circuits	8		
Table Q Miscellaneous Circuits	8		

SECTION 040-014-811

1.05 Removable paper armature stops and paper separators may be used on relays not listed in this section only if the relay has both hold and release timing requirements, or both hold and release current flow requirements specified in the circuit requirement tables. The specified requirements shall be met after the armature stops or separators are applied. However, removable paper armature stops or separators shall not be applied to any relay equipped with removable metal armature stops, nor to any relay having permalloy pole pieces, unless otherwise specified in this section. Pole pieces stamped with a U are permalloy.

1.06 The notes and the requirement changes covered in the tables of Parts 3 and 4 of this section are important, as they give electrical and mechanical requirements that are in addition to, or supersede, the corresponding information given in the circuit requirement tables. Adjustment and circuit difficulties may be encountered unless the requirements given in the notes are used at the time the stop or separator is applied.

1.07 When the circuit requirement tables show operate or hold requirements greater than, or nonoperate or release requirements less than, the values specified in the table of Parts 3 and 4, the values shown in the circuit requirement tables shall be used.

1.08 Unless otherwise specified in the circuit requirement tables, the requirements recommended in the notes and changes covered in Parts 3 and 4, for use when relays are equipped with separators or removable paper armature stops, are also satisfactory when the relays are not so equipped.

2. UNRESTRICTED APPLICATION—NO CHANGES IN ELECTRICAL OR MECHANICAL REQUIREMENTS

2.01 Removable paper armature stops, backstops, or separators, may be applied by the telephone companies unconditionally to the relays covered in 2.02 and 2.03 when necessary to relieve sticking conditions. Also, see 1.03 and 1.04.

2.02 B- and G-type Relays: To relieve sticking conditions between the armature and stop springs not equipped with contact metal, use the D-95367 removable paper backstop. To relieve sticking conditions between the armature and core, use the D-93568 paper armature stop.

B1	B343	B423	B578	B1071
B9	B376	B435	B579	B1076
B10	B392	B436	B581	B1086
B55	B403	B455	B582	B1131
B104	B412	B456	B584	
B144	B413	B464	B601	G41
B159	B414	B466	B1018	G80
B180	B415	B471	B1023	G81
B207	B418	B475	B1039	G88
B297	B419	B493	B1049	G94
B303	B421	B527	B1057	
B304	B422	B567	B1060	

2.03 E-, H-, R-, and AB-type Relays: To relieve sticking conditions between the armature and adjusting nut on these relays, use either the KS-7743 paper separator or the D-159461 backstop nut. To relieve sticking conditions between armature and core, use the KS-7246 paper separator.

E133	E731	E1367	E6138
E266	E733	E1510	E6168
E341	E734	E1609	E6260
E385	E735	E1610	E6296
E467	E748	E1624	E6358
E512	E781	E1632	E6380
E523	E787	E1717	E6402
E543	E792	E1736	E6403
E555	E822	E1767	E6416
E593	E827	E1815	E6417
E672	E828	E1822	E6436
E698	E853	†E1838	E6440
E699	E892	E1867	E6442
E706	E952	E1870	E6450
E707	E964	E1875	E6482
E716	E1351	E6037	E6495

H28

R32	R795	R1189	R1316	R1764
R39	R802	R1194	R1317	R1852
R71	R884	R1195	R1349	R1897
R82	R887	R1200	R1469	R1924
R94	R889	R1201	R1470	R1959
R122	R891	R1202	R1477	R1972
R458	R900	R1203	R1507	R1979
R493	R904	R1206	R1617	R2077
R518	R952	R1216	R1672	R6000
R586	R997	R1223	R1687	R6004
R603	R1022	R1246	R1728	R6017
R674	R1132	R1248	R1743	D-90634
R704	R1139	R1298	R1751	

AB2

3. UNRESTRICTED APPLICATION — WITH CHANGES IN ELECTRICAL AND MECHANICAL REQUIREMENTS

3.01 KS-7246 separators may be applied by the telephone companies to the relays listed in Table A when necessary to relieve sticking conditions. Electrical requirements, accordingly, shall be changed or added as specified in Table A. (For exceptions, see 1.07.) The remaining electrical requirements (if any) specified in the circuit requirement table shall apply unchanged. It is important that the paper separator, when applied, is smooth and tight against the pole face. Also, see 1.03 through 1.08.

TABLE A — UNRESTRICTED APPLICATION					
CODE NUMBER	REQ CHANGED	TEST WDG	VALUE TO BE USED		SEE NOTE
			TEST MA	READJ MA	
E435	Hold	P	27	25	
E436	Opr	P	45	42	
	Hold	P/S	24	22.5	
E541	Opr	P	15	11	1
		P/S	14	—	1
		P	32.5	24	2
		P/S	28	—	2
E714	Hold	P/S	33	30.5	
E715	Opr	P	60	57	
E717	Hold	P	25	23.5	
E718	Hold	P	25	23.5	
E786	Hold	P	26	24.5	
E821	Hold	S	48	45.5	
E833	Hold	S	48	45.5	
E1217	Opr	P	12	11.4	
E1503	Hold	P	20	19	
E1544	Hold	P	20	19	
E1591	Opr	P	5.3	5	
E1866	Hold	P	25	23.5	
E1873	Hold	P	20.5	19.5	
R92	Opr	P	40	38	
R161	Opr	P	17	13.2	
	Nonopr	P	5.9	6.3	
	Hold	P	10.4	9.9	
R667	Hold	S	18	14	
R1264	Hold	S	16.5	15.5	
R1319	Hold	S	26.5	25	
R1321	Hold	S	9.8	9.3	

TABLE A (Cont)					
CODE NUMBER	REQ CHANGED	TEST WDG	VALUE TO BE USED		SEE NOTE
			TEST MA	READJ MA	
R1322	Hold	P	—	15.5	
R1775	Hold	S	18	17	
	Hold	P	18	—	1
		P	39.5	—	4
		S	—	11.3	1
R1937	Arm. Travel	—	—	—	3 & 5
R1938	Opr	P	—	34	

Note 1: For relay winding alone.

Note 2: For circuit combination of relay and No. 18AJ resistor.

Note 3: The Western Electric Company does not apply separators to this relay.

Note 4: For circuit combination of relays C and Z in district selector circuits.

Note 5: After the separator is applied, the armature travel shall be
 Min 0.015 inch
 Max 0.020 inch

4. RESTRICTED APPLICATION

4.01 General: The following tables specify whether or not removable paper armature stops and separators may be applied to relieve sticking conditions on relays when used as designated in the circuits listed. Changes or additions to the electrical and mechanical requirements of relays approved for papering are covered in the notes referred to in the Arm. Stops or Separators Approved column for the particular relay. It is important that the separator, when applied, is smooth and tight against the pole face. Also, see 1.03 through 1.08.

PANEL SYSTEM

TABLE B — SENDERS — SUBSCRIBERS		
CODE NUMBER	CIRCUIT DESIGNATION	ARM. STOPS OR SEPARATORS APPROVED
B160	TG	No
B167	MTG, TG	Yes
B178	TG	No

TABLE B (Cont)		
CODE NUMBER	CIRCUIT DESIGNATION	ARM. STOPS OR SEPARATORS APPROVED
E566	TG1	Yes
E635	TG1	Yes
E644	LL	Yes
E659	TG1, TG2	No
E669	SD	Yes
E823	HR6, SD5	Yes
E1032	HC	Yes
E1036	ON2	Yes
E1167	ON, ON1, ON2	No
E1229	FO2	No
E1303	ON1	No
E1325	TS	Yes, See Note 1
E1370	HC	Yes
E1431	DB2, DG2, DG4, OB2, OG2, OG4, Z6	No
E1613	SD	Yes
E1731	CL	No
E1982	PP	No
E6033	FO2	No
E6133	L1, PH	Yes
E6185	ON1	No
E6432	TC	Yes
E6449	C4	No
E6451	C6	No
E6452	DB1, DG1, OB1, OG1, TS1, Z5, CL4	No
E6454	SKO6, SO6	No
E6455	SD5	No
E6456	CL1, CL3, FR, SD4, ST6, TS1, TS2, TS3, Z5	No
E6459	DB1, DG1, OB1, OG1, TS1, Z5	No
R33	TG2	Yes
R65	TR4	Yes
R112	TW6	No
R129	C5, DB3, DG3, OB3, OG3, R5, R6, Z5A, Z6	No
R170	CC5	No
R235	C4A	No
R420	TM	Yes
R449	SA	No
R581	CK	Yes
R1188	H5, U5	No
R1191	AL	Yes
R1192	BZ, CZ	See Note 2
R1192	H1, H2, H4, T1, T2, T4, U1, U2, U4	No
R1193	B5, C5, ST4, TH5	No

TABLE B (Cont)																																										
CODE NUMBER	CIRCUIT DESIGNATION	ARM. STOPS OR SEPARATORS APPROVED																																								
R1196	ST2, TH2	No																																								
R1197	ST5, T5, TH1, TH4	No																																								
R1210	A1, A4, B1, B2, B4, C1, C2, C4, H1, H2, H4	No																																								
R1212	A1, A4, ST1	No																																								
R1213	A2	No																																								
R1214	A5	No																																								
R1215	AC	Yes																																								
R1230	BL, CL, HL, TL, THL	Yes																																								
R1242	STL	Yes																																								
R1323	CL2	No																																								
R1365	AL	Yes																																								
R1414	FR	See Note 3																																								
R1481	A2, A5	No																																								
R1482	RL	Yes																																								
R1583	UL	Yes																																								
R1692	B5, C5, ST4, TH5	No																																								
R1697	TMS	See Note 4																																								
R1878	TMS	Yes																																								
R1965	CL3	Yes																																								
149AT	SR	See Note 5																																								
149BT	RS	No																																								
149CJ	SR	See Note 5																																								
178AD	RA	See Note 6																																								
178CL	RA	See Note 6																																								
178CW	RA	See Note 6																																								
178EG	SR	Yes																																								
D-92525	T5	Yes																																								
<p>Note 1: When these relays have a zinc-plate finish on the core, separators shall be applied by Western Electric Company.</p> <p>Note 2: Separators may be applied to this relay if the following requirements are used:</p> <table border="1"> <thead> <tr> <th rowspan="2">WINDING</th> <th rowspan="2">TEST FOR</th> <th colspan="2">VALUE TO BE USED</th> </tr> <tr> <th>TEST MA</th> <th>READJ MA</th> </tr> </thead> <tbody> <tr> <td>Sec</td> <td>Operate</td> <td>—</td> <td>29</td> </tr> <tr> <td>Sec</td> <td>Hold</td> <td>18</td> <td>17</td> </tr> <tr> <td>Pri</td> <td>Operate</td> <td>18.5</td> <td>—</td> </tr> </tbody> </table> <p>Note 3: Separators may be applied to this relay if the following requirements are used:</p> <table border="1"> <thead> <tr> <th rowspan="2">REQ CHANGED</th> <th colspan="2">VALUE TO BE USED</th> </tr> <tr> <th>TEST MA</th> <th>READJ MA</th> </tr> </thead> <tbody> <tr> <td>Operate</td> <td>37.5</td> <td>35</td> </tr> </tbody> </table> <p>Note 4: Separators may be applied to this relay if the following requirements are used:</p> <table border="1"> <thead> <tr> <th rowspan="2">WINDINGS</th> <th rowspan="2">TEST FOR</th> <th colspan="2">VALUE TO BE USED</th> </tr> <tr> <th>TEST MA</th> <th>READJ MA</th> </tr> </thead> <tbody> <tr> <td>Pri/Sec</td> <td>Operate</td> <td>20</td> <td>19</td> </tr> <tr> <td>Pri/Sec</td> <td>Nonoperate</td> <td>8.7</td> <td>9.2</td> </tr> </tbody> </table>			WINDING	TEST FOR	VALUE TO BE USED		TEST MA	READJ MA	Sec	Operate	—	29	Sec	Hold	18	17	Pri	Operate	18.5	—	REQ CHANGED	VALUE TO BE USED		TEST MA	READJ MA	Operate	37.5	35	WINDINGS	TEST FOR	VALUE TO BE USED		TEST MA	READJ MA	Pri/Sec	Operate	20	19	Pri/Sec	Nonoperate	8.7	9.2
WINDING	TEST FOR	VALUE TO BE USED																																								
		TEST MA	READJ MA																																							
Sec	Operate	—	29																																							
Sec	Hold	18	17																																							
Pri	Operate	18.5	—																																							
REQ CHANGED	VALUE TO BE USED																																									
	TEST MA	READJ MA																																								
Operate	37.5	35																																								
WINDINGS	TEST FOR	VALUE TO BE USED																																								
		TEST MA	READJ MA																																							
Pri/Sec	Operate	20	19																																							
Pri/Sec	Nonoperate	8.7	9.2																																							

TABLE B (Cont)	
Note 5:	Separators may be applied to this relay if after being applied to the relay it still functions satisfactorily under pulsing tests by sender test circuit.
Note 6:	Separators may be applied to these relays only when they are used in decoder senders and the pole piece is magnetic iron. Pole pieces stamped with a U are permalloy, and separators should not be applied.

TABLE D (Cont)	
Note 1:	When these relays have a zinc-plate finish on the core, separators shall be applied by Western Electric Company.
Note 2:	Separators should be applied to this relay if used as shown in SD 21115-01-05 and SD-21116-01 when these circuits connect to E1F signaling units.

TABLE C — SENDERS — LOCAL TANDEM, FULL SELECTOR, TANDEM, CALL DISTRIBUTING "B" SWITCHBOARD, AND SEMIMECHANICAL "A" SWITCHBOARD (SUBURBAN)		
CODE NUMBER	CIRCUIT DESIGNATION	ARM. STOPS OR SEPARATORS APPROVED
B167 E659 R1524 149AR	TG, TGM C11, TG1, TG2 TRA, TRB, TRC TB	Yes No Yes See Note
Note: The release time of this relay will be shortened when a separator is applied to the armature. This will reduce the duration of the order tone pulse but is considered satisfactory.		

TABLE E — LINE FINDER AND DISTRICT SELECTORS		
CODE NUMBER	CIRCUIT DESIGNATION	ARM. STOPS OR SEPARATORS APPROVED
B per D-92440 E1325 R132	LT H OC	Yes See Notes 1 & 2 See Notes 2 & 3
R1270 R6006 149CE	S1 L A1	Yes No Yes
149CH 149CN 177E 203A	D A1 CS CS	No Yes See Note 4 See Note 4
Note 1: Separators may be applied to this relay if the armature travel is held to: Min 0.015 inch Max 0.020 inch after the separator is applied.		
Note 2: These relays, when used in zone and overtime district selector circuits, shall be equipped with separators by the Western Electric Company, as covered in 1.03.		
Note 3: Separators may be applied by the telephone companies to this relay when not equipped with separators if the following requirements are used:		
	TEST FOR	VALUE TO BE USED
		TEST MA READJ MA
	Operate	20 19
	Nonoperate	10.4 11
When this relay is used in zone and overtime district selector circuits, the 350-ohm resistor in the district shall be short-circuited.		
Note 4: These relays may require additional maintenance effort from time to time if they are equipped with separators.		

TABLE D — INCOMING SELECTORS		
CODE NUMBER	CIRCUIT DESIGNATION	ARM. STOPS OR SEPARATORS APPROVED
B15 B44 B73	CS1, S, S1 S A, A1	Yes Yes No
B76 B268 B361	S S A, A1	Yes Yes No
B1111 F17 R132 R638	TD D, SR L L	Yes No Yes, See Note 1 Yes
R1590 S523 UAB4 Y296	D A A D	See Note 2 Yes Yes Yes

TABLE F — DECODERS AND DECODER CONNECTORS

CODE NUMBER	CIRCUIT DESIGNATION	ARM. STOPS OR SEPARATORS APPROVED
E371 R291 R628 R1267	DGE, OBE SG R SAK, SA1 to SA8, SBK, SB1 to SB8	Yes Yes Yes Yes
R1313	CLA, CLB, CLC, etc., CRA, CRB, CRC, etc., DBA, DBB, DBC, etc., DGA to DGD, OBA to OBD, OGA, OGB, OGC	Yes
R1361 R1362	CK2 CK1	Yes Yes
R1378	SAK, SA1 to SA8, SBK, SB1 to SB8	Yes
R1468	CLO, CRO, DBO, DGO, OBO, OGO	Yes
R1471	DG3, DG6, OB6, OB7, OB9	Yes
R1729 R1914 R1915	R CK1, CK2 CK3	Yes See Note See Note

Note: Separators may be applied to these relays if the following requirements are used:

CODE NUMBER	TEST FOR	VALUE TO BE USED	
		TEST MA	READJ MA
R1914	Operate	47.5	45
R1915	Operate	37.5	35.5

TABLE G — LINE, TRIP, START, AND LINK CIRCUITS

CODE NUMBER	CIRCUIT DESIGNATION	ARM. STOPS OR SEPARATORS APPROVED
B171 E788 E1149	L1 CO O, O1	Yes Yes No
E1187 E6353 E6364	CO SL TR	Yes Yes Yes
E6465 R1496 R1498	R CO CO	No Yes Yes
R1931 R1932 R2032	CL Z L	See Note See Note Yes
EA8 EA9 D-91944	CO CO RG	Yes Yes Yes

TABLE G (Cont)

Note: Separators may be applied to this relay on the line, trip, start, and link circuit per SD-21626-01 only.

TABLE H — PANEL "A" AND "B" SWITCHBOARD CORD CIRCUITS

CODE NUMBER	CIRCUIT DESIGNATION	ARM. STOPS OR SEPARATORS APPROVED
B260 B577 B598	SC AS MC	Yes Yes Yes
B1013 E81 E182	CT, CT1 MGA MGA	Yes Yes Yes
E963 E1527 E1899	MGC MGC, MC MGC, MC	Yes Yes See Note

Note: Separators may be applied to this relay if the following requirements are used:

WINDING	TEST FOR	VALUE TO BE USED
		READJ MA
Primary (Wdg alone)	Hold	62.5
Primary (Parallel comb. of SC, SLC, or SLC1, and MC or MGC relays)	Hold	72

TABLE J — MISCELLANEOUS CIRCUITS

CODE NUMBER	CIRCUIT DESIGNATION	DESCRIPTION OF CIRCUIT	ARM. STOPS OR SEPARATORS APPROVED
A50 A57 B135	L1 L ST	Misc Reg Ckt Misc Reg Ckt "A" Swbd OGT	Yes Yes Yes
B1079 E199 E458	TK L L1	Rec Comp Trk Misc Reg Ckt Misc Reg Ckt	Yes Yes Yes

TABLE J (Cont)			
CODE NUMBER	CIRCUIT DESIGNATION	DESCRIPTION OF CIRCUIT	ARM. STOPS OR SEPARATORS APPROVED
E1229	FSI	Test Trk	Yes
E1383	TB	Final Sel	No
E1472	L, LR	Misc Reg Ckt	Yes
E1684	L1	Misc Reg Ckt	Yes
E6471	L	Misc Reg Ckt	Yes
G84	BG	Announcement Trk	Yes
G93	TK	Rec Comp Trk	Yes
R136	L	Office Sel	Yes
R289	C	Coin Control	Yes
R1306	Z4	Mess Reg Conn.	Yes
R1431	RL	"A" Swbd Keyset	Yes
R6006	SH	Cordless "B" Link	No

MANUAL SYSTEM

TABLE K — PANEL CALL INDICATOR TRUNKS		
CODE NUMBER	CIRCUIT DESIGNATION	ARM. STOPS OR SEPARATORS APPROVED
B15	S, S3	Yes
B73	A, AO	Yes
B361	A, AO	Yes
B1084	A	Yes
E34	S1	Yes
E561	RC	Yes
E945	RC	Yes
E1706	RC	Yes

TABLE L — MISCELLANEOUS TRUNK AND TRUNK APPLIQUE CIRCUITS		
CODE NUMBER	CIRCUIT DESIGNATION	ARM. STOPS OR SEPARATORS APPROVED
B15	—	Yes
B59	A, L	Yes
B468	L	Yes
E1001	LM	No
G49	S1	Yes
G83	S	Yes
R73	SL	No
R494	WO	Yes
R550	P	No
R583	PU	Yes
R1165	SL	No
R1765	SL	Yes
R1784	R1	See Note 1
R1787	P	No
T4	RC	See Note 2

TABLE L (Cont)		
<i>Note 1:</i> Separators may be applied to this relay if the following requirements are used:		
	VALUE TO BE USED	
TEST FOR	TEST MA	READJ MA
Operate	33	31
<i>Note 2:</i> Separators may be applied to this relay only if timing requirements are specified in the circuit requirement tables.		

TABLE M — PANEL CALL INDICATOR CONTROL AND LAMP CIRCUITS		
CODE NUMBER	CIRCUIT DESIGNATION	ARM. STOPS OR SEPARATORS APPROVED
E34	Lamp	Yes
E433	ST	Yes
E437	HO2	Yes
E576	HO2	Yes
E598	PC	Yes
E600	PC	Yes
E686	HO2	Yes
E697	Z	No
E745	KC	See Note 1
E843	HO	See Note 1
E956	ST	Yes
E959	DO	See Note 1
E1128	Lamp	No
E1207	U1	See Note 1
E1542	H, T, ST	No
E1838	Lamp	See Note 2
E1839	Lamp	No
E6166	HO2	Yes
E6369	U1	See Note 1
R923	KL	Yes
R1414	KL	No
R1449	HO	Yes
R1450	HO	No

<i>Note 1:</i> Separators may be applied to these relays if the following requirements are used:			
	VALUE TO BE USED		
NOTE NUMBER	TEST FOR	TEST MA	READJ MA
1	Operate	5.3	5
	Hold	26.5	25
1	Operate	35	—
1	Hold	22.5	21
	Operate	29	27.5
2	Operate	48	45.5
<i>Note 2:</i> Separators shall not be applied to the E1838 relay if it replaces the E1128 relay in this circuit.			

TABLE N — "A" SWITCHBOARD CORD CIRCUITS

CODE NUMBER	CIRCUIT DESIGNATION	ARM. STOPS OR SEPARATORS APPROVED
B2	SC	Yes
B3	SA, SC	Yes
B4	SA, SC	Yes
B18	A, C	Yes
B76	A, C	Yes
B337	R	Yes
B374	SL3	Yes
B577	A3	Yes
E144	FR	No
E302	AR, AS, FL, R	Yes
E1718	F	No
E1899	MC	See Note
R234	FR	No

Note: Separators may be applied to this relay if the following requirements are used:

WINDING	VALUE TO BE USED	
	TEST FOR	READJ MA
Primary (Wdg alone)	Hold	62.5
Primary (Parallel comb. of SC, SLC, or SLC1, and MC or MGC relays)	Hold	72

TABLE O — MISCELLANEOUS CIRCUITS

CODE NUMBER	CIRCUIT DESIGNATION	DESCRIPTION OF CIRCUIT	ARM. STOPS OR SEPARATORS APPROVED
A2	CO	Sub Line	Yes
A26	CO	Sub Line	Yes
AB4	CO	Sub Line	Yes
E238	R	No. 1 Position Dial Ckt	No
E1601	R	No. 1 Position Dial Ckt	No
R75	PM2	Type C Control Ckt No. 1 Swbd	Yes
R440	AV	Step-by-Step CI Recorder	No

TABLE O (Cont)

CODE NUMBER	CIRCUIT DESIGNATION	DESCRIPTION OF CIRCUIT	ARM. STOPS OR SEPARATORS APPROVED
R1070	PM	Position Control Ckt	No
R1318	TK	No. 1 or 2 Info Desk	Yes
R6002	W	ADCI Recorder	See Note

Note: The requirements given for a relay equipped with separators are usually also satisfactory when the relay is not equipped with separators. This relay is an exception, and the following current flow values must be used only when relay is equipped with separators. See the circuit requirement tables for the values to use when the relay is not equipped with separators.

TEST FOR	VALUES TO BE USED	
	TEST MA	READJ MA
Operate	24	22.5
Nonoperate	10	10.5
Hold	13.6	12.9

STEP-BY-STEP SYSTEM

TABLE P — CALL INDICATOR AND "A" SWITCHBOARD TRUNK CIRCUITS

CODE NUMBER	CIRCUIT DESIGNATION	ARM. STOPS OR SEPARATORS APPROVED
B424	L	Yes
E1490	K	Yes
G45	H	Yes
G49	L	Yes
G51	L	Yes
G93	L1	Yes
J52	RR, RT	No

TABLE Q — MISCELLANEOUS CIRCUITS

CODE NUMBER	CIRCUIT DESIGNATION	DESCRIPTION OF CIRCUIT	ARM. STOPS OR SEPARATORS APPROVED
B598	MC	"A" Swbd Cord	Yes
E1527	MC	"A" Swbb Cord	Yes
G37	L	Test Line, No. 12C Local Test Desk	Yes

TABLE Q (Cont)			
CODE NUMBER	CIRCUIT DESIGNATION	DESCRIPTION OF CIRCUIT	ARM. STOPS OR APPROVED SEPARATORS
G37	L	Test Line, No. 1C Repair Service Desk	Yes
G51	L	Test Line, No. 12C Local Test Desk	Yes
G51	L	Test Line, No. 1C Repair Service Desk	Yes
G51	A	By-pass Sel	Yes
J51	MR1	Power Alarm	No
R508	CO	Line Finder	Yes
R913	L	Line Finder	Yes
149AR	SL	Test Line, No. 12C Local Test Desk	Yes
149AR	N	No. 1, 350A, 355A Coin Trks	Yes
149AR	SR	No. 1, 350A OGT	Yes
149AR	H, H1	711 PBX, 2-way Tie	Yes
149BH	SL	Test Line, No. 12C Local Test Desk	Yes
149CE	H	Dial Long Lines No. 1, 350A, 355A, 360A	See Note
149CG	N	No. 1, 350A, 355A Coin Trks	Yes
149CG	SR	No. 1, 350A OGT	Yes
149CG	H, H1	711 PBX, 2-way Tie	Yes
149CH	N	N Coin Trk	Yes
149CN	H	Dial Long Line, Nos. 1, 350A, 355A, 360A	See Note
149CN	H1	No. 1, 350A OGT	Yes
178EB	H2	No. 1, 350A OGT	Yes

Note: Separators may be applied to this relay if the following requirements are used in addition to the current flow requirements:

TEST FOR	TEST MA	READJ MA
Hold	1	0.9

TOLL SYSTEM

TABLE R — NO. 3 SWITCHBOARD TRUNK CIRCUITS		
CODE NUMBER	CIRCUIT DESIGNATION	ARM. STOPS OR SEPARATORS APPROVED
B199	S	Yes
B523	S	Yes
B558	S	Yes
B560	S	Yes
B1009	F	Yes
B1024	S	Yes
B1085	S	Yes
178CA	A	Yes

TABLE S — MISCELLANEOUS CIRCUITS			
CODE NUMBER	CIRCUIT DESIGNATION	DESCRIPTION OF CIRCUIT	ARM. STOPS OR SEPARATORS APPROVED
B33	—	No. 2 Toll Cord	Yes
B43	BR	No. 1 Toll Cord	Yes
B191	S1	Telegraph Loop Terminal	Yes
B261	SL	No. 1 Toll Cord	Yes
B265	B	Alarm Trk	Yes
B458	DT	No. 1 OGT	Yes
B516	B	Alarm Trk	Yes
B558	S	Sub Line	Yes
B583	S	Teletypewriter Swbd	No
B1019	S	Incoming Trk	Yes
B1025	S, TS	No. 3 Swbd Ringdown Toll Line	Yes
B1034	A	Intertoll Dial Auxiliary Trk	Yes
B1042	DC	1000-cycle Term. Ringer	No
B1092	L	Toll Tandem Idle Indicating	Yes
B1114	P1, F1	Alarm Trk	Yes
E28	B	No. 1 Swbd Ringdown Toll Line	No
J1	RU	1000-cycle Term. Ringer	No
R857	C	No. 3 Toll Cord	No
R1127	B	Talking Service Signaling Ckt	Yes
R1292	A	No. 3 Swbd Dial Ckt	No
R1495	WO	No. 1 Inc Trk	Yes

TABLE S (Cont)			
CODE NUMBER	CIRCUIT DESIGNATION	DESCRIPTION OF CIRCUIT	ARM. STOPS OR SEPARATORS APPROVED
R1523	F	Alarm Ckt	Yes
T9	E	Teletypewriter Sel	See Note 3
T11	F	Teletypewriter Sel	No
149P	B, E, F	Teletypewriter Swbd	Yes, See Note 1
149T	GR2	No. 3 or 11 Signaling	Yes
149T	C	Sig 135-20 Inter. Ring.	Yes
149T	C	Sig 135-20 Term. Ring.	Yes
149AD	—	Teletypewriter Line	Yes
149BD	B	No. 3, 3C Rec-Compl Trk	Yes
149BL	D	No. 3 Operator Position	Yes
149BL	B, K	No. 3 Position Dial	Yes
149CD	SR	1000-cycle Signaling	Yes
149CE	B, E, F	Teletypewriter Swbd	Yes, See Note 1
149CE	B, K	No. 3 Position Dial	Yes
149CE	D	No. 3 Operator Position	Yes
162B	SR	No. 3, 3C, or 3CF Intertoll Patching Ckt	Yes
162B	S3, S4	20-20 Cycle Sig Inter Ringer	See Note 2
162B	GR1	No. 3 or 11 20-cycle Signaling	See Note 2
162B	RL	No. 1 Toll Cord	See Note 4
162B	SR	No. 1 Toll Line	Yes
162B	DA	Toll Tandem Aux Trk	Yes
178AA	C	Ringling Control	Yes

Note 1: When these relays have a zinc-plated finish on the core, separators shall be applied by Western Electric Company.

Note 2: Separators may be applied to this relay if the following requirements are used:

TEST FOR	VALUE TO BE USED	
	TEST MA	READJ MA
Operate	5.3	5

TABLE S (Cont)			
Note 3: Separators may be applied to this relay only if timing requirements are specified in the circuit requirement tables.			
Note 4: Separators may be applied to these relays if the following requirements are used:			
REQ CHANGED	SOAK	TEST MA	READJ MA
Operate	FS	13.3	12.6
Hold	FS	2.9	2.7
Release	FS	0.6	0.7

COMMON SYSTEMS

TABLE T — MISCELLANEOUS CIRCUITS			
CODE NUMBER	CIRCUIT DESIGNATION	DESCRIPTION OF CIRCUIT	ARM. STOPS OR SEPARATORS APPROVED
B1070	A	Inc Trk	Yes
B1156	LV1, LV2	800 Power Plant Ringing	Yes
R87	ZS	Emergency Alarm	Yes
R927	PG	Opr Tel and Trk, No. 3, 4, 6A, or 6B info Desk	Yes
R1757	GA	Emergency Alarm	Yes
149CP	S, SO, SO1, SO2	Service Obs	Yes
178AC	R1	Trk Ckt	Yes
178CN	FL	Comp Cord No. 15C Swbd	Yes
186A	R	Long PBX Line	See Note

Note: Separators may be applied to this relay if the following requirements are used:

TEST FOR	VALUE TO BE USED	
	TEST MA	READJ MA
Hold	26.5	25
Operate	35	—

PBX SYSTEMS

TABLE U — MISCELLANEOUS CIRCUITS			
RELAY CODE NUMBER	CIRCUIT DESIGNATION	DESCRIPTION OF CIRCUIT	ARM. STOPS OR SEPARATORS APPROVED
149AR	H, H1	No. 711A Tie Line	Yes
149AR	SR	No. 701A, 702A, or 711A Trunk	Yes
149AT	SR	No. 100 Key Eqpt	No
149BD	B	Line and Link	No
149CG	H, H1	No. 711A Tie Line	Yes
149CG	SR	No. 701A, 702A, or 711A Trunk	Yes
149CJ	SR	No. 100 Key Eqpt	No
149CP	S	Line and Link	No
149CP	SR	No. 100 Key Eqpt	No
149CR	SR	Line and Link	No
178CN	T	Line and Link	No
178CN	K	No. 606A or 702A Cord	Yes
178CN	Z	No. 100 Key Eqpt	Yes
178CN	F1, T	No. 550C, 550SC, 551A, B, and D, and 600C Tie Trunks	Yes
178ED	T	Trunk	No
186A	R	Cord, Line, or Trunk	Yes
186B	R	Trunk	Yes
A2	CO	Subs and Tie Line	Yes
B2	A, AS	Cord and Dial	Yes
B2	A to E S & TEL	Trunk and Connecting Ckt	Yes
B3	C, CS	Cord and Dial	Yes
B10	A, B, C, N	Aux Signal	Yes
B21	BUZ, T	Ringling and Buzzer	Yes
B31	R, R1	2-way Tie Line	No
B42	A, C, AS, CS	Cord	Yes
B74	H2	Trunk	Yes
B365	H	2-way Trunk	Yes
B383	RS, FS	No. 606A or 702A Cord	Yes
B552	H3	Trunk	Yes
B1048	S, AS	Cord	Yes
B1082	S	Line	Yes
B1088	A	Cord	Yes
B1089	C	Cord	Yes
E4	L	CO Trunk	Yes
G1	B	Tel and Dial	Yes
G92	BR	Tel and Dial	Yes
J12	RU	No. 606A or 702A Cord	No
R1409	L	Line and Link	Yes
(SC)206AD	C	Tel and Dial	Yes
(SC)207DD	A	Tel and Dial	Yes
(SC)228A	B	Tel and Dial	Yes
(SC)245MM	G	Cord	Yes
(SC)253AC	D	Tel and Dial	Yes
(SC)257A	L	Trunk	See Note
(SC)263BM	D	Tel and Dial	Yes
(SC)263ZBM	D	Tel and Dial	Yes
(SC)285HL	C	Tel and Dial	Yes
(SC)366A	D	Cord	Yes

(SC)—Indicates Stromberg-Carlson relay.

Note: KS-7744 separators are approved for application between armature and core and also between armature and backstop as required.