

**AUTOMATIC NUMBER IDENTIFICATION
OUTPULSER CIRCUIT
OPERATION TESTS
NO. 1 CROSSBAR OFFICES**

1. GENERAL

1.001 This addendum supplements Section 216-905-501, Issue 3.

1.002 This addendum is issued to revised verifications which have changed due to a circuit modification in the outpulser circuit and to make minor corrections.

4. METHOD

The following changes apply to Part 4 of the section:

- (a) Test A, Step 12c — revised
- (b) Test C, Steps 13d, 14d, 16d — revised
- (c) Test D, Steps 7c, 9 — revised

STEP	ACTION	VERIFICATION
		A. Regular Call
→ 12c	If tip party has been simulated — Restore TP key.	
		C. Work Timer
7	Operate OFF- key not associated with a PBX arranged for AIOD service.	
8	Operate THO-, HO-, TO-, UO- keys to simulate any calling line directory number.	
9	Operate WT1 key.	
10	Operate ST key.	At OITT — OB, IRL, KP, TM1, RL lamps lighted. Minor alarm occurred. Trouble ticket printed.
11	At trouble ticketer frame — Momentarily operate AR key.	Minor alarm retired.
		Check trouble ticket for : 5 in character position 3 9 in character position 8 3 in character position 25 - in character position 29 1 in character position 33
		Note: If trouble ticket was not printed, wait until trouble ticketer is idle; then restore ST key and repeat Steps 10 and 11.

STEP	ACTION	VERIFICATION
12	At OITT — Restore ST key.	All lamps extinguished.
→ 13d	If office is arranged for AIOD service — Restore OFF- key.	
→ 14d	Operate OFF- and THO- keys associated with PBX groups arranged for AIOD service to select AIOD office code number. <i>Note:</i> Any THO- key may be associated with an AIOD translator for number to be indenti- fied. Operate THO- key in accordance with local assignment for translator selection.	
15d	Operate ST key.	OB, IRL, IOD, KP, TM1, RL lamps lighted. Trouble ticket printed. Minor alarm occurred.
→ 16d	At trouble ticketer frame — Momentarily operate AR key.	Minor alarm retired. Check trouble ticket for: 5 in character position 3 9 in character position 8 3 in character position 25 7 in character position 27 - in character position 29 1 in character position 33 <i>Note:</i> If trouble ticket was not printed, wait until trouble ticketer is idle; then restore ST key and repeat Steps 15d and 16d.
17	At OITT — Restore ST key.	All lamps extinguished.
18	Restore all keys not required for next test.	
D. Timer Two — Continuity Check Failure		
→ 7c	If tip party has been simulated — Restore TP key.	
8	Operate WT2 key.	
→ 9	Operate ST key.	If ZM or no option is provided — At OITT — OB, TRS, TM1, TM2, CCKF, IRL, RL, IO I2 lamps lighted. Trouble ticket printed. Minor alarm occurred. If ZN option is provided — At OITT — OB, TRS, TM1, TM2, CCKF, RL lamps lighted. Trouble ticket printed. Minor alarm occurred.

STEP	ACTION	VERIFICATION
10	At trouble ticketer frame — Momentarily operate AR key.	Minor alarm retired. Check trouble ticket for: 5 in character position 3 9 in character position 8 4 in character position 20 - in character position 29 1 in character position 32 3 in character position 33 Note: If trouble ticket was not printed, wait until trouble ticketer is idle; then restore ST key and repeat Steps 9 and 10.
11	At OITT — Restore ST key.	All lamps extinguished.
12	Restore all keys not required for next test.	