

AUTOMATIC NUMBER IDENTIFICATION
OUTPUTSERS CIRCUIT
OPERATION TESTS
STEP-BY-STEP OFFICES
ARRANGED FOR ANI-TYPE B

1. GENERAL

1.001 This addendum supplements Section 227-545-500, Issue 3.

1.002 This addendum is issued to revise verifications in the steps of several tests which have changed due to a circuit modification in the outputser circuit and to make minor changes.

4. METHOD

The following changes apply to Part 4 of the section:

- (a) Test A, Steps 12c — revised
- (b) Test D, Steps 14d, 16d — revised
- (c) Test E, Steps 7c, 9 — revised

STEP	ACTION	VERIFICATION
		A. Regular Call
12c	If tip party has been simulated — Restore TP key.	
		D. Work Timer
14d	Operate OFF- and THO- keys associated with PBX groups arranged for AIOD service to select AIOD office code number. <i>Note:</i> Any THO- key may be associated with an AIOD translator for number to be identified. Operate THO- key in accordance with local assignment for translator selection.	
16d	At trouble ticketer frame — Momentarily operate AR key.	Minor alarm retired. Check trouble ticket for: 5 in character position 3 9 in character position 8 3 in character position 25 7 in character position 27 – in character position 29 1 in character position 33 <i>Note:</i> If trouble ticket was not printed, wait until trouble ticketer is idle; then restore ST key and repeat Steps 15d and 16d.

STEP	ACTION	VERIFICATION
E. Timer Two — Continuity Check Failure		
7c	If tip party has been simulated — Restore TP key.	
9	Operate ST key.	At OITT — OB, TRS, TM1, TM2, CCKF, RL lamps lighted. Trouble ticket printed. Minor alarm occurred. If ZM or no option is provided — IRL, I0, I1 lamps lighted.