

DIMENSION[®] 2000 AND CUSTOM PBX
(CSS 201L)
X-Ray Test 12
(Tape Interface Test)

1. GENERAL INFORMATION
 2. RECORDS
 3. TEST EQUIPMENT
 4. TEST PROCEDURES
 5. MINIMUM CIRCUIT PACK REQUIREMENTS
-

1. GENERAL INFORMATION

1.1 Description

- 1.11 This section describes the procedures to be followed to perform X-Ray Test 12.
- 1.12 X-Ray Test 12 is an abbreviated tape test. This test performs the same tests as Test 27 except for the early warning and end of tape checks. This test takes about two minutes.

2. RECORDS

- 2.1 Form SD-97-1313 is required for recording the results of this test.

3. TEST EQUIPMENT

- 3.1 Test Sets - See Section 400 of Handbook 281.

4. TEST PROCEDURES

4.1 Preliminary

- 4.11 Since this test is performed automatically in X-Ray Test 01, it should only be performed when trouble is suspected.
- 4.12 This test should only be run after X-Ray Test 27 has passed and should never be run more than five minutes without X-Ray Test 27 being re-run to retension the tape on the cartridge.

PRIVATE

THE INFORMATION CONTAINED HEREIN SHOULD NOT BE DISCLOSED TO UNAUTHORIZED PERSONS. IT IS MEANT SOLELY FOR USE BY AUTHORIZED BELL SYSTEM EMPLOYEES.

4. TEST PROCEDURES (Cont'd)

4.2 Test Execution

4.21 To execute X-Ray Test 12, momentarily operate the EXECUTE, 1, 2 keys at the MAAP.

4.3 Test Pass Indication

4.31 The spare MAAP LED lighting (or the Alarm Panel - PASS) indicates that X-Ray Test 12 passed.

4.32 This completes the X-Ray testing per X-Ray Test 12.

5. MINIMUM CIRCUIT PACK REQUIREMENTS

5.1 The system should be equipped per the C.O.D. for this test.

Reason for Issue:
New Section

Manager, Denver PBX PECC