

DIMENSION[®] PBX
DCTS FEATURE TEST
LAST LINE PREFERENCE

CONTENTS

1. GENERAL
2. TEST SET UP
3. LAST LINE PREFERENCE TEST
4. RESTORATION
-

1. GENERAL

1.1 This test section provides testing information for Last Line Preference.

1.2 Last Line Preference automatically connects the station user to the same line previously connected upon going off-hook.

2. TEST SET-UP

2.1 Connect Electronic Telephone Set to circuit selected with Last Line Preference. This set will be referred to as Set-L in the testing procedure.

3. LAST LINE PREFERENCE TEST

3.1 At Set-L verify that only one I-USE lamp is lighted (if no I-USE lamps are lighted select one line pick up button and depress).

3.2 At Set-L go off-hook.

3.21 Status lamp associated with I-USE lamp steadily lighted. Dial tone heard.

3.3 At Set-L go on-hook.

3.31 Status lamp associated with I-USE lamp goes off.

3.4 At Set-L depress any additional assigned line pick-up button other than the last line used.

3.41 I-USE lamp for selected line lights and I-USE lamp for previous line goes out.

3.5 At Set-L go off-hook.

3.51 Status lamp associated with selected line lighted steadily. Dial tone heard.

3.6 At Set-L go on-hook.

3.61 Status lamp goes out; I-USE lamp remains lighted.

3.7 At Set-L go off-hook.

3.71 Status lamp associated with lighted I-USE lamp steadily lighted. Dial tone heard.

3.8 Hang up Set-L.

4. RESTORATION

4.1 Determine requirements of next test and disconnect telephone sets not required.

Manager, Denver PBX PECC

PRIVATE

THE INFORMATION CONTAINED HEREIN SHOULD NOT BE DISCLOSED TO UNAUTHORIZED PERSONS. IT IS MEANT SOLELY FOR USE BY AUTHORIZED BELL SYSTEM EMPLOYEES. Printed in U.S.A.