

LINE JUNCTOR REDISTRIBUTION

5IL - 5LCC to 8IL - 8LCC

CONTENTS

- |  |   |
|--|---|
| <p>1. GENERAL</p> <p>2. PREPARATION FOR ROUTINE OF INCOMING TRUNKS</p> <p>3. STEP NO. 1 TERM. MARKER</p> <p>4. STEP NO. 2 LINE JUNCTOR CONNECTOR FRAME</p> | <p>5. STEP NO. 3 LINE JUNCTOR GROUPING FRAME</p> <p>6. STEP NO. 4 TIP, RING AND SLEEVE TEST</p> <p>7. CLEAN-UP WORK</p> |
|--|---|

1. GENERAL

This section covers the redistribution of line junctors

From:  
ED-25713-10, Chart 4, 5IL & 5LCC with 100 Junctors per HC

To:  
ED-25713-10, Chart 7, 8IL & 8LCC with 96 or 104 junctors per HC

2. PREPARATION FOR ROUTINE OF INCOMING TRUNKS

2.1 Preparation for routine of incoming trunks are made as specified in Handbook 40, Section 90, Paragraph 3.

2.2 Paragraph 3.4 of Section 90 refers to temporary cross-connections in the term. marker.

2.21 These cross-connections are as follows:

- JR5 to JGA5
- JGE5
- JR6 to JGA6
- JGE6
- JR7 to JGA7
- JGE7

2.3 No cross-connections are to be removed. The cross-connections specified in Paragraph 2.21 are to be installed over the existing connections.

3. STEP NO. 1 TERM. MARKER

3.1 Remove each marker from service and block to use 1st subgroup junctors only, per SD-25511-01, Table 11, for 5 incoming frames.

3.2 Remove the temporary cross-connections installed under Paragraph 2.21.

3.3 Change the present cross-connections per T-25283-54, to agree with T-25283-56.

3.4 At the completion of Paragraph 3.3 on each marker, block to use 1st subgroup per SD-25511-01, Table 11, for 8 incoming frames and return to service.

4. STEP NO. 2 LINE JUNCTOR CONNECTOR FRAME

4.1 Change the M - J straps of the LJA & LJB terminal strips per Figure 1.

Line Choice Number	0	1	2	3	4	5	6	7	8	9
From T-25275-18		Fig 10	Fig 11	Fig 12	Fig 13					
To T-25275-18		Fig 3	Fig 3	Fig 3	Fig 16					

FIG. 1 MODIFICATION OF M AND J STRAPS (Par. 4.1)

5. STEP NO. 3 LINE JUNCTOR GROUPING FRAME

5.1 Disconnect all cross connections except those shown in Figure 2.

LINE CHOICE	INC. FRAME	CHANNEL	LINE LINK VERTICAL								
			7	6	5	4	3	2	1	0	
8A	8	3,7						4R			
8B		3,7						4L			
8A	8	0,4,8					OR				
8B		0,4,8					OR				
9A	9	0,4,8					4R	3R	2R	1R	OR
9B		0,4,8					4L	3L	2L	1L	OL

FIG. 2 REUSED CROSS-CONNECTIONS (Par 5.1)

5.2 Connect 300 1st subgroup junctors (cabled junctors)

5.3 Connect the cross-connections not connected in the preliminary work. There are 280 junctors to be cross-connected as specified on ED-25713-10, chart 7.

6. STEP NO. 4 TIP, RING AND SLEEVE TEST

6.1 Buzz test the T and R of all junctors established under Paragraph 5.2 and 5.3.

6.2 Remove a marker from service and use this marker and the TTI to check the sleeve of all 1st subgroup junctors.

6.3 Block this marker, per SD-25511-01, Table 11 to use 2nd subgroup junctors only for 8 I, and use the marker and the TTI to check the sleeves of all 2nd subgroup junctors.

6.4 Remove the blocks from all the markers, and after making any necessary checks, restore them to service.

7.2 The JPL relay per SD-25511-01, shall be left in place for use in future transitions.

7. CLEAN-UP WORK

7.1 The markers and junctors are now operating in the standard manner for the 8 I - 8LCC distribution and the incoming trunks in frames 5, 6 and 7 may now be loaded.

No arrows are shown  
due to extensive changes

R. E. RAHMES

Engineer of Installation