

LINE JUNCTOR REDISTRIBUTION
2IL-2LCC TO 4IL-4LCC

CONTENTS

- | | |
|----------------------------------------------------------------------------------------------------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| <p>1. GENERAL</p> <p>2. PREPARATION FOR ROUTINE OF INCOMING TRUNKS</p> <p>3. STEP NO. 1 TERM. MARKER</p> | <p>4. STEP NO. 2 LINE JUNCTOR CONNECTOR FRAME</p> <p>5. STEP NO. 3 LINE JUNCTOR GROUPING FRAME</p> <p>6. STEP NO. 4 TIP, RING AND SLEEVE TEST</p> <p>7. CLEAN-UP WORK</p> |
|----------------------------------------------------------------------------------------------------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------|

1. GENERAL

1.1 This section covers the redistribution of line junctors

FROM:

ED-25713-10, Chart 1, 2IL & 2LCC with 80 junctors per HC

TO:

ED-25713-10, Chart 3, 4IL & 4LCC with 80 junctors per HC

2. PREPARATION FOR ROUTINE OF INCOMING TRUNKS

2.1 Preparation for tests of incoming trunks are made as specified in Handbook 40, Section 90, Paragraph 3.

2.2 Paragraph 3.4 of Section 90 refers to temporary cross connections in the term. marker frames.

2.21 These cross connections are as follows;

JR2	to	JGA2 JGB2 JGC2 JGE2
JR3	to	JGA3 JGB3 JGC3 JGE3

2.3 No cross connections are to be removed. The cross connections specified in Paragraph 2.21 are to be installed over the existing connections.

3. STEP NO. 1 TERM. MARKER

3.1 Remove each marker from service and block to use 1st subgroup junctors only, per SD-25511-01. Table 11, for 2 incoming frames.

3.2 Remove the temporary cross-connections installed under Paragraph 2.21.

3.3 Change the present cross-connections per T-25283-51, to agree with T-25283-53.

3.4 At the completion of Paragraph 3.3 on each marker, block to use 1st subgroup per SD-25511-01, Table 11 for 4 incoming frames and return to service.

4. STEP NO. 2 LINE JUNCTOR CONNECTOR FRAME

4.1 Change the M-J straps of the LJA & LJB terminal strips per Figure 1.

Line Choice Number	0	1	2	3	4	5	6	7	8	9
From T-25275-18		Fig. 4								
To T-25275-18		Fig. 7								

FIG. 1 MODIFICATION OF M AND J STRAPS (Par. 4.1)

5. STEP NO. 3 LINE JUNCTOR GROUPING FRAME

5.1 Disconnect all cross connections except those shown on Figure 2.

Line Choice	Inc Frame	Channel	Line Link Vertical			
			3	2	1	0
5A 5B	5	0-9			OR OL	
8A 8B	8					1R 1L
9A 9B	9				1R 1L	OR OL

FIG. 2 REUSED CROSS CONNECTIONS (Par. 5.1)

5.2 Connect the cross connections not cross connected in the preliminary work. There are 240 junctors to be connected as specified on ED-25713-10, Chart 3.

6. STEP NO. 4 TIP, RING AND SLEEVE TEST

6.1 Buzz test the T and R of all junctors established under Paragraph 5.2.

6.2 Remove a marker from service and use this marker and the TT1 to check the sleeves of all 1st subgroup junctors.

6.3 Block this marker, per SD-25511-01, Table 11 to use 2nd subgroup junctors only for 4 I, and use the marker and the TTI to check the sleeves of all 2nd subgroup junctors.

6.4 Remove the blocks from all the markers, and after making any necessary checks, restore them to service.

No arrows are shown due to extensive changes.

7. CLEAN-UP WORK

7.1 The markers and junctors are now operating in the standard manner for the 4 I - 4 LCC distribution and the incoming trunks in frames 2 and 3 may now be loaded.

7.2 The JPL relay per SD-2511-01, shall be left in place for use in future transitions.

7.3 The "B" and "C" step walking circuit relays JGB, RTB', RTB, OVB, JGC, RTC', RTC, OVC, per SD-25283-0104, Figure 18, shall be removed

R. E. RAHMES

Engineer of Installation

Reason for Reissue:
Complete handbook revision.

Replaces Section 42C2 6-19-47.