

**MULTILINE – 4 AND 6 BUTTON  
TELEPHONE SETS  
SELECTION**

**1. GENERAL**

**1.01** The telephone sets in Table A are capable of providing the services listed as factory supplied. Some services, such as 1A KTS, signaling, "I" hold, will require modification of the set.

**1.02** Exclusion, if listed, indicates mounting cord leads are provided but requires the addition of a D-179935 Kit of Parts to 500 series

sets. This exclusion switch is provided on panel sets.

**1.03** Refer to the service section listed for all wiring modifications.

**1.04** Sets listed as capable of handset/headset operation are equipped with jacks but the headset must be separately ordered.



TABLE A (Cont)

4- AND 6-BUTTON TELEPHONE SETS

TELEPHONE SETS SERVICES	568HB 502-541-420	568HT 502-542-406	568HF, HR 502-541-423	568HAA 502-541-425	1563HB 502-542-400	1564HK, HL 502-542-402	1565GK 502-542-403	1565HK 502-542-404	1565LK 502-542-405	568HT, 1568HT 502-542-406	2563HB 502-543-400	2564HL 502-543-402	2565GK 502-543-403	2565HK 502-543-405	2565LK 502-543-406	2568HAA 502-543-410	752A/B 502-736-401	754 502-736-402	1752A/B 502-737-401	2752A/B 502-738-401	2754A/B 502-738-402	
3-Line PU and Hold																						
4-Line Pickup																						
5-Line PU and Hold	•	•	•	•	•	•		•		•	•	•		•		•	•	•	•	•	•	•
6-Line Pickup							•						•									
4-Line PU and Hold									•						•							
Cutoff Key									•						•							
Exclusion	•	•	•	•	•		•	•	•	•	•		•	•	•	•	•	•	•	•	•	•
Speaker-phone			•	•			•	•	•	•			•	•	•	•	•		•	•	•	•
Handset/Headset					•						•											
1A KTS					•		•	•	•		•		•	•	•		•	•	•	•	•	•
1A1-1A2 KTS	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•
Common Signaling			•	•	•	•	•	•			•	•		•		•	•	•	•	•	•	•
I Hold			•		•	•		•	•		•	•	•	•								
2/4 Wire Operation	•	•	•	•							•	•				•						
Station Busy Lamp*				•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•

\* Requires KS-15724L1 diode.