



TABLE A

POLARITY GUARD CONNECTIONS
(P-90D052 GUARD ASSEMBLY)

LEAD	REMOVE FROM		CONNECT TO
	NET.	NET.	POLARITY GUARD
Dial	BK	RR	T
Line Switch	(BK) [S-BR]	C	S
Polarity Guard	G		RR
	W		C

() CURRENT COLOR CODE
[] MD COLOR CODE

NOTES:

- CONNECTIONS SHOWN ARE FOR RINGING ON LINE 1. TO RING ON LINE 2, MOVE (R) AND (BK) RINGER LEADS TO TERMINALS 3 AND 4. TO SILENCE RINGER, CONNECT (BK) TO K TERMINAL.
- WHERE COMMON OR PRIVATE LINE RINGER IS REQUIRED, CONNECT:
 - (BL) AND (W) CORD LEADS TO E1 AND E2.
 - (R) AND (BK) RINGER LEADS TO E1 AND E2.
 - (S-R) RINGER LEAD TO A.

Fig. 1 - 1510F Telephone Set. With 25A3 Dial,
2-Line Pickup and Signaling, Connections

