

**NUMBER GROUP CONNECTOR FRAME,
BLOCK RELAY FRAME
AND RELAY RACK MOUNTED
DIRECT ACCESS PRETRANSLATOR CONNECTOR EQUIPMENT
EQUIPMENT DESIGN REQUIREMENTS
NO. 1 CROSSBAR SYSTEM**

1. GENERAL

Under J27852A

1.001 This addendum supplements Section 816-301-150.

Add:

1.002 The addendum is issued:

Notes

(a) To provide equipment information for calling line identification in agreement with SD-25276-01, Issue 29D.

A. Provide ZB wiring when calling line identification is required.

(b) To provide equipment information for automatic intercept service without line link pulsing and to rate number checking Mfr Disc. in agreement with SD-25276-01, Issue 30D.

B. Provide ZC wiring when automatic intercept service without line link pulsing is required.

Under J27852B

Add:

4. EQUIPMENT

Notes

The following changes apply to Part 4 of the section:

A. Provide ZB wiring when calling line identification is required.

B. Provide ZC wiring when automatic intercept service without line link pulsing is required.

Under J27852D

(a) J27852A, Notes A and B—added

Remove: Lists 3 and 4

(b) J27852B, Notes A and B—added

Add:

(c) J27852D, Lists 3 and 4—removed

List 8—Equipment and wiring in addition to list 1 when calling line identification is required in accordance with SD-25276-01, Fig. 20.

(d) J27852D, List 8—added

Under Notes

(e) J27852D, Note B—revised

Change: Note B

To Read:

B. Wiring required in addition to list 1 when automatic intercept service without line link pulsing is required in accordance with SD-25276-01, Fig. 21 and Fig. 23.

5. GENERAL NOTES

The following changes apply to Part 5 of the section:

- (a) 5.10—revised
- (b) 5.12—revised
- (c) 5.13—revised
- (d) 5.21—removed
- (e) 5.36.1 and 5.36.2—added

Remove: First sentence of 5.10

Change: First sentence of 5.12

To Read:

5.12 When serving LLP with DID or AIS trunks, list 6, J27852D provides one mounting plate with 80 diodes.

Change: First sentence of 5.13

To Read:

5.13 List 7 for Direct In Dialing with No. 101 ESS provides a mounting plate with 80 diodes.

Remove: 5.21

Add:

5.36.1 Provision for AIS without LLP on the block relay frame may be made by cross connecting OFT lead to OFT- punching, NFI- leads to NF-punching, and NCI- leads to NC- punching for number group addresses. Additional cross connections for line link locations are RFI- leads to RF- punching, and HGI- leads to HG punchings.

5.36.2 Further cross connections at the LDF are required for AIS without LLP. For number group addresses connect NSI- leads to NS- punching and for line link location connect LSI leads to LS-punching.

Under List of A&M Only and Mfr Disc. Equipment

Add:

EQUIPMENT	RATING	DETAILS LAST SHOWN IN ISSUE	REPLACING EQUIPMENT
J27852D,L3	Mfr Disc.	8	—
L4	Mfr. Disc.	8	—

Bell Telephone Laboratories, Incorporated

Dept 5245