

BELL SYSTEM PRACTICES
Station Installation and Maintenance

SECTION C34.301
Issue 2, 4-17-34
Standard

DIAL MOUNTINGS AND DIAL ADAPTERS DESCRIPTION AND USE

1. GENERAL

1.01 This section gives a brief description of the various dial mountings and dial adapters and lists their uses in connection with station apparatus. It is reissued to add the 6000D dial mounting and the 58A dial adapter.

DIAL MOUNTINGS

Code No.	Description and Use										
30A	Black finished metal mounting for use with 52 type dial adapter and a 2 or 4 type dial on residence system sets. (Includes .112-36 screws one—11/32" long, two—3/16" long.)										
33A	Consists of 30A dial mounting and a black finished base to permit mounting on walls at subscriber stations.										
37A	Black finished metal mounting arranged to mount transmitter, 52A dial adapter and a 2H or 4H type dial on manual wall sets. (1—M4J cord, a connecting block and mounting screws are furnished.)										
39A-3 39A-4 39A-5 39A-6 39A-7 39A-8 39A-11 39A-12	<table style="border: none;"> <tr> <td style="padding-right: 10px;">Black</td> <td rowspan="8" style="font-size: 3em; vertical-align: middle;">}</td> <td rowspan="8">Consists of an offset pedestal to which is attached a 30A dial mounting and a 52C dial adapter. (Furnished with mounting screws.) Used with C1 type hand set mountings for mounting 2H or 4H type dials.</td> </tr> <tr><td>Ivory</td></tr> <tr><td>Gray</td></tr> <tr><td>Old Brass</td></tr> <tr><td>Statuary Bronze</td></tr> <tr><td>Oxidized Silver</td></tr> <tr><td>Medium Gold</td></tr> <tr><td>Dark Gold</td></tr> </table>	Black	}	Consists of an offset pedestal to which is attached a 30A dial mounting and a 52C dial adapter. (Furnished with mounting screws.) Used with C1 type hand set mountings for mounting 2H or 4H type dials.	Ivory	Gray	Old Brass	Statuary Bronze	Oxidized Silver	Medium Gold	Dark Gold
Black	}	Consists of an offset pedestal to which is attached a 30A dial mounting and a 52C dial adapter. (Furnished with mounting screws.) Used with C1 type hand set mountings for mounting 2H or 4H type dials.									
Ivory											
Gray											
Old Brass											
Statuary Bronze											
Oxidized Silver											
Medium Gold											
Dark Gold											

DIAL MOUNTINGS—Continued

Code No.	Description and Use
6000D	See sections in Division C50 covering Key Equipment No. 100.
6030A	Consists of a 30A dial mounting, a cable for making connections between the dial and the terminal block of the set and a cable holder and nut for attaching cable to the face plate of 574 and 577 type sets.

DIAL ADAPTERS

Code No.	Description and Use
52B	Used for mounting 2E type dials in 6000D Dial Mountings.
52C	Black finished plate provided with machine screws for attaching 2H and 4H type dials to dial mountings.
56A	A metal cup provided with nuts for attaching a 147 type number plate and a 2HH or a 4HH dial to 50 and 150 type coin collectors and other station apparatus.
58A	A flat semi-circular adapter used to mount dial and 56A dial adapter in 300 type telephone sets. Furnished with screws, lock washers and hexagon nuts.