

**RINGER CONNECTIONS**  
**TIP-PARTY IDENTIFICATION**  
**FOR STATIONS CONNECTED TO LONG-LINE EQUIPMENT**

**1.00 GENERAL**

**1.01** Ringer leads must be reversed at 2-party tip stations with ground identification when these stations are connected to a long line circuit. This prevents bell tap. To do this, reverse all four ringer leads. This is necessary to prevent losing the proper tip-party identification. A typical example of these connections is shown in Table A.

**TABLE A**

**RINGER CONNECTIONS OF 500C, D TELEPHONE SETS**

1000Ω IDFY GRD			2650Ω IDFY GRD		
Ringer Lead	From	To	Ringer Lead	From	To
S-R	B	K	S-R	G	B
R	K	B	R	B	G
BK	G	B	BK	B	K
S	B	G	S	K	B

**1.02** This information will be included in the following sections when they are reissued:

C38.113	C38.609	C38.635
C38.173	C38.611	C38.636
C38.555	C38.612	C38.637
C38.573	C38.613	C38.640.04
C38.575	C38.629	C38.820
C38.601	C38.633	C38.821.02
C38.603		