

STATION SETS — MAGNETO
SELECTION FOR GENERAL USE

1.00 INTRODUCTION

This section covers, in table form, the selection of magneto station sets for general use.

2.00 SELECTION

TABLE A — SELECTION OF MAGNETO SETS FOR GENERAL USE

| Class of Service | Wall Set | Combined Tel Set | Associated Sub. Set | Hand Tel Set | Desk Stand | Associated Sub. Set |
|--|----------|------------------|------------------------|--------------------------------|----------------|----------------------|
| Individual Line, PBX and Nonselective Code Ringing on rural lines having eight or less stations and a loop resistance from central office to any station of 800 ohms or less | 417AH | 307A 357A | 299F or D-176680 | 202H 211E 213E* 215A* | 151AL 152AB | 415H |
| Nonselective Code Ringing on rural lines having more than eight stations or a loop resistance from central office to any station of more than 800 ohms | 417P | 307A 357A | 299F | 202H 211E 213E* 215A* | 151AL 152AB | 400A or 400K |
| 2-Party Selective 4-Party Semiselective Regular Stations | 417BS | 307A 357A | 299F or D-176680 | 202H 211E 213E* 215A* | 151AL 152AB | 415E |
| 2-Party Selective 4-Party Semiselective Stations with Inductive Noise | 417CD | 307A 357A | 299F or D-176680 | 202H 211E 213E* 215A* | 151AL 152AB | 400CD or 415CD |
| 4-Party Selective Regular Stations | 417BS | 309A | 299F or D-176680 | 202H 211E 213E* 215A* | 151AL 152AB | 415E |
| 4-Party Selective Stations with Inductive Noise | 417CD | 309A | 299F or D-176680 | 202H 211E 213E* 215A* | 151AL 152AB | 400CD or 415CD |
| Divided Code | 417CD | 307A 357A | 299F or D-176680 | 202H 211E 213E* 215A* | 151AL 152AB | 400CD or 415CD |

* For use where more than one hand telephone set is used with one subscriber set.

2.01 The 357A telephone set is produced in ivory as well as black. The 307A telephone set is produced in the colors shown in Table B.

TABLE B
COLOR CHART FOR 307A TELEPHONE SET

| Color | Code |
|--------|------------|
| Ivory | 307A — 50A |
| Green | 307A — 51A |
| Gray | 307A — 52A |
| Red | 307A — 53A |
| Brown | 307A — 54A |
| Beige | 307A — 55A |
| Yellow | 307A — 56A |
| Blue | 307A — 57A |

TABLE C — TRANSMISSION ZONING CHART FOR MAGNETO OFFICES

| Zone | Class of Service | 1st Choice Equipment | | | | | Alternate Equipment | | | | |
|------|------------------|----------------------|------------|----------|---------------------|-----------|---------------------|------------|----------|---------------------|-----------|
| | | Handset Stations | | | Nonhandset Stations | | Handset Stations | | | Nonhandset Stations | |
| | | Type Handle | Trans Unit | Rec Unit | Trans /Unit | Rec /Unit | Type Handle | Trans Unit | Rec Unit | Trans /Unit | Rec /Unit |
| M1 | All | F1 | F1 | HA1 | 635/F1 | 706/HA1 | F1 | F1 | HA1 | 635/F1 | 706/HA1 |
| M2 | All | | | | | | F4 or F5 | T1 | U1 | None | None |

Note: Use an F5 rather than F4 handset when a 4-conductor cord with an F-type handset is required.