

**DIAL SELECTIVE INTERCOMMUNICATING LINES
 WITH FLASHING LINE LAMPS
 AND/OR
 AUTOMATIC CUT-OFF
 TERMINATIONS IN APPARATUS CABINET**

1. GENERAL

1.01 This addendum supplements Section C66.209, Issue 2. It is issued to show CO lead connections, information on flashing or nonflashing line lamps, to revise connection information on the 207B key telephone unit, and to specify wiring changes which may be necessary on some 207B key telephone units as initial manufacture.

Add new paragraph as follows:

1.06 If the single spurt audible signal seems to be less than 1 second in duration, check the wiring connections of the KS13491, List 2, 47 OHM "A" and "B" resistors. The "A" resistor from the "T" relay should terminate on punching No. "3" of the KS16171 "A" capacitor; and the "B" resistor from "B" relay should terminate on punching No. "2" of the "A" capacitor.

9.04a◆ Replace with the following:

Run Straps as Shown Below:

LEAD DESIG.	K.T.U.		ALL 208A K.T.U. TERM.
	207B	207A	
	T.S."B"	TERM.	
R	2	2	13
T	1	1	12
H	26 & 28	3	14
A	23	4	17

LEAD DESIG.	1st AND ALL 208A K.T.U. TERM.
LF	26
LAMP POWER	28
LAMP GRD	29

9.04c◆ Replace with the following:

Run Straps as Shown Below:

LEAD DESIG.	K.T.U.		ALL 208A K.T.U. TERM.
	207B	207A	
	T.S."B"	TERM.	
D	3	26	15

LEAD DESIG.	K.T.U.		1st 208A K.T.U. TERM.
	207B	207A	
	T.S."B"	TERM.	
B	29	27	16
CO	5		21

Reference: SD69199-0102, Fig. 16, Issue 5-D

9.04g Add the following:

Run Straps as Shown Below:

207B K.T.U. TERM. STRIP "B"		
	TERM.	TERM.
WITH FLASHING LAMP	26	28
WITHOUT FLASHING LAMP	27	29

9.05b◆ Replace with the following:

Run Straps Between K.T.U. as Shown Below:

LEAD DESIG.	K.T.U.		ALL SUCCEEDING 208A K.T.U. TERM.
	207B	207A	
	T.S."B"	TERM.	
D	3	26	15

LEAD DESIG.	K.T.U.		1st 208A K.T.U. TERM.
	207B	207A	
	T.S."B"	TERM.	
B	27 & 29	27	16

Note: ◆ The term "common strapping" refers to strapping which must be furnished by the installer between the (207-TYPE) K.T.U. and the 208A K.T.U. and the 26B K.T.U., regardless of the number of stations provided.

TABLE 9.10

Replace with the following:

POWER CONNECTIONS FOR BUSY LAMPS BETWEEN CENTRAL OFFICE OR PRIVATE BRANCH EXCHANGE LINE UNIT (202A, 202B, or 212A) AND 207-TYPE DIAL SELECTIVE INTERCOMMUNICATING LINE UNIT.

SELECT TYPE K.T.U. AND CONNECT AS SHOWN BELOW:

LEAD DESIG.	CO OR PBX LINE K.T.U.			K.T.U.	
	202A	202B	212A	207B	207A
	TERM.	TERM.	T.S."A"	T.S."B"	TERM.
LAMP POWER	31	39	39	29	28
LAMP GRD	30	40	40	30	29

References: SD69199-01, Fig. 53
 SD69203-01, Fig. 51
 SD69203-01, Figs. 67 and 68

9.11 Replace with the following:

POWER CONNECTIONS FOR TRANSMITTER POWER SUPPLY AND "C" RELAY POWER SUPPLY BETWEEN CENTRAL OFFICE OR PRIVATE BRANCH EXCHANGE LINE UNIT (202A, 202B, or 212A) AND DIAL SELECTIVE INTERCOMMUNICATING LINE UNIT (207-TYPE) AND SIGNAL CIRCUIT UNIT FOR FLASHING LINE LAMPS AND AUTOMATIC CUT-OFF OF DIAL SELECTIVE INTERCOMMUNICATING STATIONS (208A)

SELECT TYPE K.T.U. AND CONNECT AS SHOWN BELOW:

LEAD DESIG.	CO OR PBX LINE K.T.U.			K.T.U.		
	202A	202B	212A	207B	207A	208A
	TERM.	TERM.	T.S."A"	T.S."B"	TERM.	TERM.
BAT	38	29	29	9	35	39
GRD	40	30	30	10	34	40

References: SD69199-01, Fig. 52
 SD69199-01, Figs. 53 and 54
 SD69203-01, Fig. 51
 SD69203-01, Figs. 67 and 68