

ISSUE	1	1/25/54
DATE	11-28-51	6-10-53

SEQUENCE CHART




TABLE A
STEERING CIRCUIT PROGRESS

DIGIT	RA	EV	OD	AS	BS	CS	DS	ES	FS	GS	HS	JS	KS	LS	MX
KP			H+	H+											
A	O R	O H	R H	R	O H										
B	O R	R	O H		R	O H									
C	O R	O H	R			R	O H								
D	O R	R	O H				R	O H							
E	O R	O H	R					R	O H						
F	O R	R	O H						R	O H					
G	O R	O H	R							R	O H				
H	O R	R	O H								R	O H			
J	O R	O H	R									R	O H		
K	O R	R	O H										R	O H	
L	O R	O H	R											R	O H
START	O R	H H	O H												H H

O DENOTES RELAY OPERATED
H DENOTES RELAY HELD
R DENOTES RELAY RELEASE
+ DENOTES INITIALLY OPERATED AT SEIZURE FROM OFF-NORMAL GROUND

TABLE B

CODES	CHANNEL NO. & FREQUENCY					
	(0) 700~	(1) 900~	(2) 1100~	(4) 1300~	(7) 1500~	(10) 1700~
KP			X			X
1	X	X				
2	X		X			
3		X	X			
4	X			X		
5		X		X		
6			X	X		
7	X				X	
8		X			X	
9			X		X	
0				X	X	
ST					X	X

MF INCOMING SENDER
REGISTRATION
WITH
RECEIVING CKT. SD-95087