

<u>CONTENTS</u>	<u>PAGE</u>
INDEX	3
COAXIAL CORDS	12
INTRODUCTION	13
CODED CORDS	
CODED PLUGS	21
KS PLUGS	57
COMMERCIAL PLUGS	89
RECEIVERS AND TRANSMITTERS	95
TOOLS	99
MISCELLANEOUS (Commercial and KS)	103
MISCELLANEOUS	107
POWER CORDS (KS)	121
CORD ASSEMBLIES:	
PATCHING	125
TESTING	139



INDEX

Code	Page	Code	Page	Code	Page	Code	Page
26	119	D4BP	107	D12E	81	D50K	68, 72
330	119	D4BR	107	D12F	108	D50L	68, 73
437	119	D5R	107	D12H	109	D50N	73
540	119	D5S	107	D14B	109	D50P	68, 73
630	40	D5U	107			D50R	73
642	30	D5W	107	D14L	109	D50S	73
643	30, 35	D5AH	107	D14M	109	D50T	73
725	119	D5AJ	107	D14N	81	D50W	73
742	21	D5AK	107	D16E	67		
785	40, 97	D5AL	107	D16F	109	D50AA	79
815	21, 101	D5AM	107	D16G	71	D50AB	73, 80
893	101	D5AN	107	D20H	71	D50AD	73, 88
895	119	D6W	108	D20J	109	D50AE	68, 73
D2M	53	D6AA	108	D20K	71	D50AF	73, 80, 89
D3AH	107	D6AB	108	D24D	71	D55A	73
D3BN	53	D6AC	89	D24E	72	D56A	68, 74
D3BP	53	D6AD	108	D25C	82	D75A	66, 68
D3BR	53	D6AE	108	D25D	72, 82	D75B	66, 68
D3BS	54	D6AF	108	D26D	72	D80B	68, 74
D3BT	89	D6AG	108	D30D	72	D80C	68, 74
D3BU	107	D8J	108	D34B	72	D94B	68, 74
D4Y	107	D8L	108	D35B	79		
D4BC	54	D8P	108	D35C	79, 83	D100C	68
D4BD	107	D9H	108	D42A	72	D100D	68
D4BF	107	D10N	84, 108	D50C	72	D100E	69, 74
D4BH	54	D10P	108	D50D	72	D100F	74
D4BJ	54	D10R	108	D50F	72	D100G	74
D4BK	54	D10S	79	D50G	72, 81	D100H	69, 74
D4BM	54	D10T	71, 79	D50H	79	D100J	71, 74, 88
D4BN	107	D12B	108	D50J	72	D120C	69, 75

INDEX

Code	Page	Code	Page	Code	Page	Code	Page
D120D	69, 75	D200L	76, 80	H3AS	109	H4DH	111
D120E	69, 81	D200M	70, 76	H3AT	109	H4DJ	111
D120F	69, 75	D200N	70, 76	H3AU	109	H4DK	50
D120G	69, 75	D200P	70, 76	H4A	109	H4DL	50
D120H	69, 75	D200R	70, 76			H4DM	50
D120J	75	D200S	55, 76	H4BM	89	H4DN	50
D120K	55, 75	D200T	55, 76	H4BN	109	H4DP	50
D150B	69, 75	D200U	55, 76	H4BU	109	H4DR	50
D150C	69, 75	D250A	70, 76	H4BW	110	H4DS	111
D150D	69, 75	D250B	71, 76	H4BY	25	H5E	28, 38
D150E	69, 75	D250C	71, 76	H4CB	110	H5P	111
D150G	69, 75	D250D	71, 78	H4CC	110	H5R	111
D150H	69, 76	D250E	78, 80	H4CD	25	H5S	111
D150J	69, 76	D250F	78	H4CE	25	H5T	111
D150K	70, 76	D250G	71, 78	H4CF	110	H5U	111
D150L	70, 76	D250H	71, 78	H4CJ	110	H5W	89
D150M	70, 76	D250J	55, 78	H4CL	110	H5Y	89
D150N	70, 76	D250K	55, 78			H5AA	111
D150P	76	D300B	71, 78	H4CN	110	H5AB	111
D150R	70, 76	D300C	71, 78	H4CP	110	H5AC	111
D150S	76	H2A	38	H4CS	110	H5AD	111
D150T	76	H2B	109	H4CT	110	H5AE	111
D150U	55, 76	H2C	38	H4CW	110	H6A	56
D200D	70, 76	H3K	109	H4CY	110	H6B	111
D200E	70, 76	H3L	38	H4DA	110	H6C	111
D200F	70, 76	H3N	109	H4DB	110	H6E	111
D200G	70, 76	H3T	109	H4DD	50	H6F	47
D200H	70, 76	H3U	109	H4DE	110	L2W	95
D200J	76, 80	H3AN	109	H4DF	110	L2Y	95
D200K	76, 80	H3AR	109	H4DG	111	L2AA	38

INDEX

Code	Page	Code	Page	Code	Page	Code	Page
L2AD	50,95	L4CR	51,95	M2EG	89	M4K	90
L3K	30	L5A	112	M2EH	58	M4N	90
L4AC	25,95,112	L6H	47	M2EJ	30	M4P	114
L4AK	25,95,112	L6J	47	M2EK	103	M4R	54
L4AW	25,95,112			M2EL	58	M4S	25
L4BC	112	L8A	45	M2EM	99	M4T	28
L4BG	25	M1G	112	M2EN	113	M4Y	90
L4BH	25	M1N	30	M2EP	113	M4AB	90
L4BM	25	M1P	24	M2ER	49	M4AC	90
L4BR	50	M1R	112	M2ES	87,89	M4AD	57
L4BS	50			M2ET	60	M4AE	57,58
L4BT	112	M1U	113	M2EU	60	M4AF	114
L4BU	51	M1W	113	M2EW	103	M4AG	90
L4BW	51	M1Y	103	M2EY	114	M4AH	54
L4BY	51	M1AA	103	M2FA	83	M4AJ	103
L4CA	51	M1AC	103	M2FB	41	M4AK	103
L4CB	51	M2AR	113	M2FC	103	M4AM	51
L4CC	51	M2CB	89	M2FD	87	M5F	36
L4CD	46	M2CC	113	M2FE	51	M5G	114
L4CE	47	M2CG	25	M3C	89	M5K	58,90
L4CF	112	M2CK	113	M3D	89	M5L	90
L4CG	30	M2CN	38	M3AL	27	M5M	114
L4CH	112	M2CP	113	M3AN	27	M6AA	90
L4CJ	112	M2DC	113	M3AT	89	M6AB	90
L4CK	112	M2DD	113	M3AU	89	M6AC	114
L4CL	112	M2DG	89	M3AW	90	M6AD	58
L4CM	51	M2DK	113	M3AY	90	M6AE	47
L4CP	51	M2DS	89	M3BL	40,114	M6AG	90
		M2DW	113	M3BN	114	M6AH	57
		M2EC	103	M3BR	56,57		
		M2EF	113				

INDEX

Code	Page	Code	Page	Code	Page	Code	Page
M7C	114	M15A	28	M26E	85, 91	P1G	38
M7M	90	M15B	57	M26F	84, 91	P1H	23
M7N	64	M15D	83, 84	M26H	78, 80	P1L	38
M7P	83, 84	M15E	83, 84	M29A	103	P1M	92
M8C	24	M15F	83, 85	M30B	68, 80, 84	P1N	92
M8D	114	M15G	85	M33A	58	P1P	38, 57
M8E	28, 66	M16B	67	M36A	82	P1R	24, 38
M8F	57	M18A	67	M36B	54, 55, 82	P1T	87
M8H	57, 58	M18B	81	M36C	54, 82	P1W	88, 99
M9B	114	M21A	57	M36D	54, 82	P1Y	99
M9C	57	M24A	114	M36E	82	P2A	38
M10A	91	M24B	91	M36F	82	P2B	24, 30
M11A	114	M24C	81	M40A	55	P2G	29
M11D	28, 91	M24D	103	M42A	79, 80, 91	P2H	30
M11F	91	M24E	87	M42B	80, 84	P2J	30
M12C	66	M24F	54, 81	M45A	54, 84	P2P	29
M12E	28, 91	M24G	54, 81	M50A	61	P2R	21, 38, 46
M12F	66	M24H	55, 81	M50E	55, 80	P2T	23, 38
M12G	28, 91	M24J	54, 82	M50F	80, 82	P2AA	23
M12H	57	M24K	55, 82	M50G	79, 82	P2AH	29
M12J	91	M25A	83, 85	M50H	82	P2AK	38
M12L	114	M25B	85	M50J	79, 81	P2AR	38
M12M	78, 83	M25C	85	M50K	55, 79	P2AS	38
M12P	83	M25D	85	M50L	81	P2AT	41, 114
M13A	114	M25E	78, 85	M72A	86	P2AU	114
M14B	83	M25F	83	M80A	79, 81	P2AW	41
M14C	78	M26A	83, 91	P1A	21	P2AY	41
M14D	84	M26B	85, 91	P1B	38	P2BA	41, 103
M14E	80	M26C	85, 91	P1D	30	P2BB	59
M14F	81	M26D	83, 91	P1E	28		

INDEX

Code	Page	Code	Page	Code	Page	Code	Page
P2BC	41	P2CU	39, 42	P2EM	51	P3AP	44
P2BD	42	P2CW	30	P2EN	51, 64	P3AR	92
P2BE	42, 114	P2CY	45, 92	P2EP	23, 51	P3AT	37
P2BG	30, 37	P2DA	30, 42	P2ER	115	P3AU	29
P2BH	92	P2DB	92	P2ES	32, 104	P3AW	66, 104
P2BJ	42	P2DC	46, 92	P3A	32	P3AY	51, 104
P2BK	27, 30	P2DD	46, 92	P3B	23, 32	P3BA	85
P2BM	30, 64	P2DE	42	P3D	29	P3BB	92
P2BP	92	P2DG	42	P3E	27, 32	P3BC	29
P2BR	60	P2DH	85	P3F	29, 32	P3BD	29
P2BS	42, 60	P2DJ	30, 47	P3H	22, 32, 92	P3BE	50, 52
P2BT	60	P2DK	39, 47	P3J	23	P3BF	40, 52
P2BU	61, 115	P2DN	41, 42	P3K	32	P3BG	92
P2BW	42	P2DR	87	P3L	29, 32	P3BH	32
P2BY	30	P2DS	30, 88	P3N	23, 32	P4H	25, 37
P2CA	30	P2DT	42, 104	P3P	27		
P2CB	30	P2DU	30, 43	P3R	21, 32, 46		
P2CC	44	P2DW	43	P3S	21, 32, 46		
P2CD	30, 115	P2DY	49	P3U	32, 40	P4S	36
P2CF	30, 61	P2EA	37, 42	P3W	28, 29	P4Y	29, 32, 40
P2CG	30	P2EB	49	P3AA	22, 32	P4AD	23, 41
P2CH	30, 103	P2EC	42			P4AE	25, 43
P2CJ	42	P2ED	45	P3AF	57, 92	P4AF	27, 59
P2CK	92, 104	P2EE	115	P3AG	66	P4AH	26
P2CL	30, 92	P2EF	115	P3AH	44	P4AJ	59
P2CM	30, 92	P2EG	23, 49	P3AJ	32, 57	P4AK	62, 93, 104
P2CN	92, 104	P2EH	26, 23	P3AK	57, 58	P4AL	62, 93, 104
P2CP	30, 38	P2EJ	30, 51	P3AL	32	P4AM	62, 93, 104
P2CR	104	P2EK	30, 51	P3AM	32	P4AN	61, 85
P2CT	30	P2EL	51	P3AN	32	P4AP	61, 85

INDEX

Code	Page	Code	Page	Code	Page	Code	Page
P4AR	48	P6T	43	P20D	62, 63	R2BY	95
P4AS	47, 99	P8A	57	P20E	62, 63	R2CC	95
P4AU	47	P8B	57, 59	P20F	45, 59	R2CD	95
P4AW	49	P8E	58, 59	P20G	44, 59	R2CE	95
P4AY	21, 47	P9A	61, 63	P20L	45, 63	R2CF	33, 95
P4BA	48, 53	P9B	45	P20M	59, 93	R2CG	95
P4BB	22, 52	P9C	61, 63	P21A	65, 66	R2CH	95
P4BC	21, 46, 52	P9D	86	P22A	104	R2CJ	96
P4BD	52	P9E	84, 86	P24A	67	R2CL	96
P4BE	21, 52	P9F	58	P24B	93	R2CR	96
P4BF	52	P9G	86	P25A	87	R2CS	96
P4BH	40, 52, 92	P9H	61, 86	P32A	46, 115	R2CU	29, 96
P4BJ	40, 52	P9J	61, 66	P33A	58, 59	R2DA	39, 96
P5B	29, 32, 40	P9K	61, 66	P35A	65	R2DB	39, 96
P5C	93	P9L	56	P40C	45, 93	R2DE	96
P5D	36	P9M	56	P50A	67	R2DM	96
P5E	93	P10B	84, 86	P50B	86	R2DN	96
P5F	57	P10C	79, 86	P50C	67	R2DP	33, 96
P5J	41, 47	P11B	66, 67	P59A	44, 65	R2DW	96
P5K	61, 66	P11C	93	P75A	67	R2DY	96
P5L	47, 104	P12A	58	P86A	79, 86	R2ED	96
P6B	22, 33	P12B	59	P100A	86	R2EE	54, 96
P6K	41, 48	P12C	84, 87	P100B	86, 87	R2EY	96
P6L	47	P14A	44, 60	R2H	95	R2FA	96
P6M	48	P14B	87	R2BC	95	R2FE	96
P6N	48	P14C	61, 67	R2BK	95	R2FG	26, 96
P6P	57, 58, 59	P18A	67	R2BR	95	R2FK	115
P6R	48, 50	P19A	61, 63	R2BS	95	R2FL	97
P6S	43	P20A	56, 60	R2BT	95	R2FM	52, 97
		P20C	62, 63, 67	R2BU	95	R4C	97

INDEX

Code	Page	Code	Page	Code	Page	Code	Page
R4D	97	T4A	52	W1AS	99	W2AF	117
S1A	22	T4C	47	W1AT	116	W2AG	97, 117
S1B	33	T7A	116	W1AU	116	W2AJ	97, 117
S1C	39	T9A	116	W1AW	93	W2AK	117
S2A	39	W1B	33	W1AY	99	W2AL	99
S2B	33	W1C	22, 99	W1BA	116	W2AP	25
S2F	21	W1H	37, 99	W1BB	88	W2AR	26, 99
S2L	39	W1L	99	W1BC	88	W2AS	33, 117
S2M	33	W1M	99	W1BD	88	W2AW	26
S3A	29	W1N	104	W1BE	116	W2AY	26
S3B	33	W1P	21	W1BF	116	W2BA	117
S3C	23	W1T	116	W1BG	117	W2BB	29
S3F	23	W1U	116	W2A	22	W2BC	27
S3G	29	W1W	33	W2B	39	W2BD	39, 99
S3H	29	W1Y	116	W2C	33	W2BE	117
S3J	33	W1AA	116	W2D	117	W2BF	23, 117
S3K	27	W1AB	116	W2F	39	W2BG	97
S3L	27, 33	W1AC	33, 93	W2H	39	W2BH	97
S3N	29	W1AD	104	W2J	33	W2BJ	39, 99
		W1AE	37, 99	W2L	29	W2BK	21, 39
S4C	52, 115	W1AF	99	W2M	33	W2BL	100, 104
S6D	43	W1AG	116	W2N	39	W2BM	43
S6E	43	W1AH	116	W2R	33	W2BP	23
T1C	115	W1AJ	116	W2S	23	W2BR	29, 52
T1D	115	W1AK	99	W2T	33	W2BS	33
T1E	115	W1AL	116	W2W	33, 99	W2BT	117
T1H	115	W1AM	41, 116	W2Y	117	W2BY	39
T1M	115	W1AN	116	W2AA	39	W2CA	37
T2R	115	W1AP	116	W2AB	99	W2CB	100, 104
T3K	116	W1AR	116	W2AE	97, 117	W2CC	33

INDEX

Code	Page	Code	Page	Code	Page	Code	Page
W2CF	33, 100	W2EE	105, 118	W2FU	65, 100	W3AC	23, 34
W2CG	39	W2EF	22, 118	W2FW	105	W3AD	106
W2CJ	100	W2EG	118	W2FY	29	W3AE	35
W2CK	33	W2EH	40, 100	W2GA	28	W3AF	94
W2CL	22, 104	W2EL	34	W2GB	23, 88	W3AG	106
W2CN	33, 105	W2EM	40	W2GC	50, 105	W3AH	106, 118
W2CP	34	W2EP	93	W2GD	50, 93	W3AJ	35, 100
W2CR	34	W2ER	118	W2GE	34	W3AL	35
W2CS	39, 117	W2ES	43	W2GF	52	W3AM	40
W2CT	39, 42, 47, 117	W2ET	105	W2GG	52	W3AN	35
W2CU	42	W2EU	34, 93	W2GH	52	W3AP	35
W2CW	117	W2EW	93, 105	W2GK	52, 100	W3AR	40
W2DB	117	W2EY	118	W2GL	50	W3AT	35, 94
W2DC	42, 105	W2FA	118	W2GM	50, 94	W3AU	94
W2DD	105, 117	W2FB	34	W3A	34	W3AW	35
W2DE	105	W2FC	34	W3B	105	W3AY	118
W2DF	60, 105, 118	W2FD	118	W3C	34	W3BB	29
W2DG	60, 118	W2FE	40	W3E	34, 100	W3BC	88, 94
W2DH	118	W2FF	40	W3F	34	W3BD	94, 100
W2DJ	34	W2FG	48	W3K	29	W3BE	35, 100
W2DK	118	W2FH	118	W3L	100	W3BF	35, 41
W2DL	34			W3M	34, 100	W3BG	35
W2DM	28			W3N	34, 100	W4H	35
W2DR	39, 100	W2FL	40	W3R	25, 28	W4J	22
W2DS	64	W2FM	52	W3S	100	W4M	26, 22
W2DT	105	W2FN	34	W3U	27	W4P	24
W2DW	93	W2FP	88, 105	W3W	36	W4R	35
W2DY	64, 65	W2FR	34, 100	W3Y	29	W4Y	26
W2EB	39, 93	W2FS	40, 97	W3AA	41, 105	W4AC	26
W2ED	105, 118	W2FT	34, 97	W3AB	28, 34	W4AD	26

INDEX

Code	Page	Code	Page	Code	Page	Code	Page
W4AE	22, 26	W4CC	24, 45, 53	W9A	86	W35A	65
W4AF	26	W4CD	27, 53	W10A	22, 100	W48A	94
W4AG	24, 26, 45	W4CE	53	W10B	63	W50A	79, 81
W4AL	26, 27	W4CF	46, 53	W12A	101	W50B	87, 106
W4AN	26	W4CG	53	W12B	63		
W4AR	118	W4CH	22, 53	W12D	63		
W4AS	36	W4CJ	50, 53	W13A	62, 63		
W4AT	94	W4CK	50, 53	W13B	62, 63		
W4AU	58, 59	W5B	37, 94	W14B	58		
W4AW	35	W5C	58	W14C	64		
W4AY	22, 118	W5D	23, 28, 106	W15A	44		
W4BA	60	W5E	119	W16B	65		
W4BB	118	W6A	35, 119	W16C	67		
W4BD	36	W6C	35, 119	W17A	62, 63		
W4BF	26, 46, 100	W6D	35	W18B	63		
W4BH	59, 63	W6E	56	W20A	63		
W4BJ	40, 119	W6G	119	W20C	63		
		W6H	45	W20D	64		
W4BL	44, 48	W6J	48	W20E	60		
W4BM	37	W6K	48	W20F	64, 106		
W4BN	47	W6L	49	W20H	56, 119		
W4BP	48	W7A	35	W20J	67		
W4BR	50	W7B	22, 97, 100	W21B	119		
W4BS	50, 52	W7C	64	W21C	119		
W4BT	43, 52	W8C	63	W21D	119		
W4BU	43	W8D	59, 64	W23A	119		
W4BW	23, 53	W8E	62	W23B	119		
W4BY	53	W8F	94	W25A	86		
W4CA	53	W8G	24	W25B	86		
W4CB	22, 53	W8H	119	W25C	86		

COAXIAL CORDS

Code	Page	Code	Page
M2ET	60	P2DY	49
M2EU	60	P2EA	37, 42
M2EY	114	P2EB	49
M2FB	41	P2EC	42
M2FC	103	P2ED	115
M24E	87	P2EE	115
P2AT	41, 114	P2ER	115
P2AU	114	P3AG	66
P2AW	41	P3AH	44
P2BA	41, 103	P3AP	44
P2BB	59	P3AT	37
P2BC	41	P5E	93
P2BD	42	W2CU	42
P2BE	42, 114	W2DC	42, 105
P2BJ	42	W2DD	105, 117
P2BP	92	W2DF	60, 105, 118
P2BR	60	W2DG	60, 118
P2BS	42, 60	W2DH	118
P2BT	60	W2DW	93
P2BU	61, 115	W2EB	39, 93
P2BW	42	W2EH	40, 100
P2CC	44	W2ES	43
P2CD	30, 115	W2FP	88, 105
P2CJ	42	W3AF	94
P2CT	30		
P2DE	42		
P2DG	42		
P2DN	41, 42		
P2DT	42, 104		
P2DW	43		

INTRODUCTION

This is one of a series of Engineering Reference Data Bulletins containing information on apparatus designed by the Bell Telephone Laboratories, Incorporated for other than military applications, and manufactured by the Western Electric Company or by other suppliers in accordance with specifications prepared by the Bell Laboratories. It is intended primarily for use by engineers of the Bell Laboratories, and contains information on apparatus which may be rated AT&TCo Standard, A&M Only, or Special; codes classified ML; or codes designated for nonassociate use. Codes rated Manufacture Discontinued are not included.

Items designated as PREFERRED are those recommended for use wherever practicable. Items not so designated are NONPREFERRED and should not be specified in new applications unless there is no other way of economically accomplishing the desired results. The NONPREFERRED items include (a) the older designs which may have been superseded but are still required for maintenance purposes, (b) designs more expensive to manufacture than others which may perform the same function, and (c) items in such small demand that they are more costly to furnish.

It is planned to bring this bulletin up to date periodically. However, the information contained herein may not be complete and ratings of the items are not shown. Therefore, the final selection of apparatus should be made on the basis of the usual sources of information, such as the Western Electric Apparatus Card Catalog, the manufacturing specifications, and price data. For information regarding the output of apparatus refer to the Western Electric Report A-822.1.

The bulletin may include some codes of apparatus for which catalog cards will not be found in the Western Electric Apparatus Card Catalog. Such codes are in general rated "Component Part". This rating is applied to apparatus where it is believed that the associated telephone companies will have no need for apparatus card catalog information and orders for the apparatus from the field are not expected.

INTRODUCTION

When apparatus which is not listed on a white card in the Western Electric Apparatus Card Catalog is selected for use in new applications, the Head, Standards and Material Engineering Department 8251, Bell Telephone Laboratories, Incorporated, Holmdel, New Jersey, should be notified of the new use and probable demand so that consideration can be given to rerating the apparatus. When such new applications are made within the Bell Laboratories, the selection should first be discussed with the department responsible for the design of the apparatus.

GENERAL

Letter-number-letter codes, as applied to cords, have the following significance: The first letter of the code designates the principal use of the cord as described below; the number following the first letter indicates the number of conductors in the cord; and the third letter or letters arbitrarily indicates a variation in physical structure, such as different color or length of free conductors, cord tips, bands, covering, or insulation.

Principal uses of cords as designated by initial letters in the code are as follows:

- D - Desk stand cords which are also known as mounting cords or line cords. They are generally used between the telephone set and connecting blocks, plugs, or subsets (ringers).
- H - Handset cords which are cords directly connected to handsets.
- L - Operator telephone set cords or head telephone set cords.
- M - Miscellaneous cords which are not classified under any other designations.
- P - Patching cords which are usually arranged for a jack, plug, or connector at each end of the cord for patching purposes.

INTRODUCTION

R - Receiver cords.

S - Switchboard cords which are usually arranged at one end for connecting to a switchboard and at the other end with a plug.

T - Transmitter cords.

W - Testing cords.

D, H, R, and T cords are collectively known as station cords.

This bulletin is arranged in sections based on the apparatus with which the cords are most frequently associated. For example, cords designed for use with coded plugs are found in the first section, the coded plugs numerically arranged and the cords alphabetically listed for each plug. Any cord designed for use with more than one apparatus code will be found listed under each apparatus code. Some cords are supplied with the apparatus (plugs, etc) as a part of the cord but, in general, the apparatus associated with the cord must be ordered separately. In the Cord Assemblies section, the cord assemblies are arranged in the same manner as in the other sections. Cord assemblies are complete with plugs, tools, or jacks as specified. The code number has the following significance: The first number signifies the number of conductors in the cord, the letter following the first number designates the principal use of the cord (P for patching and W for testing), and the ensuing numbers and letters signify variables in length, color, or equipment, etc.

INTRODUCTION

The following abbreviations are used in all tables in the bulletin:

Abbreviations:

Under "Type"

S - Straight cord

R - Retractable cord (spring cord)

Y - Cord with separate arms

T - Textile covering (Cotton braid, Nylon, etc)

W - Waterproof covering, either rubber or synthetic (Neoprene, PVC, etc)

Under "Jacket Material" and "Conductor Insulation"

T - Textile covering (Cotton braid, Nylon, etc)

W - Waterproof covering, either rubber or synthetic (Neoprene, PVC, etc)

Under "Plug End", "Other End", "End A", or "End B"

T - Tip

R - Ring

S - Sleeve

All conductors are tinsel unless otherwise indicated.

NOTES

- (P) - Preferred Code.
- (a) - Tinsel and copper conductors.
- (b) - Single conductor.
- (c) - Available in more than one color.
- (d) - Twenty-two conductors.
- (e) - Has 300-ohm resistor in series with green conductor.
- (f) - Plug is replaceable with Automatic Electric D-5773 Plug.
- (g) - Has internal 1200-ohm resistor.
- (h) - Has KS-8010 switch.
- (j) - One conductor is electrically connected to stay cord hook.
- (k) - Switch, approximately 2 feet from meter end, has four positions - OFF, LOW, MED, and HIGH.
- (l) - Tinsel and stranded wire conductors.
- (m) - Three conductors.
- (n) - Cord reel.
- (p) - Has switch to operate transmitter circuit.
- (r) - Plug is replaceable by 79C Test Set.
- (s) - 10 ft adjusted to have a capacitance of 280 pF min and 300 pF max.
- (t) - DC resistance of conductors is 0.48 ohms per foot.

NOTES

- (u) - Two conductors.
- (w) - Has fuse integral with one conductor.
- (y) - 728A Cable wound in a coil 16 inches in diameter and bound with tape.
- (aa) - Solid copper conductors.
- (ab) - A 17-dB pad is located in each end of the cord in each tip and ring circuit.
- (ac) - A 23-dB pad is located in each end of the cord in each tip and ring circuit.
- (ad) - Also arranged for No. 240A Switch.
- (ae) - Or No. 42A or No. 47B Connecting Block.
- (af) - Or No. 42A Connecting Block.
- (ag) - Also available with KS-8586,L24 Socket, or KS-14525,L4 Connector at one end and KS-14524, L8 Connector at other end.
- (ah) - Has resistor in series with certain terminals
- (ak) - Also equipped with No. 201A Jack Mounting with two No. 236A jacks and two No. 239A jacks at this end.
- (al) - Braided copper shield forms fourth conductor.
- (am) - KS-16645,L1, 47,000-ohm resistor is connected in series with conductor and encased in plug shell.
- (an) - Hubbell 7059, 7092, 7479, or 7588 cap or 7084, 7091, or 7464 body.
- (ap) - H. B. Jones P-404-CCT Plug or S-404-CCT Socket.
- (ar) - Other bodies or caps are available.

NOTES

- (as) - Pyle-National AP-610 contact unit and APD-2005 plug shell.
- (at) - Arranged for transmitter also.
- (au) - Has No. 516A Capacitor connected to one clip.
- (aw) - Has resistance of approximately 190 ohms for 48-volt operation.
- (ay) - Has resistance of approximately 92 ohms for 24-volt operation.
- (ba) - Arranged for receiver also.
- (bc) - All conductors are electrically common.
- (bd) - Has internal 2000-ohm resistor. Also arranged for No. 471A Jack.
- (be) - Bound together at center with 3/8 inch of brown cotton.
- (bf) - Bound with brown textile yarn.
- (bg) - Arranged for connection to No. 44A Connecting Block.
- (bh) - Two conductors are 18Ga, remainder are tinsel.
- (bj) - Flexible stainless steel covering.
- (bk) - Equipped with bushing over flexible collar.
- (bl) - Arranged for 1AH2 microswitch.
- (bm) - May be ordered in length required.
- (bn) - Six conductors.
- (bp) - Eight conductors.
- (br) - Four conductors.

NOTES

- (bs) - Has special nut and bushing for attachment to explosion-proof handsets.
- (bt) - Plug cap is molded on cord and is polarized.
- (bu) - Plug cap is molded on cord and is non-polarized.
- (by) - KS-7586L11 (-49) is available in 2 foot length only.



PLUGS (CODED)



CODED PLUGS

Code	Conductor					Plug End	Other End
	Length (Feet)	Type	Jkt Mat.	In- sul.	Type		
1							
(P) P1A	1,2,4,6	S	T	W		1E	1E Plug
(P) S1A	4,6	S	T	W		1D or 1E	Spade Tip
(P) W1C	12,20	S	T	W	(a)	1D, 1E	360-Type Tool
W1P	6,12,20	S	T	W		1E	KS-6780 Clip
(P) 815 (b)	12	S	T	W	(a)	1E	Tool
186							
W2BK	6,30	S	T	W		186	347 Plug
209							
S2F	4,6,8	S	T(c)	W		209	Spade Tips
214							
742 (d)	6	S	T	T		214	Soldered Connections
234,235							
(P) P2R	19-1/2	S	T	W		234	347-Type Plug
(P) P3R	19-1/2	S	T	W		234	310 Plug
(P) P3S	19-1/2	S	T	W		234	310 Plug
(P) P4AY	8	S	T	W		234	425A Plug
(P) P4BC	19-1/2	S	T	W		234,235	464C Plug
(P) P4BE (e)	19-1/2	S	T	W		234,235	464C Plug

See pages 17-20 for notes.

CODED PLUGS

Code	Conductor						Plug End	Other End
	Length (Feet)	Type	Jkt Mat.	In- sul.	Type			
(P) W4J	19-1/2	S	T	W		234	Spade Tips	
W4M	19-1/2	S	T	W		234	289B Plug	
W4CH	19-1/2	S	T	W		234	464A Plug	
240								
(P) P3H	5, 6, 7, 8-1/2, 9-1/2, 10	S	T	W		240-Type (f)	310 Plug	
(P) P3AA	10	S	T	W	18Ga	240A	310 Plug	
(P) P4BB	12	S	T	W		240B, C or K	464C Plug	
(P) P6B	11	Y	T	W		2-240B	2-310 Plug	
W2A	6	S	T	T		240A	Spade Tips	
(P) W2CL	4	S	T	W		240A or H	KS-8010 Switch (g)	
W2EF	5	S	T	W		240A	Pin-Type Tips	
(P) W4AE	6	S	T	W		240A	289B Plug	
(P) W4AY	8	S	T	T		240A	471A Jack (h)	
(P) W4CB	6	S	T	W		240A	464C Plug	
(P) W7B	11	Y	T	W		240H, 716E Receiver	Spade Tips	
W10A	10	S	T	T		240D	370-Type Tool	

CODED PLUGS

Code	Conductor					Plug End	Other End
	Length (Feet)	Type	Jkt Mat.	In- sul.	Type		
241							
P1H	1	S	W	W	18Ga	241A-T	241A Plug-T
(P) P2T	6	S	T	W		241 Type-T	347 Plug
(P) P2AA	1, 2, 3, 4, 6, 15	S	T	W		241 Type-T	241-Type Plug-T
(P) P2EG	6	S	W	W		241A	446A Plug
(P) P2EH	6	S	W	W		241A	291B Plug
(P) P2EP	6	S	T	W		241B	464A Plug
P3B	10	S	T	W		241 Type	310 Plug
(P) P3J	1, 2, 3, 4, 6	S	T	W		241 Type	241-Type Plug
(P) P3N	3, 6, 15, 20	S	T	W		241 Type	310 Plug
(P) P4AD	6	S	T	T		241B	354A, B Plug
S3C	6	S	T	W		241 Type	Spade Tips
(P) S3F	6, 8	S	T	W		241 Type	Spade Tips
W2S	2-1/2	S	T	W		241 Type-T	Spade Tips
(P) W2BP	2-1/2, 6	S	T	W		241 Type-T	Spade Tips
(P) W2GB	6	S	W	W		241 Type	KS-19531 Plug
(P) W5D	6	Y	T	W		241A	307A Plug, Test Clips
251							
(P) W4AC	6	Y	T	W		251B, C, D or E	289B Plug
(P) W4BW	6	S	T	W		2-251 Type	464C Plug

CODED PLUGS

Code	Conductor					Plug End	Other End
	Length (Feet)	Type	Jkt Mat.	In- sul.	Type		
252							
(P) W4P	19-1/2	S	T	W		252 Type	Spade Tips
(P) W4AG	12,	S	T	W		252A,B	289B Plug
	19-1/2						
(P) W4CC	12	S	T	W		2,252	464C Plug
257							
(P) P2B	1,2,3, 4,6	S	T	W		257A-T,R	257A Plug-T,R
263							
(P) M1P	30	S	W	W	18Ga	263A	Spade Tips
(P) P1R	2,3,4, 6,8,10	S	W	W	18Ga	263A	347A Plug
274							
D8J-9	5-1/2	S	T	W		274A	Spade Tips
(P) D8P-9	5-1/2	S	T	W		274A	Spade Tips
M8C	75	S	T	W	22Ga	274A	Taped Butt
(P) W8G	6	S	W	W	27Ga	274A	Teletype Ter- minals
278							
(P) P1G	5	S	W	W	18Ga	278A	347B Plug-T
(P) W1N	10	S	W	W	18Ga	278A	Test Clips

CODED PLUGS

Code	Conductor					Plug End	Other End
	Length (Feet)	Type	Jkt Mat.	In- sul.	Type		
288							
(P) P4H	1, 2, 3, 4, 6	S	T(c)	W		288A	288A Plug
(P) P4AE	7	S	T	W	22Ga	288A	360D Plug
W2AP	6	S	T	T		288B-S	Spade Tips
289							
(P) H4BY-3	4, 9, 13	S	W	W		289B	Spade Tips (j)
(P) H4CD-3	7	R	W	W		289B	Spade Tips (j)
(P) H4CE-3	9, 13	R	W	W		289B	Spade Tips (j)
L4AC	5-1/2	S	T	T		289B	Spade Tips (bk)
L4AK	7, 15	R	T	W		289B	Receiver, Transmitter
(P) L4AW	6	S	T	T		289B	Receiver, Transmitter
L4BG	5	R	W	W		289B	Eyelet Tips
L4BH	9, 15	R	T	W		289B	Eyelet Tips
L4BJ-52	5	S	W	W		289B	Eyelet Tips
L4BM	5, 7	S	T	W		289B	Tubular Tips
(P) M2CG	10 in.	S	T	W		289B-T	Spade Tips
(P) M4S	3, 6	S	T	W		289B	Spade Tips

CODED PLUGS

Code	Conductor					Plug End	Other End
	Length (Feet)	Jkt Type	Jkt Mat.	In- sul.	Type		
(P) P4AH	6	Y	T	W		289B	2-301A Plug
(P) R2FG	3-1/2	Y	T	T		289B-T	Tubular Tips
W2AR	28	S	T	T		289B-T	360-Type Tool
W2AW	6	S	T	w	18Ga	289B-T	Test Clips
(P) W2AY	9-1/2	S	W	W		289B	Test Clips
W4M	19-1/2	S	T	W		289B	234 Plug
(P) W4Y	6	S	T	W		289B	Tubular and Spade Tips
(P) W4AC	6	Y	T	W		289B	251 Plug
(P) W4AD	6	Y	T	W		289B	KS-6780 Clips
(P) W4AE	6	S	W	W		289B	240A Plug
(P) W4AF	10	S	T	W		289B	521A or B Key
(P) W4AG	12, 19-1/2	S	T	W		289B	252-Type or 412 Plug
(P) W4AL	12	S	T	W		289B	301A Plug
W4AN	6	S	T	W		289B	Twin Plug
(P) W4BF	6	Y	T	W		289B	413 Plug, 360 Tools
291							
(P) P2EH	6	S	W	W		291B	241A Plug

CODED PLUGS

Code	Conductor						Other End
	Length (Feet)	Jkt Type	In- Mat.	In- sul.	Type	Plug End	
(P) P3E	1, 2, 3, 4, 6, 8, 10, 12, 15, 20, 25	S	T (c)	W		291B	291B Plug
(P) S3L	6	S	T (c)	W		291B	Spade Tips
301							
P2BK	15	S	T	W		301A	310 Plug
(P) P4AF	6	Y	T	W		301A	464C Plug
(P) W4AL	12	S	T	W		301A	289B Plug
(P) W4CD	12	S	T	W		301A	464A Plug
304							
(P) M3AL	6	S	W	W	16Ga	304A	Soldered Connections
(P) S3K	5	S	T	W		304A	Spade Tips
(P) W2BC	5-1/2	S	W	W	16Ga	304A-T,R	Spade Tips
305							
(P) M3AN	7	S	T	W	18Ga	305A	Spade Tips
(P) P3P	2, 4, 6, 8, 10, 12	S	T	W	18Ga	305A	305A Plug
(P) W3R	6	S	T	W		305A	308A Plug
(P) W3U	4, 10	S	W	W	18Ga	305A	Spade Tips

CODED PLUGS

Code	Length (Feet)	Conductor				Plug End	Other End
		Type	Jkt Mat.	In- sul.	Type		
306							
(P) M4T	6	S	T	W		306A	307A Plug
(P) W2DM	10	S	T	W		306A	Phone Tip Plug(k)
307							
(P) M4T	6	S	T	W		307A	306A Plug
(P) M8E	6	S	T	W	18Ga	307A	KS-14769 Plug
(P) M11D	6	S	T	W	22Ga	307A	Johnson 625 Plug
(P) M12E	6	S	T	W	22Ga	307A	Johnson 625 Plug
(P) M12G	6	S	T	W	22Ga	307A	Johnson 625 Plug
(P) M15A	6, 10	S	T	W	22Ga	307A	307A Plug
(P) P3W	6	S	T	W		307A	309 Plug
(P) W5D	6	Y	T	W		307A	241A Plug
308							
(P) W2GA	6	S	W	W		308A	Spade Tips
(P) W3R	6	S	T	W		308A	305A Plug
(P) W3AB	12, 25	S	W	W	18Ga	308A	310 Plug
309							
H5E	5	S	T	W		309	Eyelet Tips (j)
(P) P1E	3	S	T	W		309	309 Plug-R

CODED PLUGS

Code	Length (Feet)	Conductor					Plug End	Other End
		Type	Jkt Mat.	In- sul.	Type			
(P) P2G	10	S	T	W		309-T,R	309 Plug-T,R	
(P) P2P	10	S	T	W		309-T,R	310 Plug-T,S	
(P) P2AH	10	S	T	W		309-T,R	310 Plug-T,S	
(P) P3D	9 in. 3,6,8	S	T(c)	W		309	309 Plug	
(P) P3F	4,6,8	S	T(c)	W		309	310 Plug	
(P) P3L	6,12	S	T	W	(a)	309	310 Plug	
(P) P3W	6	S	T	W		309	307A Plug	
(P) P3AU	2	Y	T	W		3-309	2-309 Plug	
P3BC	2	Y	T	W		2-309-T,S	309 Plug-T,S	
P3BD	2	Y	T	W		2-309	2-309 Plug	
(P) P4Y	7	Y	T	T		309-R,310	351A Plug	
(P) P5B	7	Y	T	T		309-T,R; 310	351B Plug	
(P) R2CU	6	S	T	T		309-T,R	716-Type Rec- eiver	
(P) S3A	2-1/2, 4-1/2, 6,8,9, 10	S	T(c)	W		309	Spade Tips	
(P) S3G	6	S	T(c)	W	(1)	309	Spade Tips	
(P) S3H	5	S	T	W		309	Spade Tips	
(P) S3N	5-1/2	S	T(c)	W		309	Spade Tips	
(P) W2L	5	S	T	W		309-T,S	Spade Tips	
(P) W2BB	5	S	T	W	(a)	309-T,R	Spade Tips	
(P) W2BR	4	S	T	W	18Ga	309-T,S	Spade Tips	
(P) W2FY	10	S	W	W	22Ga	309	Pin Tips	
(P) W3K	4,6	S	T	W		309	Spade Tips	
(P) W3Y	19-1/2	S	T	W		309	KS-6780 Clips	
(P) W3BB	8 in.	S	T	W		309	Banana Plugs	

CODED PLUGS

Code	Length (Feet)	Type	Jkt Mat.	Conductor		Plug End	Other End
				In- sul.	Type		
(P) 642 (m)	3-1/2, 5	Y	T	T		309	3-309 Plug-S
(P) 643 (m)	3, 5	Y	T	T		3-309-S	310 Plug
KS-14975, L6	4	(n)	T	W		309	(n)
KS-16517	4	S	W	W		309	Spade Tips
310							
H3L	6	S	T	W		310	Spade Tips
(P) L3K	5	S	W	W		310	Eyelet Tips (h)
L4CG	7, 15	R	W	W		310	Tubular Tips
(P) M1N	100	S	W	W	18Ga	310-R	Spade Tips
(P) M2EJ	14	S	T	W	(a)	310	Soldered Connections
M3BL	2-1/2	S	W	W	18Ga	310-T, R	239A Jack
(P) P1D	6	S	W	W	18Ga	310-R	310 Plug-R
(P) P2B	1, 2, 3, 4, 6	S	T	W		310-T, R	310 Plug-T, R
(P) P2H	10	S	T	W		310 Plug-T, R	310 Plug-T, R
(P) P2J	6, 9	S	T	W		310-T, S	310 Plug-T, S
(P) P2P	10	S	T	W		310-T, S	309 Plug-T, R
(P) P2AE	4	S	T	W	18Ga	310-T, R	289B Plug-S
(P) P2AH	10	S	T	W		310-T, S	309 Plug-T, R
P2BG	2	S	T	W	18Ga	310-T, R	334A Plug
P2BK	15	S	T	W		310-T, R	301A Plug
(P) P2BM	3, 13	S	T	T		310-T, R	KS-14520 Plug

CODED PLUGS

Code	Length (Feet)	Type	Jkt Mat.	Conductor			Other End
				In- sul.	Type	Plug End	
(P) P2BY	2	Y	T	W		310	2-310 Plug- T,R
(P) P2CA	2	Y	T	W		2-310-T,R	2-310 Plug- T,R
(P) P2CB	2	Y	T	W		2-310-T,R	2-310 Plug- T,R
(P) P2CD	6 in.	S	W	W	Coax	310-T,R	477A Jack
(P) P2CF	4	S	T	W		310	KS-14340 Plug
(P) P2CG	5	S	T	W		310-T,R	310 Plug-T,R
(P) P2CH	6	S	T	W		310-T,R	KS-14530 Connector
(P) P2CL	3, 6, 12	S	T	W	20Ga	310-T,R	Grip-Rite Plug
(P) P2CM	10	S	W	W	18Ga	310-T,S	Hubbell 7464 Conn
(P) P2CP	6, 15	S	W	W		310-T,S	347 Plug
(P) P2CT	4	S	W	W	Coax	310	KS-13737 Plug
(P) P2CW	8	S	T	W	20Ga	310	Phone Tip Plugs
(P) P2DA	4	S	T	W		310	359A Plug
(P) P2DJ	6	S	T	W		310-T,R	425A Plug-T
(P) P2DS	12	S	W	W	20Ga	310-T,R	KS-19531,L1 and L2 Plugs
(P) P2DU	12	S	T	W		310	359A Plug
(P) P2EJ	4	S	T	W	18Ga	310-T,R	464A Plug
(P) P2EK	6	S	T	W	18Ga	310-T,R	464C Plug

CODED PLUGS

Code	Conductor					Plug End	Other End
	Length (Feet)	Type	Jkt Mat.	In- sul.	Type		
P2ES	4	S	T	W		310	Gen Radio 274MB Plug
(P) P3A	3	Y	T	T		310	3-310 Plug-R
P3B	10	S	T	W		310	241-Type Plug
(P) P3E	1, 2, 3, 4, 6, 8, 10, 12, 15, 20, 25	S	T(c)	W		310	310 Plug
(P) P3F	4, 6, 8	S	T(c)	W		310	309 Plug
(P) P3H	5, 6, 7, 8, 8-1/2, 9-1/2, 10	S	T	W		310	240A Plug(f)
(P) P3K	6, 12	S	T	W	(a)	310	310 Plug
(P) P3L	6, 12	S	T	W	(a)	310	309 Plug
(P) P3N	3, 6, 15, 20	S	T	W		310	241-Type Plug
(P) P3R	19-1/2	S	T	W		310	234 Plug
(P) P3S	19-1/2	S	T	W		310	234 Plug
(P) P3U	7	S	T	W		310	351A or B Plug
(P) P3AA	10	S	T	W	18Ga	310	240A Plug
(P) P3AJ	10, 15, 20, 25	S	T	W		310	310 Plug
(P) P3AL	2	Y	T	W		2-310-T,S	310 Plug-T,S
(P) P3AM	2	Y	T	W		2-310	2-310 Plug
(P) P3AN	2	Y	T	W		3-310	2-310 Plug
(P) P3BH	6, 12	S	W	W	22Ga	310	310 Plug
(P) P4Y	7	Y	T	T		310, 309	351A Plug

CODED PLUGS

Code	Conductor						Other End
	Length (Feet)	Type	Jkt Mat.	In- sul.	Type	Plug End	
(P) P5B	7	Y	T	T		310, 309	351B Plug
(P) P6B	11	Y	T	W		2-310	2-240B Plug
(P) R2CF	6	S	T	T		310-T,R	716-Type Receiver
R2DP	8	Y	T	T		310-T,S	Receiver
S1B	6	S	T	W		310-T	Spade Tip
(P) S2B	4, 6, 8, 10	S	T(c)	W		310-T,S	Spade Tips
(P) S2M	5, 12	S	T(c)	W		310-T,S	Spade Tips
(P) S3B	4, 5, 6, 8, 10	S	T(c)	W		310	Spade Tips
(P) S3J	5	S	T	W		310	Spade Tips
(P) S3L	6	S	T(c)	W		310	Spade Tips
(P) W1B	10	S	T	W	(a)	310	KS-6780 Tips
(P) W1W	12	S	T	W	(a)	310-T	Test Clip
W1AC	6	S	W	W	18Ga	310-R	Hubbell 9970 Plug
(P) W2C	10, 15	S	T	W		310-T,R	Test Clip
(P) W2J	9-1/2	S	T	W		310-T,R	Pin Tip
(P) W2M	9	S	T	W	(a)	310-T,S	Test Clip
(P) W2R	6	Y	T	W	(a)	310-T,S	Spade Tips
(P) W2T	9	S	T	W		310-T,S	Test Clip
(P) W2W	6, 10, 30	Y	T	W		310-T,R	360-Type Tool
(P) W2AS	8	S	T	T		310-T,R	522A Key
(P) W2BS	5	S	T	T		310-T,S	Spade Tips
(P) W2CC	8	Y	W	W	18Ga	310-T,R	Test Clips
(P) W2CF	1	S	T	W		310-T,R	360B and C Tools
(P) W2CK	5, 10	S	T	T		310-T,R	Tubular Tips
(P) W2CN	6	S	T	W		310-T,R	Test Clips

CODED PLUGS

Code	Length (Feet)	Conductor				Plug End	Other End
		Type	Jkt Mat.	In- sul.	Type		
(P) W2CP	1-3/4	S	T	W		310-T,R	Spade Tips
(P) W2CR	5	S	W	W	18Ga	310-T,R	Soldered Connections
(P) W2DJ	2	S	T	T		310-T,R	Spade Tips
(P) W2DL	2, 5-1/2	S	W	W	18Ga	310-T,R	Spade Tips
(P) W2EL	8	Y	T	W		310-T,S	Clip Tips
(P) W2EU	17	S	T	W		310-T,R	H.B. Jones S202-CCT-THR Socket
(P) W2FB	5	S	T	W		310-T,R	Test Clips
(P) W2FC	4	R	W	W		310-T,R	Transfer Clip
(P) W2FN	6	S	W	W	22Ga	310	310 Plug
(P) W2FR	5	S	T	W	20Ga	310-T,R	360-Type Tools
(P) W2FT	4	R	W	W		310	Tubular Tips
(P) W2GE	5	S	W	W		310	Banana Plugs
(P) W3A	12	S	T	W		310	KS-6780 Clips
W3C	10	S	T	W		310	Test Clips
W3E	10	Y	T	W		310	419A Tool
(P) W3F	4, 10	S	T	W		310	Spade Tips
(P) W3M	6, 15	S	T	W		310	360-Type Tool
(P) W3N	6	S	T	W		310	443A, 503A Tools
(P) W3AB	12, 25	S	W	W	18Ga	310	308A Plug
(P) W3AC	4	Y	W	W		310	Spade Tips(P)

CODED PLUGS

Code	Length (Feet)	Conductor				Plug End	Other End
		Type	Jkt Mat.	In- sul.	Type		
(P) W3AE	5	S	W	W	18Ga	310	Spade Tips
(P) W3AJ	12	S	T	W		310	620A Tool
(P) W3AL	5	S	W	W	18Ga	310	Pin Tips
(P) W3AN	4, 9	S	T	W		310	Test Clips
(P) W3AP	4-1/2	Y	T	W	25Ga	310	Test Clips
(P) W3AT	4	S	T	W		310	General Radio 274NK Plug, Mueller #30 Clip
(P) W3AW	6	S	T	W		310	Pin Tips
(P) W3BE	5	S	T	W	20Ga	310	360-Type Tools
(P) W3BF	6	S	T	W	20Ga	310	351A Plug
(P) W3BG	10	S	W	W	22Ga	310	Unfinished Cond
(P) W4H	10	S	T	W		2-310-T,R	508A Key
W4R	8	S	T	W		2-310	Soldered Connections
(P) W4AW	6	S	T	W		310	Spade Tips
(P) W6A	20	S	T	W		3-310-T,R	523A Key
W6C	5-1/2	S	T	W		2-310	508A Key
(P) W6D	1-1/2, 5-1/2	S	T	W		2-310	Spade Tips
(P) W7A	10	S	T	W		3-310	Spade Tips
(P) 643 (m)	3, 5	Y	T	T		310	3-309 Plug-S

CODED PLUGS

Code	Conductor						Other End
	Length (Feet)	Jkt Type	In- Mat.	Insul.	Type	Plug End	
KS-14975,L5	4	(n)	T	W		310	(n)
KS-16124,L3	4	(n)	T	W		310	(n)
KS-16516,L1	6-1/2	S	T	W		310	Eyelet Tips
KS-16516,L2	4	S	T	W		310	Eyelet Tips
315							
(P) P4S	4,6,10	S	T	W		315 Type	315-Type Plug
(P) W3W	6	S	T	W	18Ga	315A	Spade Tips
(P) W4BD	12	S	T	W		315A	Soldered Connections
316							
(P) M5F	7	S	T	W	18Ga	316A	Spade Tips
(P) P5D	10	S	T	W	18Ga	316A	316A Plug
(P) W4AS	10	S	T	W		316A	Spade Tips
324							

CODED PLUGS

Code	Conductor						Plug End	Other End
	Length (Feet)	Type	Jkt Mat.	In- sul.	Type			
327								
(P) P4H	1,2,3, 4,6	S	T(c)	W			327A	327A Plug
(P) W2CA	5-1/2	S	W	W	16Ga		327A-T	Spade Tips
(P) W4BM	4	S	T	W			327A	Spade Tips
330								
(P) W5B	11	S	W	W	18Ga		5-330 Type	Johnson 645 Plug
334								
P2BG	2	S	W	W	18Ga		334A	310 Plug-T,R
336								
(P) W1AE	12	S	W	W			336A	360-Type Tool
337								
(P) P2EA	4	S	W	W	Coax		337C	358B Plug
345								
(P) P3AT	3,6	S	W	W	760A		345B (a)	345B Plug

CODED PLUGS

Code	Conductor						Plug End	Other End
	Length (Feet)	Type	Jkt Mat.	In- sul.	Type			
346								
(P) H2A	10 in.	S	T	W		346A	346A Plug	
(P) H2C	10 in.	S	T	W		346A	Spade Tips	
347								
H5E	5	S	T	W		347B	Eyelet Tips (j)	
(P) L2AA	4	R	W	W		347B	Tubular Tips	
(P) M2CN	1-1/2, 3,6,10	S	T(c)	W		347 Type	Spade Tips	
(P) P1B	1,2,3, 4,6	S	T	W		347-Type-T	347-Type Plug-T	
(P) P1G	5	S	W	W	18Ga	347-Type-T	278A Plug	
(P) P1L	6	S	W	W	18Ga	347B-T	347B Plug-T	
(P) P1P	2	S	W	W	18Ga	347-Type-T	KS-8585L10 Plug	
(P) P1R	2,3,4, 6,8,10	S	W	W	18Ga	347-Type-T	263A Plug	
(P) P2A	6in., 1, 2,3,4,6	S	T(c)	W		347 Type	347 Type Plug	
(P) P2R	19-1/2	S	T	W		347 Type	234 Plug	
(P) P2T	6	S	T	W		347 Type	241-Type Plug-T	
(P) P2AK	8	S	W	W	18Ga	347-Type-T,S	347-Type Plug-T,S	
(P) P2AR	4	Y	T	W		347 Type	2-347-Type Plug-T	
(P) P2AS	7-1/2	S	T	W		347 Type	347-Type Plug	
(P) P2CP	6, 15	S	W	W		347 Type	310 Plug-T,S	

CODED PLUGS

Code	Conductor						Plug End	Other End
	Length (Feet)	Type	Jkt Mat.	In- sul.	Type			
(P) P2CU	6	S	T	W			347A	359A Plug
(P) P2DK	6	S	T	W			347 Type	425A Plug-T,R
(P) R2DA	3-1/2	S	T	T			347 Type (r)	Tubular Tips
(P) R2DB	3,6,10	S	T	T			347 Type	Tubular Tips
(P) S1C	6	S	T	W			347 Type-T	Spade Tips
(P) S2A	3,4,6,8	S	T(c)	W			347 Type	Spade Tips
(P) S2L	5,6-1/2	S	T	W			347 Type	Spade Tips
(P) W1H	6,10, 12, 19-1/2	S	W	W	18Ga		347B-T	360-Type Tool
(P) W2B	1-3/4	S	T	W			347 Type	Spade Tips
(P) W2F	9-1/2	S	T	W			347 Type	Test Clips
(P) W2H	6	S	T	W	(a)		347 Type	Spade Tips
W2N	3	S	T	W			347 Type	Spade Tips
(P) W2AA	5	S	T	W	(a)		347 Type	Spade Tips
(P) W2BD	20	S	T	T			347 Type	360A and C Tools
(P) W2BJ	6	S	T	W			347 Type	513A Tool
W2BK	6,30	S	T	W			347 Type	186 Tool
(P) W2BY	4-1/2	S	W	W	18Ga		347A	Spade Tips
(P) W2CG	6	S	T	W			347 Type	Tubular Tips
W2CS	9	S	T	W	18Ga		2-347 Type-T	466B Jack
W2CU	2,10	S	W	W	Coax		347A	358A Plug
(P) W2DR	6	S	T	W			347 Type	572A Tool
(P) W2EB	2-5/6	S	W	W	Coax		347B	Hubbell Plugs

CODED PLUGS

Code	Conductor					Plug End	Other End
	Length (Feet)	Jkt Type	Jkt Mat.	In- sul.	Type		
(P) W2EH	10 (s)	S	W	W	Coax	347B	572B Tool
(P) W2EM	3	S	T	W	20Ga	347 Type	Test Clips
(P) W2FE	9-1/2,	S	T	W		347 Type	Test Clips
W2FF	19-1/2 4-1/2	S	W	W	(t)	347 Type	Eyelet Tips
(P) W2FL	16	S	W	W		347C	P-19E386 JK Assem
(P) W2FS	3	R	W	W		347D	Tubular Tips
(P) W3AM	22	S	W	W		347A-T,S	Terminal Strip
(P) W3AR	6	S	T	W		347 Type	Test Clips
(P) W4BJ	8	S	T	W		347 Type	508A Key
(P) 630 (u)	5-1/2	S	T	T		347 Type	Pin Tips
(P) 785 (u)	4	S	T	W	18Ga	347 Type-T,S	Receiver
351							
(P) P3U	7	S	T	W		351A or B	310 Plug
(P) P3BF	7	S	T	W		351A	464B Plug
(P) P4Y	7	S	T	T		351A	309-R; 310 Plugs
P4BH	7	S	T	W		351A or B(e)	464-Type Plug
(P) P4BJ	7	S	T	W		351E	464C Plug
(P) P5B	7	S	T	T		351B	309-R; 310 Plugs

CODED PLUGS

Code	Conductor						Plug End	Other End
	Length (Feet)	Type	Jkt Mat.	In- sul.	Type			
(P) P5J	7	S	T	W		351B	425A Plug	
(P) P6K	7	S	T	W		351G	428A Plug	
(P) W1AM	8	S	T	T		351F	Pin Type Plug	
(P) W3AA	5	S	T	W		351A	KS-8010 Switch (bd)	
(P) W3BF	6	S	T	W	20Ga	351A	Tubular Tips 310 Plug	
352								
(P) P2AY	5-1/2 in.	S	T	T		352A	352A Plug	
354								
(P) P4AD	6	S	T	T		354A and B	241B Plug	
(P) P2DN	5-1/2	S	W	W	Coax	354C	358A Plug	
358								
(P) M2FB	1, 2	S	W	W	Coax	358C	358C Plug	
(P) P2AT	6, 10	S	W	W	Coax	358A	466B Jack	
(P) P2AW	6 in., 1-1/2, 2	S	W	W	Coax	358A	358A Plug	
(P) P2BA	3, 6, 10 4	S	W	W	Coax	358A	KS-13739 Jack	
(P) P2BC	4, 6	S	W	W	Coax	358A	KS-13737 Plug	

CODED PLUGS

Code	Conductor					Plug End	Other End
	Length (Feet)	Type	Jkt Mat.	In- sul.	Type		
(P) P2BD	25	S	W	W	Coax	358A	358A Plug
(P) P2BE	600	S	W	W	Coax	358A	477A Jack
(P) P2BJ	2, 4, 6, 8	S	W	W	Coax	358A	358A Plug
(P) P2BS	1	S	W	W	Coax	358A	KS-14317L3 Plug
(P) P2BW	50	(Y)	W	W	(Y)	358A	358A Plug
(P) P2CJ	5-1/2	S	W	W	Coax	358A	Banana Plugs
(P) P2DE	6 in., 4	S	W	W	728A	358A	503A Jack
(P) P2DG	4	S	W	W	Ca	358A	Molded double-pin plug
(P) P2DN	5-1/2	S	W	W	Coax	358A	354C Plug
(P) P2DT	1	S	W	W	729A	358A	KS-14982L3 Jack
(P) P2EA	4	S	W	W	Coax	358B	337C Plug
(P) P2EC	1	S	W	W	730A	358A	440A Plug
W2CU	2, 10	S	W	W	Coax	358A	347A Plug
(P) W2DC	5-1/2	S	W	W	Coax	358A	Test Clips
359							
(P) P2CU	6	S	T	W		359A	347A Plug
(P) P2DA	4	S	T	W		359A	310 Plug

CODED PLUGS

Code	Length (Feet)	Jkt Type	In- Mat. sul.	Conductor		Plug End	Other End
				Type	Type		
(P) P2DU	12	S	T	W		359A	310 Plug
360							
(P) P4AE	7	S	T	W	22Ga	360D	288A Plug
361							
(P) W2BM	1-1/2	Y	T	W		361	Test Clips
371							
(P) P6S	6, 8	S	W	W		371C	371C Plug
(P) P6T	2, 4	S	W	W		371C	371C Plug
(P) S6D	4-1/2,	S	T(c)	W		371C	Spade Tips
	5-2/3,						
	7,						
	8-1/4, 9						
(P) S6E	8-1/4	S	T(c)	W		371C	Spade Tips
(P) W4BT	6	S	T	W		371C	464A Plug
(P) W4BU	5	S	T	W		371C	Tubular Tips
374							
(P) P2DW	9 in.	S	W	W	730A	374A	374A Plug
(P) W2ES	4	S	W	W	(Ca) Coax	374B	Test Clips

CODED PLUGS

Code	Conductor					Plug End	Other End
	Length (Feet)	Jkt. Type	In- sul. Mat.	Type	Type		
379							
(P) P3AH	2, 4, 6, 10	S	T	W	Coax	379A	379A Plug
(P) P3AP	5-1/2	S	T	W	Coax	379A	Banana Plugs
385							
(P) W15A	3	S	T	W	22Ga	385A	Soldered Connections
388							
(P) P14A	6 (aa)	S	W	W	22Ga	388B	KS-13875 Plug
(P) P59A	3 (aa)	Y	W	W	24Ga	388A	2-KS-14554-L2 Conn
396							
(P) W4BL	16	Y	T	W		396A; 360B and C Tools	2-431A Plugs
397							
(P) P2CC	2	S	W	W	Coax	397A	Test Clips
398							
(P) P20G	10	S	T	W	22Ga	10-398A	KS-8586L51 Socket

CODED PLUGS

Code	Conductor					Plug End	Other End
	Length (Feet)	Jkt Type	In- Mat.	sul.	Type		
399							
(P) P20F	18	S	W	W	27Ga	399A	KS-8586L51 Socket
400A							
(P) P40C	1-1/6	Y	W	W	27Ga	400A	Cannon K03- 19-20SN Socket
405							
(P) P20L	25	S	W	W	27Ga	405A	KS-14461L3 Plug
406							
(P) P9B	4, 8	S	T	W		406A	406A Plug
(P) W6H	20	S	T	W		406A	Test Clips
L8A	7	R	W	W		406B	Tubular Tips (ad)
407							
(P) P2CY	10 in.	S	W	W	18Ga	407A	H.B. Jones P202-CCT Plug
412							
(P) W4AG	12, 19-1/2	S	T	W		412	289B Plug
(P) W4CC	12	S	T	W		2-412	464C Plug

CODED PLUGS

Code	Conductor					Plug End	Other End
	Length (Feet)	Type	Jkt Mat.	In- sul.	Type		
413							
(P) P2DD	10 in.	S	W	W	18Ga	413C, 413D	H.B. Jones
(P) W4BF	6	Y	T	W		413	P202-CCT Plug
(P) W4CF	6	Y	T	W		413	289B Plug, 360-Type Tools 464C Plug
415							
(P) P2R	19-1/2	S	T	W		415A	347 Plug
(P) P3R	19-1/2	S	T	W		415A	310 Plug
(P) P3S	19-1/2	S	T	W		415A	310 Plug
(P) P4AT	6, 8, 10	S	T	W		415A	425A Plug
(P) P4BC	19-1/2	S	T	W		415A	464C Plug
417							
(P) P2DC	10 in.	S	W	W	18Ga	417A	H.B. Jones P202-CCT Plug
422							
(P) L4CD	18	R	W	W		422A	Tubular Tips
424							
(P) P32A	4	S	W	W	27Ga	424C	217B Conn

CODED PLUGS

Code	Conductor					Plug End	Other End
	Length (Feet)	Type	Jkt. Mat.	In- sul.	Type		
425							
(P) H6F	4, 9, 13	R	W (c)	W		425A	Spade Tips
(P) L4CE	18	R	W	W		425A	Eyelet Tips
(P) L6H	7, 12, 18	R	W	W		425A	240A Switch Tubular Tips
(P) L6J	7, 12	R	T	W		425A	225A Switch Tubular Tips
(P) M6AE	6	S	T	W	22Ga	425A	Soldered Con- nections
(P) P2DJ	6	S	T	W		425A	310 Plug
(P) P2DK	6	S	T	W		425A	347 Plug
(P) P4AS	6, 8, 10, 20	S	T	W		425A	360-Type Tools
(P) P4AT	6, 8, 10	S	T	W		425A	415A Plug
(P) P4AU	8	S	T	W		425A	Chucks
(P) P4AY	8	S	T	W		425A	234 Plug
(P) P5J	7	S	T	W		425A	351B Plug
(P) P5L	8	S	T	W		425A	Test Clips
(P) P6J	3, 6	S	T	T		425A	425A Plug
(P) P6L	1, 3, 5, 6, 7, 8, 9, 10, 15, 20, 25	S	T (c)	W		425A	425A Plug
(P) T4C	13	R	W	W		425A	Unfinished Cond
(P) W4BN	6	S	T	W		425A	Eyelet Tips

CODED PLUGS

Code	Conductor						Plug End	Other End
	Length (Feet)	Type	Jkt Mat.	In- sul.	Type			
(P) W4BP	6	S	T	W		425A	Soldered Con- nections	
(P) W6J	5-2/3	S	T	W		425A	Spade Tips	
(P) W6K	5-2/3	S	T	W		425A	Spade Tips	
428								
(P) P4AR	5, 8	S	T	W		428A	428A Plug	
(P) P4BA	5	S	W	W	27Ga	428A	470A Plug	
(P) P6K	7	S	T	W		428A	351G Plug	
P6R	7	S	W	W	27Ga	428A	459A Plug	
(P) W2FG	6	S	T	W		428A	Spade Tips	
430								
(P) P6M	10, 15, 20	S	W	W	22Ga	430A (ab)	430A Plug	
(P) P6N	10, 15, 20, 25	S	W	W	22Ga	430A (ac)	430A Plug	
431								
(P) W4BL	16	Y	T	W		2-431A	396A Plug, 360B and C Tools	

CODED PLUGS

Code	Conductor					Plug End	Other End
	Length (Feet)	Type	Jkt. Mat.	In- sul.	Type		
440							
(P) P2EB	1, 2, 3, 6, 9	S	W	W	730A Ca	440A	440A Plug
(P) P2EC	1	S	W	W	730A Ca	440A	358A Plug
(P) P2ED	1	S	W	W	730A Ca	440A	477B Jack
444							
(P) M2ER	6, 11	S	W(c)	W		444A	261A Switch
446							
(P) P2EG	6	S	W	W		446A	241A Plug
W6L	5-2/3	S	T	W		446A	Spade Tips
448							
(P) P2DY	9 in., 1	S	W	W	730A Ca	448A	448A Plug
449							
(P) P4AW	1-1/3	S	W	W	27Ga	449A	Free Conduc- tors
453							
(P) P2EF	8 in.	Y	T	W		2-453A	Test Clips

CODED PLUGS

Code	Length (Feet)	Type	Jkt Mat.	Conductor		Plug End	Other End
				In- sul.	Type		
459							
P3BE	7	S	W	W		459A	464B Plug
P6R	7	S	W	W		459B	428A Plug
463							
(P) W2GC	3	S	W	W		463A	Test Clips
(P) W2GD	10 in.	S	W	W	18Ga	463A	H.B. Jones P202-CCT Plug
W2GL	3	S	T	W		463A	Test Clips
W2GM	10 in.	S	W	W	18Ga	463A	H.B. Jones P202-CCT Plug
(P) W4BR	16	S	T	W		463A	464A Plug
(P) W4BS	16	S	T	W		2, 463A	464A Plug
W4CJ	16	S	T	W		463A	464A Plug
W4CK	6 in.	S	T	W		2, 463A	464A Plug
464							
H4DD	4, 13	R	W(c)	W		464A	Spade Tips
H4DK	4, 9, 13	R	W(c)	W		464A	Spade Tips
H4DL-3	4, 9, 13	S	W	W		464A	Spade Tips(j)
H4DM-3	7	R	W	W		464A	Spade Tips
H4DN-3	7	R	W	W		464A	Spade Tips(j)
H4DP-3	9, 13	R	W	W		464A	Spade Tips(j)
H4DR-3	4	S	W	W		464A	Spade Tips(j)
L2AD	4, 5-1/2	S	T	T		464A	723A Receiver
(P) L4BR	5	S	W	W		464A	Eyelet Tips
(P) L4BS	5	R	W	W		464A	Eyelet Tips

CODED PLUGS

Code	Conductor						Other End
	Length (Feet)	Type	Jkt Mat.	In- sul.	Type	Plug End	
(P) L4BU	12	R	W	W		464A (ad)	Eyelet Tips
(P) L4BW	9, 15	R	W	W		464A	Eyelet Tips
(P) L4BY	10	R	W	W		464A	Tubular Tips
(P) L4CA	7, 15	R	W	W		464A	(h) Eyelet Tips
(P) L4CB	7, 10	R	W	W		464A	Eyelet Tips
(P) L4CC	5, 7	S	W	W		464A	Eyelet Tips
L4CM	13	R	W	W		464A	Tubular Tips
L4CP	4, 6	S	T	T		464A	Tubular Tips
L4CR	4	S	T	T		464A	2-Receivers
(P) M2FE	1	S	T	W		464A	Spade Tips
(P) M4AM	3, 6	S	T	W		464C	Spade Tips
(P) P2EJ	4	S	T	W	18Ga	464A	310 Plug
(P) P2EK	6	S	T	W	18Ga	464C	310 Plug
(P) P2EL	1, 2, 3, 4, 6, 8	S	T	W		464C	464C Plug
(P) P2EM	8	S	T	W		464C	310 Plug
(P) P2EN	13	S	T	W		464C	KS-14520 Plug
(P) P2EP	6	S	T	W		464A	241B Plug
(P) P3AY	6-2/3	S	T	W	22Ga	464A	Switchcraft 750 Plugs Gen Radio No. 274MB Plug

CODED PLUGS

Code	Length (Feet)	Conductor				Plug End	Other End
		Type	Jkt. Mat.	In- sul.	Type		
P3BE	7	S	W	W		464B	459A Plug
(P) P3BF	7	S	T	W		464B	351A Plug
(P) P4BB	12	S	T	W		464C	240-Type Plug
(P) P4BC	19-1/2	S	T	W		464C	234,235 or 415A Plugs
(P) P4BD	4,6	S	T	W		464C	464C Plug
(P) P4BE	19-1/2	S	T	W		464C	234,235 Plug
(P) P4BF	6	Y	T	W		464C	2-301A Plugs
P4BH	7	S	T	W		464	351A or B(e) Plug
(P) P4BJ	7	S	T	W		464B	351E Plug
(P) R2FM	3-1/2	S	T	W		464A	2-Receivers
S4C	6	S	T(c)	W		464 Type	Spade Tips
(P) T4A	13	R	W	W		464A	Unfinished Cond
(P) W2FM	16	S	W	W		464A	Chucks
W2GF	6	S	T	W	18Ga	464A	Test Clips
(P) W2GG	9-1/2	S	T	W		464C	Test Clips
W2GH	5-1/2	S	W	W	16Ga	464 Type	Spade Tips
(P) W2GK	28	S	T	W		464A	2-360-Type Tools
(P) W2BR	16	S	T	W		464A	463A Plug
(P) W4BS	16	S	T	W		464A	2-463A Plugs
(P) W4BT	6	S	T	W		464A	371C Plug

CODED PLUGS

Code	Conductor						Plug End	Other End
	Length (Feet)	Type	Jkt Mat.	In- sul.	Type			
(P) W4BW	6	Y	T	W		464C	2-251 Plugs	
(P) W4BY	6	S	T	W		464A	Spade and Tubular Tips	
(P) W4CA	6	Y	T	W		464C	KS-6780 Conn Clips	
(P) W4CB	6	S	T	W		464C	240A Plug	
(P) W4CC	12	S	T	W		464C	2-252 or 412 Plugs	
(P) W4CD	12	S	T	W		464A	301A Plug	
W4CE	10	S	T	W		464A	521A or B Key	
(P) W4CF	6	Y	T	W		464C	2-413 Plugs	
W4CG	4	S	T	W		464 Type	Spade Tips	
W4CH	19-1/2	S	T	W		464 Type	234 Plug	
W4CJ	16	S	T	W		464A	463A Plug	
W4CK	6 in.	S	T	W		464A	2-463A Plugs	
470								
(P) P4BA	5	S	W	W	27Ga	470A	428A Plug	
505								
D2M	18	S	W	W	20Ga	505A	Switchcraft 820 Jack	
(P) D3BN	5-1/2	S	W(c)	W		505A (ae)	Spade Tips	
(P) D3BP	5-1/2	S	W(c)	W		505A (ae)	Spade Tips	
(P) D3BR-3	5-1/2, 9, 13	R	W	W		505A (ae)	Spade Tips	

CODED PLUGS

Code	Conductor						Plug End	Other End
	Length (Feet)	Type	Jkt Mat.	In- sul.	Type			
(P) D3BS	5-1/2, 9, 13	R	W(c)	W			505A (ae)	Spade Tips
(P) D4BC-3	5-1/2, 9, 13	R	W	W			505A (ae)	Spade Tips
(P) D4BH	5-1/2, 9, 13	R	W(c)				505A (ae)	Spade Tips
(P) D4BJ	5-1/2	S	W(c)	W			505A (ae)	Spade Tips
(P) D4BK-3	5-1/2	S	W	W			505A (ae)	Spade Tips
(P) D4BM	9	S	W(c)	W			505A (af)	Spade Tips
(P) M4R	75	S	W	W	22Ga		505A	Taped Butt
(P) M4AH	6	S	W	W	27Ga		505A	Clip Tips
(P) R2EE	4-1/4	Y	T	W			505A	2-Receiver
507								
(P) M24F	4	S	W	W	27Ga		2-507A	KS-16785L6 Plug
(P) M24G	1, 5	S	W	W	27Ga		2-507A	KS-16785L6 Plug
(P) M24J	1, 5	S	W	W	27Ga		2-507A	KS-16785L6 Plug
(P) M36B	7	S	W	W	27Ga		2-507A, 508C, 508D	KS-16785L13 Plug
(P) M36C	4	S	W	W	26Ga		2-507A	KS-16785L7 Plug
(P) M36D	4	S	W	W	26Ga		2-507A	KS-16785L7 Plug
(P) M45A	3-1/3	S	W	W	27Ga		507A, Spade Tips	2-KS-19087 Plug

CODED PLUGS

Code	Length (Feet)	Conductor				Plug End	Other End
		Type	Jkt Mat.	In- sul.	Type		
M50E	6-1/2	S	W	W	27Ga	507A, Spade Tips	KS-16690L3 Conn
(P) M50K	4	S	W	W	27Ga	507A, Spade Tips	KS-16689L1 Plug
508							
D120K	8	S	W(c)	W		508 Type	KS-16689L5 Plug
D150U	8	S	W(c)	W		508 Type	3-KS-16689L1 Plugs
(P) D200S	8	S	W(c)	W		508 Type	5-KS-16689L5 Plugs
D200T	8	S	W(c)	W		508 Type	4-KS-16689L1 Plugs
D200U	8	S	W(c)	W		508 Type	4-KS-16689L1 Plugs
D250J	8	S	W(c)	W		508-Type, Spade Tips	5-KS-16689L5 Plugs
D250K	8	S	W(c)	W		508 Type	5-KS-16689L1 Plugs
(P) M24H	1, 4, 10	S	W	W		5-508 Type	KS-16785L13 Plug
(P) M24K	4	S	W	W		6-508 Type	KS-16785L13 Plug
(P) M36B	7	S	W	W		508C, 508D, 2-507A	KS-16785L13 Plug
908							
(P) M40A	8	S	W	W	27Ga	908B	908B Conn

CODED PLUGS

Code	Conductor					Plug End	Other End
	Length (Feet)	Jkt Type	In- Mat.	sul. Type			
PIECE-PART PLUGS							
(P) H6A	5	Y	T	W		P-12A539, P-337732	Eyelet Tips (j)
P9L	6-1/2	S	T	W		P-46C220	Unfinished Conductors
P9M	8, 12	S	T	W		P-46C220	Unfinished Conductors
(P) P20A	12	S	W	W		P-18E407	KS-19088L5 Conn
(P) W20H	15	Y	W	W	Coax	P-337449	206A Conn
(P) W6E	5	S	W	W	20Ga	P-267188	Unfinished Conductors
(P) M3BR	10	S	W	W	22Ga	P-19E401	KS-8585L9 Plug

PLUGS (KS)

PLUGS (KS)



KS PLUGS

Code	Conductor						Plug End	Other End
	Length (Feet)	Jkt Type	In- Mat.	In- sul.	Type			
KS-8585								
(P) M3BR	10	S	W	W	22Ga	KS-8585L9	P-19E401 Connector	
(P) M4AD	2	S	T	T	22Ga	KS-8585L9	Spade Tips	
(P) M4AE	1	S	W	W	18Ga	KS-8585L9 or L48	Soldered Con- nections	
(P) M6AH	6	S	W	W	27Ga	KS-8585L17	Clip Tips	
M6AJ	9-1/2	S	W	W	27Ga	KS-8585L10	Spade Tips	
(P) M8F	2-1/2	S	T	T	22Ga	KS-8585L25	Spade Tips	
(P) M8H	10 in., 3-1/2	S	W	W	18Ga	KS-8585L52	KS-8586L53 Socket	
M9C	2-1/2	S	T	W	22Ga	KS-8585L40	Spade Tips	
(P) M12H	3	S	T	T	22Ga	KS-8585L27	Spade Tips	
(P) M15B	2, 8	S	T	T	22Ga	KS-8585L25 (ag)	KS-8585L25 Plug	
(P) M21A	7	S	T	T	22Ga	KS-8585L30	Spade Tips	
(P) P1P	2	S	W	W	18Ga	KS-8585L10	347 Plug	
(P) P3AK	1	S	W	W	18Ga	KS-8585L9	KS-8586L6 Socket	
(P) P4AF	1	S	W	W	18Ga	KS-8585L10	KS-8586L7 Socket	
(P) P4AJ	3, 6	S	W	W	18Ga	KS-8585L9	KS-8586L6 Socket	
(P) P5F	6	S	W	W	20Ga	KS-8585L17	KS-8585L4 Plug	
(P) P6P	10 in., 6-1/2	S	T	W	18Ga	KS-8585L45	KS-8586L50 Socket	
(P) P8A	5, 3	S	T	T	22Ga	KS-8585L10	KS-8585, L10 Plug	
(P) P8B	10	S	T	T	22Ga	KS-8585L10	KS-8586L7 Socket	

KS PLUGS

Code	Length (Feet)	Conductor				Plug End	Other End
		Type	Jkt Mat.	In- sul.	Type		
(P) P8E	12	S	W	W	22Ga	KS-8585L10	KS-8586L7 Socket
(P) P9F	10	S	W	W	27Ga	KS-8585L19	Spade Tips
(P) P12A	1, 3, 5	S	T	T	22Ga	KS-8585L40	KS-8585L40 Plug
(P) P33A	4	S	T	T	22Ga	KS-8585L26	KS-8586L16 Socket
(P) W4AU	6	S	T	T	22Ga	KS-8585L9 (w)	KS-8586L6 Plug
(P) W5C	7-1/2	S	T	W		KS-8585L15; 310	Soldered Con- nections
(P) W14B	3-2/3	S	T	W	27Ga	KS-8585L9 and L17	Soldered Con- nections
(P) W20B	6 (ah)	S	T	W	22Ga	3-KS-8585L17; 1-L9	Unfinished Cond
KS-8586							
(P) M2EH	3	S	W	W	18Ga	KS-8586L9	Spade Tips
(P) M2EL	12	S	T	W	20Ga	KS-8586L9	Test Clips
(P) M4AE	1	S	W	W	18Ga	KS-8586L6 or L52	Soldered Con- nections
(P) M5K	2	S	W	W	20Ga	KS-8586L4	Amphenol 91-MC4M Conn
(P) M6AD	2-1/2	S	W	W	20Ga	KS-8586L4	Spade Tips
(P) M8H	10 in., 3-1/2	S	W	W	18Ga	KS-8586L53	KS-8585L52 Plug
(P) M33A	2	S	T	T	22Ga	KS-8586L16	Soldered Con- nections
(P) P3AK	1	S	W	W	18Ga	KS-8586L6	KS-8585L9 Plug

KS PLUGS

Code	Length (Feet)	Type	Jkt Mat.	Conductor			Plug End	Other End
				In- sul.	Type			
(P) P4AF	1	S	W	W	18Ga	KS-8586L7	KS-8585L10 Plug	
(P) P4AJ	3,6	S	W	W	18Ga	KS-8586L6	KS-8585L9 Plug	
(P) P6P	10 in., 6-1/2	S	T	W	18Ga	KS-8586L50	KS-8585L45 Plug	
(P) P8B	10	S	T	T	22Ga	KS-8586L7	KS-8585L10 Socket	
(P) P8E	12	S	W	W	22Ga	KS-8586L7	KS-8585L10 Plug	
(P) P12B	6	S	T	T	22Ga	KS-8586L36	KS-8586L36 Socket	
(P) P20F	18	S	W	W	27Ga	KS-8586L51	399A Plug	
(P) P20G	10	S	T	W	22Ga	KS-8586L51	10-398A Plugs	
(P) P20M	15	S	W	W	27Ga	KS-8586L51	Cannon K01- 19-20PN Conn	
(P) P33A	4	S	T	T	22Ga	KS-8586L16	KS-8585L26 Plug	
(P) W4AU	6	S	T	T	22Ga	KS-8586L6 (w)	KS-8585L9 Plug	
(P) W4BH	6	S	T	W	22Ga	KS-8586L6	KS-14461L3 Plug	
(P) W8D	6	S	T	T	22Ga	KS-8586L7	KS-14524L8 Conn	
KS-13737								
(P) P2BB	6	S	W	W	Coax	KS-13737	KS-13737 Plug	
(P) P2BC	4,6	S	W	W	Coax	KS-13737	358A Plug	
(P) P2CT	4	S	W	W	Coax	KS-13737	310 Plug	

KS PLUGS

Code	Conductor						Plug End	Other End
	Length (Feet)	Jkt Type	In- Mat.	In- sul.	Type			
KS-13836								
(P) W2DF	15,30	S	W	W	Coax	KS-13836L1	206A Con- nector	
(P) W2DG	30	S	W	W	Coax	KS-13836L2	206B Con- nector	
KS-13875								
(P) P14A	6 (aa)	S	W	W	22Ga	KS-13875	388B Plug	
(P) P20A	12 (aa)	S	W	W	22Ga	KS-13875	KS-13895L1 Plug	
(P) W4BA	4-1/2	S	W	W	16Ga	KS-13875	Unfinished Cond	
(P) W20E	10	S	T	W	27Ga	KS-13875	Soldered Con- nections	
KS-13895								
(P) P20A	12 (aa)	S	W	W	22Ga	KS-13895L1	KS-13875 Plug	
KS-14317								
(P) M2ET	3	S	W	W	Coax	KS-14317L3	552A Jack	
(P) M2EU	3	S	W	W	Coax	KS-14317L3	557A Jack	
(P) P2BR	15,25, 45	S	W	W	Coax	KS-14317L3	KS-14317L3 Plug	
(P) P2BS	1	S	W	W	Coax	KS-14317L3	358A Plug	
(P) P2BT	1,5,50	S	W	W	Coax	KS-14317L3	KS-14317L3 Plug	

KS PLUGS

Code	Length (Feet)	Type	Jkt Mat.	In- sul.	Conductor		Other End
					Type	Plug End	
(P) P2BU	1,600	S	W	W	Coax	KS-14317L3	KS-14982L3 Jack
KS-14340							
(P) P2CF	4	S	T	W		KS-14340	310 Plug
KS-14453							
(P) M50A	2	S	W	W	24Ga	KS-14453L2	Soldered Con- nections
KS-14460							
(P) P4AN	6 in., 12	S	T	W	27Ga	KS-14460L2	KS-19088L5 Conn
(P) P4AP	6 in.	S	W	W	27Ga	KS-14460L2	KS-19088L5 Conn
(P) P5K	6 in., 12	S	T	W	27Ga	KS-14460L2	KS-16370L2 Conn
(P) P9A	12	S	T	W		KS-14460L3	KS-14461L3 Plug
(P) P9C	12	S	T	W		KS-14460L3	KS-14461L3 Plug
(P) P9H	8	S	T	W	24Ga	KS-14460L3	KS-19088L5 Conn
(P) P9J	8	S	T	W	24Ga	KS-14460L3	KS-16370L28 Conn
(P) P9K	8	S	T	W	24Ga	KS-14460L3	KS-16370L2 Conn
(P) P14C	6 in.	S	W	W	22Ga	KS-14460L3	KS-16370L42 Conn
(P) P19A	10	S	T	W	27Ga	KS-14460L3	KS-14461L3 Plug

KS PLUGS

Code	Length (Feet)	Type	Jkt Mat.	Conductor			Plug End	Other End
				In- sul.	Type			
(P) P20C	5-1/2, 25	S	T	W	22Ga	KS-14460L3	KS-14461L3 Plug	
(P) P20D	3-1/4	S	T	W	24Ga	KS-14460L3	KS-14461L3 Plug	
(P) P20E	5-1/2	S	T	W	22Ga	KS-14460L3	KS-14461L3 Plug	
(P) W8E	4	S	T	W	22Ga	KS-14460L2	Soldered Con- nections	
(P) W13A	2	S	T	W	27Ga	KS-14460L3	KS-14461L3 Plug	
(P) W13B	6	S	T	W	16Ga 20Ga	KS-14460L3	KS-14461L3 Plug	
(P) W17A	8	S	T	W	22Ga	KS-14460L3	KS-14461L3 Plug	
(P) W18B	9	S	T	W	27Ga	KS-14460L3 (ak)	KS-14461L3 Plug	
W20A	2	S	T	W	22Ga	KS-14460L3	KS-14461L3 Plug	
(P) W20C	6	S	T	W	22Ga	KS-14460L3	KS-14461L3 Plug	
(P) W20D	10	S	T	W	22Ga	KS-14460L3	KS-14461L3 Plug	
(P) W20E	10	S	T	W	22Ga	KS-14460L3	Unfinished Cond	
KS-14461								
(P) P4AK	13 (al)	S	W	W	20Ga	KS-14461L2	Amphenol Conn	
(P) P4AL	13 (al)	S	W	W	20Ga	KS-14461L2	Amphenol Conn	
(P) P4AM	13 (al)	S	W	W	20Ga	KS-14461L2	Amphenol Conn	

KS PLUGS

Code	Conductor						Other End
	Length (Feet)	Type	Jkt Mat.	In- sul.	Type	Plug End	
(P) P9A	12	S	T	W		KS-14461L3	KS-14460L3 Plug
(P) P9C	12	S	T	W		KS-14461L3	KS-14460L3 Plug
(P) P19A	10	S	T	W	27Ga	KS-14461L3	KS-14460L3 Plug
(P) P20C	5-1/2, 25	S	T	W	22Ga	KS-14461L3	KS-14460L3 Plug
(P) P20D	3-1/4	S	T	W	24Ga	KS-14461L3	KS-14460L3 Plug
(P) P20E	5-1/2	S	T	W	22Ga	KS-14461L3	KS-14460L3 Plug
(P) P20L	25	S	W		27Ga	KS-14461L3	405A Plug
(P) W4BH	6	S	T	W	22Ga	KS-14461L3	KS-8586L6 Socket
(P) W8C	4	S	T	W	22Ga	KS-14461L3	Unfinished Cond
(P) W10B	4	S	T	W	22Ga	KS-14461L2	Soldered Con- nections
(P) W12B	2	S	T	W	22Ga	KS-14461L3	Unfinished Cond
(P) W12D	2-2/3	S	T	W	24Ga	KS-14461L3	Soldered Con- nections
(P) W13A	2	S	T	W	27Ga	KS-14461L3	KS-14460L3 Plug
(P) W13B	6	S	T	W	16Ga 20Ga	KS-14461L3	KS-14460L3 Plug
(P) W17A	8	S	T	W	22Ga	KS-14461L3	KS-14461L3 Plug
(P) W18B	9	S	T	W	27Ga	KS-14461L3	KS-14460L3 Plug (ak)
W20A	2	S	T	W	22Ga	KS-14461L3	KS-14460L3 Plug
(P) W20C	6	S	T	W	22Ga	KS-14461L3	KS-14460L3 Plug

KS PLUGS

Code	Length (Feet)	Type	Jkt Mat.	Conductor			Plug End	Other End
				In- sul.	Type			
(P) W20D	10	S	T	W	22Ga	KS-14461L3	KS-14460L3 Plug	
(P) W20F	19	S	T	W	22Ga	KS-14461L3	20-Test Clips	
KS-14520								
(P) P2BM	3, 13	S	T	T		KS-14520	310 Plug-T,R	
(P) P2EN	13	S	T	W		KS-14520	464C Plug	
(P) W2DS	4	S	T	T		KS-14520	Tip Plugs	
(P) W2DY	4	S	T	W	20Ga	KS-14520	KS-14530 Conn	
KS-14524								
(P) W8D	6	S	T	T	22Ga	KS-14524L8	KS-8586L7 Socket	
(P) W14C	10	S	W	W	22Ga	KS-14524L7	Spade Tips	
KS-14527								
(P) W7C	3	S	W	W	27Ga	KS-14527	KS-14527L2 Receptacle	
KS-14528								
(P) M7N	11 in.	S	W	W	24Ga	KS-14528L2	Free Conduc- tors	
(P) W7C	3	S	W	W	27Ga	KS-14528	KS-14527L2 Conn	

KS PLUGS

Code	Conductor						Plug End	Other End
	Length (Feet)	Jkt Type	In- Mat.	In- sul.	Type			
KS-14530								
(P) W2DY	4	S	T	W		KS-14530	KS-14520 Plug 360-Type Tools	
W2FU	10	S	T	W	20Ga	KS-14530		
KS-14554								
(P) P35A	6 (aa)	S	W	W	24Ga	KS-14554	KS-14555 Conn 388A Plug KS-14555L2 Conn	
(P) P59A	3 (aa)	Y	W	W	24Ga	KS-14554		
(P) W35A	12	S	W	W	27Ga	KS-14554L2		
KS-14555								
(P) P35A	6 (aa)	S	W	W	24Ga	KS-14555	KS-14554 Conn KS-14554L2 Conn	
(P) W35A	12	S	W	W	27Ga	KS-14555L2		
KS-14596								
(P) W16B	4	S	T	T	22Ga	KS-14596	Soldered Con- nections	
KS-14671								
(P) P21A	12	S	T	W	22Ga	KS-14671	KS-14672L2 Conn	

KS PLUGS

Code	Conductor						Plug End	Other End
	Length (Feet)	Jkt Type	In- Mat.	In- sul.	Type			
KS-14672								
(P) P21A	12	S	T	W	22Ga	KS-14672L2	KS-14671L2 Conn	
KS-14769								
(P) M8E	6	S	T	W	16Ga	KS-14769	307A Plug	
(P) M12C	5	S	T	T	22Ga	KS-14769	Spade Tips	
M12F	8	S	T	T	22Ga	KS-14769	Spade Tips	
KS-16288								
(P) P3AG	2, 5, 10, 20	S	W	W	760A Ca	KS-16288L2	KS-16288L2 Plug	
KS-16370								
D75A-61	8	S	W	W	27Ga	KS-16370L17	6-KS-16671L1 Plugs	
(P) D75B-61	8	S	W	W	27Ga	KS-16370L17	6-KS-16671L1 Plugs	
(P) P3AW	12	S	T	W	22Ga	KS-16370L2	General Radio 274MB Plug	
(P) P5K	6 in., 12	S	T	W	27Ga	KS-16370L2	KS-14460L2 Plug	
(P) P9J	8	S	T	W	24Ga	KS-16370L28	KS-14460L3 Plug	
(P) P9K	8	S	T	W	24Ga	KS-16370L2	KS-14460L3 Plug	
(P) P11B	8	S	W	W	22Ga	KS-16370L26	KS-16409L29 Conn	

KS PLUGS

Code	Length (Feet)	Jkt Type	Mat.	Conductor			Plug End	Other End
				In- sul.	Type			
(P) P14C	6 in.	S	W	W	22Ga	KS-16370L42	KS-14460L3 Plug	
(P) P18A	12	S	W	W	22Ga	KS-16370L28	KS-16409L31 Conn	
(P) P50C	9	S	W	W	22Ga	KS-16370L48	KS-16370L48 Plug	
(P) P75A	9	S	W	W	22Ga	KS-16370L47	KS-16370L47 Plug	
(P) W16C	10	S	T	W	24Ga	KS-16370L42	Spade Tips	
KS-16409								
(P) M18A	10	S	W	W	27Ga	KS-16409L4	Unfinished End	
(P) P11B	8	S	W	W	22Ga	KS-16409L29	KS-16470L26 Conn	
(P) P18A	12	S	W	W	22Ga	KS-16409L31	KS-16370L28 Conn	
(P) P50A	7	S	W	W		KS-16409L11	KS-16409L11 Conn	
(P) W20J	8	S	W	W	W	KS-16409L7	Free Conduc- tors	
KS-16426								
(P) D16E-51	8	S	W	W	27Ga	KS-16426L2	Spade Tips	
(P) P24A	8	S	W	W	27Ga	KS-16426L5	KS-16426L5 Plug	
KS-16476								
(P) M16B	1-1/4, 1-3/4	S	T	W	24Ga	KS-16476L1	Soldered Con- nections	

KS PLUGS

Code	Conductor					Plug End	Other End
	Length (Feet)	Jkt Type	Jkt Mat.	In- sul.	Type		
(P) M30B	8-1/2	Y	W	W	27Ga	KS-16476L8	KS-16690L1, KS-19087L1 Conn
KS-16671							
(P) D50K	5-1/2	S	W(c)	W	27Ga	KS-16671L1; Spade Tips	KS-16689L1 Plug
(P) D50L	8	S	W(c)	W	27Ga	3-KS-16671L1; 4-Term. Strips	KS-16689L1 Plug
(P) D50P	6	S	W(c)	W	27Ga	KS-16671L1; Term. Strips	KS-16689L1 Plug
D50AE-61	8	S	W	W	27Ga	KS-16671L1; 4-Term. Strips	KS-16689L1 Plug
(P) D56A	8	S	W(c)	W	27Ga	3-KS-16671L1; 4-Term. Strips	KS-16689L5 Plug
D75A-61	8	S	W	W	27Ga	6-KS-16671L1	KS-16370L17 Plug
(P) D75B-61	8	S	W	W	27Ga	6-KS-16671L1	KS-16370L17 Plug
(P) D80B	8	S	W(c)	W	27Ga	5-KS-16671L1; 6-Term. Strips	KS-16689L1 Plug
(P) D80C	8	S	W(c)	W	27Ga	3-KS-16671L1; 4-Term. Strips	2-KS-16689L1 Plugs
(P) D94B	8	S	W(c)	W	27Ga	3-KS-16671L1; 3-Term. Strips	KS-16689L5 Plugs
(P) D100C	8	S	W(c)	W	27Ga	3-KS-16671L1; Spade Tips	2-KS-16689L1 Plugs
D100D	8	S	W(c)	W	27Ga	3-KS-16671L1; 2-Term. Strips; Spade Tips	2-KS-16689L1 Plugs

KS PLUGS

Code	Length (Feet)	Jkt Type	Jkt Mat.	In- sul.	Conductor		Other End
					Type	Plug End	
(P) D100E-51	8	S	W	W	27Ga	3-KS-16671L1; Spade Tips	2-KS-16689L1 Plugs
(P) D100H	8	S	W(c)	W	27Ga	8-KS-16671L1	KS-16689L1 Plug
(P) D120C	8	S	W(c)	W	27Ga	3-KS-16671L1; Spade Tips	3-KS-16689L5 Plugs
(P) D120D	8	S	W(c)	W	27Ga	3-KS-16671L1; 4-Term. Strips; Spade Tips	3-KS-16689L5 Plugs
(P) D120E-61	8	S	W	W	27Ga	3-KS-16671L1; 4-Term. Strips; Spade Tips	3-KS-16689L11 Plugs
(P) D120F-3	8	S	W	W	27Ga	3-KS-16671L1; Spade Tips	3-KS-16689L5 Plugs
(P) D120G	8	S	W(c)	W	27Ga	3-KS-16671L1; Spade Tips	3-KS-16689L5 Plugs
(P) D120H	8	S	W(c)	W	27Ga	5-KS-16671L1; Spade Tips	3-KS-16689L1 Plugs
(P) D150B	8	S	W(c)	W	27Ga	7-KS-16671L1; Spade Tips	3-KS-16689L1 Plugs
(P) D150C	8	S	W(c)	W	27Ga	7-KS-16671L1; Spade Tips	3-KS-16689L1 Plugs
(P) D150D	8	S	W(c)	W	27Ga	5-KS-16671L1; Spade Tips	3-KS-16689L1 Plugs
(P) D150E	8	S	W(c)	W	27Ga	7-KS-16671L1; Spade Tips	3-KS-16689L1 Plugs
(P) D150G	8	S	W(c)	W	27Ga	8-KS-16671L1	3-KS-16689L1 Plugs
(P) D150H	8	S	W(c)	W	27Ga	8-KS-16671L1	3-KS-16689L1 Plugs
(P) D150J	8	S	W(c)	W	27Ga	8-KS-16671L1	3-KS-16689L1 Plugs

KS PLUGS

Code	Length (Feet)	Type	Jkt Mat.	In- sul.	Conductor		Other End
					Type	Plug End	
(P) D150K-61	8	S	W	W	27Ga	5-KS-16671L1; Spade Tips	3-KS-16689L1 Plugs
(P) D150L	8	S	W(c)	W	27Ga	8-KS-16671L1	3-KS-16689L1 Plugs
(P) D150M	8	S	W(c)	W	27Ga	3-KS-16671L1	3-KS-16689L1 Plugs
(P) D150N	8	S	W(c)	W	27Ga	7-KS-16671L1	3-KS-16689L1 Plugs
(P) D150R	8	S	W(c)	W	27Ga	3-KS-16671L1	3-KS-16689L3 Plugs
(P) D200D	8	S	W(c)	W	27Ga	3-KS-16671L1; 2-Term. Strips; Spade Tips	4-KS-16689L1 Plugs
(P) D200E	8	S	W(c)	W	27Ga	3-KS-16671L1; Spade Tips	4-KS-16689L1 Plugs
(P) D200F	8	S	W(c)	W	27Ga	5-KS-16671L1; Spade Tips	5-KS-16689L1 Plugs
(P) D200G	8	S	W(c)	W	27Ga	13-KS-16671L1	4-KS-16689L1 Plugs
(P) D200H	8	S	W(c)	W	27Ga	5-KS-16671L1; 5-Term. Strips	5-KS-16689L5 Plugs
(P) D200M-61	8	S	W	W	27Ga	5-KS-16671L1	5-KS-16689L5 Plugs
(P) D200N-61	8	S	W	W	27Ga	5-KS-16671L1	5-KS-16689L5 Plugs
(P) D200P	8	S	W(c)	W	27Ga	8-KS-16671L1	4-KS-16689L1 Plugs
(P) D200R	8	S	W(c)	W	27Ga	13-KS-16671L1	4-KS-16689L1 Plugs
(P) D250A	8	S	W(c)	W	27Ga	14-KS-16671L1	5-KS-16689L1 Plugs

KS PLUGS

Code	Length (Feet)	Type	Jkt Mat.	Conductor			Plug End	Other End
				In- sul.	Type			
(P) D250B	8	S	W(c)	W	27Ga	14-KS-16671L1	5-KS-16689L1 Plugs	
(P) D250C	8	S	W(c)	W	27Ga	14-KS-16671L1	5-KS-16689L1 Plugs	
(P) D250D	8	S	W(c)	W	27Ga	14-KS-16671L1	5-KS-16689L1 Plugs	
(P) D250G	8	S	W(c)	W	27Ga	8-KS-16671L1 1-KS-16689L1	5-KS-16689L3 Plugs	
(P) D250H	8	S	W(c)	W	27Ga	13-KS-16671L1	5-KS-16689L3 Plugs	
(P) D300B	8	S	W(c)	W	27Ga	3-KS-16671L1; 4-Term. Strips	6-KS-16689L1 Plugs	
D300C	8	S	W(c)	W	27Ga	6-KS-16671L1	6-KS-16689L1 Plugs	
KS-16672								
(P) D100J	5-1/2, 9, 13, 25	S	W(c)	W	27Ga	2-KS-16672L3	2-KS-16689L1 Plugs	
KS-16689								
D10T	5-1/2	S	W(c)	W	27Ga	KS-16689L1	KS-16690L3 Conn	
(P) D16G-3	5-1/2, 9, 13, 25	S	W	W	27Ga	KS-16689L1	Spade Tips	
(P) D20H	5-1/2, 9, 13, 25	S	W(c)	W	27Ga	KS-16689L1	Terminal Strips	
(P) D20K	5-1/2, 9, 13, 25	S	W(c)	W	27Ga	KS-16689L1	Spade Tips	
D20L	5-1/2	S	W(c)	W	27Ga	KS-16689L1	KS-16690L3 Conn	
D24D	5-1/2	S	W(c)	W	27Ga	KS-16689L1	2-Term. Strips; Spade Tips	

KS PLUGS

Code	Length (Feet)	Type	Conductor				Plug End	Other End
			Jkt Mat.	In- sul.	Type			
(P) D24E	5-1/2, 9, 13, 25	S	W(c)	W	27Ga	KS-16689L1	Spade Tips	
(P) D25D-61	5-1/2, 9	S	W	W	27Ga	KS-16689L1	KS-19087L2 Conn	
(P) D26D	9	S	W(c)	W	27Ga	KS-16689L5	Term. Strips; Spade Tips	
(P) D30D	5-1/2, 9, 13, 25	S	W(c)	W	27Ga	KS-16689L5	5-Term. Strips; Spade Tips	
D34B	5-1/2	S	W(c)	W	27Ga	KS-16689L5	2-Term. Strips; Spade Tips	
(P) D42A	5-1/2, 9, 13, 25	S	W(c)	W	27Ga	KS-16689L1	2-Term. Strips; Spade Tips	
(P) D50C	5-1/2, 9, 13, 25	S	W(c)	W	27Ga	KS-16689L1	2-Term. Strips; Spade Tips	
(P) D50D	5-1/2, 9, 13, 25	S	W(c)	W	27Ga	KS-16689L1	2-Term. Strips; Spade Tips	
D50F-51	3	S	W	W	27Ga	KS-16689L1	Spade Tips	
(P) D50G-61	8	S	W	W	27Ga	2-KS-16689L1	KS-16785L8 Plug	
(P) D50J-61	5-1/2, 9, 13, 25	S	W	W	27Ga	KS-16689L1	2-Term. Spade Tips	
(P) D50K	5-1/2	S	W(c)	W	27Ga	KS-16689L1	KS-16671L1 Plug; Spade Tips	

KS PLUGS

Code	Length (Feet)	Type	Jkt Mat.	In- sul.	Conductor		Plug End	Other End
					Type			
(P) D50L	8	S	W(c)	W	27Ga	KS-16689L1	3-KS-16671L1 Plugs; 4-Term. Strips	
(P) D50N	5-1/2, 9, 13, 25	S	W(c)	W	27Ga	KS-16689L1	6-Term. Strips; Spade Tips	
(P) D50P	6	S	W(c)	W	27Ga	KS-16689L1	KS-16671L1 Plug; Term. Strip	
(P) D50R-61	5-1/2	S	W	W	27Ga	KS-16689L1	Term. Strip; Spade Tips	
(P) D50S	5-1/2, 9, 13, 25	S	W(c)	W	27Ga	KS-16689L1	7-Term. Strips; Spade Tips	
(P) D50T	5-1/2, 9, 13, 25	S	W(c)	W	27Ga	KS-16689L1	5-Term. Strips; Spade Tips	
(P) D50W	5-1/2, 9, 13, 25	S	W(c)	W	27Ga	KS-16689L1	6-Plugs; Spade Tips	
(P) D50AB	5-1/2, 9, 13, 25	S	W(c)	W	27Ga	KS-16689L1	KS-16690L3 Conn	
(P) D50AD	5-1/2, 9, 13, 25	S	W(c)	W	27Ga	KS-16689L1	KS-20552L1 Conn	
D50AE-60	8	S	W	W	27Ga	KS-16689L1	3-KS-16671L1 Plugs; 3-Term. Strips	
(P) D50AF	10	Y	W(c)	W	27Ga	KS-16689L1	KS-16690L1 Conn	
(P) D55A	8	S	W(c)	W	27Ga	KS-16689L1	Terminal Plugs	

KS PLUGS

Code	Length (Feet)	Conductor					Plug End	Other End
		Type	Jkt Mat.	In- sul.	Type			
(P) D56A	8	S	W(c)	W	27Ga	2-KS-16689L5	3-KS-16671L1 Plugs; 4- Term. Strips	
(P) D80B	8	S	W(c)	W	27Ga	2-KS-16689L1	5-KS-16671L1 Plugs; 6- Term. Strips	
(P) D80C	8	S	W(c)	W	27Ga	2-KS-16689L1	3-KS-16671L1 Plugs; Spade Tips	
(P) D94B	8	S	W(c)	W	27Ga	3-KS-16689L5	3-KS-16671L1 Plugs; 3- Term. Strips	
(P) D100C	8	S	W(c)	W	27Ga	2-KS-16689L1	3-KS-16671L1 Plugs; Spade Tips	
D100D	8	S	W(c)	W	27Ga	2-KS-16689L1	3-KS-16671L1 Plugs; 2- Term. Strips; Spade Tips	
(P) D100E-51	8	S	W	W	27Ga	2-KS-16689L1	3-KS-16671L1 Plugs; Spade Tips	
(P) D100F	8	S	W(c)	W	27Ga	2-KS-16690L1	2-KS-16690L3 Conn	
(P) D100G-61	8	S	W	W	27Ga	2-KS-16689L2	2-KS-16689L1 Plugs	
(P) D100H	8	S	W(c)	W	27Ga	2-KS-16689L1	8-KS-16671L1 Plugs	
(P) D100J	5-1/2, 9, 13, 25	S	W(c)	W	27Ga	2-KS-16689L1	2-KS-16672L3 Conn	

KS PLUGS

Code	Length (Feet)	Type	Conductor				Plug End	Other End
			Jkt Mat.	In- sul.	Type			
(P) D120C	8	S	W(c)	W	27Ga	3-KS-16689L5	3-KS-16671L1 Plugs; Spade Tips	
(P) D120D	8	S	W(c)	W	27Ga	3-KS-16689L5	3-KS-16671L1 Plugs; 4- Term.Strips; Spade Tips	
(P) D120F-3	8	S	W	W	27Ga	3-KS-16689L5	2-KS-16671L1 Plugs; Spade Tips	
(P) D120G	8	S	W(c)	W	27Ga	3-KS-16689L5	3-KS-16671L1 Plugs; Spade Tips	
(P) D120H	8	S	W(c)	W	27Ga	3-KS-16689L1	5-KS-16671L1 Plugs; Spade Tips	
(P) D120J	8	S	W(c)	W	27Ga	3-KS-16689L5	Terminal Plugs; Spade Tips	
D120K	8	S	W(c)	W	27Ga	3-KS-16689L5	508-Type Plugs	
(P) D150B	8	S	W(c)	W	27Ga	3-KS-16689L1	7-KS-16671L1 Plugs; Spade Tips	
(P) D150C	8	S	W(c)	W	27Ga	3-KS-16689L1	7-KS-16671L1 Plugs; Spade Tips	
(P) D150D	8	S	W(c)	W	27Ga	3-KS-16689L1	5-KS-16671L1 Plugs; Spade Tips	
(P) D150E	8	S	W(c)	W	27Ga	3-KS-16689L1	7-KS-16671L1 Plugs; Spade Tips	
(P) D150G	8	S	W(c)	W	27Ga	3-KS-16689L1	8-KS-16671L1 Plugs	

KS PLUGS

Code	Conductor						Other End
	Length (Feet)	Jkt Type	Mat.	In- sul.	Type	Plug End	
(P) D150H	8	S	W(c)	W	27Ga	3-KS-16689L1	8-KS-16671L1 Plugs
(P) D150J	8	S	W(c)	W	27Ga	3-KS-16689L1	8-KS-16671L1 Plugs
(P) D150K-61	8	S	W	W	27Ga	3-KS-16689L1	5-KS-16671L1 Plugs; Spade Tips
(P) D150L	8	S	W(c)	W	27Ga	3-KS-16689L1	8-KS-16671L1 Plugs
(P) D150M	8	S	W(c)	W	27Ga	3-KS-16689L1	3-KS-16671L1 Plugs
(P) D150N	8	S	W(c)	W	27Ga	3-KS-16689L1	7-KS-16671L1 Plugs
(P) D150P	8	S	W(c)	W	27Ga	3-KS-16689L1	7-Plugs; Spade Tips
(P) D150R	8	S	W(c)	W	27Ga	3-KS-16689L3	3-KS-16671L1 Plugs
D150S	8	S	W(c)	W	27Ga	3-KS-16689L1	Terminal Plugs; Tips
(P) D150T	8	S	W(c)	W	27Ga	3-KS-16689L1	Terminal Plugs; Spade Tips
D150U	8	S	W(c)	W	27Ga	3-KS-16689L1	508-Type Plugs
(P) D200D	8	S	W(c)	W	27Ga	4-KS-16689L1	3-KS-16671L1 Plugs; Spade Tips
(P) D200E	8	S	W(c)	W	27Ga	4-KS-16689L1	3-KS-16671L1 Plugs; Spade Tips
(P) D200F	8	S	W(c)	W	27Ga	5-KS-16689L5	5-KS-16671L1 Plugs; Spade Tips

KS PLUGS

Code	Length (Feet)	Type	Jkt Mat.	Conductor		Plug End	Other End
				In- sul.	Type		
(P) D200G	8	S	W(c)	W	27Ga	4-KS-16689L1	13-KS-16671L1 Plugs
(P) D200H	8	S	W(c)	W	27Ga	5-KS-16689L5	5-KS-16671L1 Plugs; 6- Term. Strips
(P) D200J	8	S	W(c)	W	27Ga	4-KS-16689L1	4-KS-16690L3 Plugs; Spade Tips
(P) D200K	8	S	W(c)	W	27Ga	4-KS-16689L1	4-KS-16690L3 Conn; Term. Strips
(P) D200L	8	S	W(C)	W	27Ga	4-KS-16689L1	4-KS-16690L3 Conn
(P) D200M-61	8	S	W	W	27Ga	5-KS-16689L5	5-KS-16671L1 Plugs
(P) D200N-61	8	S	W	W	27Ga	5-KS-16689L5	5-KS-16671L1 Plugs
(P) D200P	8	S	W(c)	W	27Ga	4-KS-16689L5	8-KS-16671L1 Plugs
(P) D200R	8	S	W(c)	W	27Ga	4-KS-16689L1	13KS-16671L1 Plugs
(P) D200S	8	S	W(c)	W	27Ga	5-KS-16689L5	508-Type Plugs
D200T	8	S	W(c)	W	27Ga	4-KS-16689L1	508-Type Plugs
D200U	8	S	W(C)	W	27Ga	4-KS-16689L1	508-Type Plugs
(P) D250A	8	S	W(c)	W	27Ga	5-KS-16689L1	14-KS-16671L1 Plugs
(P) D250B	8	S	W(c)	W	27Ga	5-KS-16689L1	14-KS-16671L1 Plugs
(P) D250C	8	S	W(c)	W	27Ga	5-KS-16689L1	14-KS-16671L1 Plugs

KS PLUGS

Code	Length (Feet)	Type	Jkt Mat.	Conductor			Plug End	Other End
				In- sul.	Type			
(P) D250D	8	S	W(c)	W	27Ga	5-KS-16689L1	14-KS-16671L1 Plugs	
(P) D250E	8	S	W(c)	W	27Ga	5-KS-16689L1	5-KS-16690L3 Conn	
(P) D250F	8	S	W(c)	W	27Ga	5-KS-16689L3	Plugs; Spade Tips	
(P) D250G	8	S	W(c)	W	27Ga	5-KS-16689L3	8-KS-16671L1 Plugs; 1-KS-16689L1 Plug	
(P) D250H	8	S	W(c)	W	27Ga	5-KS-16689L3	13-KS-16671L1 Plug	
D250J	8	S	W(c)	W	27Ga	5-KS-16689L5	508-Type Plugs; Spade Tips	
D250K	8	S	W(C)	W	27Ga	5-KS-16689L1	508-Type Plugs	
(P) D300B	8	S	W(c)	W	27Ga	6-KS-16689L1	3-KS-16671L1 Plugs; 4- Term. Strips	
D300C	8	S	W(c)	W	27Ga	6-KS-16689L1	6-KS-16671L1 Plugs	
(P) M12M-61	6	S	W	W	27Ga	KS-16689L1	KS-19087L5 Conn; Spade Tips	
(P) M14C	1 Ft. 11 in., 5-1/2	S	W	W	27Ga	KS-16689L5	Spade Tips	
(P) M25E	7	S	W	W	27Ga	KS-16689L1	KS-19088L2 Conn	
(P) M26H	3	S	W	W	27Ga	KS-16689L1	KS-16690L3 Conn	

KS PLUGS

Code	Length (Feet)	Type	Jkt Mat.	Conductor			Plug End	Other End
				In- sul.	Type			
(P) M42A	6	S	W	W	27Ga	KS-16689L1; KS-16690L3 Com- mercial Plugs	KS-16690L3 Conn	
(P) M50G	6, 9, 18	S	W	W	27Ga	KS-16689L1	KS-16785L8 Plug	
(P) M50J	3	S	W	W	27Ga	KS-16689L1	KS-16690L3 Conn	
(P) M50K	4	S	W	W	27Ga	KS-16689L1	507A Plug; Spade Tips	
M80A	3	S	W	W	27Ga	KS-16689L1	KS-16690L3 Conn	
(P) P10C	10 in.	S	W	W	27Ga	KS-16689L1	KS-19088L2 Conn	
(P) P86A	5	S	W	W	27Ga	2-KS-16689L1	2-KS-19162L3 Plugs	
(P) W50A	7 in.	Y	W	W	27Ga	KS-16689L2 KS-16690L3	Connecting Block	
KS-16690								
D10S	5-1/2	S	W(c)	W	27Ga	KS-16690L3	Spade Tips	
D10T	5-1/2	S	W(c)	W	27Ga	KS-16690L3	KS-16689L1 Plug	
D20M	5-1/2	S	W(c)	W	27Ga	KS-16690L3	Spade Tips	
D35B-51	3	S	W	W	27Ga	KS-16690L3	Spade Tips	
(P) D35C-61	5-1/2, 9	S	W	W	27Ga	KS-16690L1	KS-19087L2 Conn	
(P) D50H-3	5-1/2	S	W	W	27Ga	KS-16690L3	Term. Strips; Spade Tips	
(P) D50AA-3	13-1/2 in.	S	W	W	27Ga	KS-16690L3	Spade Tips	

KS PLUGS

Code	Conductor						Plug End	Other End
	Length (Feet)	Type	Jkt Mat.	In- sul.	Type			
(P) D50AB	5-1/2, 9, 13, 25	S	W(c)	W	27Ga	KS-16690L3	KS-16689L1 Plug	
(P) D50AF	10	Y	W(c)	W	27Ga	KS-16690L1	KS-16689L1 Plug	
(P) D100F	8	S	W(c)	W	27Ga	2-KS-16690L3	2-KS-16689L1 Plugs	
(P) D200J	8	S	W(c)	W	27Ga	4-KS-16690L3	4-KS-16689L1 Plugs	
(P) D200K	8	S	W(c)	W	27Ga	4-KS-16690L3; Term. Strips	4-KS-16689L1 Plugs	
(P) D200L	8	S	W(c)	W	27Ga	4-KS-16690L3	4-KS-16689L1 Plugs	
(P) D250E	8	S	W(c)	W	27Ga	5-KS-16690L3	14-KS-16689L1 Plugs	
(P) M14E	5-1/2	S	W	W	27Ga	KS-16690L3	Spade Tips	
(P) M26H	3	S	W	W	27Ga	KS-16690L3	KS-16689L1 Plug	
(P) M30B	8-1/2	Y	W	W	27Ga	KS-16690L1	KS-19087L1 Conn KS-16476L8 Plug	
(P) M42A	6	S	W	W	27Ga	KS-16690L3	KS-16689L1 Plug; KS-16690L3 Conn; Com Plugs	
(P) M42B	8-1/2	S	W	W	27Ga	KS-16690L3	6-KS-19087L1 Conn	
(P) M50E	6-1/2	S	W	W	27Ga	KS-16690L3	507A Plug; Spade Tips	
(P) M50F	6, 12, 18	S	W	W	27Ga	KS-16690L3	KS-16785L8 Plug	

KS PLUGS

Code	Length (Feet)	Type	Jkt Mat.	Conductor		Plug End	Other End
				In- sul.	Type		
(P) M50J	3	S	W	W	27Ga	KS-16690L3	KS-16689L1 Plug
(P) M50L	1-1/2	S	W	W	27Ga	KS-16690L3	6-Term. Strips
M80A	3	S	W	W	27Ga	KS-16690L3	KS-16689L1 Plug
(P) W50A	7 in.	Y	W	W	27Ga	KS-16690L3 KS-16689L2	Connecting Block
KS-16785							
(P) D12E	1-1/4	S	W	W	27Ga	KS-16785L9	Spade Tips
D14N-61	3	S	W	W	27Ga	KS-16785L5	Spade Tips
(P) D50G-61	8	S	W	W	27Ga	KS-16785L8	2-KS-16689L1 Plug
(P) D120E-61	8	S	W	W	27Ga	KS-16785L11	KS-16671L1 Plug; 4-Term. Strips
(P) M14F	10	S	W	W	27Ga	KS-16785L8	Spade Tips
M18B	10	S	W	W	27Ga	KS-16785L8	Spade Tips
(P) M24C	1-1/2, 3-1/3, 6-1/2	S	W	W	27Ga	KS-16785L6	KS-16785L6 Plug
(P) M24F	4	S	W	W	27Ga	KS-16785L6	2-507A Plugs
(P) M24G	1, 5	S	W	W	27Ga	KS-16785L6	2-507A Plugs
(P) M24H	1, 4, 10	S	W	W	27Ga	KS-16785L13	5-508-Type Plugs

KS PLUGS

Code	Length (Feet)	Type	Jkt Mat.	Conductor			Plug End	Other End
				In- sul.	Type			
(P) M24J	1, 5	S	W	W	27Ga	KS-16785L6	2-507A Plugs	
(P) M24K	4	S	W	W	27Ga	KS-16785L13	6-508-Type Plugs	
(P) M36A-61	2, 3-1/3	S	W	W	27Ga	KS-16785L13	Free Conduc- tors	
(P) M36B	7	S	W	W	27Ga	KS-16785L13	2-507-Type Plugs, 2-508-Type Plugs	
(P) M36C	4	S	W	W	26Ga	KS-16785L7	507A Plugs	
(P) M36D	4	S	W	W	26Ga	KS-16785L7	507A Plugs	
(P) M36E	4, 10, 50	S	W	W	26Ga	KS-16785L13	KS-16785L13 Plug	
(P) M36F	4, 10	S	W	W	26Ga	KS-16785L8 and L13	KS-16785L13 Plug	
(P) M50F	6, 8, 12	S	W	W	27Ga	KS-16785L8	KS-16690L3 Conn	
(P) M50G	6, 9, 18	S	W	W	27Ga	KS-16785L8	KS-16689L1 Plug	
(P) M50H	3, 6, 9, 12	S	W	W	27Ga	KS-16785L8	KS-16785L8 Plug	
KS-19087								
(P) D25C-61	5-1/2, 9	S	W	W	27Ga	KS-19087L2	Spade Tips	
(P) D25D-61	5-1/2, 9	S	W	W	27Ga	KS-19087L2	KS-16689L1 Plug	

KS PLUGS

Code	Length (Feet)	Type	Jkt Mat.	In- sul.	Conductor		Other End
					Type	Plug End	
(P) D35C-61	5-1/2, 9	S	W	W	27Ga	KS-19087L2	KS-16690L1 Plug
(P) M2FA	8	S	W	W		KS-19087L2	Butt End
(P) M7P	6-1/2, 9	S	W	W		KS-19087L4	KS-19088L4 Conn
(P) M12M-61	6	S	W	W	27Ga	KS-19087L5; Spade Tips	KS-16689L1 Plug
(P) M12P	11	S	W	W	27Ga	KS-19087L23	Bare Conduc- tors
M14B	9 in.	S	W	W	27Ga	KS-19087L2	Term. Strips; Spade Tips
(P) M15D-61	5	S	W	W	27Ga	KS-19087L1	KS-19088L1 Conn
(P) M15E-61	5	S	W	W	27Ga	KS-19087L1	KS-19088L1 Conn
(P) M15F	5, 15	S	W	W	27Ga	KS-19087L1	KS-19088L1 Conn
(P) M25A-61	5, 9, 25, 50	S	W	W	27Ga	KS-19087L2	KS-19088L2 Conn
(P) M25F	3	S	W	W	27Ga	KS-19087L2	Spade Tips
(P) M26A	5 in.	S	W	W	27Ga	KS-19087L2	Cannon K03- 19-20PN-A106 Connector
(P) M26D	5 in.	S	W	W	27Ga	KS-19087L2	Cannon K03- 21-30PN-A106 Connector

KS PLUGS

Code	Conductor						Other End
	Length (Feet)	Jkt Type	Mat.	In- sul.	Type	Plug End	
(P) M26F	5 in.	S	W	W	27Ga	KS-1908712	Cannon K03- 19-20PN-A106 Connector
(P) M30B	8-1/2	Y	W	W	27Ga	KS-19087L1	KS-16690L1 Conn KS-16476L8 Conn
(P) M42B	8-1/2	S	W	W	27Ga	6-KS-19087L1	KS-16690L3 Conn
(P) M45A	3-1/3	S	W	W	27Ga	KS-19087L2 and 16	507A Plug; Spade Tips
(P) P9E	3	S	W	W	27Ga	KS-19087L5	KS-19088L5 Conn
(P) P10B	6	S	W	W	27Ga	KS-19087L18	KS-19088L15 Conn
(P) P12C	5	S	W	W	27Ga	KS-19087L2	KS-19402L1 Plug
KS-19088							
(P) D10N-61	9	S	W	W	27Ga	KS-19088L1	Spade Tips
(P) M7P	6-1/2, 9	S	W	W	27Ga	KS-19088L4	KS-19087L4 Conn
(P) M14D	5-1/2	S	W	W	27Ga	KS-19088L1	Spade Tips
(P) M15D-61	5	S	W	W	27Ga	KS-19088L1	KS-19087L1 Conn
(P) M15E-61	5	S	W	W	27Ga	KS-19088L1	KS-19087L1 Conn

KS PLUGS

Code	Length (Feet)	Type	Jkt Mat.	Conductor		Plug End	Other End
				In- sul.	Type		
(P) M15F	5, 15	S	W	W	27Ga	KS-19088L1	KS-19087L1 Conn
(P) M15G	8	S	W	W	27Ga	KS-19088L1	Spade Tips
(P) M25A-61	5, 9, 25, 50	S	W	W	27Ga	KS-19088L2	KS-19087L2 Conn
(P) M25B	6 ft., 11 in., 4, 10	S	W	W	27Ga	KS-19088L2	KS-19088L2 Conn
(P) M25C	11 in.	S	W	W	27Ga	KS-19088L2	Printed Ckt Card
(P) M25D	7	S	W	W	27Ga	KS-19088L2	Spade Tips
(P) M25E	7	S	W	W	27Ga	KS-19088L2	KS-16689L1 Plug
(P) M26B	5 in.	S	W	W	27Ga	KS-19088L2	Cannon K01- 19-20SN A106 Connector
(P) M26C	5 in., 5	S	W	W	27Ga	KS-19088L2	Cannon K03- 19-20SN A106 Connector
(P) M26E	5 in.	S	W	W	27Ga	KS-19088L2	Cannon K01- 21-30SN A106 Connector
(P) P2DH	12	S	W	W	22Ga	KS-19088L5	P-18E407 Plug
(P) P3BA	12	S	W	W	22Ga	KS-19088L5	Twin Banana Plugs
(P) P4AN	6 in., 12	S	T	W	27Ga	KS-19088L5	KS-14460L2 Plug
(P) P4AP	6 in.	S	W	W	27Ga	KS-19088L5	KS-14460L2 Plug

KS PLUGS

Code	Conductor						Other End
	Length (Feet)	Jkt Type	Jkt Mat.	In- sul.	Type	Plug End	
(P) P9D	9	S	T	W	27Ga	KS-19088L5	Spade Tips
(P) P9E	3	S	T	W	27Ga	KS-19088L5	KS-19087L5 Conn
(P) P9G	9 in.	S	W	W	27Ga	KS-19088L4	KS-19088L4 Conn
(P) P9H	8	S	T	W	24Ga	KS-19088L5	KS-14460L3 Plug
(P) P10B	6	S	W	W	27Ga	KS-19088L15	KS-19087L18 Conn
(P) P10C	10 in.	S	W	W	27Ga	KS-19088L2	KS-16689L1 Plug
(P) W9A	10	S	T	W	27Ga	KS-19088L1	Spade Tips
(P) W9B	5	S	T	W	24Ga	KS-19088L5	Test Points, Clip
(P) W25A	9 in., 1-2/3, 6, 6, 9	S	W	W	27Ga	KS-19088L2	Spade Tips
(P) W25B	6	S	W	W	27Ga	KS-19088L2	Printed Ckt Board
(P) W25C	4-1/2	S	T	W	24Ga	KS-19088L2	Test Points
KS-19162							
(P) M72A	10	S	W	W	27Ga	KS-19162L8	Butt End
(P) P50B	10, 25	S	W	W	27Ga	KS-19162L3	KS-19163L25 Conn
(P) P86A	5	S	W	W	27Ga	2-KS-19162L3	2-KS-16689L1 Plugs
(P) P100A	30	S	W	W	27Ga	KS-19162L3	KS-19162L4 Plug
(P) P100B	50	S	W	W	27Ga	KS-19162L3	KS-19163L3 Conn

KS PLUGS

Code	Length (Feet)	Type	Jkt Mat.	Conductor		Plug End	Other End
				In- sul.	Type		
(P) W50B	19	S	T	W	22Ga	KS-19162L3	KS-16336L2 Clips
KS-19163							
(P) P25A	4, 8, 12	S	W	W	27Ga	KS-19163L9	KS-19163L9 Conn
(P) P50B	10, 25	S	W	W	27Ga	KS-19163L25	KS-19162L3 Plug
(P) P100B	50	S	W	W	27Ga	KS-19163L3	KS-19163L3 Plug
KS-19402							
(P) M24E	6	S	W	W	Coax	KS-19402L2	KS-19402L1 Plug
(P) P12C	5	S	W	W	27Ga	KS-19402L1	KS-19087L2 Plug
KS-19471							
(P) P14B	4-1/2	S	W	W	22Ga	KS-19471	KS-19471 Plug
KS-19531							
(P) M2ES	5-1/2	S	W	W	18Ga	KS-19531L1 and L2	Hubbell 7484 Conn
(P) M2FD	8	S	T	W		2-KS-19531L1	Pin Tips
(P) P1T	2	S	W	W	20Ga	KS-19531L1(am)	KS-19531L1 Plug
(P) P2DR	12	S	W	W	18Ga	KS-19531L1 and L2	KS-19531L1 and L2 Plugs

KS PLUGS

Code	Length (Feet)	Type	Jkt Mat.	Conductor			Plug End	Other End
				In- sul.	Type			
(P) P2DS	12	S	W	W	20Ga	KS-19531L1 and L2	310 Plug	
(P) W1BB	2	S	W	W	20Ga	KS-19531L2	Test Clip	
(P) W1BC	4 in.	S	W	W	20Ga	KS-19531L2	KS-19531L2 Plug	
(P) W1BD	8	S	W	W	20Ga	KS-19531L2	Special Test Point	
(P) W2FP	8	S	W	W	Coax	KS-19531L1 and L2	Gen. Radio 274NK Plug	
(P) W2GB	6	S	W	W		KS-19531	241-Type Plug	
(P) W3BC	6	S	T	W	20Ga	KS-19531L1 and L2	Bendix PT Conn	
KS-20269								
(P) P1W	2	S	T	W		KS-20269L2	360B Tool	
KS-20552								
(P) D50AD	5-1/2, 9, 13, 25	S	W(c)	W	27Ga	KS-20552L1	KS-16689L1 Plug	
D100J	5-1/2, 9, 13, 25	S	W(c)	W	27Ga	2-KS-20552L1	2-KS-16689, L1 Plugs	



PLUGS (COMMERCIAL)



COMMERCIAL PLUGS

Code	Length (Feet)	Type	Jkt Mat.	In- sul.	Conductor		Other End
					Type	Plug End	
(P) D3BT	5-1/2	S	W	W	27Ga	Cannon MC23E-8-3SN	Spade Tips
(P) D6AC-61	9	S	W	W	27Ga	Cannon MC23E-10-6PN	Spade Tips
(P) D50AF	10	Y	W(c)	W	27Ga	Viking 2VH10/1JN5 Conn	KS-16689L1 Plug KS-16690L1 Plug
(P) H4BM-3	4	R	W	W		Amphenol 91-MC4M	Spade Tips
(P) H5W-3	4	S	T	W		Cannon 035324	Spade Tips
(P) H5Y-3	3-1/2	R	W	W		Amphenol 91-MC4M	Spade Tips
(P) M2CB	6	S	W	W	18Ga	Bryant HUT Cap	Soldered Connections
(P) M2DG	9 in., 2-1/2, 3-1/2, 6-1/2	S	W	W	18Ga	(an)	Spade Tips
(P) M2DS	50	S	W	W	18Ga	Hubbell 7091 Body	Test Clips
(P) M2EG	3-1/2	S	W	W	18Ga	Hubbell 7059 Cap	Test Clips
M2ES	5-1/2	S	W	W	18Ga	Hubbell 7484 Conn	KS-19531L1 and L2 Plugs
(P) M3C	6, 50	S	W	W	14Ga	Hubbell 7308 Body	Hubbell 7055 Cap
(P) M3D	50	S	W	W	14Ga	Hubbell 7308 Body	Battery Lugs
M3AT	2	S	W	W	18Ga	(ap)	Spade Tips

COMMERCIAL PLUGS

Code	Length (Feet)	Type	Jkt Mat.	Conductor			Plug End	Other End
				In- sul.	Type			
M3AU	9 in., 1-1/2, 2, 3-1/2, 5	S	W	W	18Ga	Hubbell 7092 Cap or Hubbell 7084 Body	Spade Tips	
M3AW	2	S	W	W	18Ga	Hubbell 7082 Body (ar)	Spade Tips	
(P) M3AY	2-3/4, 6	S	W	W	18Ga	Hubbell 7082 Body (ar)	Spade Tips	
(P) M4K	1-1/2, 2-1/2	S	W	W	18Ga	Hubbell 7251 Cap	Spade Tips	
(P) M4N	3	S	W	W	16Ga	Hubbell 7351 Body	Soldered Con- nections	
(P) M4Y	3	Y	W	W	18Ga	Hubbell 7241 Cap	2-Hubbell 7091 Body	
M4AB	2-1/2	S	W	W	18Ga	Hubbell 7055 Cap	Spade Tips	
M4AC	2-1/2	S	W	W	18Ga	Hubbell 7251 Cap	Spade Tips	
(P) M4AG	9-1/4 in.	S	W	W	18Ga	Hubbell 7055 Cap	Hubbell 7351 Conn Body	
(P) M5K	2	S	W	W	20Ga	Amphenol 91-MC4M	KS-8586L4 Socket	
(P) M5L	2, 3, 6-1/2	S	W	W	20Ga	Amphenol 91-MC4M	Amphenol 91-MC4M	
M6AA	4	S	W	W	20Ga	Cannon P5-CG-12S	Cannon P5- CG-11S	
(P) M6AB	18	S	W	W	18Ga	(as)	Spade Tips	
(P) M6AG	3-1/2	S	W	W	18Ga	Hubbell 5264 Cap	2-Hubbell 7593 Conn Body	
(P) M7M	5	S	T	W	22Ga	Amphenol AN3106- 16S-1P	Spade Tips	
M9D	6	S	T	T	22Ga	H.B. Jones S-212-CCT	Spade Tips	

COMMERCIAL PLUGS

Code	Conductor						Plug End	Other End
	Length (Feet)	Jkt Type	Jkt Mat.	In- sul.	Type			
(P) M10A	6	S	T	T	22Ga	H.B. Jones S-410-CCT-RST	Spade Tips	
(P) M11D	6	S	T	W	22Ga	Johnson 625	307A Plug	
M11F	5	S	W	W	22Ga	U.S. Components 990-10M2HSSL- DM-30 Conn	U.S. Com- ponents 990- 10M2HSSL- DM-30 Conn	
(P) M12E	6	S	T	W	22Ga	Johnson 625	307A Plug	
(P) M12G	6	S	T	W	22Ga	Johnson 111-625	307A Plug	
(P) M12J	5	S	T	W	22Ga	Amphenol AN- 3106-20-27P	Spade Tips	
(P) M24B	6-1/2	S	T	T	22Ga	Cinch 261-31-24- 512	Cinch 261-31- 24-512 Plug	
(P) M26A	5 in.	S	W	W	27Ga	Cannon K03-19- 20PN-A106	KS-19087L2 Conn	
(P) M26B	5 in.	S	W	W	27Ga	Cannon K01-19- 20SN-A106	KS-19088L2 Conn	
(P) M26C	5 in., 5	S	W	W	27Ga	Cannon K03-19- 20SN-A106	KS-19088L2 Conn	
(P) M26D	5 in.	S	W	W	27Ga	Cannon K03-21- 30PN-A106	KS-19087L2 Conn	
(P) M26E	5 in.	S	W	W	27Ga	Cannon K01-21- 30SN-A106	KS-19088L2 Conn	
(P) M26F	5 in.	S	W	W	27Ga	Cannon K01-19- 20PN-A106	KS-19087L2 Conn	
(P) M42A	6	S	W	W	27Ga	Molex Products PT1375P Plug; 2-PT1375R Recep- tacle; KS-16689L1 Plug; KS-16690L3 Conn	KS-16690L3 Conn	

COMMERCIAL PLUGS

Code	Length (Feet)	Type	Jkt Mat.	Conductor			Plug End	Other End
				In- sul.	Type			
(P) P1M	1	S	W	W	20Ga	Hubbell 716S19	Hubbell 716S19 Plug	
(P) P1N	3	S	W	W	20Ga	Grip-Rite	Grip-Rite Plug	
(P) P2BH	12	S	W	W	18Ga	Hubbell 7547 Cap	Hubbell 7506 Body	
(P) P2BP	3-1/6	S	W	W	Coax	General Radio 274NK	Gen Radio 274NK Plug	
(P) P2CK	12	S	T	W	20Ga	Grip-Rite	KS-14530 Conn	
(P) P2CL	3, 6, 12	S	T	W	20Ga	Grip-Rite	310 Plug	
(P) P2CM	10	S	W	W	18Ga	Hubbell 7464 Conn	310 Plug	
(P) P2CN	6	S	W	W	18Ga	Hubbell 7464 Conn	Hubbell 7479 Cap	
(P) P2CY	10 in.	S	W	W	18Ga	H.B. Jones P202-CCT	407A Plug	
(P) P2DB	23	S	W	W	18Ga	H.B. Jones P-2402-CCE	H.B. Jones S-202-CCT- THR Socket	
(P) P2DC	10 in.	S	W	W	18Ga	H.B. Jones P-202-CCT	2-417A Plugs	
(P) P2DD	10 in.	S	W	W	18Ga	H.B. Jones P-202-CCT	2-413-Type Plugs	
(P) P3H	5, 6, 7, 8, 8-1/2, 9-1/2, 10	S	T	W		AE Co. D-5773	310 Plug	
(P) P3AF	30	S	W	W		Hubbell 7484 Body	Hubbell 7484 Body	
(P) P3AR	10	S	W	W	18Ga	Hubbell 7555G Conn	Hubbell 5264 Cap	
(P) P3BB	6	S	W	W	18Ga	Hubbell 7484 Conn	Hubbell 7485 Cap	
(P) P3BG	10	S	W	W	18Ga	Hubbell 6600 Conn	Hubbell 5264 Cap	

COMMERCIAL PLUGS

Code	Length (Feet)	Type	Jkt Mat.	Conductor			Plug End	Other End
				In- sul.	Type			
(P) P4AK	13 (al)	S	W	W	20Ga	Amphenol-Borg 91-858	KS-14461L2 Plug	
(P) P4AL	13 (al)	S	W	W	20Ga	Amphenol-Borg 91-858	KS-14461L2 Plug	
(P) P4AM	13 (al)	S	W	W	20Ga	Amphenol-Borg 91-858	KS-14461L2 Plug	
(P) P5C	10	S	W	W	20Ga	Amphenol 08M	Amphenol 08M	
(P) P5E	10	S	W	W	22Ga Coax	Amphenol AN3106A-14S-5S	Amphenol AN3106A-14S- 5S	
(P) P11C	6	S	W	W	27Ga	Amphenol 86-CP11	Amphenol 78S11 Socket	
(P) P20M	15	S	W	W	27Ga	Cannon K01-19- 20PN	KS-8586L51 Socket	
(P) P24B	2	S	W	W	27Ga	Cannon K03-21- 30PN	Cannon K03- 21-30PN	
(P) P40C	1-1/6	Y	W	W	27Ga	Cannon K03-19- 20SN	400A Plug	
W1AC	6	S	W	W	18Ga	Hubbell 9970 Cap	310 Plug-R	
(P) W1AW	1-2/3	S	W	W	20Ga	Pomona P24 Plug	8-Mueller Test Clips	
(P) W2DW	8, 10	S	W	W	Coax	General Radio 274NK	Phone Plug	
(P) W2EB	2-5/6	S	W	W	Coax	Hubbell Inter- lock	347B Plug	
(P) W2EP	1	S	W	W	18Ga	H.B. Jones P-202-CCT	Test Clips	
(P) W2EU	17	S	T	W		H.B. Jones S202-CCT-THR	310 Plug	
(P) W2EW	1	S	T	W		H.B. Jones P202-CCT	KS-6780 Clips	
(P) W2GD	10 in.	S	W	W	18Ga	H.B. Jones P202-CCT	463A Plug	

COMMERCIAL PLUGS

Code	Length (Feet)	Type	Jkt Mat.	In- sul.	Conductor		Other End
					Type	Plug End	
W2GM	10 in.	S	W	W	18Ga	H.B. Jones P-202-CCT	463A Plug
W3AF	10	S	T	W	Coax	Amphenol AN3106- 14S-5S	Special Ter- minals
(P) W3AT	4	S	T	W		Gen Radio 274NK; Test Clip	310 Plug
(P) W3AU	4,9	S	T	W		Gen Radio 274NK; Test Clip	Test Clips
(P) W3BC	6	S	T	W	20Ga	Bendix PT Con- nector	KS-19531L1 and L2 Plugs
(P) W3BD	8	S	T	W	20Ga	Bendix PT Con- nector	360-Type and 624 Tools
(P) W4AT	5	S	T	W		Hubbell 7485 Cap	Tubular Tips
(P) W5B	11	S	W	W	18Ga	Johnson 645	330-Type Plug
(P) W8F	6	S	T	W	22Ga	H.B. Jones	H.B. Jones
					27Ga	P408-CCE	S-408-CCT Socket
(P) W48A	10	S	W	W	27Ga	U.S. Components Conn SM1- 26F1HRSL-DM-30 SM1-26M1HRSL- DM30	Test Panel
KS-19666L1	10	S	W	W	18Ga	Gen Elec 1GC- 3A335	Belden PH-104 Conn





RECEIVERS AND TRANSMITTERS

Code	Length (Feet)	Type	Jkt Mat.	Conductor		Receiver End	Other End
				In- sul.	Type		
(P) L2W	4, 5-1/2	S	T	T		716A,B,D or E	283B Plug
(P) L2Y	4-1/2	S	T	T		Receiver (at)	Test Clips (au)
L2AD	4, 5-1/2	S	T	T		723A Receiver	464A Plug
L4AC	5-1/2	S	T	W		Receiver (at)	289B Plug
L4AK	7, 15	R	T	W		Receiver (at)	289B Plug
(P) L4AW	6	S	T	T		528 (at)	289B Plug
L4CR	4	S	T	T		2-Receivers	464A Plug
(P) R2H	2-1/2	S	T	W		Receiver	Spade Tips
(P) R2BC	4	S	T	W		716A,B,D, or E	Test Clips
R2BK-3	4	S	T	T		Receiver	Spade Tips
(P) R2BR	1-1/4, 2-1/2, 5-1/2	S	T	T		Receiver	Spade Tips
(P) R2BS	2-1/2	S	T	W		Receiver	Spade Tips
(P) R2BT	2-1/2, 3-1/2	S	T	T		Receiver	Spade Tips
(P) R2BU	1-5/6, 2-1/2	S	W	W		Receiver	Spade Tips
(P) R2BY	1 ft. 1/2 in.	S	W	W		Receiver	Spade Tips
R2CC	4-1/4	Y	T	W		2-716B,C,D, or E	Pin Tips
(P) R2CD	2, 4	S	T	W		716B,C,D, or E	Pin Tips
R2CE	2-1/2	S	T	W		Receiver	Spade Tips
(P) R2CF	6	S	T	T		716B,C,D, or E	310 Plug-T,R
(P) R2CG	4-1/4	Y	T	T		2-Receivers	Spade Tips
R2CH	2-1/2	S	T	W		Receiver	Spade Tips

RECEIVERS AND TRANSMITTERS

Code	Conductor					Receiver End	Other End
	Length (Feet)	Type	Jkt Mat.	In- sul.	Type		
(P) R2CJ	4	S	T	T		717A	Spade Tips
(P) R2CL	2-1/2, 5-1/2	S	T	W		Receiver	Spade Tips
(P) R2CR	2-1/4	S	T	W		Receiver	Pin Tips
R2CS	2-1/2	S	T	W		Receiver	Spade Tips
(P) R2CU	6	S	T	T		716B,C,D, or E	309 Plug-T,R
(P) R2DA	3-1/2	Y	T	T		2-Receivers	347 Plug
(P) R2DB	3,6,10	S	T	T		Receiver	347 Plug-T,S
(P) R2DE	4	S	T	T		509	Spade Tips
(P) R2DM	6	S	T	T		Receiver	Pin Tips
(P) R2DN	2-1/2	S	T	T		Receiver	Soldered Con- nections
R2DP	8	Y	T	T		2-Receivers	310 Plug-T,S
(P) R2DW	1-1/4, 3,6	S	T	W		Receiver	Spade Tips
(P) R2DY	2-1/4,3	S	W	W		706A	Spade Tips
R2ED	1-1/2	S	W	W		558	Eyelet Tips
(P) R2EE	4-1/4	Y	T	W		2-716B,C,D or E	505A Plug
R2EY	3	S	T	W		Receiver	Spade Tips
(P) R2FA	2,4	S	T	W		Receiver	Spade Tips
R2FE	1-1/2	S	W	W		558B	Spade Tips
(P) R2FG	3-1/2	Y	T	T		2-Receivers	289B Plug-T

RECEIVERS AND TRANSMITTERS

Code	Length (Feet)	Type	Jkt Mat.	Conductor		Receiver End	Other End
				In- sul.	Type		
(P) R2FL	4 ft. 3-1/2 in.	R	W	W		731A	Spade Tips
(P) R2FM	3-1/2	S	T	W		2-Receivers	464A Plug
(P) R4C	4-2/3	S	T	T		2-Receivers	Spade Tips
R4D	6	Y	T	T		2-Receivers	Spade Tips
(P) W2AE	2-1/2	S	T	W		716B,C,D, or E (at)	Test Clips
(P) W2AG	2-1/2	S	T	W		716B,C,D, or E (at)	Test Clips
W2AJ	3-1/2	S	T	W		Receiver (at)	Test Clips
W2BG	2-1/2	S	T	W		Receiver (at)	Test Clips
W2BH	6	S	T	W		Receiver	Test Clips
(P) W2FS	3	R	W	W		723A	347D Plug
(P) W2FT	4	R	W	W		723A	310 Plug
(P) W7B	11	Y	T	W		716E, 240H Plug	Spade Tips
785 (u)	4	S	T	W	18Ga	Receiver	347 Plug



TOOLS



TOOLS


Code	Conductor						Tool End	Other End
	Length (Feet)	Type	Jkt Mat.	In- sul.	Type			
(P) M2EM	7 in.	S	T	W		360B and C	Square Chucks	
(P) P1W	2	S	T	W		360B	KS-20269 Plug	
(P) P1Y	1	S	T	W		360A	360A Tool	
(P) P4AS	6, 8, 10, 20	S	T	W		360A, B and C	425A Plug	
(P) W1C	12, 20	S	T	W		360 Type	1D or 1E Plug	
(P) W1H	6, 10, 12, 19-1/2	S	T	W	18Ga	360 Type	347B Plug-T	
W1L	3-1/2	S	T	W		360 Type	89 Cord Tip	
(P) W1M	2, 3-1/2	S	T	W		360 Type	Test Clip	
(P) W1AE	12	S	W			360 Type	336A Plug	
(P) W1AF	8-1/2	S	T	T	(aw)	360A	360A Tool	
(P) W1AK	6	S	W	W	20Ga	360B	Banana Plug	
(P) W1AS	3-1/2	S	T	W		360A	Special Chuck	
(P) W1AY	8-1/2	S	W	W	18Ga	360A	360A Tool	
(P) W2W	6, 10, 30	Y	T	W		2-360 Type	310 Plug-T, R	
(P) W2AB	6	S	T	T		2-360A	716-Type Re- ceiver	
(P) W2AL	5	S	T	T		442A	2-360A Tools	
W2AR	28	S	T	T		2-360 Type	289B Plug-T	
(P) W2BD	20	S	T	T		360 Type	347 Plug	
(P) W2BJ	6	S	T	W		513A	347 Plug	

TOOLS

Code	Length (Feet)	Type	Jkt Mat.	Conductor		Tool End	Other End
				In- sul.	Type		
(P) W2BL	10-1/3	S	T	W	(aw)	Test Clips	Eyelet Tips
(P) W2CB	10-1/3	S	T	T	(ay)	Test Clips	Eyelet Tips
(P) W2CF	1	S	T	W		360 Type	310 Plug
(P) W2CJ	4	S	T	W		360 Type	Tubular Tips
(P) W2DR	6	S	T	W		572A	347-Type Plug
(P) W2EH	10 (s)	S	W	W	Coax	572B	347B Plug
(P) W2FR	5	S	T	W	20Ga	2-360 Type	310 Plug
W2FU	10	S	T	W	20Ga	2-360 Type	KS-14530 Plug or H.H. Smith No. 255 Plug
(P) W2GK	28	S	T	W		2-360 Type	464A Plug
W3E	10	S	T	W		419A	310 Plug
W3L	5	S	T	W		360 Type	Spade Tips
(P) W3M	6, 15	S	T	W		360 Type	310 Plug
(P) W3N	6	S	T	W		443A and 503A	310 Plug
(P) W3S	2	S	T	T		518A and 360A	Receiver
(P) W3AJ	12	S	T	W		620A	310 Plug
(P) W3BD	8	S	T	W	20Ga	3-360 Type 3-624B	Bendix PT Conn
(P) W3BE	5	S	T	W	20Ga	3-360 Type	310 Plug
(P) W4BF	6	Y	T	W		360A, 413 Plug	289B Plug
(P) W7B	11	Y	T	W		2-360B (bb)	Spade Tips
W10A	10	S	T	T		370-Type	240D Plug

TOOLS

Code	Conductor					Tool End	Other End
	Length (Feet)	Type	Jkt Mat.	In- sul.	Type		
(P) W12A	1-1/2 in.	S	T	T	(bc)	360 Type	360-Type Tool
(P) 815 (b)	12	S	T	W		262	1E Plug
(P) 893 (b)	36	S	T	W		360A	360A Tool



**MISCELLANEOUS
(COMMERCIAL AND KS)**

MISCELLANEOUS
(COMMERCIAL AND KS)

MISCELLANEOUS (Commercial and KS)

Code	Length (Feet)	Conductor					End A	End B
		Type	Jkt Mat.	In- sul.	Type			
M1Y	6 in.	S	T	W	22Ga	Zierick 194 Cap	107 Cord Tip	
(P) M1AA	4 in., 6 in., 8 in.	S	T	W	22Ga	National 8 Cap	107 Cord Tip	
(P) M1AC	6 in.	S	T	T	22Ga	Zierick 194 Cap	107 Cord Tip	
(P) M2EC	7 in.	S	T	T	22Ga	Zierick 117 Cap	Spade Tips	
(P) M2EK	8	S	T	W	(a)	Test Clips	Soldered Con- nections	
(P) M2EW	2-1/2	S	W	W	20Ga	U.S. Components 990-7-2FSG-DM30 Conn	U.S. Compon- ents 990-10- 4M2HRSL-C- DM30 Conn	
(P) M2FC	5	S	W	W	Coax	KS-14982L3 Jack	477D Jack	
(P) M4AJ	4	S	W	W	22Ga	Bendix PC Conn	Spade Tips	
(P) M4AK	10	S	W	W	22Ga	Bendix PC Conn	Butt End	
(P) M24D	2-1/2	S	W	W	22Ga	U.S. Components SM1-26M1HRSL DM30 Conn	2-477B Jacks; U.S. Comp 990-7-2FSG- DM30 Conn	
M29A	5	S	W	W	22Ga	U.S. Components 980-34F2HSSL- DM30 Conn	U.S. Compon- ents 980- 34F2HSSL- DM30 Conn	
(P) P2BA	4	S	W	W	Coax	KS-13739 Jack	358A Plug	
(P) P2CH	6	S	T	W		KS-14530 Conn	310 Plug-T,R	

MISCELLANEOUS (Commercial and KS)

Code	Length (Feet)	Type	Jkt Mat.	In- sul.	Conductor		End A	End B
					Type			
(P) P2CK	12	S	T	W	20Ga		KS-14530 Conn	Grip-Tite Plug
(P) P2CN	6	S	W	W	18Ga		Hubbell 7464 Conn	Hubbell 7479 Cap
(P) P2CR	8	S	T	W			Insuline 885R Plug	Insuline 855B Plug
(P) P2DT	1	S	W	W	729A		KS-14982L3 Jack Ca	358A Plug
P2ES	4	S	T	W			Gen Radio 274MB Plug	310 Plug
(P) P3AW	12	S	T	W	22Ga		Gen Radio 274MB Plug	KS-16370L2 Conn
(P) P3AY	6-2/3	S	T	W	22Ga		Switchcraft 750 Plug Gen Radio 274MB Plug	464A Plug
(P) P4AK	13 (al)	S	W	W	20Ga		Amphenol Conn	KS-14461L2 Plug
(P) P4AL	13 (al)	S	W	W	20Ga		Amphenol Conn	KS-14461L2 Plug
(P) P4AM	13 (al)	S	W	W	20Ga		Amphenol Conn	KS-14461L2 Plug
(P) P5L	8	S	T	W			Mueller Clips	425A Plug
(P) P22A	2	S	W	W	22Ga		Cannon K03 Conn	Cannon K03 Conn
(P) W1N	10	S	W	W	18Ga		Test Clips	278A Plug
(P) W1AD	4 ft. 7 in.	S	W	W	16Ga		Test Clips	Spade Tips
(P) W2BL	10-1/3	S	T	W	(aw)		KS-6780 Clips	Eyelet Tips
(P) W2CB	10-1/3	S	T	W	(ay)		KS-6780 Clips	Eyelet Tips
(P) W2CL	4	S	T	W			KS-8010 Switch (G)	240 Plug

MISCELLANEOUS (Commercial and KS)

Code	Length (Feet)	Type	Jkt Mat.	In- sul.	Conductor		End A	End B
					Type			
(P) W2CN	6	S	T	W			Test Clips	310 Plug-T,R
(P) W2DC	5-1/2	S	W	W	Coax		Test Clips	358A Plug
(P) W2DD	15	Y	W	W	Coax		Test Clips, Spade Tips	206A Conn
(P) W2DE	4	S	W	W	18Ga		Test Clips	Spade Tips
(P) W2DF	15,30	Y	W	W	Coax		Test Clips	206A and KS-13836 Conn
(P) W2DT	1	Y	W	W	20Ga		Test Clips	466B Jack, 411C Tool
(P) W2ED	4 in.	S	W	W	20Ga		Test Clips	466B Jack
(P) W2EE	4 in.	S	W	W	20Ga		Grip-Rite Plug, Test Clip	466B Jack
(P) W2ET	3-3/4	Y	W	W			H.H. Smith 295 Phone Tips	Test Clips
(P) W2EW	1	S	T	W			KS-6780 Clips	H.B. Jones P-202-CCT Plug
(P) W2FP	8	S	W	W	Coax		Gen Radio 274NK Plug	KS-19531L1 and L2 Plugs
(P) W2FW	35	S	W	W	18Ga		Test Clips	H.B. Jones P-2402-CCE Plug
(P) W2GC	3	S	W	W			Test Clips	463A Plug
(P) W3B	6-1/2	S	T	W	(a)		Test Clips	Spade Tips
(P) W3AA	5	S	T	W			KS-8010 Switch (bd)	351A Plug

MISCELLANEOUS (Commercial and KS)

Code	Length (Feet)	Type	Jkt Mat.	Conductor		End A	End B
				In- sul.	Type		
(P) W3AD	5	S	W	W	18Ga	Test Clips	Spade Tips
(P) W3AG	20	S	W	W	18Ga	Test Clips	Spade Tips
(P) W3AH	4	Y	T	W		KS-8010 Switch (bd)	Test Clips
(P) W5D	6	Y	T	W		KS-6780 Clips	241A, 307A Plugs
(P) W20F	19	S	T	W	22Ga	20-KS-16336L2 Clips	KS-14461L3 Plug
(P) W50B	19	S	T	W	22Ga	50-KS-16336L2 Clips	KS-19162L3 Plug

MISCELLANEOUS





MISCELLANEOUS

Code	Conductor						End A	End B
	Length (Feet)	Type	Jkt Mat.	In- sul.	Type			
(P) D3AH	3/8 in.	S	(be)	W			Spade Tips	Spade Tips
(P) D3BU	9, 13, 25	S	W(c)	W			42A Connecting Block	Spade Tips
(P) D4Y	11 in.	S	T	W			Spade Tips	Spade Tips
(P) D4BD	5-1/2, 9, 13, 25	S	W(c)	W			Spade Tips	Spade Tips
(P) D4BF-3	5-1/2, 9, 13, 25	S	W	W			Spade Tips	Spade Tips
(P) D4BN-3	10 in.	S	W	W			Spade Tips	Spade Tips
(P) D4BP	9, 13, 25	S	W(c)	W			42A Connecting Block	Spade Tips
D4BR-50	2-1/2	S	W	W			Spade Tips	Spade Tips
(P) D5R	9 in.	S	T	W			Spade Tips	Spade Tips
D5S	3/8 in.	S	(be)	W			Spade Tips	Spade Tips
(P) D5U	5 in.; 10-1/4 in.	S	T	W			Spade Tips	Spade Tips
(P) D5W	2-3/4 in.	S	T	W			Spade Tips	Spade Tips
(P) D5AH	1-1/4 in.	S	(bf)	W	20Ga		Spade Tips	Spade Tips
(P) D5AJ	1-1/4 in.	S	(bf)	W	20Ga		Spade Tips	Spade Tips
(P) D5AK	5-1/2, 9, 13, 25	S	W	W			Spade Tips	Spade Tips
(P) D5AL	5-1/2, 9, 13, 25	S	W(c)	W			Special Lock- Type Plug	Spade Tips (af)
(P) D5AM	11 in.	S	W	W			Spade Tips	Spade Tips
D5AN	5-1/2 9, 13	R	W	W			Special Lock- Type Plug	Spade Tips (af)

MISCELLANEOUS

Code	Conductor					End A	End B
	Length (Feet)	Type	Jkt Mat.	In- sul.	Type		
(P) D6W	5-1/2, 9, 13, 25	S	W(c)	W		Spade Tips	Spade Tips
(P) D6AA	5-1/2, 9, 13, 25	S	W(c)	W		Spade Tips	Spade Tips
(P) D6AB	5-1/2, 9, 13	S	W(c)	W		Spade Tips	Spade Tips
(P) D6AD	1-1/3, 5-1/2, 9, 13, 25	S	W(c)	W	27Ga	Spade Tips (bg)	Spade Tips
(P) D6AE	1-1/4 in.	S	W	W	20Ga	Spade Tips	Spade Tips
(P) D6AF	5-1/2, 9, 13, 25	S	W(c)	W		Spade Tips	Spade Tips
(P) D6AG-61	1-3/4	S	W	W		Spade Tips	Spade Tips
D8J-9	5-1/2	S	T	W		Spade Tips	Spade Tips
D8L	5-1/2	S	T	W		Spade Tips	Spade Tips
(P) D8P-9	5-1/2	S	T	W		Spade Tips	Spade Tips
(P) D9H	1-3/4	S		W	22Ga	Spade Tips	Spade Tips
(P) D10N-61	9	S	W	W	27Ga	Spade Tips	KS-19088L1 Conn
(P) D10P	5-1/2, 9, 13, 25	S	W(c)	W	27Ga	Spade Tips (bg)	Spade Tips
(P) D10R	1-1/3, 5-1/2, 9, 13, 25	S	W(c)	W	27Ga	Spade Tips (bg)	Spade Tips
(P) D12B	5-1/2	S	T	W	(bh)	Spade Tips	Spade Tips
(P) D12F	9, 13, 25	S	W(c)	W	27Ga	Spade Tips	Spade Tips

MISCELLANEOUS

Code	Conductor					End A	End B
	Length (Feet)	Type	Jkt Mat.	In- sul.	Type		
D12H-3	5-1/2	S	W	W	27Ga	Spade Tips	Spade Tips
(P) D14B	5-1/2	S	T	W	22Ga	Spade Tips	Spade Tips
(P) D14L	5-1/2, 9, 13, 25	S	W(c)	W	27Ga	Spade Tips (bg)	Spade Tips; Term. Strips
(P) D14M	1, 5	S	W(c)	W	27Ga	Spade Tips	Spade Tips
(P) D16F	5-1/2, 9, 13, 25	S	W(c)	W	27Ga	Spade Tips (bg)	Spade Tips
(P) D20J	5-1/2, 9, 13, 25	S	W(c)	W	27Ga	Spade Tips (bg)	Spade Tips
(P) H2B	4	S	T	W		Test Clips	Spade Tips
H3K	6	S	T	W		Spade Tips	Spade Tips
(P) H3N-9	1-1/2	S	T	W		Spade Tips	Spade Tips
H3T	5-1/2	S	T	W		Spade Tips	Spade Tips
H3U	6	S	T	W		Spade Tips	Spade Tips
(P) H3AN-3	4, 9	R	W	W		Eyelet Tips	Spade Tips
(P) H3AR-3	4, 9, 13	R	W	W		Spade Tips	Spade Tips
(P) H3AS-3	1-1/3, 4, 9, 13	S	W	W		Spade Tips	Spade Tips
(P) H4AT-3	3	R	W	W		Spade Tips	Spade Tips
(P) H3AU	2 ft. 5 in.	S	W (bj)	W		Spade Tips	Spade Tips
(P) H4A	3	S	T	W		Spade Tips	Spade Tips
(P) H4BN-3	3	R	W	W		Spade Tips	Spade Tips
(P) H4BU-3	4	S	W	W		Spade Tips (j)	Spade Tips

MISCELLANEOUS

Code	Conductor					End A	End B
	Length (Feet)	Type	Jkt Mat.	In- sul.	Type		
(P) H4BW-3	4, 9, 13	S	W	W		Spade Tips (j)	Spade Tips
(P) H4CB-3	4	R	W	W		Spade Tips (j)	Spade Tips
(P) H4CC-3	4, 7	R	W	W		Spade Tips (j)	Spade Tips
(P) H4CF-3	4	R	W	W		Spade Tips (bk)	Eyelet Tips
(P) H4CJ	4, 9, 13	R	W(c)	W		Spade Tips	Spade Tips
(P) H4CL	4, 9, 13	S	W(c)	W		Spade Tips	Spade Tips
(P) H4CN-3	3	R	W	W		Spade Tips (j)	Spade Tips
(P) H4CP	3	R	W(c)	W		Spade Tips	Spade Tips
(P) H4CS-3	1-1/6	S	W	W		Spade Tips	Spade Tips
H4CT	4, 13	R	W(c)	W		Spade Tips	Spade Tips
(P) H4CW	3	R	W(c)	W		Spade Tips	Spade Tips
(P) H4CY	2 ft. 5 in.;	S	W (bj)	W		Spade Tips	Spade Tips
(P) H4DA	4-1/2 2 ft. 5 in.;	S	W (bj)	W		Spade Tips	Spade Tips
(P) H4DB	4-1/2						
	5-1/2, 9, 13	R	W	W		Push-in Lock Plug	Push-in Lock Plug
H4DE	6	S	W	W		Push-in Lock Plug	Eyelet Tips
(P) H4DF-61	3-1/2	R	W	W		Push-in Lock Plug	Spade Tips

MISCELLANEOUS

Code	Conductor					End A	End B
	Length (Feet)	Type	Jkt Mat.	In- sul.	Type		
(P) H4DG	2 ft.	S	W	W		Spade Tips	Spade Tips
	5 in.		(bj)				
(P) H4DH	2 ft.	S	W	W		Spade Tips	Spade Tips
	5 in.		(bj)				
H4DJ	5-1/2	R	W(c)	W		Push-in Lock Plug	Push-in Lock Plug
(P) H4DS	6	S	W	W		Push-in Lock Plug	Eyelet Tips
(P) H5P	4	R	W(c)	W		Spade Tips	Spade Tips
(P) H5R-3	4	S	W	W		Spade Tips	Spade Tips
(P) H5S-3	7	R	W	W		Spade Tips	Spade Tips
							(j)
(P) H5T-3	5	R	W	W		Spade Tips	Spade Tips
							(j)
(P) H5U-3	4	S	T	W		Spade Tips	Spade Tips
(P) H5AA	5-1/2, 9, 13	R	W	W		Special Lock- Type Plug	Special Lock- Type Plug
(P) H5AB-3	4	R	W	W		Spade Tips	Spade Tips
(P) H5AC	9	R	W(c)	W		Push-in Lock Plug	Spade Tips
(P) H5AD	5-1/2	R	W(c)	W		Push-in Lock Plug	Push-in Lock Plug
(P) H5AE	5-1/2	R	W(c)	W		Push-in Lock Plug	Spade Tips
(P) H6B-3	3-1/3	S	T	W		Spade Tips	Spade Tips
(P) H6C-3	4, 9, 13	R	W	W		Spade Tips	Spade Tips
(P) H6E	4, 9, 13	R	W(c)	W		Spade Tips	Spade Tips

MISCELLANEOUS

Code	Conductor					End A	End B
	Length (Feet)	Jkt Type	Mat.	In- sul.	Type		
L4AC	5-1/2	S	T	W		Spade Tips (ba)	289-Type Plug
L4AK	7, 15	R	T	W		Tubular Tips (ba)	289-Type Plug
(P) L4AW	6	S	T	T		Tubular Tips (ba)	289-Type Plug
L4BC	1-5/6, 3	S	W	W		Eyelet Tips	Eyelet Tips
(P) L4BT	5	S	W	W		Spade Tips	Eyelet Tips
(P) L4CF	9	R	W	W		Spade Tips	Eyelet Tips
L4CF							
L4CH	5-1/6	S	W	W		Spade Tips	Spade Tips
L4CJ	5-1/6	S	W	W		Spade Tips	Spade Tips
L4CK	3	S	W	W		Spade Tips	Spade Tips
L4CL	3	S	W	W		Spade Tips	Spade Tips
L5A	15	Y, R	T	W		Eyelet Tips (bl)	Spade Tips
(P) M1G	2 ft. 3/4 in. 2 ft. 2 3/4 in. 2 ft. 5 3/4 in.	S	T	T		107 Cord Tip	Soldered Con- nection
(P) M1R	4 3/4 in., 6 3/4 in. 7 1/2 in., 9 in., 11 1/4 in.	S	T	T		107 Cord Tip	107 Cord Tip

MISCELLANEOUS

Code	Length (Feet)	Type	Jkt Mat.	In- sul.	Conductor		End A	End B
					Type			
(P) M1U	2 in., 4 in., 6 in., 8 in., 11 in.	S	T	T	22Ga		107 Cord Tip	Special Clip
(P) M1W	5 1/2 in., 7 in., 10 in.,	S	W	W			Spade Tips	Spade Tips
M2AR	30	S	W	W	18Ga		Spade Tips	Soldered Con- nections
(P) M2CC	5-1/2	S	W	W	18Ga		Soldered Con- nections	Spade Tips
(P) M2CK-9	5-1/2	S	T	W			Spade Tips	Spade Tips
(P) M2CP	4	S	T	W			Test Clips	Pin Tips
(P) M2DC	6	S	T	W			Tubular Tips	Spade Tips
(P) M2DD	6 in.	S	T	T	22Ga		Grid Clips	Spade Tips
(P) M2DK	4-1/2 in., 6 in., 8 in.	S	T	W	22Ga		Grid Clips	Spade Tips
(P) M2DW	7	S	W	W			Spade Tips	Push Button
(P) M2EF	6-1/2	S	W	W	18Ga		Spade Tips	Soldered Con- nections
(P) M2EN	7 in.	S	T	W			Chucks	Chucks
(P) M2EP	5-1/2	S	W	W			Spade Tips	2012B Trans- former

MISCELLANEOUS

Code	Length (Feet)	Type	Jkt Mat.	Conductor		End A	End B
				In- sul.	Type		
(P) M2EY	6 in., 5	S	W	W	Coax	477D Jack	477D Jack
M3BL	2-1/2	S	W	W	18Ga	239A Jack	310 Plug
(P) M3BN	8	S	W(c)	W	22Ga	Spade Tips	Spade Tips
(P) M4P	4-5/8 in.	S	T	W		Spade Tips	Spade Tips
(P) M4AF	2	S	T	T	22Ga	Wire Leads	Spade Tips (at)
M5G	9	S	W	W	18Ga	Soldered Con- nections	Soldered Con- nections
(P) M5M	5-1/2	S	W(c)	W		Spade Tips	Spade Tips
M6AC	3/8 in.	S	(be)	W		Spade Tips	107 Cord Tips
(P) M7C	7 in.	S	T	W	22Ga	Spade Tips	Soldered Con- nections
M8D	3/8 in.	S	(be)	W		Spade Tips	107 Cord Tips
M9B	3/8 in.	S	(be)	W		Spade Tips	107 Cord Tips
(P) M11A	50	S	W	W	18Ga	Spade Tips	Soldered Con- nections
(P) M12L	10	S	W(c)	W	24Ga	2-215C Jacks; 2-355C Jacks	Butt End
(P) M13A	9 in.	S	T	W	22Ga	Soldered Con- nections	Spade Tips
(P) M24A	75	S	T	T	22Ga	Soldered Con- nections	Soldered Con- nections
(P) P2AT	6, 10	S	W	W	Coax	466B Jack	358A Plug
(P) P2AU	10 in.	S	W	W	Coax	466B Jack	466B Jack
(P) P2BE	600	S	W	W	Coax	477A Jack	358A Plug

MISCELLANEOUS

Code	Conductor						End A	End B
	Length (Feet)	Jkt Type	In- Mat.	In- sul.	Type			
(P) P2BU	600	S	W	W	Coax	KS-14982L3 Jack	KS-14317L3 Plug	
(P) P2CD	6 in.	S	W	W	Coax	477A Jack	310 Plug	
(P) P2ED	1	S	W	W	730A	477B Jack	440A Plug	
(P) P2EE	1	S	W	W	730A	477B Jack	560A Jack	
(P) P2ER	25	S	W	W	729A	503B Jack	503B Jack	
(P) P32A	4	S	W	W	27Ga	217B Connector	424C Plug	
(P) R2FK	5-1/2	S	W(c)	W		Spade Tips	Spade Tips	
(P) S6A	4-1/2, 5-3/4, 7, 9	Y	T(c)	W		Molded-on Twin Plug	Spade Tips	
(P) S6B	5-3/4, 8-1/4, 9	S	T(c)	T		Molded-on Twin Plug	Spade Tips	
S6C	12-1/4	S	T(c)	T		Molded-on Twin Plug	Spade Tips	
(P) T1C	6 in., 8 in., 9 7/8 in., 1	S	T	W		Spade Tips	Spade Tips	
(P) T1D	9 7/8 in.,	S	W	W		Spade Tips	Spade Tips	
T1E	9 7/8 in.	S	W	W		Spade Tips	Spade Tips	
(P) T1H	8 in.	S	W	W		Spade Tips	Spade Tips	
(P) T1M	2 1/2 in.	S	T	T		Eyelet Tips	Eyelet Tips	
(P) T2R	6	S	T	W		Spade Tips	Spade Tips	

MISCELLANEOUS

Code	Conductor						End A	End B
	Length (Feet)	Type	Jkt Mat.	In- sul.	Type			
(P) T3K	2-1/2	S	W	W	18Ga	Spade Tips	Spade Tips	
(P) T7A	5-1/2,	S	W(c)	W	27Ga	2-Term. Strips	Spade Tips	
	9, 13							
(P) T9A	5-1/2	S	W(c)	W	27Ga	2-Term. Strips	Spade Tips	
(P) W1T	3, 5	S	T	W		Test Clip	Spade Tip	
(P) W1U	1-2/3	S	T	T		Test Clip	KS-6780 Clip	
(P) W1Y	8 in.	S	W	W		Test Clip	Test Clip	
(P) W1AA	6	S	W	W		Spade Tip	Spade Tip	
(P) W1AB	6	S	W	W		Spade Tip	Spade Tip	
(P) W1AG	1	S	T	W	18Ga	Test Clip	Pin Tip	
W1AH	6	S	W	W	18Ga	Test Clip	Eyelet Tip	
(P) W1AJ	1	S	W	W	16Ga	206C Connector	206C Con- nector	
(P) W1AL	2	S	W	W		.045 Chuck	.045 Chuck	
(P) W1AM	8	S	T	T		Pin-Type Plug	351F Plug	
(P) W1AN	3	S	W	W	18Ga	Test Clip	Test Clip	
(P) W1AP	1 ft.,	S	T	T		Test Clip	Test Clip	
	1/2 in.							
W1AR	1-2/3	S	T	W		Chuck	Pin-Type Tip	
(P) W1AT	1-2/3	S	W	W		Chuck	Pin-Type Tip	
(P) W1AU	4-1/2	S	T	W		Test Clip	Eyelet Tip	
(P) W1BA	7-5/6	S		W	18Ga	Test Clip	Eyelet Tip	
(P) W1BE	10 in.	S	W	W	20Ga	Mueller Test Clip	Special Test Point	
(P) W1BF	5-1/3	S	W	W	22Ga	Terminal Assem- bly	Terminal Assembly	

MISCELLANEOUS

Code	Length (Feet)	Type	Jkt Mat.	Conductor		End A	End B
				In- sul.	Type		
(P) W1BG	5 1/4 in.	S	W		22Ga	Terminal Assem- bly	Unfinished Conductor
(P) W2D	19-1/2	S	T	W		Spade Tips	Test Clips
(P) W2Y	30	S	W	W	18Ga	Pin Tips	Tubular Tips
(P) W2AE	2-1/2	S	T	W		Spade Tips (ba)	Test Clips
(P) W2AF	4	S	T	W		Spade Tips	Test Clips
(P) W2AG	2-1/2	S	T	W		Eyelet Tips (ba)	Test Clips
W2AJ	3-1/2	S	T	W		Spade Tips (ba)	Test Clips
(P) W2AK	4	S	T	W		Pin Tips	Test Clips
(P) W2AS	8	S	T	T		Spade Tips	310 Plug-T,R
(P) W2BA	4	S	T	W		Test Clips	Pin Tips
(P) W2BE	6	S	T	W		Eyelet Tips	Test Clips
(P) W2BF	6	S	T	W		Eyelet Tips	Test Clips
(P) W2BT	4	S	T	W		Test Clips	Tubular Tips
W2CS	9	S	T	W	18Ga	466B Jack	347-Type Plug-T
(P) W2CT	5	S	T	W	18Ga	466B Jack	Spade Tips
(P) W2CW	4, 6, 8	S	W	W	18Ga	Pin Tips	Spade Tips
(P) W2DB	4	S	T	W		Test Clips	Tubular Tips
(P) W2DD	15	Y	W	W	Coax	206A Connector	Spade Tips, Test Clip

MISCELLANEOUS

Code	Length (Feet)	Jkt Type	Jkt Mat.	Conductor		End A	End B
				In- sul.	Type		
(P) W2DF	15,30	Y	W	W	Coax	206A Connector	KS-13836L1 Conn; Test Clip
(P) W2DG	30	S	W	W	Coax	206B Connector	KS-13836L2 Conn
(P) W2DH	15	Y	W	W	Coax	206A Connector	Phone Tip Plug
W2DK	6	S	W	W		Pin Tips	Spade Tips
(P) W2ED	4 in.	S	W	W	20Ga	466B Jack	Test Clips
(P) W2EE	4 in.	S	W	W	20Ga	466B Jack	Grip-Tite Plug; Test Clips
W2EF	5	S	T	W		Pin-Type Tips	240A Plug
(P) W2EG	6	S	T	W		Spade Tips	Spade Tips
(P) W2ER	6	S	W	W		Spade Tips	Spade Tips
(P) W2EY	4	S	T	W		Test Clips	Spade Tips
W2FA	4-1/2	S	W	W	36Ga	Soldered Connec- tions	Spade Tips
(P) W2FD	9-1/2, 19-1/2	S	T	W		Spade Tips	Test Clips
(P) W2FH	6 in.	S	T	W		Test Clips	Chucks
(P) W3AH	4	Y	T	W		Test Clips	KS-8010 Sw (bd)
(P) W3AY	4	S	W	W	22Ga	Spade Tips	Spade and Eyelet Tips
W4AR	5	S	T	W		Twin Plug	Tubular Tips
(P) W4AY	8	S	T	T		471A Jack (h)	240A Plug
W4BB	7	S	W	W		Spade Tips	Spade Tips

MISCELLANEOUS

Code	Length (Feet)	Type	Jkt Mat.	Conductor		End A	End B
				In- sul.	Type		
(P) W4BJ	8	S	T	W		Spade Tips	508A Key
(P) W5E	2	S	T	W		E-Z Hooks	Unfinished Conductors
(P) W6A	20	S	T	W		Spade Tips	3-310 Plugs- T,R
W6C	5-1/2	S	T	W		508A Key	2-310 Plugs
(P) W6G	2-1/6	S	T	W		Soldered Connec- tions	Eyelet Tips
(P) W8H	8	S	W	W	27Ga	E-Z Hooks	Unfinished Conductors
(P) W20H	11-1/2	S	T	W	24Ga	Spade Tips	Spade Tips
(P) W21B	5	S	W	W	27Ga	Spade Tips	Eyelet Tips
(P) W21C	10	S	T	W	24Ga	Spade Tips	Soldered Con- nections
(P) W21D	10	S	T	W	24Ga	Spade Tips	Soldered Con- nections
(P) W23A	11-1/2	S	T	W	24Ga	Soldered Connec- tions	Soldered Con- nections
(P) W23B	11-1/2	S	T	W	24Ga	Soldered Connec- tions	Soldered Con- nections
(P) 26 (b)	3,6,9	S	W	W		Pin Tip	Pin Tip
(P) 330 (b)	6	S	T	T		Spade Tip	Spade Tip
(P) 437 (b)	6	S	W	T		Pin Tip	Spade Tip
(P) 540 (b)	5 in. (bm)	S	T	T		Bare Conductor	Bare Con- ductor
(P) 725 (bn)	7 in.	S	T	T	22Ga	Spade Tips	Soldered Con- nections
(P) 895 (bp)	6 in.	S	T	T	22Ga	Spade Tips	Soldered Con- nections

MISCELLANEOUS

KS	Conductor					End A	End B
	Length (Feet)	Type	Jkt Mat.	In- sul.	Type		
KS- 16304 (m)	5-1/4	S	W	W		Spade Tips	Spade Tips
KS- 16708 (br)	9	R	W	W		Spade Tips	Spade Tips
KS- 16720 (m)		R	W	W		Spade Tips (bs)	Spade Tips
L1	4						
L2	9						
KS- 16721 (br)		R	W	W		Spade Tips (bs)	Eyelet Tips
L1	4						
L2	9						
KS- 16745 (br)		S	W	W		Spade Tips	Eyelet Tips
L1	6						
L2	10						
KS- 20205 (m)		S	W	W		Belden PH150 Plug	Belden SPH- 314 Conn
L1	6-1/2						
KS- 20219 (br)		S	W(c)	W		Spade Tips	Eyelet Tips
L1,L3	6						
L2,L4	10						

POWER CORDS (KS)

KS	Conductor						End A	End B
	Length (Feet)	Type	Jkt Mat.	In- sul.	Type			
7585	3, 6, 10,	S	W(c)	W	18Ga	Plug Cap (bt)	Soldered Con-	
L1, L2,	15, 20,						nections	
L11,	25							
L12,								
(u)								
7586	(by), 6,	S	W(c)	W	18Ga	Plug Cap (bu)	Soldered Con-	
L1, L2,	10, 15,						nections	
L11,	25							
L12,								
(u)								
7993	10, 15,	S	W	W	18Ga	Plug Cap (bt)	Soldered Con-	
(u)	20, 25						nections	
8401	2 ft.,	S	W	W	14Ga	Plug Cap (bu)	Soldered Con-	
(u)	7-1/2						nections	
	in.							
13881	6	S	W	W	18Ga	Plug Cap (bt)	Soldered Con-	
(u)							nections	
14440	20	S	W	W	18Ga	Plug Cap (bu)	Soldered Con-	
L41,							nections	
L42 (m)								
14440	6	S	W	W	18Ga	Plug Cap (bt)	Soldered Con-	
L44 (m)							nections	
14532	10	S	W	W	18Ga	Plug Cap (bt)	Soldered Con-	
L1, L7,							nections	
L14 (m)								
14532	2	S	W	W	18Ga	Plug Cap (bt)	Soldered Con-	
L2, L12							nections	
(m)								
14532	15	S	W	W	18Ga	Plug Cap (bt)	Soldered Con-	
L3 (m)							nections	
14532	20	S	W	W	18Ga	Plug Cap (bt)	Soldered Con-	
L4 (m)							nections	
14532	25	S	W	W	18Ga	Plug Cap (bt)	Soldered Con-	
L5 (m)							nections	

POWER CORDS (KS)

KS	Conductor					End A	End B
	Length (Feet)	Type	Jkt Mat.	In- sul.	Type		
14532 L6, L13 (m)	2, 10	S	W	W	18Ga	Plug Cap (bt)	Spade Tips
14532 L8, L15, L18 (m)	10	S	W	W	18Ga	Plug Cap (bt)	Hubbell 7484 Conn
14532 L11 (m)	6, 10, 15, 20, 25	S	W	W	18Ga	Plug Cap (bt)	Soldered Con- nections
14532 L16 (m)	10	S	W	W	18Ga	Plug Cap (bt)	Hubbell 7593 Conn
14532 L17 (m)	10, 25	S	W	W	18Ga	Plug Cap (bt)	Soldered Con- nections
14532 L20 (m)	10	S	W	W	18Ga	Plug Cap (bt)	Hubbell 6600 Conn
14532 L21 (m)	9	S	W	W	18Ga	Plug Cap (bt)	Soldered Con- nections
14798 L1, L4 (u)	8-1/2	S	W	W	18Ga	Plug Cap (bu)	Soldered Con- nections
14798 L2 (u)	8	S	W	W	18Ga	Plug Cap (bu)	Soldered Con- nections
14798 L3 (u)	6	S	W	W	18Ga	Plug Cap (bu)	Soldered Con- nections
16017 (m)	6	S	W	W	18Ga	Plug Cap (bt)	Soldered Con- nections
16054 L1, L2 (u)	5-2/3	S	W	W	18Ga	Angle Plug Cap (bu)	Soldered Con- nections
16054 L11, L12 (u)	11-2/3	S	W	W	18Ga	Angle Plug Cap (bu)	Soldered Con- nections

POWER CORDS (KS)

KS	Conductor						End A	End B
	Length (Feet)	Type	Jkt Mat.	In- sul.	Type			
16935 L1, L11 (m)	6	S	W	W	18Ga	Angle Plug Cap (bu)	Soldered Conn, Spade Tip	
16935 L2, L12 (m)	12	S	W	W	18Ga	Angle Plug Cap (bu)	Soldered Conn, Spade Tip	
16935 L13, L14 (m)	1-1/2	S	W	W	18Ga	Angle Plug Cap (bu)	Soldered Conn, Spade Tip	
16941 L1, L11 (br)	6	S	W	W	18Ga	Plug Cap (bt)	Soldered Con- nections	
20274 L1 (m)	10	S	W	W	18Ga	Plug Cap (bt)	Belden PH104 Connector	
20340 L1 (m)	10	S	W	W	18Ga	Plug Cap (bt)	Soldered Con- nections	



CORD ASSEMBLIES



PATCHING CORD ASSEMBLIES

Code	Length (Feet)	Plug	Cord	Color
1E				
1P1A	2	2-1E	P1A	SL
234				
2P11A	19-1/2	234,347C	P2R	GN
3P18A	19-1/2	234,310	P3R	BLK
3P18B	19-1/2	234,310	P3R	BLK
3P19A	19-1/2	234,310	P3S	GN
4P6A	19-1/2	234,289B	P4L	GN
4P9A	19-1/2	234,289B	P4R	GN
4P26A	8	234,425A	P4AY	BLK
235				
4P7A	19-1/2	235,289B	P4L	GN
240				
2P36A	6	240L,310	P3H	SL
2P36B	7	240L,310	P3H	SL
2P36C	8	240L,310	P3H	SL
2P36D	8-1/2	240L,310	P3H	SL
2P36E	9-1/2	240L,310	P3H	SL
3P2A	10	240A,310	P3H	SL
3P2B	5	240F,310	P3H	SL
3P2C	10	240H,310 (c)	P3H	SL
3P30A	10	240A,310	P3AA	BLK
3P32A	5	240B,310	P3H	SL
3P33A	10	240B,310	P3H	SL
3P35A	10	240H,310	P3H	SL
4P4A	12	240B,289B	P4K	BLK
4P4B	12	240B,289B	P4K	BLK

(c) Black shells.

PATCHING CORD ASSEMBLIES

Code	Length (Feet)	Plug	Cord	Color
4P5A	12	240C, 289B	P4K	BLK
5P3A	10	240B, 2-310 (b)	2-P3H	SL
5P3B	10	240B, 2-310 (b)	2-P3H	SL
5P5A	10, 12	240C, 310, 464C	P3H, P4BB	BLK, SL
6P3A	5	240B, 2-310 (b)	2-P3H	SL
6P4A	10	240C, 2-310 (b)	2-P3H	SL
6P4B	10	240C, 2-310 (b)	2-P3H	SL
6P4C	10	240C, 2-310 (b)	2-P3H	SL
6P5A	10	240G, 2-310 (b)	2-P3H	SL
6P6A	11	2-240B, 2-310 (b)	P6B	RD
241				
1P9A	1	2-241A	P1H	BLK
2P12A	6	241A, 347C	P2T	SL
2P13A	3	2-241A	P2AA	SL
2P13B	6	2-241A	P2AA	SL
2P13C	15	2-241A	P2AA	SL
2P13D	2	2-241A	P2AA	SL
2P14A	3	2-241B	P2AA	SL
2P37A	6	241A, 446A	P2EG	BLK
2P38A	6	241A, 291B	P2EH	BLK
3P13A	3	2-241A	P3J	RD
3P14A	3	2-241B	P3J	RD
3P14B	6	2-241B	P3J	RD
3P17A	3	241A, 310	P3N	GN
3P17B	6	241A, 310	P3N	GN
3P17C	15	241A, 310	P3N	GN
4P21A	6	241B, 354A, 354B	P4AD	BR
248				
6P2A	6	2-248A	2-P3E	SL

(b) One red shell and one black.

PATCHING CORD ASSEMBLIES

Code	Length (Feet)	Plug	Cord	Color
257				
2P5A	3	257A, 310	P2B	GN
3P10A	6	257A, 310	P3E	SL
3P11A	6	257B, 310	P3E	SL
262				
3P24A	3	3-262E, 310 (c)	643	BR
277				
3P22A	3-1/2	3-277B, 309 (c)	642	BR
288				
4P3A	6	2-288A	P4H	GN
4P22A	7	288A, 360D	P4AE	BR
289				
4P4A	12	289B, 240B	P4K	BLK
4P4B	12	289B, 240B	P4K	BLK
4P5A	12	289B, 240C	P4K	BLK
4P6A	19-1/2	289B, 234	P4L	GN
4P7A	19-1/2	289E, 235	P4L	GN
4P8A	4	2-289B	P4N	SL
4P8B	6	2-289B	P4N	SL
4P9A	19-1/2	289B, 234	P4R	GN
4P23A	6	289B, 2-301A	P4AH	BLK
4P24A	19-1/2	289B, 415A	P4L	GN
5P5A	10, 12	289B, 240C, 310	P3H, P4K	BLK
291				
2P38A	6	291B, 241A	P2EH	BLK

(c) Black shells.

PATCHING CORD ASSEMBLIES

Code	Length (Feet)	Plug	Cord	Color
301				
4P23A	6	2-301A, 289B	P4AH	BLK
305				
3P20A	4	2-305A	P3P	SL
3P20B	6	2-305A	P3P	SL
3P20C	12	2-305A	P3P	SL
309				
1P7A	3	2-309	P1E	SL
2P6A	10	309, 310	P2AH	SL
2P7A	10	2-309 (b)	P2G	SL-RD
2P10A	10	309, 310	P2P	SL-RD
2P10B	10	309, 310 (c)	P2P	SL-RD
2P22A	8	309 (c), 464C	P2EM	BR
2P23A	6	2-309	P3D (d)	SL
3P3A	6	2-309	P3D	SL
3P3B	8	2-309	P3D	SL
3P3C	3	2-309	P3D	SL
3P3D	9 in.	2-309	P3D	SL
3P4A	6	309, 113B Ga	P3D (e)	SL
3P5A	6	309, 115B Ga	P3D	SL
3P12A	4	309, 310	P3F	SL
3P12B	4	309, 310	P3F	RD

(b) One red shell and one black.

(c) Black shells.

(d) P3D cord with red conductor cut off at each end of cord body.

(e) Also equipped with No. 121A cord weight.

PATCHING CORD ASSEMBLIES

Code	Length (Feet)	Plug	Cord	Color
3P12C	4	309,310	P3F	GN
3P12D	4	309,310	P3F	BLK
3P12E	6	309,310	P3F	SL
3P12F	6	309,310 (f)	P3F	SL
3P12G	6	309,310 (c)	P3F	SL
3P12H	8	309,310	P3F	SL
3P16A	6	309,310	P3L	BLK
3P16B	12	309,310	P3L	BLK
3P21A	3-1/2	4-309 (c)	642	BR
3P21B	3-1/2	4-309 (c)	642	WH
3P21C	5	4-309 (c)	642	WH
3P22A	3-1/2	309,3-277B (c)	642	BR
3P29A	8	309,310	P3F	RD-GN
3P31A	8	2-309	P3D	RD-GN
4P14A	7	309,310,351A	P4Y	BLK
5P2A	7	309,310,351B	P5B	BLK
310				
1P5A	2	310,320B	P2B (a)	GN
1P6A	6	2-310	P1D	BLK
2P4A	3	2-310	P2B	GN
2P4B	4	2-310	P2B	GN
2P4C	6	2-310	P2B	GN
2P5A	3	310,257A	P2B	GN
2P6A	10	310,309	P2AH	SL
2P8A	10	2-310 (b)	P2H	SL-RD
2P9A	9	2-310	P2J	BLK
2P9B	6	2-310	P2J	BLK

(a) P2B cord with ring (red) conductor cut off at each end of cord body.

(b) One red shell and one black.

(c) Black shells.

(f) Gray shells.

PATCHING CORD ASSEMBLIES

Code	Length (Feet)	Plug	Cord	Color
2P9C	6	2-310 (c)	P2J	BLK
2P10A	10	310, 309	P2P	SL-RD
2P10B	10	310, 309 (c)	P2P	SL-RD
2P15A	6	310, 425a	P2DJ	SL
2P16A	4	310, 464A	P2EJ	SL
2P27A	6	310, 464C	P2EK	SL
2P28A	10	310 (k)	P2CM	BLK
2P30A	15	310, 347D	P2CP	BLK
2P30B	6	310, 347D	P2CP	BLK
2P32A	8	310, Tip Plugs	P2CW	BLK
2P33A	4	310 (c), 359A	P2DA	RD-SL
2P36A	6	310, 240L	P3H	SL
2P36B	7	310, 240L	P3H	SL
2P36C	8	310, 240L	P3H	SL
2P36D	8-1/2	310, 240L	P3H	SL
2P36E	9-1/2	310, 240L	P3H	SL
3P1A	3	4-310 (c)	P3A	BR
3P2A	10	310, 240A	P3H	SL
3P2B	5	310, 240F	P3H	SL
3P2C	10	310 (c), 240H	P3H	SL
3P6A	1	2-310	P3E	SL
3P6C	6	2-310 (f)	P3E	SL
3P6D	6	2-310 (c)	P3E	SL
3P6E	8	2-310	P3E	SL
3P6F	10	2-310	P3E	SL
3P6G	12	2-310	P3E	SL
3P6H	15	2-310	P3E	SL
3P6J	20	2-310	P3E	SL

(c) Black shells.

(f) Gray shells.

(k) Black shells. Also equipped with Hubbell 7464 body.

PATCHING CORD ASSEMBLIES

Code	Length (Feet)	Plug	Cord	Color
3P6K	25	2-310	P3E	SL
3P7A	6	2-310	P3E	SL
3P7B	3	2-310	P3E	SL
3P7C	8	2-310 (c)	P3E	GN
3P7D	2	2-310 (c)	P3E	SL
3P7E	4	2-310	P3E	SL
3P8A	6	310, 123B Ga	P3E (e)	SL
3P8B	6	310, 123B Ga	P3E	SL
3P9A	6	310, 125B Ga	P3E	SL
3P10A	6	310, 257A	P3E	SL
3P11A	6	310, 257B	P3E	SL
3P12A	4	310, 309	P3F	SL
3P12B	4	310, 309	P3F	RD
3P12C	4	310, 309	P3F	GN
3P12D	4	310, 309	P3F	BLK
3P12E	6	310, 309	P3F	SL
3P12F	6	310, 309 (f)	P3F	SL
3P12G	6	310, 309 (c)	P3F	SL
3P12H	8	310, 309	P3F	SL
3P15A	6	2-310	P3K	BLK
3P15B	12	2-310	P3K	BLK
3P16A	6	310, 309	P6L	BLK
3P16B	12	310, 309	P6L	BLK
3P17A	3	310, 241A	P3N	GN
3P17B	6	310, 241A	P3N	GN
3P17C	15	310, 241A	P3N	GN
3P18A	19-1/2	310, 234	P3R	BLK
3P18B	19-1/2	310, 234	P3R	BLK
3P19A	19-1/2	310, 234	P3S	GN

(c) Black shells.

(e) Also equipped with No. 121A cord weight.

(f) Gray shells.

PATCHING CORD ASSEMBLIES

Code	Length (Feet)	Plug	Cord	Color
3P23A	3	4-310 (c)	643	BR
3P23B	5	4-310 (c)	643	WH
3P24A	3	310, 3-262E (c)	643	BR
3P27A	7	310, 351A	P3U	BLK
3P27B	7	310 (c), 351A	P3U	BLK
3P28A	7	310, 351B	P3U	BLK
3P29A	8	310, 309	P3F	RD-GN
3P30A	10	310, 240A	P3AA	BLK
3P32A	5	310, 240B	P3H	SL
3P33A	10	310, 240B	P3H	SL
3P35A	10	310, 240H	P3H	SL
3P36A	10	2-310 (c)	P3AJ	RD-SL
3P36B	15	2-310 (c)	P3AJ	RD-SL
3P36C	20	2-310 (c)	P3AJ	RD-SL
3P36D	25	2-310 (c)	P3AJ	RD-SL
3P39A	19-1/2	310, 415A	P3R	BLK
3P39B	19-1/2	310, 415A	P3R	BLK
3P40A	19-1/2	310, 415A	P3S	GN
4P14A	7	310, 309, 351A	P4Y	BLK
5P2A	7	310, 309, 351B	P5B	BLK
5P3A	10	2-310 (b), 240B	2-P3H	SL
5P3B	10	2-310 (b), 240B	2-P3H	SL
5P5A	10, 12	310, 240C, 464C	P3H, P4BB	BLK, SL
6P3A	5	2-310 (b), 240B	2-P3H	SL
6P4A	10	2-310 (b), 240C	2-P3H	SL
6P4B	10	2-310 (b), 240C	2-P3H	SL
6P4C	10	2-310 (b), 240C	2-P3H	SL
6P5A	10	2-310 (b), 240C	2-P3H	SL
6P6A	11	2-310 (b), 2-240B	P6B	RD

(b) Has one red shell and one black.
(c) Black shells.

PATCHING CORD ASSEMBLIES

Code	Length (Feet)	Plug	Cord	Color
315				
4P17A	4	2-315A	P4S	RD
4P17B	6	2-315A	P4S	RD
4P17C	10	2-315A	P4S	RD
4P17D	6	2-315B	P4S	RD
316				
5P4A	10	2-316A	P5D	SL
320				
1P5A	2	320B, 310	P2B (a)	GN
324				
4P15A	7	324B, 351B	P4AA	BLK
4P16A	7	324B, 351A	P4AA	BLK
4P20A	7	324B, 351E	P4AC	BLK
327				
4P18A	2	2-327A	P4H	SL
4P18B	4	2-327A	P4H	SL
4P18C	6	2-327A	P4H	SL
4P18D	6	2-327A	P4H	BLK
338				
6P9A	10	2-338A	P6F (g)	RD-SL
6P9B	15	2-338A	P6F (g)	RD-SL
6P9C	20	2-338A	P6F (g)	RD-SL
6P9D	25	2-338A	P6F (g)	RD-SL

(a) Has ring (red) conductor cut off at each end.
 (g) Contains a 17-dB pad in each tip and ring circuit

PATCHING CORD ASSEMBLIES

Code	Length (Feet)	Plug	Cord	Color
6P10A	10	2-338A	P6G (h)	RD-SL
6P10B	15	2-338A	P6G (h)	RD-SL
6P10C	20	2-338A	P6G (h)	RD-SL
6P10D	25	2-338A	P6G (h)	RD-SL
347				
1P2A	3	2-347C	P1E	SL
1P3A	3	2-347D	P1B	SL
1P4A	2	2-347D	P1B	SL
1P4B	4	2-347D	P1B	SL
1P4C	6	2-347D	P1B	SL
1P8A	5	347D	P1G	BLK
1P11A	6	2-347D	P1L	BLK
2P1A	6 in.	2-347C	P2A	RD
2P1B	2	2-347C	P2A	RD
2P1C	4	2-347C	P2A	RD
2P1D	6	2-347C	P2A	RD
2P2A	3	2-347C	P2A	RD
2P3A	3	2-347D	P2A	RD
2P3B	6	2-347D	P2A	RD
2P11A	19-1/2	347C, 234	P2R	GN
2P12A	6	347C, 241A	P2T	SL
2P20A	8	2-347D	P2AK	BLK
2P24A	6	2-347D, 157A Ga	P2A (e)	RD
2P25A	4	347C, 2-347D	P2AR	RD
2P30A	15	347D, 310	P2CP	BLK
2P30B	6	347D, 310	P2CP	BLK
2P31A	6	347C, 359A	P2CU	RD-SL
2P35A	19-1/2	347C, 415A	P2R	GN

(e) Also equipped with a No. 121A cord weight.

(h) Contains a 23-dB pad in each tip and ring circuit.

PATCHING CORD ASSEMBLIES

Code	Length (Feet)	Plug	Cord	Color
351				
3P27A	7	351A, 310	P3U	BLK
3P27B	7	351A, 310 (c)	P3U	BLK
3P28A	7	351B, 310	P3U	BLK
3P34A	7	351A, 464B	P3BF	BLK
4P14A	7	351A, 309, 310	P4Y	BLK
4P15A	7	351B, 324B	P4AA	BLK
4P16A	7	351A, 324B	P4AA	BLK
4P20A	7	351E, 324B	P4AC	BLK
5P2A	7	351B, 309, 310	P5B	BLK
5P6A	7	351B, 425A	P5J	BLK
6P11A	7	351G, 428A	P6K	BLK
6P12A	7	351G, 425A	P6K	BLK
353				
4P19A	8	2-353A	P4AB	SL
354				
4P21A	6	354A, B, 241B	P4AD	BR
359				
2P31A	6	359A, 347C	P2CU	RD-SL
2P33A	4	359A, 310	P2DA	RD-SL
360				
4P22A	7	360D, 288A	P4AE	BR
406				
9P1A	4	2-406A	P9B	BLK
9P1B	8	2-406A	P9B	BLK

(c) Black shells.

PATCHING CORD ASSEMBLIES

Code	Length (Feet)	Plug	Cord	Color
413				
2P34A	10 in.	413C, 413D	P2DD	RD-BLK
415				
2P35A	19-1/2	415A, 347C	P2R	GN
3P39A	19-1/2	415A, 310	P3R	BLK
3P39B	19-1/2	415A, 310	P3R	BLK
3P40A	19-1/2	415A, 310	P3S	GN
4P24A	19-1/2	415A, 289B	P4L	GN
425				
2P15A	6	425A, 310	P2DJ	SL
4P26A	8	425A, 234	P4AY	BLK
5P6A	7	425A, 351B	P5J	BLK
5P7A	8	425A (k)	P5L	BLK
6P1A	6	2-425A	P6L	SL
6P1B	3	2-425A	P6L	SL
6P1C	8	2-425A	P6L	SL
6P1D	1	2-425A	P6L	SL
6P7A	3	2-425A	P6L	RD-SL
6P7B	5	2-425A	P6L	RD-SL
6P7C	7	2-425A	P6L	RD-SL
6P7D	9	2-425A	P6L	RD-SL
6P8A	6	2-425A	P6L	GN
6P8B	10	2-425A	P6L	GN
6P8C	15	2-425A	P6L	GN
6P8D	20	2-425A	P6L	GN
6P8E	25	2-425A	P6L	GN
6P12A	7	425A, 351G	P6K	BLK

(k) Also equipped with five No. 30 Mueller Clips.

PATCHING CORD ASSEMBLIES

Code	Length (Feet)	Plug	Cord	Color
428				
4P19A	8	2-428A	P4AR	SL
4P19B	5	2-428A	P4AR	SL
6P11A	7	428A, 351G	P6K	BLK
430				
6P9A	10	2-430A	P6M	RD-SL
6P9B	15	2-430A	P6M	RD-SL
6P9C	20	2-430A	P6M	RD-SL
6P10A	10	2-430A	P6N	RD-SL
6P10B	15	2-430A	P6N	RD-SL
6P10C	20	2-430A	P6N	RD-SL
6P10D	25	2-430A	P6N	RD-SL
446				
2P37A	6	446A, 241A	P2EG	BLK
464				
2P16A	4	464A, 310	P2EJ	SL
2P21A	8	2-464C	P2EL	RD
2P22A	8	464C, 309 (c)	P2EM	BR
2P27A	6	464C, 310	P2EK	SL
3P34A	7	464B, 351A	P3BF	BLK
5P5A	10, 12	464C, 310, 240C	P3H, P4BB	BLK
KS-19471				
14P1A	4-1/2	2-KS-19471L1	P14B	BLK
14P1B	4-1/2	2-KS-19471L2	P14B	BLK
14P1C	4-1/2	2-KS-19471L3	P14B	BLK
14P1D	4-1/2	2-KS-19471L4	P14B	BLK

(c) Black shells.

PATCHING CORD ASSEMBLIES

Code	Length (Feet)	Plug	Cord	Color
14P1E	4-1/2	2-KS-19471L5	P14B	BLK
14P1F	4-1/2	2-KS-19471L6	P14B	BLK
14P1G	4-1/2	2-KS-19471L7	P14B	BLK
14P1H	4-1/2	2-KS-19471L8	P14B	BLK
14P1J	4-1/2	2-KS-19471L9	P14B	BLK
14P1K	4-1/2	2-KS-19471L10	P14B	BLK
624 Tool				
1P12A	1	2-624B	P1Y	RD
Commercial				
2P28A	10	Hubbell 7464 Body, 310 Plug (c)	P2CM	BLK
2P29A	6	Hubbell 7464 Body and 7479 Cap	P2CN	BLK
3P38A	10	Hubbell 7555G body and 5264 Cap	P3AR	BLK

(c) Black shells.

TESTING CORD ASSEMBLIES

Code	Length (Feet)	Plug	Jack	Tool	Cord	Color
1B Plug						
1W6A	12	1B	-	360B	W1C	GY-GN
1E Plug						
1W4A	12	1E	-	-	W1P	BLK
1W6B	20	1E	-	360B	W1C	GY-GN
1W9A	20	1E	-	360A	W1C	GY-GN
1W12A	12	1E	-	262	815	BLK
240-Type Plug						
2W39A	4	240A	471A	-	W2CL	BLK
2W40A	4	240H	471A	-	W2CL	BLK
2W45A	4	240B	471A	-	W2CL	BLK
4W5A	6	240A, 464C	-	-	W4CB	BLK
4W10A	8	240A	471A	-	W4AY	BLK
241-Type Plug						
2W3A	3	241A	-	-	P2AA	SL
2W14A	2-1/2	241A	-	-	W2S	GN
2W15A	2-1/2	241A	-	-	W2BP	GN
2W15B	6	241A	-	-	W2BP	GN
2W51A	6	241, KS-19531L1, L2	-	-	W2GB	BLK
3W2A	6	241A	-	-	S3F	SL
251-Type Plug						
4W3A	6	251B, C, D, E; 464C	-	-	W4BW	BLK

TESTING CORD ASSEMBLIES

Code	Length (Feet)	Plug	Jack	Tool	Cord	Color
252-Type Plug						
4W6A	12	252A,B; 464C	-	-	W4CC	GN
263-Type Plug						
1W2A	30	263A	-	-	M1P	BLK
289-Type Plug						
2W2A	4	289B	-	-	L2K	BR
4W1A	6	289B	-	-	L4R	BR
4W1B	10	289B	-	-	L4R	BR
4W1C	12	289B	-	-	L4R	BR
4W1D	20	289B	-	-	L4R	BR
4W8A	6	289B	-	-	W4AN	GN
4W12A	6	289B; 413A B, C, and D	-	360B, 360C	W4BF	BLK
301-Type Plug						
4W7A	12	301A and 464A	-	-	W4CD	GN
304-Type Plug						
2W26A	5-1/2	304A	-	-	W2BC	BLK
308-Type Plug						
3W7A	12	308A, 310	-	-	W3AB	BLK
309-Type Plug						
2W11A	5	309	-	-	W2L	BLK
2W25A	5	309	-	-	W2BB	BLK

TESTING CORD ASSEMBLIES

Code	Length (Feet)	Plug	Jack	Tool	Cord	Color
2W29A	6	309	-	-	R2CU	BR
2W30A	4	309	-	-	W2BR	BLK
3W6A	19-1/2	309	-	-	W3Y	BR
310-Type Plug						
1W1A	100	310	-	-	M1N	BLK
1W5A	10	310	-	-	W1B	GN
1W5B	10	310 (f)	-	-	W1B	GN
1W7A	12	310	-	-	W1W	GN
1W11A	12	310	-	-	W1W	GN
1W15A	6	310 (g)	-	-	W1AC	BLK
2W4A	6	310	-	-	R2CF	BR
2W5A	6	310	-	-	S2B	SL
2W5B	10	310	-	-	S2B	RD
2W6A	10	310	-	-	W2C	GN
2W9A	9-1/2	310	-	-	W2J	GN
2W12A	9	310	-	-	W2M	BLK
2W12B	9	310 (c)	-	-	W2M	BLK
2W13A	6	310	-	-	W2R	RD
2W16A	9	310	-	-	W2T	BLK
2W17A	6	310	-	360B, 360C	W2W	SL
2W17B	30	310	-	360B, 360C	W2W	SL
2W17C	10	310	-	360B, 360C	W2W	SL
2W17D	1	310	-	360B, 360C	W2CF	SL
2W22A	8	310	522A Key	-	W2AS	BLK
2W33A	5	310	-	-	W2BS	BLK

(c) Black shells.

(f) Gray shells.

(g) Also equipped with Hubbell 9970 plug cap.

TESTING CORD ASSEMBLIES

Code	Length (Feet)	Plug	Jack	Tool	Cord	Color
2W38A	5	310	471A	-	W2CK	BLK
2W42A	5-1/2	310	-	-	W2DL	BLK
2W43A	8	310	-	-	W2EL	RD
2W48A	5	310	-	360B, 360C	W2FR	BLK
2W50	4	310 (c)	-	-	W2FT	BLK
3W1A	10	310	-	-	S3B	SL
3W3A	12	310	-	-	W3A	SL
3W4A	6	310	-	360A, B,C	W3M	SL
3W4B	15	310	-	360A, B,C	W3M	SL
3W7A	12	310, 308A	-	-	W3AB	BLK
3W9A	5	310 (c)	-	-	W3AE	BLK
3W13A	12	310	-	620A	W3AJ	BLK
3W13B	12	310 (c)	-	620A	W3AJ	BLK
3W14A	4	310	-	-	W3AN	SL
3W14B	9	310	-	-	W3AN	SL
3W15A	4	310	-	-	W3AT	SL
3W18A	5	310	-	360A, B,C	W3BE	BLK
3W19A	6	310, 351A	-	-	W3BF	BLK
3W20A	6	310, 351B	-	-	W3BF	BLK
6W1A	20	310 (j)	-	-	W6A	GN
315-Type Plug						
3W5A	6	315A	-	-	W3W	BLK
316-Type Plug						
4W9A	10	316A	-	-	W4AS	BLK

(c) Black shells.

(j) One red shell, one black, one gray.

TESTING CORD ASSEMBLIES

Code	Length (Feet)	Plug	Jack	Tool	Cord	Color
327-Type Plug						
2W36A	5-1/2	327A	-	-	W2CA	BLK
336-Type Plug						
1W16A	12	336A	-	360B	W1AE	BLK
338-Type Plug						
6W2A	6	338A	-	-	2- S3B	SL
347-Type Plug						
1W3A	6	347C	-	-	S1C	SL
1W8A	10	347D	-	360A	W1H	BLK
1W14A	19-1/2	347C	-	360A	W1H	BLK
1W14B	12	347C	-	360A	W1H	BLK
2W7A	19-1/2	347C	-	-	W2F	GN
2W7B	12	347C	-	-	W2F	GN
2W8A	9-1/2	347D	-	-	W2F	GN
2W19A	5	347D	-	-	W2AA	BLK
2W20A	5	347C	-	-	W2AA	BLK
2W28A	5-1/2	347C	-	-	630	BR
2W32A	6	347C	-	-	R2DB	BR
2W35A	4-1/2	347C	-	-	W2BY	BLK
2W44A	3	347C	-	-	W2EM	BLK
2W47A	9-1/2	347C	-	-	W2FE	GN
2W47B	19-1/2	347C	-	-	W2FE	GN
351-Type Plug						
1W17A	8	351F	-	-	W1AM	BR-GN
3W8A	5	351A	471A	-	W3AA	BLK

TESTING CORD ASSEMBLIES

Code	Length (Feet)	Plug	Jack	Tool	Cord	Color
3W19A	6	351A, 310	-	-	W3BF	BLK
3W20A	6	351A, 310	-	-	W3BF	BLK
382-Type Plug						
3W11A	6	382A	-	-	S2B, S3B	SL
383-Type Plug						
3W12A	6	383A	-	-	S2B, S3B	SL
412-Type Plug						
4W11A	12	412A and B, 464C	-	-	W4CC	GN
413-Type Plug						
4W12A	6	413A, B, C, and D; 464C	-	360B 360C		
425-Type Plug						
6W2A	5-3/4	425A	-	-	W6K	SL
428-Type Plug						
2W34A	6	428A	-	-	W2FG	BLK
464-Type Plug						
2W24A	9-1/2	464C	-	-	W2GG	GN
2W36A	5-1/2	464C	-	-	W2GH	BLK
4W2A	6	464C	-	-	L4CP	BR

TESTING CORD ASSEMBLIES

Code	Length (Feet)	Plug	Jack	Tool	Cord	Color
4W3A	6	464C, 251 Type	-	-	W4BW	BLK
4W4A	6	464C	-	-	W4CA	BLK
4W5A	6	464C, 240A	-	-	W4CB	BLK
4W6A	12	464C, 252A and B	-	-	W4CC	GN
4W7A	12	464A, 301A	-	-	W4CD	GN
4W11A	12	464C, 412A and B	-	-	W4CC	GN
4W12A	6	464C, 413A, B, C, and D	-	360A, 360B	W4CF	BLK
360-Type Tool						
1W13A	3	-	-	2- 360A	893	RD
1W13B	6	-	-	2- 360A	893	RD
2W21A	6	-	-	2- 360A	W2AB	BR
2W41A	4	-	471A	360A, 360B	W2CJ	BLK
471A Jack						
2W37A	4	-	471A	-	W2DB	BLK
2W38A	5	310	471A	-	W2CK	BLK
2W39A	4	240A	471A	-	W2CL	BLK
2W40A	4	240H	471A	-	W2CL	BLK
2W41A	4	-	471A	360A and B	W2CJ	BLK
2W45A	4	240B	471A	-	W2CL	BLK
3W10A	4	-	471A	-	W3AH	BLK

TESTING CORD ASSEMBLIES

Code	Length (Feet)	Plug	Jack	Tool	Cord	Color
KS-14530 Connector						
2W49A	10	2-KS-14530	-	360A and B	W2FU	BLK
Commercial						
2W46A	2-1/2	Mallory No. 75 2-	-	-	R2DN	BR
2W49B	10	H.H. Smith No. 255	-	360A and B	W2FU	BLK
3W17A	4	AT8255D Cable Clip	-	-	W3AY	GY
3W17B	4	AT8255E Cable Clip	-	-	W3AY	GY