



Astro Pyle PTBL7C Speakers Replacement

A guide to replace the speakers of the Astro Pyle PTBL7C.

Written By: Abdulelah



INTRODUCTION

This will guide you through the process of replacing your Astro Pyle PTBL7C's speakers.

TOOLS:

- Desoldering Braid (1)
- Desoldering Pump (1)
- Portable Soldering Iron (1)
- Heavy-Duty Spudger (1)
- Tweezers (1)

PARTS:

- Astro Pyle PTBL7C Speakers (1)

Step 1 — Case Separation



- Slide the flat end of the spudger under the front edge of the screen and carefully pry it open.

i The front edge is the side with the buttons on it.

★ You may hear a cracking sound when pulling the case off of the device. This is normal, and is just the clips being pulled apart. However, be careful and pull the clips slowly/cautiously to avoid damage.

⚠ Be aware of the speaker cable when removing the case, as it is still attached to the motherboard.

Step 2 — Tape Removal



- Locate the Speakers; they should be attached to the case as shown.
- Follow the wires back to the motherboard, removing all tape covering the wires along the way.

(i) This will make it easier to move the wires around.

Step 3 — Desoldering Speakers



- Desolder the black wire from the motherboard. This will separate the speakers from the board, allowing you to replace them.

⚠ Exercise EXTREME caution while soldering. It is very easy to burn yourself, or damage the surrounding components. For a basic guide of how to desolder, follow this link:
<http://www.dummies.com/programming/elect...>

To reassemble your device, follow these instructions in reverse order.