



# Asus ROG Strix GL702VM-BHI7N09 Back Panel Replacement

This guide will describe how to remove the back panel of the Asus ROG Strix GL702VM-BHI7N09 in order to expose the components inside.

Written By: Zach Langer



This document was generated on 2019-10-22 07:34:22 PM (MST).

## INTRODUCTION

This guide explains how to open the back panel of the Asus ROG Strix GL702VM-BHI7N09. The back panel is the first step in replacing any part on the laptop, and it holds together the body of the laptop which houses all the main components. This is a relatively simple task.

## TOOLS:

- [iFixit Opening Tools](#) (1)
- [Phillips #1 Screwdriver](#) (1)

## Step 1 — Back Panel



- Flip the laptop over to the back panel, with the serial numbers facing up.
- Using a Phillips #1 screwdriver, remove the ten 12 mm screws from the back panel.

## Step 2



**⚠** The snap seals don't need a lot of pressure to open, and may break if forced. Be gentle with the opening tool.

- Wedge the sharp edge of the plastic opening tool into the seam between the back panel and the rest of the laptop, then gently pry the panel up.  
*(i)* There will be a snapping sound as you remove the back panel, but that is just the seal loosening.
- Continue breaking the seals by sliding the plastic opening tool around the entire laptop under the seam until the back panel is free.
- Once you have broken all the seals, carefully lift the panel off.

To reassemble your device, follow these instructions in reverse order.