



# Asus ROG Strix GL702VM-BHI7N09 Fan Replacement

This guide explains how to remove the fans of the Asus ROG Strix GL702VM-BHI7N09 for replacement.

Written By: Zach Langer



This document was generated on 2019-10-14 07:31:01 PM (MST).

## INTRODUCTION

This guide explains how to remove the fans of the Asus ROG Strix GL702VM-BHI7N09 for replacement. Any of the three fans in the laptop can be replaced following these instructions.

### TOOLS:

- [iFixit Opening Tools](#) (1)
- [Phillips #1 Screwdriver](#) (1)

## Step 1 — Back Panel



- Flip the laptop over to the back panel, with the serial numbers facing up.
- Using a Phillips #1 screwdriver, remove the ten 12 mm screws from the back panel.

## Step 2



**⚠** The snap seals don't need a lot of pressure to open, and may break if forced. Be gentle with the opening tool.

- Wedge the sharp edge of the plastic opening tool into the seam between the back panel and the rest of the laptop, then gently pry the panel up.  
*(i)* There will be a snapping sound as you remove the back panel, but that is just the seal loosening.
- Continue breaking the seals by sliding the plastic opening tool around the entire laptop under the seam until the back panel is free.
- Once you have broken all the seals, carefully lift the panel off.

## Step 3 — Fan




- Using a Phillips #1 screwdriver, remove the four indicated 4 mm screws that hold the black fan and the silver one adjacent to it.

## Step 4




- The smaller black fan must be removed before the larger gray fan on the right can be taken out.*
- To remove the black fan, pull gently on the connecting cables outlined.

## Step 5



- Unplug the white connector by gently pulling the cables.
- Lift off the gray fan.

## Step 6



- Using a Phillips #1 screwdriver, remove the two indicated 4 mm screws from the other gray fan.

## Step 7



- Unplug the white connector by gently pulling it towards the center of the computer.
- Lift the fan out of the body of the laptop to remove it.

To reassemble your device, follow these instructions in reverse order.