



Bem Wireless HL2739B Charging base motherboard Replacement

This guide is to instruct users how to remove and replace the motherboard in the Bem Wireless HL2739B charging base.

Written By: Ryan McQueeney



INTRODUCTION

Is your charging base not functioning correctly? It's probably the motherboard.

TOOLS:

- [iFixit Opening Tools](#) (1)
- [Tweezers](#) (1)
- [Metal Spudger](#) (1)
- [J1 Screwdriver Bit](#) (1)

Step 1 — Charging Base Battery




- Peel the rubber cover back from the corner of the auxiliary charging base to reveal the screw.

Step 2



- Use the J1 bit attached to the screwdriver to remove the four 10mm screws from the bottom of the auxiliary charging base.


Step 3



- Lift the bottom cover away from the rest of the auxiliary charging base.

⚠ There are wires connecting the battery and cover to the rest of the auxiliary charging base. Be careful when removing the auxiliary charging base cover.

Step 4



- Using the tweezers, pull the wires from the auxiliary charging base's internal chip.

⚠ Be careful not to damage the chip when you remove the wires.

ⓘ It will likely require soldering to reassemble the auxiliary charging base after this step.

Step 5 — Charging Base Motherboard



- Using tweezers, remove the black wire from the motherboard

Step 6



- Using the plastic opening tool, gently pry the motherboard up and remove it from the charging base.

(i) There are no screws to be removed from the motherboard.

To reassemble your device, follow these instructions in reverse order.