




# Dell Optiplex 745 Ultra Small Form Factor RAM Replacement

This guide will help you to replace or upgrade the RAM modules within your Dell Optiplex 745.


Written By: donnavon



## INTRODUCTION

In this tutorial we will discuss how to remove and re-install memory into a Dell Optiplex 745 Ultra Small Form Factor. The Dell Optiplex 745 Ultra Small Form Factor encases two DIMM memory slots that can both house a 2GB memory module, allowing a total maximum of 4GB of memory in this machine.

## Step 1 — Side Panel



⚠ Make sure to shut down the computer! you can do this by going to the start menu and clicking shutdown.

⚠ Ensure all cables, speakers and other devices are unplugged and turned off before opening the computer case.

## Step 2



- Lay the computer on its side; you will see a blue knob. Turn said knob 90 degrees counter clockwise.

## Step 3



- Slide the panel case forward about 1/2 inch while knob is turned.
- Lift panel case off computer.

## Step 4 — Hard Drive



- Remove power and data cables

 Ground yourself before removing any internal components.

## Step 5



- Locate blue tabs as shown to the left and right of the hard disk drive
- Squeeze tabs and slide hard disk drive towards you, then lift up on the drive.

## Step 6 — RAM



- Press down on the two white tabs on either side of the memory module; the RAM will pop out.

 Be sure you are grounded to avoid electrostatic discharge and to place your memory modules in an anti-static bag.

To reassemble your device, follow these instructions in reverse order.