



# Lenovo Y50-70 Touch Fan Replacement

This guide will show you the steps on how to replace the Lenovo Y50-70 Touch fans.

Written By: Vivian



## INTRODUCTION

This guide will walk you through two basic steps: removing the back and removing the fan.

### TOOLS:

- Phillips #1 Screwdriver (1)


### PARTS:

- 2.25W Sunon Cooling Fan (1)

Cooling Fan


Serial Number: EG60070S1-C060-S99

## Step 1 — Back




- Remove all twelve 6 mm screws from the back of the laptop using a Phillips #1 screwdriver.
- *(i)* Apply a lot of pressure to prevent the screws from stripping.
-  Make sure to turn off the computer first!

## Step 2




- Gently pull the back cover off the laptop. It should come off easily.

## Step 3 — Fan



- Remove the three 3.5 mm screws from the fan with a Philips #1 screwdriver.


## Step 4



- Pull the wire tabs up one at a time to separate them from the motherboard.

⚠ Do not pull too hard on the wire tabs. It may damage the connection between the wires and motherboard.


## Step 5



- Remove the black and white antenna cables from the wireless card.



**⚠** Do not pull too hard on the antenna cables, as it might damage the connection to the wireless card.

## Step 6



- Lift up the fan slightly.
- Gather the antenna cables(black and white) and speaker wires (red, black, blue, and white). Carefully move them away from the fan.

## Step 7



- Lift the fan off of the laptop.

To reassemble your device, follow these instructions in reverse order.