




Lenovo Z70-80 Motherboard Replacement

Use this guide to replace the motherboard for your Lenovo Z70-80.

Written By: Eduardo Delgado





INTRODUCTION

This guide will demonstrate the step by step process on how to replace the motherboard in your Lenovo Z70-80.

TOOLS:

- [Phillips #0 Screwdriver](#) (1)
- [iFixit Opening Tools](#) (1)
- [54 Bit Driver Kit](#) (1)
- [Spudger](#) (1)
- [Metal Spudger Set](#) (1)
- [Anti-Static Wrist Strap](#) (1)
- [Ruler](#) (1)

Step 1 — Battery



- Use your fingers to push both latches away from each other to release the battery.
- Pull the battery out.

Step 2 — Back Panel



- Remove the two Phillips #0 screws from the bottom panel.
- Slide the panel down slightly, and then lift to pull it off.

Step 3 — Optical Drive




- Remove the single 3mm Phillips #0 screw from the optical drive.
- Pull the optical drive out of the side.

Step 4 — Electric Fan



- Remove the three 6mm Phillips #0 screws from the fan.
- Disconnect the fan from the motherboard by pulling up on the plug.

Step 5 — Motherboard




- Remove all the 3-7mm Phillips #0 screws to remove the back cover.
- ⚠ There is a sticker covering the screw marked with a red arrow. This sticker will have to be removed in order to reach the screw.

Step 6




- Carefully take out the keyboard and remove all of the 3mm Phillips screws.
- ⓘ There is a tiny black tab you have to flip up on the ZIF connector so it can open and safely be removed.

Step 7



- Remove all ribbon cables and connectors from the front and back of the laptop.
- ⓘ Remember to open the tiny tabs on ZIF connectors to safely remove them.

Step 8




- Remove the 3mm screw and safely pull out the cables from the hooks holding them in place.

Step 9



- With care pry open the cover off the laptop using the regular or metal spudger.

Step 10



- Unplug the two black cables from the motherboard which are marked by the red squares.
- Remove all the 3mm screws from the motherboard. Then, carefully remove the motherboard from the laptop.

 Always pick up the motherboard by the edges.

To reassemble your device, follow these instructions in reverse order.